

731 Enterprise Drive Lexington, KY 40510

Telephone: 859-226-1000 Facsimile: 859-226-1040 www.intertek-etlsemko.com

MPE Calculation

§ 1.1310: The criteria listed in table 1 shall be used to evaluate the environmental impact of human exposure to radiofrequency (RF) radiation as specified in §1.1307(b), except in the case of portable devices which shall be evaluated according to the provisions of §2.1093 of this chapter.

Part 1.1310 Limits for Maximum Permissible Exposure (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm ²)	Averaging time (minutes)
(A) Lin	nits for Occupationa	/Controlled Exposur	es	
0.3–3.0	614	1.63	*(100)	6
3.0-30	1842/f	4.89/f	*(900/f2)	6
30–300	61.4	0.163	1.0	6
300-1500			f/300	6
1500–100,000			5	6
(B) Limits	for General Populati	on/Uncontrolled Exp	osure	-
0.3–1.34	614	1.63	*(100)	30
1.34–30	824/f	2.19/f	*(180/f ²)	30

0.3–1.34	614	1.63	*(100)	30
1.34–30	824/f	2.19/f	*(180/f ²)	30
30-300	27.5	0.073	0.2	30
300–1500			f/1500	30
1500–100,000			1.0	30

 f = frequency in MHz
* = Plane-wave equivalent power density
NOTE 1 TO TABLE 1: Occupational/controlled limits apply in situations in which persons are exposed as a consequence of their employment provided those persons are fully aware of the potential for exposure and can exercise control over their exposure. Limits for occupational/controlled exposure also apply in situations when an individual is transient through a location where occupational/controlled limits apply in situations when an individual is transient through a location where occupational/controlled exposure also apply in situations when an individual is transient through a location where occupational limits apply in situations. pational/controlled limits apply provided he or she is made aware of the potential for exposure.

NOTE 2 TO TABLE 1: General population/uncontrolled exposures apply in situations in which the general public may be exposed, or in which persons that are exposed as a consequence of their employment may not be fully aware of the potential for exposure or can not exercise control over their exposure.



731 Enterprise Drive Lexington, KY 40510

Telephone: 859-226-1000 Facsimile: 859-226-1040 www.intertek-etlsemko.com

RSS-102 Issue 5 Exposure Limits:

Table 4: RF Field Strength Limits for Devices Used by the General Public (Uncontrolled Environment)

Frequency Range (MHz)	Electric Field (V/m rms)	Magnetic Field (A/m rms)	Power Density (W/m ²)	Reference Period (minutes)
0.003-10 ²¹	83	90	¥	Instantaneous*
0.1-10	¥	0.73/ f	¥	6**
1.1-10	$87/f^{0.5}$	14 H		6**
10-20	27.46	0.0728	2	6
20-48	58.07/ f 0.25	$0.1540/f^{0.25}$	8.944/ f ^{0.5}	6
48-300	22.06	0.05852	1.291	6
300-6000	$3.142 f^{0.3417}$	$0.008335 f^{0.3417}$	$0.02619 f^{0.6834}$	6
6000-15000	61.4	0.163	10	6
15000-150000	61.4	0.163	10	$616000/f^{1.2}$
150000-300000	$0.158 f^{0.5}$	$4.21 \ge 10^{-4} f^{0.5}$	$6.67 \ge 10^{-5} f$	$616000/f^{1.2}$
Note: f is frequency *Based on nerve stin ** Based on specific	in MHz.	30	· · · · · · · · · · · · · · ·	

1.1 Test Procedure

An MPE evaluation for was performed in order to show that the device was compliant with §2.1091. The maximum power density was calculated for each transmitter at a separation distance of 20cm.

For each transmitter the maximum RF exposure at a 20 cm distance using the formula: $ConductedPower_{mW} = 10^{ConductedPower(dBm)/10}$

$$PowerDensity = \frac{ConductedPower_{mW} \times Ant.Gain}{4\pi \times (20_{cm})^2}$$



731 Enterprise Drive Lexington, KY 40510

Telephone: 859-226-1000 Facsimile: 859-226-1040 www.intertek-etlsemko.com

1.2 Results:

- Maximum Conducted Output Power = 276.1mW
- Maximum Antenna Gain = 1.47dbi
- Maximum Conducted Output Power = (10*log(.2761mW/.001mW) = 24.41db

Power Density = (24.41dbm + 1.47dbi) / 5025.6

Power Density = $.077 \text{mW/cm}^2$

Limit at 2.4GHz = 1mW/cm²

RSS-102 Issue 5 Exposure Limit at 2.4GHz = 5.35W/m²

Power Density = .77W/m²

The calculated maximum power density at 20cm distance is less that the limit for general population / uncontrolled exposure.

