



# FCC TEST REPORT

**Test report  
On Behalf of  
LG Electronics USA, Inc.  
For  
4G Mobile phone  
Model No.: LM-X210LMW**

**FCC ID: ZNFX210LMW**

**Prepared for :** LG Electronics USA, Inc.  
1000 Sylvan Ave. Englewood Cliffs, New Jersey, United States 07632

**Prepared By :** Shenzhen HUAKE Testing Technology Co., Ltd.  
1F, B2 Building, JunfengZhongchengZhizao Innovation Park, Fuhai Street,  
Bao'an District, Shenzhen City, China

**Date of Test:** Jun 25, 2019 ~ July 15, 2019

**Date of Report:** July 15, 2019

**Report Number:** HK1907111624-5E



## TEST RESULT CERTIFICATION

**Applicant's name** .....: LG Electronics USA, Inc.  
**Address** .....: 1000 Sylvan Ave. Englewood Cliffs, New Jersey, United States  
07632  
**Manufacture's Name**.....: OPTIEMUS ELECTRONICS LIMITED  
**Address** .....: D-348, Sector 63, Gautam Budh Nagar, Noida, Uttar Pradesh  
201307 India


### Product description

**Trade Mark:** LG  
**Product name**.....: 4G Mobile phone  
**Model and/or type reference** : LM-X210LMW


**Standards** .....: FCC Rules and Regulations Part 15 Subpart C Section 15.247  
ANSI C63.10: 2013

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen HUAK Testing Technology Co., Ltd. is acknowledged as copyright owner and source of the material. Shenzhen HUAK Testing Technology Co., Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

**Date of Test** .....:  
**Date (s) of performance of tests** .....: Jun 25, 2019 ~ July 15, 2019  
**Date of Issue**.....: July 15, 2019  
**Test Result**.....: **Pass**

Testing Engineer :   
\_\_\_\_\_  
(Gary Qian)

Technical Manager :   
\_\_\_\_\_  
(Eden Hu)

Authorized Signatory :   
\_\_\_\_\_  
(Jason Zhou)



## TABLE OF CONTENTS

<b>1. Test Result Summary .....</b>	<b>4</b>
1.1. TEST PROCEDURES AND RESULTS.....	4
1.2. TEST FACILITY .....	4
1.3. MEASUREMENT UNCERTAINTY .....	5
<b>2. EUT Description .....</b>	<b>6</b>
2.1. GENERAL DESCRIPTION OF EUT .....	6
2.2. CARRIER FREQUENCY OF CHANNELS .....	7
2.3. OPERATION OF EUT DURING TESTING .....	7
2.4. DESCRIPTION OF TEST SETUP .....	7
<b>3. General Information .....</b>	<b>8</b>
3.1. TEST ENVIRONMENT AND MODE .....	8
3.2. DESCRIPTION OF SUPPORT UNITS .....	9
<b>4. Test Results and Measurement Data .....</b>	<b>10</b>
4.1. CONDUCTED EMISSION .....	10
4.2. TEST RESULT .....	12
4.3. MAXIMUM CONDUCTED OUTPUT POWER .....	14
4.4. EMISSION BANDWIDTH.....	16
4.5. POWER SPECTRAL DENSITY .....	21
4.6. CONDUCTED BAND EDGE AND SPURIOUS EMISSION MEASUREMENT .....	26
4.7. RADIATED SPURIOUS EMISSION MEASUREMENT .....	31
4.8. ANTENNA REQUIREMENT .....	52
4.9. PHOTOGRAPH OF TEST.....	53
4.10. PHOTOS OF THE EUT .....	55



# 1. Test Result Summary

## 1.1. TEST PROCEDURES AND RESULTS

Requirement	CFR 47 Section	Result
Antenna requirement	§15.203/§15.247 (c)	PASS
AC Power Line Conducted Emission	§15.207	N/A
Conducted Peak Output Power	§15.247 (b)(3) §2.1046	PASS
6dB Emission Bandwidth	§15.247 (a)(2) §2.1049	PASS
Power Spectral Density	§15.247 (e)	PASS
Band Edge	§15.247(d) §2.1051, §2.1057	PASS
Spurious Emission	§15.205/§15.209 §2.1053, §2.1057	PASS

**Note:**

1. PASS: Test item meets the requirement.
2. Fail: Test item does not meet the requirement.
3. N/A: Test case does not apply to the test object.
4. The test result judgment is decided by the limit of test standard.

## 1.2. TEST FACILITY

Test Firm : Shenzhen HUAKE Testing Technology Co., Ltd.

Address 1F, B2 Building, JunfengZhongchengZhizao Innovation Park, Fuhai Street, Bao'an District, Shenzhen City, China



### 1.3. Measurement Uncertainty

The reported uncertainty of measurement  $y \pm U$ , where expanded uncertainty  $U$  is based on a standard uncertainty multiplied by a coverage factor of  $k=2$ , providing a level of confidence of approximately 95 %.

No.	Item	MU
1	Conducted Emission	$\pm 2.56\text{dB}$
2	RF power, conducted	$\pm 0.12\text{dB}$
3	Spurious emissions, conducted	$\pm 0.11\text{dB}$
4	All emissions, radiated(<1G)	$\pm 3.92\text{dB}$
5	All emissions, radiated(>1G)	$\pm 4.28\text{dB}$
6	Temperature	$\pm 0.1^\circ\text{C}$
7	Humidity	$\pm 1.0\%$



## 2. EUT Description

### 2.1. GENERAL DESCRIPTION OF EUT

Equipment	4G Mobile phone
Model Name	LM-X210LMW
Serial No.	N/A
Model Difference	N/A
FCC ID	<b>ZNFX210LMW</b>
Antenna Type	Internal Antenna
Antenna Gain	1.3dBi
Operation frequency	802.11b/g/n 20:2412~2462 MHz
Number of Channels	802.11b/g/n20: 11CH
Modulation Type	CCK/OFDM/DBPSK/DAPSK
Power supply:	DC 5V 2A from AC Adapter or DC3.85V By Battery



## 2.2. Carrier Frequency of Channels

Channel List for 802.11b/802.11g/802.11n (HT20)							
Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
01	2412	04	2427	07	2442	10	2457
02	2417	05	2432	08	2447	11	2462
03	2422	06	2437	09	2452		

**Note:**

In section 15.31(m), regards to the operating frequency range over 10 MHz, the Lowest frequency, the middle frequency, and the highest frequency of channel were selected to perform the test, and the selected channel see below:

## 2.3. Operation of EUT during testing

Operating Mode

The mode is used: **Transmitting mode for 802.11b/802.11g/802.11n (HT20)**


Low Channel: 2412MHz

Middle Channel: 2437MHz

High Channel: 2462MHz

## 2.4. DESCRIPTION OF TEST SETUP

Operation of EUT during conducted testing and Radiation testing:



Operation of EUT Above 1GHz Radiation testing:



- Adapter information  
Model:UP0920  
Input:100-240V~,50/60Hz,0.3A  
Output:5VDC,2A



### 3. Genera Information

#### 3.1. Test environment and mode

Operating Environment:	
Temperature:	25.0 °C
Humidity:	56 % RH
Atmospheric Pressure:	1010 mbar
Test Mode:	
Engineering mode:	Keep the EUT in continuous transmitting by select channel and modulations(The value of duty cycle is 98.46%)
<p>The sample was placed (0.8m below 1GHz, 1.5m above 1GHz)above the ground plane of 3m chamber. Measurements in both horizontal and vertical polarities were performed. During the test, each emission was maximized by: having the EUT continuously working, investigated all operating modes, rotated about all 3 axis (X, Y &amp; Z) and considered typical configuration to obtain worst position, manipulating interconnecting cables, rotating the turntable, varying antenna height from 1m to 4m in both horizontal and vertical polarizations. The emissions worst-case are shown in Test Results of the following pages.For the full battery state and The output power to the maximum state.</p>	

<p>We have verified the construction and function in typical operation. All the test modes were carried out with the EUT in transmitting operation, which was shown in this test report and defined as follows:</p>	
<p><b>Per-scan all kind of data rate in lowest channel, and found the follow list which it was worst case.</b></p>	
Mode	Data rate
802.11b	1Mbps
802.11g	6Mbps
802.11n(H20)	6.5Mbps
Final Test Mode:	
Operation mode:	Keep the EUT in continuous transmitting with modulation
<p>1. For WIFI function, the engineering test program was provided and enabled to make EUT continuous transmit/receive.</p> <p>2.According to ANSI C63.10 standards, the test results are both the “worst case” and “worst setup” 1Mbps for 802.11b, 6Mbps for 802.11g, 6.5Mbps for 802.11n(H20).Duty cycle setting during the transmission is 98.5% with maximum power setting for all modulations.</p>	





### 3.2. Description of Support Units

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

Equipment	Model No.	Serial No.	FCC ID	Trade Name
/	/	/	/	/

**Note:**

- 1. All the equipment/cables were placed in the worst-case configuration to maximize the emission during the test.*
- 2. Grounding was established in accordance with the manufacturer's requirements and conditions for the intended use.*
- 3. For conducted measurements (Output Power, 6dB Emission Bandwidth, Power Spectral Density, Spurious Emissions), the antenna of EUT is connected to the test equipment via temporary antenna connector, the antenna connector is soldered on the antenna port of EUT, and the temporary antenna connector is listed in the Test Instruments.*



## 4. Test Results and Measurement Data

### 4.1. Conducted Emission

#### Test Specification

<b>Test Requirement:</b>	FCC Part15 C Section 15.207														
<b>Test Method:</b>	ANSI C63.10:2013														
<b>Frequency Range:</b>	150 kHz to 30 MHz														
<b>Receiver setup:</b>	RBW=9 kHz, VBW=30 kHz, Sweep time=auto														
<b>Limits:</b>	<table border="1"> <thead> <tr> <th rowspan="2">Frequency range (MHz)</th> <th colspan="2">Limit (dBuV)</th> </tr> <tr> <th>Quasi-peak</th> <th>Average</th> </tr> </thead> <tbody> <tr> <td>0.15-0.5</td> <td>66 to 56*</td> <td>56 to 46*</td> </tr> <tr> <td>0.5-5</td> <td>56</td> <td>46</td> </tr> <tr> <td>5-30</td> <td>60</td> <td>50</td> </tr> </tbody> </table>	Frequency range (MHz)	Limit (dBuV)		Quasi-peak	Average	0.15-0.5	66 to 56*	56 to 46*	0.5-5	56	46	5-30	60	50
Frequency range (MHz)	Limit (dBuV)														
	Quasi-peak	Average													
0.15-0.5	66 to 56*	56 to 46*													
0.5-5	56	46													
5-30	60	50													
<b>Test Setup:</b>	<p>The diagram illustrates the test setup. A horizontal line at the top represents the 'Reference Plane'. Below it, a 'Test table/Insulation plane' is shown. On this table, an 'E.U.T' (Equipment Under Test) and an 'AC power' source are connected. A 'LISN' (Line Impedance Stabilization Network) is connected to the AC power line. The distance from the Reference Plane to the top of the LISN is 40cm. The distance from the top of the LISN to the EMI Receiver is 80cm. The EMI Receiver is connected to the LISN. A 'Filter' is connected to the AC power line, and 'AC power' is supplied to the filter.</p> <p><i>Remark:</i>  E.U.T: Equipment Under Test  LISN: Line Impedance Stabilization Network  Test table height=0.8m</p>														
<b>Test Mode:</b>	Charging + transmitting with modulation														
<b>Test Procedure:</b>	<ol style="list-style-type: none"> <li>1. The E.U.T is connected to the main power through a line impedance stabilization network (L.I.S.N.). This provides a 50ohm/50uH coupling impedance for the measuring equipment.</li> <li>2. The peripheral devices are also connected to the main power through a LISN that provides a 50ohm/50uH coupling impedance with 50ohm termination. (Please refer to the block diagram of the test setup and photographs).</li> <li>3. Both sides of A.C. line are checked for maximum conducted interference. In order to find the maximum emission, the relative positions of equipment and all of the interface cables must be changed according to ANSI C63.10: 2013 on conducted measurement.</li> </ol>														
<b>Test Result:</b>	N/A														

**Test Instruments**


<b>Conducted Emission Shielding Room Test Site (843)</b>				
<b>Equipment</b>	<b>Manufacturer</b>	<b>Model</b>	<b>Serial Number</b>	<b>Calibration Due</b>
Receiver	R&S	ESCI 7	HKE-010	Dec. 27, 2019
L.I.S.N. Artificial Mains Network	R&S	ENV216	HKE-002	Dec. 27, 2019
LISN	R&S	ENV216	HKE-059	Dec. 27, 2019
Conducted test software	Tonscend	TS+ Rev 2.5.0.0	HKE-081	N/A

**Note:** The calibration interval of the above test instruments is 12 months and the calibrations are traceable to international system unit (SI).



## 4.2. Test Result

Test Specification: Line



Suspected List						
NO.	Freq. [MHz]	Level [dBμV]	Factor [dB]	Limit [dBμV]	Margin [dB]	Detector
1	0.5010	47.33	10.04	56.00	8.67	PK
2	0.6720	49.70	10.05	56.00	6.30	PK
3	1.0860	47.02	10.07	56.00	8.98	PK
4	2.8365	41.13	10.21	56.00	14.87	PK
5	4.2405	41.42	10.25	56.00	14.58	PK
6	5.4105	42.22	10.26	60.00	17.78	PK


Remark: Margin = Limit – Level

**Notes:**

1. An initial pre-scan was performed on the line and neutral lines with peak detector.
2. Quasi-Peak and Average measurement were performed at the frequencies with maximized peak emission.
3. Final Level = Receiver Read level + LISN Factor + Cable Loss
4. If the average limit is met when using a quasi-peak detector receiver, the EUT shall be deemed to meet both limits and measurement with the average detector receiver is unnecessary.



Test Specification: Neutral



Suspected List						
NO.	Freq. [MHz]	Level [dBµV]	Factor [dB]	Limit [dBµV]	Margin [dB]	Detector
1	0.5055	46.21	10.04	56.00	9.79	PK
2	0.6720	48.37	10.05	56.00	7.63	PK
3	0.9780	44.78	10.06	56.00	11.22	PK
4	1.5000	44.44	10.10	56.00	11.56	PK
5	4.2450	39.70	10.25	56.00	16.30	PK
6	9.0015	41.82	10.11	60.00	18.18	PK

Remark: Margin = Limit – Level

**Notes:**

1. An initial pre-scan was performed on the line and neutral lines with peak detector.
  2. Quasi-Peak and Average measurement were performed at the frequencies with maximized peak emission.
  3. Final Level = Receiver Read level + LISN Factor + Cable Loss.
- If the average limit is met when using a quasi-peak detector receiver, the EUT shall be deemed to meet both limits and measurement with the average detector receiver is unnecessary.




**Test Data**

<b>TX 802.11b Mode</b>			
Test Channel	Frequency	MaximumPeak Conducted Output Power	LIMIT
	(MHz)	(dBm)	dBm
CH01	2412	12.24	30
CH06	2437	12.12	30
CH11	2462	12.09	30
<b>TX 802.11g Mode</b>			
CH01	2412	11.46	30
CH06	2437	11.15	30
CH11	2462	11.04	30
<b>TX 802.11n20 Mode</b>			
CH01	2412	10.39	30
CH06	2437	10.27	30
CH11	2462	10.11	30



## 4.4. Emission Bandwidth

### Test Specification

<b>Test Requirement:</b>	FCC Part15 C Section 15.247 (a)(2)
<b>Test Method:</b>	KDB 558074
<b>Limit:</b>	>500kHz
<b>Test Setup:</b>	 <p style="text-align: center;">Spectrum Analyzer                      EUT</p>
<b>Test Mode:</b>	Transmitting mode with modulation
<b>Test Procedure:</b>	<ol style="list-style-type: none"> <li>1. The testing follows FCC KDB Publication No. 558074 DTS D01 Meas. Guidance v05.</li> <li>2. Set to the maximum power setting and enable the EUT transmit continuously.</li> <li>3. Make the measurement with the spectrum analyzer's resolution bandwidth (RBW) = 100 kHz. Set the Video bandwidth (VBW) = 300 kHz. In order to make an accurate measurement. The 6dB bandwidth must be greater than 500 kHz.</li> <li>4. Measure and record the results in the test report.</li> </ol>
<b>Test Result:</b>	PASS

### Test Instruments

RF Test Room				
Equipment	Manufacturer	Model	Serial Number	Calibration Due
Spectrum analyzer	Agilent	N9020A	HKE-048	Dec. 27, 2019
RF Cable (9KHz-26.5GHz)	Tonscend	170660	N/A	Dec. 27, 2019
RF automatic control unit	Tonscend	JS0806-2	HKE-060	Dec. 27, 2019
RF test software	Tonscend	JS1120-B Version 2.6	HKE-083	N/A

**Note:** The calibration interval of the above test instruments is 12 months and the calibrations are traceable to international system unit (SI).



**Test data**

Test channel	6dB Emission Bandwidth (MHz)		
	802.11b	802.11g	802.11n(H20)
Lowest	8.657	15.70	16.29
Middle	9.134	16.44	17.37
Highest	8.647	15.76	16.68
Limit:	>500k		
Test Result:	PASS		

Test plots as follows:




### 802.11b Modulation

#### Lowest channel



#### Middle channel




#### Highest channel






### 802.11g Modulation


#### Lowest channel



#### Middle channel




#### Highest channel






### 802.11n (HT20) Modulation


#### Lowest channel



#### Middle channel



#### Highest channel





**Test data**

EUT Set Mode	Channel	Result(dBm/30kHz)	Result(dBm/3kHz)
802.11b	Lowest	-3.13	-13.13
	Middle	-8.09	-18.09
	Highest	-2.19	-12.19
802.11g	Lowest	-2.87	-12.87
	Middle	-6.97	-16.97
	Highest	-2.04	-12.04
802.11n(H20)	Lowest	-3.5	-13.5
	Middle	-8.05	-18.05
	Highest	-2.94	-12.94
PSD test result(dBm/3kHz)= PSD test result(dBm/30kHz)-10			
Limit: 8dBm/3kHz			
TestResult:	PASS		

Test plots as follows:




### 802.11b Modulation

#### Lowest channel



#### Middle channel




#### Highest channel






### 802.11g Modulation


#### Lowest channel



#### Middle channel



#### Highest channel









### 802.11n (HT20) Modulation


#### Lowest channel



#### Middle channel



#### Highest channel





**Test Instruments**


RF Test Room				
Equipment	Manufacturer	Model	Serial Number	Calibration Due
Spectrum analyzer	Agilent	N9020A	HKE-048	Dec. 27, 2019
High pass filter unit	Tonscend	JS0806-F	HKE-055	Dec. 27, 2019
RF Cable (9KHz-26.5GHz)	Tonscend	170660	N/A	Dec. 27, 2019
RF automatic control unit	Tonscend	JS0806-2	HKE-060	Dec. 27, 2019
RF test software	Tonscend	JS1120-B Version 2.6	HKE-083	N/A

**Note:** The calibration interval of the above test instruments is 12 months and the calibrations are traceable to international system unit (SI).




### Test Data

### 802.11b Modulation






### 802.11g Modulation







802.11n (HT20) Modulation







## 4.7. Radiated Spurious Emission Measurement

### Test Specification

<b>Test Requirement:</b>	FCC Part15 C Section 15.209					
<b>Test Method:</b>	ANSI C63.10: 2013					
<b>Frequency Range:</b>	9 kHz to 25 GHz					
<b>Measurement Distance:</b>	3 m					
<b>Antenna Polarization:</b>	Horizontal & Vertical					
<b>Operation mode:</b>	Transmitting mode with modulation					
<b>Receiver Setup:</b>	Frequency	Detector	RBW	VBW	Remark	
	9kHz- 150kHz	Quasi-peak	200Hz	1kHz	Quasi-peak Value	
	150kHz- 30MHz	Quasi-peak	9kHz	30kHz	Quasi-peak Value	
	30MHz-1GHz	Quasi-peak	100KHz	300KHz	Quasi-peak Value	
	Above 1GHz	Peak	1MHz	3MHz	Peak Value	
Peak		1MHz	10Hz	Average Value		
<b>Limit:</b>	Frequency	Field Strength (microvolts/meter)	Measurement Distance (meters)			
	0.009-0.490	2400/F(KHz)	300			
	0.490-1.705	24000/F(KHz)	30			
	1.705-30	30	30			
	30-88	100	3			
	88-216	150	3			
	216-960	200	3			
	Above 960	500	3			
	Frequency	Field Strength (microvolts/meter)	Measurement Distance (meters)	Detector		
	Above 1GHz	500	3	Average		
5000		3	Peak			
<b>Test setup:</b>	For radiated emissions below 30MHz					
	<p>Distance = 3m</p> <p>0.8m</p> <p>EUT</p> <p>Turn table</p> <p>Ground Plane</p> <p>Computer</p> <p>Pre -Amplifier</p> <p>Receiver</p>					
30MHz to 1GHz						



Above 1GHz



**Test Procedure:**

1. For the radiated emission test below 1GHz:  
 The EUT was placed on a turntable with 0.8 meter above ground. The EUT was set 3 meters from the interference receiving antenna, which was mounted on the top of a variable height antenna tower. The EUT was arranged to its worst case and then tune the antenna tower (from 1 m to 4 m) and turntable (from 0 degree to 360 degrees) to find the maximum reading. A pre-amp and a highPASS filter are used for the test in order to get better signal level.
- For the radiated emission test above 1GHz:  
 Place the measurement antenna on a turntable with 1.5 meter above ground, which is away from each area of the EUT determined to be a source of emissions at the specified measurement distance, while keeping the measurement antenna aimed at the source of emissions at each frequency of significant emissions, with polarization oriented for maximum response. The measurement antenna may have to be higher or lower than the EUT, depending on the radiation pattern of the emission and staying aimed at the emission source for receiving the maximum signal. The final measurement antenna elevation shall be that which maximizes the





	<p>emissions. The measurement antenna elevation for maximum emissions shall be restricted to a range of heights of from 1 m to 4 m above the ground or reference ground plane.</p> <ol style="list-style-type: none"><li>3. Corrected Reading: Antenna Factor + Cable Loss + Read Level - Preamp Factor = Level</li><li>4. For measurement below 1GHz, If the emission level of the EUT measured by the peak detector is 3 dB lower than the applicable limit, the peak emission level will be reported. Otherwise, the emission measurement will be repeated using the quasi-peak detector and reported.</li><li>5. Use the following spectrum analyzer settings:<ol style="list-style-type: none"><li>(1) Span shall wide enough to fully capture the emission being measured;</li><li>(2) Set RBW=100 kHz for <math>f &lt; 1</math> GHz; <math>VBW \geq RBW</math>; Sweep = auto; Detector function = peak; Trace = max hold;</li><li>(3) Set RBW = 1 MHz, <math>VBW = 3</math> MHz for <math>f \geq 1</math> GHz for peak measurement.</li></ol></li></ol> <p>For average measurement: <math>VBW = 10</math> Hz, when duty cycle is no less than 98 percent. <math>VBW \geq 1/T</math>, when duty cycle is less than 98 percent where T is the minimum transmission duration over which the transmitter is on and is transmitting at its maximum power control level for the tested mode of operation.</p>
<b>Test results:</b>	PASS

**Test Instruments**

<b>Radiated Emission Test Site (966)</b>				
<b>Name of Equipment</b>	<b>Manufacturer</b>	<b>Model</b>	<b>Serial Number</b>	<b>Calibration Due</b>
Receiver	R&S	ESCI-7	HKE-010	Dec. 27, 2019
Spectrum analyzer	Agilent	N9020A	HKE-048	Dec. 27, 2019
Spectrum analyzer	R&S	FSP40	HKE-025	Dec. 27, 2019
Preamplifier	EMCI	EMC051845SE	HKE-015	Dec. 27, 2019
Preamplifier	Agilent	83051A	HKE-016	Dec. 27, 2019
Loop antenna	Schwarzbeck	FMZB 1519 B	HKE-014	Dec. 27, 2019
Broadband antenna	Schwarzbeck	VULB 9163	HKE-012	Dec. 27, 2019
Horn antenna	Schwarzbeck	9120D	HKE-013	Dec. 27, 2019
High gain antenna	Schwarzbeck	LB-180400KF	HKE-054	Dec. 27, 2019
Preamplifier	Schwarzbeck	BBV 9743	HKE-006	Dec. 27, 2019
High pass filter unit	Tonscend	JS0806-F	HKE-055	Dec. 27, 2019
Antenna Mast	Keleto	CC-A-4M	N/A	N/A
Position controller	Taiwan MF	MF7802	HKE-011	Dec. 27, 2019
Radiated test software	Tonscend	TS+ Rev 2.5.0.0	HKE-082	N/A
RF Cable(below1GHz)	Times	9kHz-1GHz	HKE-117	Dec. 27, 2019
RF Cable(above 1GHz)	Times	1-40G	HKE-034	Dec. 27, 2019


**Note:** The calibration interval of the above test instruments is 12 months and the calibrations are traceable to international system unit (SI).



### Test Data

Please refer to following diagram for individual  
Below 1GHz

### Horizontal




Suspected List								
NO.	Freq. [MHz]	Level [dBµV/m]	Factor [dB]	Limit [dBµV/m]	Margin [dB]	Height [cm]	Angle [°]	Polarity
1	89.1700	29.46	-17.27	43.50	14.04	100	277	Horizontal
2	171.620	20.92	-17.23	43.50	22.58	100	98	Horizontal
3	201.690	29.07	-15.02	43.50	14.43	100	82	Horizontal
4	267.650	28.86	-13.63	46.00	17.14	100	271	Horizontal
5	375.320	25.16	-10.91	46.00	20.84	100	69	Horizontal
6	674.080	30.05	-4.69	46.00	15.95	100	296	Horizontal

Remark: Transd = Cable lose + Antenna factor - Pre-amplifier; Margin = Limit – Level



**Vertical**



Suspected List								
NO.	Freq. [MHz]	Level [dBµV/m]	Factor [dB]	Limit [dBµV/m]	Margin [dB]	Height [cm]	Angle [°]	Polarity
1	100.810	24.85	-15.40	43.50	18.65	100	281	Vertical
2	170.650	29.62	-17.27	43.50	13.88	100	240	Vertical
3	200.720	28.77	-15.04	43.50	14.73	100	34	Vertical
4	248.250	24.62	-13.47	46.00	21.38	100	213	Vertical
5	378.230	23.74	-10.86	46.00	22.26	100	138	Vertical
6	671.170	28.93	-4.60	46.00	17.07	100	143	Vertical

Remark: Transd = Cable lose + Antenna factor - Pre-amplifier; Margin = Limit – Level

**Above 1GHz****RADIATED EMISSION TEST**

LOW CH1 (802.11b Mode)/2412

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4824	62.45	-3.64	58.81	74	-15.19	peak
4824	46.86	-3.64	43.22	54	-10.78	AVG
7236	57.85	-0.95	56.9	74	-17.1	peak
7236	44.67	-0.95	43.72	54	-10.28	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4824	63.45	-3.64	59.81	74	-14.19	peak
4824	47.68	-3.64	44.04	54	-9.96	AVG
7236	56.59	-0.95	55.64	74	-18.36	peak
7236	44.1	-0.95	43.15	54	-10.85	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.



MID CH6 (802.11b Mode)/2437

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4874	61.36	-3.51	57.85	74	-16.15	peak
4874	45.35	-3.51	41.84	54	-12.16	AVG
7311	57.88	-0.82	57.06	74	-16.94	peak
7311	47.46	-0.82	46.64	54	-7.36	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4874	65.37	-3.51	61.86	74	-12.14	peak
4874	47.27	-3.51	43.76	54	-10.24	AVG
7311	58.18	-0.82	57.36	74	-16.64	peak
7311	46.66	-0.82	45.84	54	-8.16	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.



## HIGH CH11 (802.11b Mode)/2462

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4924	65.57	-3.43	62.14	74	-11.86	peak
4924	46.47	-3.43	43.04	54	-10.96	AVG
7386	58.68	-0.75	57.93	74	-16.07	peak
7386	43.47	-0.75	42.72	54	-11.28	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4924	63.38	-3.43	59.95	74	-14.05	peak
4924	46.46	-3.43	43.03	54	-10.97	AVG
7386	54.72	-0.75	53.97	74	-20.03	peak
7386	41.54	-0.75	40.79	54	-13.21	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Remark:

- (1) Measuring frequencies from 1 GHz to the 25 GHz.
- (2) "F" denotes fundamental frequency; "H" denotes spurious frequency. "E" denotes bandedge frequency.
- (3) \* denotes emission frequency which appearing within the Restricted Bands specified in provision of 15.205, then the general radiated emission limits in 15.209 apply.
- (4) Data of measurement within this frequency range shown "---" in the table above means the reading of emissions are attenuated more than 20dB below the permissible limits or the field strength is too small to be measured.
- (5) The IF bandwidth of EMI Test Receiver between 30MHz to 1GHz was 120KHz, 1 MHz for measuring above 1 GHz, below 30MHz was 10KHz.
- (6) When the test results of Peak Detected below the limits of Average Detected, the Average Detected is not need completed. For example: Top Channel at Fundamental 73.16dB $\mu$ V/m(PK Value) < 93.98(AV Limit), at harmonic 53.20 dB $\mu$ V/m(PK Value) < 54dB $\mu$ V/m(AV Limit), the Average Detected not need to completed.



## LOW CH1 (802.11g Mode)/2412

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4824	63.32	-3.64	59.68	74	-14.32	peak
4824	49.71	-3.64	46.07	54	-7.93	AVG
7236	56.38	-0.95	55.43	74	-18.57	peak
7236	42.52	-0.95	41.57	54	-12.43	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4824	58.79	-3.64	55.15	74	-18.85	peak
4824	46.45	-3.64	42.81	54	-11.19	AVG
7236	56.38	-0.95	55.43	74	-18.57	peak
7236	42.11	-0.95	41.16	54	-12.84	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.





MID CH6 (802.11g Mode)/2437

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4874	62.85	-3.51	59.34	74	-14.66	peak
4874	44.65	-3.51	41.14	54	-12.86	AVG
7311	57.75	-0.82	56.93	74	-17.07	peak
7311	45.63	-0.82	44.81	54	-9.19	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4874	61.74	-3.51	58.23	74	-15.77	peak
4874	46.35	-3.51	42.84	54	-11.16	AVG
7311	57.75	-0.82	56.93	74	-17.07	peak
7311	44.38	-0.82	43.56	54	-10.44	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.



## HIGH CH11 (802.11g Mode)/2462

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4924	61.68	-3.43	58.25	74	-15.75	peak
4924	47.47	-3.43	44.04	54	-9.96	AVG
7386	56.35	-0.75	55.6	74	-18.4	peak
7386	41.37	-0.75	40.62	54	-13.38	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4924	57.45	-3.43	54.02	74	-19.98	peak
4924	47.67	-3.43	44.24	54	-9.76	AVG
7386	56.21	-0.75	55.46	74	-18.54	peak
7386	38.57	-0.75	37.82	54	-16.18	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Remark:

- (1) Measuring frequencies from 1 GHz to the 25 GHz.
- (2) "F" denotes fundamental frequency; "H" denotes spurious frequency. "E" denotes bandedge frequency.
- (3) \* denotes emission frequency which appearing within the Restricted Bands specified in provision of 15.205, then the general radiated emission limits in 15.209 apply.
- (4) Data of measurement within this frequency range shown "---" in the table above mean the reading of emissions are attenuated more than 20dB below the permissible limits or the field strength is too small to be measured.
- (5) The IF bandwidth of EMI Test Receiver between 30MHz to 1GHz was 120KHz, 1 MHz for measuring above 1 GHz, below 30MHz was 10KHz.
- (6) When the test results of Peak Detected below the limits of Average Detected, the Average Detected is not need completed. For example: Top Channel at Fundamental 73.16dBuV/m(PK Value) <93.98(AV Limit), at harmonic 53.20 dBuV/m(PK Value) <54dBuV/m(AV Limit), the Average Detected not need to completed.



LOW CH1 (802.11n/H20 Mode)/2412

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4824	63.87	-3.64	60.23	74	-13.77	peak
4824	44.35	-3.64	40.71	54	-13.29	AVG
7236	55.14	-0.95	54.19	74	-19.81	peak
7236	42.35	-0.95	41.4	54	-12.6	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4824	62.45	-3.64	58.81	74	-15.19	peak
4824	46.53	-3.64	42.89	54	-11.11	AVG
7236	58.91	-0.95	57.96	74	-16.04	peak
7236	44.38	-0.95	43.43	54	-10.57	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.



MID CH6 (802.11n/H20 Mode)/2437

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4874	57.62	-3.51	54.11	74.00	-19.89	peak
4874	48.90	-3.51	45.39	54.00	-8.61	AVG
7311	55.20	-0.82	54.38	74.00	-19.62	peak
7311	44.39	-0.82	43.57	54.00	-10.43	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4874	60.28	-3.51	56.77	74.00	-17.23	peak
4874	45.80	-3.51	42.29	54.00	-11.71	AVG
7311	55.42	-0.82	54.60	74.00	-19.40	peak
7311	38.25	-0.82	37.43	54.00	-16.57	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.



## HIGH CH11 (802.11n/H20 Mode)/2462

Horizontal:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4924	63.49	-3.43	60.06	74	-13.94	peak
4924	45.23	-3.43	41.8	54	-12.2	AVG
7386	55.8	-0.75	55.05	74	-18.95	peak
7386	37.94	-0.75	37.19	54	-16.81	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
4924	62.79	-3.43	59.36	74	-14.64	peak
4924	45.72	-3.43	42.29	54	-11.71	AVG
7386	56.69	-0.75	55.94	74	-18.06	peak
7386	45.34	-0.75	44.59	54	-9.41	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

**Test Result of Radiated Spurious at Band edges**

Operation Mode:  
802.11b Mode TX CH Low (2412MHz)

## Horizontal

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2310.00	55.85	-5.81	50.04	74	-23.96	peak
2310.00	46.36	-5.81	40.55	54	-13.45	AVG
2390.00	61.2	-5.84	55.36	74	-18.64	peak
2390.00	52.71	-5.84	46.87	54	-7.13	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

## Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2310.00	56.93	-5.81	51.12	74	-22.88	peak
2310.00	48.64	-5.81	42.83	54	-11.17	AVG
2390.00	63.42	-5.84	57.58	74	-16.42	peak
2390.00	47.71	-5.84	41.87	54	-12.13	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.



Operation Mode: TX CH High (2462MHz)

Horizontal

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2483.50	58.44	-5.81	52.63	74	-21.37	peak
2483.50	49.26	-5.81	43.45	54	-10.55	AVG
2500.00	56.82	-6.06	50.76	74	-23.24	peak
2500.00	47.55	-6.06	41.49	54	-12.51	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2483.50	57.32	-5.81	51.51	74	-22.49	peak
2483.50	48.57	-5.81	42.76	54	-11.24	AVG
2500.00	55.81	-6.06	49.75	74	-24.25	peak
2500.00	46.58	-6.06	40.52	54	-13.48	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.



Operation Mode: 802.11g Mode TX CH Low (2412MHz)

Horizontal

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2310.00	59.21	-5.81	53.4	74	-20.6	peak
2310.00	46.24	-5.81	40.43	54	-13.57	AVG
2390.00	61.73	-5.84	55.89	74	-18.11	peak
2390.00	47.91	-5.84	42.07	54	-11.93	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2310.00	57.83	-5.81	52.02	74	-21.98	peak
2310.00	47.58	-5.81	41.77	54	-12.23	AVG
2390.00	63.26	-5.84	57.42	74	-16.58	peak
2390.00	48.93	-5.84	43.09	54	-10.91	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.





Operation Mode: TX CH High (2462MHz)

Horizontal

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2483.50	57.43	-5.65	51.78	74	-22.22	peak
2483.50	48.22	-5.65	42.57	54	-11.43	AVG
2500.00	55.75	-5.65	50.1	74	-23.9	peak
2500.00	45.25	-5.65	39.6	54	-14.4	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2483.50	56.23	-5.65	50.58	74	-23.42	peak
2483.50	47.24	-5.65	41.59	54	-12.41	AVG
2500.00	54.51	-5.65	48.86	74	-25.14	peak
2500.00	45.2	-5.65	39.55	54	-14.45	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.



Operation Mode: 802.11n/H20 Mode TX CH Low (2412MHz)

## Horizontal

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2310.00	58.34	-5.81	52.53	74	-21.47	peak
2310.00	47.48	-5.81	41.67	54	-12.33	AVG
2390.00	60.83	-5.84	54.99	74	-19.01	peak
2390.00	48.68	-5.84	42.84	54	-11.16	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.

## Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2310.00	56.45	-5.81	50.64	74	-23.36	peak
2310.00	45.95	-5.81	40.14	54	-13.86	AVG
2390.00	60.07	-5.84	54.23	74	-19.77	peak
2390.00	47.64	-5.84	41.8	54	-12.2	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.



Operation Mode: TX CH High (2462MHz)

Horizontal

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2483.50	58.75	-5.65	53.1	74	-20.9	peak
2483.50	48.78	-5.65	43.13	54	-10.87	AVG
2500.00	52.71	-5.65	47.06	74	-26.94	peak
2500.00	45.35	-5.65	39.7	54	-14.3	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.						

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dB $\mu$ V)	(dB)	(dB $\mu$ V/m)	(dB $\mu$ V/m)	(dB)	
2483.50	55.38	-5.65	49.73	74	-24.27	peak
2483.50	46.45	-5.65	40.8	54	-13.2	AVG
2500.00	52.57	-5.65	46.92	74	-27.08	peak
2500.00	43.38	-5.65	37.73	54	-16.27	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier.						
Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.						

## 4.8. ANTENNA REQUIREMENT

### Standard Applicable

For intentional device, according to FCC 47 CFR Section 15.203, an intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. And according to FCC 47 CFR Section 15.247, if transmitting antennas of directional gain greater than 6dBi are used, the power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6dBi.

### Refer to statement below for compliance.

The manufacturer may design the unit so that the user can replace a broken antenna, but the use of a standard antenna jack or electrical connector is prohibited. Further, this requirement does not apply to intentional radiators that must be professionally installed.

### Antenna Connected Construction


The antenna used in this product is a internal Antenna, The directional gains of antenna used for transmitting is 1.3dBi.

### WIFI ANTENNA



## 4.9. PHOTOGRAPH OF TEST

Radiated Emission





### Conducted Emission





#### **4.10. PHOTOS OF THE EUT**

Reference to the reporter : ANNEX A of external photos and ANNEX B of internal photos