



FCC 47 CFR § 2.1093  
IEC TR 63170-2018

**POWER DENSITY EVALUATION REPORT  
(Part 1 : Test in Static Transmission Condition)**

**FOR**

**GSM/WCDMA/LTE/5G NR Phone + BT/BLE, DTS/UNII a/b/g/n/ac/ax, NFC, WPT and UWB**

**MODEL NUMBER: SM-F946U, SM-F946U1**

**FCC ID: A3LSMF946U**

**REPORT NUMBER: 4790748041-S3V2**

**ISSUE DATE: 5/19/2023**

*Prepared for*  
**SAMSUNG ELECTRONICS CO., LTD.  
129 SAMSUNG-RO, YEONGTONG-GU, SUWON-SI,  
GYEONGGI-DO, 16677, KOREA**

*Prepared by*  
**UL KOREA, LTD.  
26TH FLOOR, 152, TEHERAN-RO, GANGNAM-GU SEOUL, 06236, KOREA**

**SUWON TEST SITE: UL KOREA, LTD. SUWON LABORATORY  
218 MAEYEONG-RO, YEONGTONG-GU,  
SUWON-SI, GYEONGGI-DO, 16675, KOREA  
TEL: (031) 337-9902  
FAX: (031) 213-5433**



**Testing Laboratory**

**TL-637**

**Revision History**

Rev.	Date	Revisions	Revised By
V1	5/15/2023	Initial Issue	--
V2	5/19/2023	Revised input power limit in Sec 7.5 Revised in Sec 8.2	Jeongyeon Won

## Table of Contents

<b>1.</b>	<b>Attestation of Test Results .....</b>	<b>5</b>
<b>2.</b>	<b>Introduction .....</b>	<b>6</b>
<b>3.</b>	<b>Measurement setup and General Information .....</b>	<b>7</b>
3.1.	<i>Power density measurement system .....</i>	<i>7</i>
3.1.1.	<i>Power density probe .....</i>	<i>7</i>
3.1.2.	<i>Power density measurement system verification.....</i>	<i>7</i>
3.2.	<i>Test Specification, Methods and Procedures .....</i>	<i>8</i>
3.3.	<i>Test Specification, Methods and Procedures .....</i>	<i>8</i>
<b>4.</b>	<b>Test Condition, Configuration, and Assessment .....</b>	<b>8</b>
4.1.	<i>Qualcomm Smart Transmit parameters .....</i>	<i>8</i>
4.2.	<i>Qualcomm Smart Transmit parameters for the 5G mmW NR .....</i>	<i>9</i>
<b>5.</b>	<b>Measurement System &amp; Test Equipment.....</b>	<b>9</b>
5.1.	<i>Measurement System.....</i>	<i>9</i>
5.2.	<i>EUmmWVx / 5G Probe E-Field mm-Wave Probe for General Near-Field Measurements .....</i>	<i>10</i>
5.3.	<i>Data Acquisition Electronics(DAE).....</i>	<i>10</i>
<b>6.</b>	<b>Measurement Procedures.....</b>	<b>11</b>
6.1.	<i>System Verification Scan Procedures .....</i>	<i>11</i>
6.2.	<i>Scan Procedures .....</i>	<i>11</i>
6.3.	<i>Total Field and Power Flux Density Reconstruction(measurement distance) .....</i>	<i>12</i>
6.4.	<i>Test Equipment.....</i>	<i>12</i>
6.5.	<i>Measurement Uncertainty.....</i>	<i>13</i>
6.6.	<i>DECISION RULE.....</i>	<i>13</i>
<b>7.</b>	<b>DUT Information .....</b>	<b>14</b>
7.1.	<i>DUT Description .....</i>	<i>14</i>
7.2.	<i>Wireless Technologies.....</i>	<i>14</i>
7.3.	<i>5G NR mmWave Test and Reporting Considerations .....</i>	<i>14</i>
7.4.	<i>Time-Averaging Algorithm for RF Exposure Compliance .....</i>	<i>15</i>
7.5.	<i>Input Power Limit.....</i>	<i>16</i>
<b>8.</b>	<b>RF Exposure Conditions (Test Configurations).....</b>	<b>22</b>
8.1.	<i>Operating mode(s).....</i>	<i>22</i>
8.2.	<i>Measurement position(s) .....</i>	<i>22</i>
<b>9.</b>	<b>Dielectric Property &amp; System Check.....</b>	<b>23</b>
9.1.	<i>Dielectric Property .....</i>	<i>23</i>
9.2.	<i>System Check.....</i>	<i>23</i>

**10. Measured and Reported (Scaled) Results ..... 24**

10.1. NR Band n258 - Closed Test Results ..... 24

10.2. NR Band n258 - Open Test Results ..... 24

10.3. NR Band n261 - Closed Test Results ..... 25

10.4. NR Band n261 - Open Test Results ..... 25

10.5. NR Band n260 - Closed Test Results ..... 26

10.6. NR Band n260 - Open Test Results ..... 26

**11. Simultaneous Transmission Conditions ..... 27**

11.1. 5G mmW NR psPD for TER Ratio analysis ..... 29

11.2. 5G mmW NR Phablet Total Exposure Ratio ..... 30

**Appendixes ..... 32**

4790748041-S3 FCC Report PD\_App A\_Setup Photos ..... 32


4790748041-S3 FCC Report PD\_App B\_System Check Plots ..... 32

4790748041-S3 FCC Report PD\_App C\_Highest Test Plots ..... 32

4790748041-S3 FCC Report PD\_App D\_Probe Calibration Certificates ..... 32

4790748041-S3 FCC Report PD\_App E\_Verification source Calibration Certificates ..... 32

### 1. Attestation of Test Results

Applicant Name	SAMSUNG ELECTRONICS CO.,LTD.	
FCC ID	A3LSMF946U	
Model Name	SM-F946U, SM-F946U1	
Applicable Standards	FCC 47 CFR § 2.1093 IEC TR 63170-2018	
Exposure Category	RADIOFREQUENCY RADIATION EXPOSURE (above 6GHz)	
	Power density Uncontrol (mW/cm <sup>2</sup> over 4cm <sup>2</sup> ) for 30min average	
fGeneral population / Uncontrolled exposure	1.0	
Applicable limit	<input checked="" type="checkbox"/> Uncontrol	
	Measured psPD	Reported psPD
n258 Result (mW/cm <sup>2</sup> over 4cm <sup>2</sup> )	0.55	0.98
n261 Result (mW/cm <sup>2</sup> over 4cm <sup>2</sup> )	0.51	0.98
n260 Result (mW/cm <sup>2</sup> over 4cm <sup>2</sup> )	0.48	0.98
Simultaneous TX	0.98	
Date Tested	4/20/2023 to 5/10/2023	
Test Results	Pass	
<p>UL Korea, Ltd. tested the above equipment in accordance with the requirements set forth in the above standards. All indications of Pass/Fail in this report are opinions expressed by UL Korea, Ltd. based on interpretations and/or observations of test results. Measurement Uncertainties were not taken into account and are published for informational purposes only. The test results show that the equipment tested is capable of demonstrating compliance with the requirements as documented in this report.</p> <p><b>Note:</b> The results documented in this report apply only to the tested sample, under the conditions and modes of operation as described herein. This document may not be altered or revised in any way unless done so by UL Korea, Ltd. and all revisions are duly noted in the revisions section. Any alteration of this document not carried out by UL Korea, Ltd. will constitute fraud and shall nullify the document. This report must not be used by the client to claim product certification, approval, or endorsement by IAS, any agency of the Federal Government, or any agency of any government. This report is written to support regulatory compliance of the applicable standards stated above.</p>		
Approved & Released By:	Prepared By:	
		
Justin Park Operations Leader UL Korea, Ltd. Suwon Laboratory	Jeongyeon Won Laboratory Engineer UL Korea, Ltd. Suwon Laboratory	

## 2. Introduction

The equipment under test (EUT) is a Phone, model SM-F946U (FCC ID: A3LSMF946U), it contains Qualcomm modems supporting 2G/3G/4/5G technologies and WLAN bands(with BT). These WWAN and WLAN(with BT) modems enable Qualcomm Smart Transmit features with algorithms to control and manage transmitting power in real time and to ensure at all times the time-averaged RF exposure from WWAN and WLAN(with BT) is in compliance with FCC requirements.

The purpose of this Part 1 report is to demonstrate that this EUT complies with FCC RF exposure limits at maximum time-averaged transmit power limits for WWAN technologies, and at maximum time-averaged transmit power limits for WLAN(with BT) technologies.

- Power density (PD) compliance for all WWAN radios (4G + 5G mmW NR) is assessed based on maximum time-averaged transmit power (static transmission condition). Relevant FCC KDBs and exclusion criteria are applied on a time-average power basis for WWAN technologies. The maximum time-averaged transmit power limits for supported WWAN technologies, bands, and antennas in this report are derived in Part 0 report.
- The validation of the Qualcomm Smart Transmit time-averaging algorithm and compliance under the Tx varying transmission scenario for WWAN and WLAN(with BT) technologies are reported in Part 2 report.
- Demonstrate compliance in simultaneous transmission scenarios involving both WWAN and WLAN(with BT) transmissions, where WWAN and WLAN(with BT) exposure is assessed based on time-averaged transmit power limits, and UWB and NFC exposure is assessed separately.

By following the above steps, this report demonstrates that this EUT complies with FCC RF exposure limits for FCC equipment authorization of FCC ID: A3LSMF946U.

The *input.power.limit* used in this report are determined and listed in Part 0 report.

Refer to compliance Summary report for product description and terminology used in this report.

### 3. Measurement setup and General Information

The SAR measurement are recorded in UL FCC Report\_SAR\_Part.1 (Report No. 4790748041-S1). This section provides the detail of the test setup used for PD measurement.

#### 3.1. Power density measurement system

The power density measurement system is constructed based on the DASY6 platform by SPEAG. The DASY6 with EummWV2 and 5G software module can measure the RF exposure (power density) up to 110GHz as close as 2mm from any transmitter.

##### 3.1.1. Power density probe

The EummWV2 probe is used in the power density measurement. It is designed for precise near-field measurements in the mm-wave range by Schmid & Partner Engineering AG of Zurich, Switzerland. The specifications are:

- Frequency range: 0.75 ~ 110 GHz
- Dynamic range: <50 – 3000 V/m (up to 10000 V/m with additional PRE-10 voltage divider)
- Linearity: < ±0.2 dB
- Supports sensor model calibration (SMC)
- ISO 17025 accredited calibration

##### 3.1.2. Power density measurement system verification

The power density system verification is performed using the SPEAG verification device. It consists of a ka-band horn antenna with a corresponding gun oscillator packaged within a cube-shaped housing.

The specification of the verification device is:

- Calibrated frequency: 30GHz at 10 mm from the case surface
- Frequency accuracy: ± 100MHz
- E-field polarization: linear
- Harmonics: -20 dBc (typ)
- Total radiated power: 14 dBm (typ)
- Power stability: 0.05 dB
- Power consumption: 5 W (max)
- Size: 100 x 100 x 100 mm
- Weight: 1kg

Table 2-1 shows the verification test results. The measured power density (PD) value is within 10% of target level. Note that the uncertainty of 5G verification source is 1.4dB (k=2).

### 3.2. Test Specification, Methods and Procedures

#### Test Specification, Methods and Procedures

The tests documented in this report were performed in accordance with FCC 47 CFR § 2.1093, the following FCC Published RF exposure KDB procedures:

- 447498 D01 General RF Exposure Guidance v06
- 447498 D03 Supplement C Cross-Reference v01
- 865664 D01 SAR measurement 100 MHz to 6 GHz v01r04
- 865664 D02 RF Exposure Reporting v01r02
- SPEAG, 5G Module V1.2 Application Note: 5G Compliance Testing, August 2018
- IEC TR 63170 Edition 1.0 2018-08

In addition to the above, [TCB workshop](#) information was used.

- [TCB workshop](#) November, 2017; Page 19 - 25, RF Exposure Procedures (Power Density Evaluation)
- [TCB workshop](#) October, 2018; Page 3, RF Exposure Procedures (Millimeter Wave Assessment)
- [TCB workshop](#) October, 2018; Page 5, RF Exposure Procedures (Millimeter Wave Measurement)
- [TCB workshop](#) April, 2019; Page 3, RF Exposure Procedures (Millimeter Wave RF Exposure Evaluation)
- [TCB workshop](#) November, 2019; Page 14, RF Exposure Procedures (Millimeter Wave Scan Requirements)

### 3.3. Test Specification, Methods and Procedures

The test sites and measurement facilities used to collect data are located at

Suwon
SAR 8
SAR 9

UL Korea, Ltd. is accredited by IAS, Laboratory Code TL-637.

The full scope of accreditation can be viewed at :

<https://www.iasonline.org/wp-content/uploads/2017/05/TL-637-cert-New.pdf>.

## 4. Test Condition, Configuration, and Assessment

### 4.1. Qualcomm Smart Transmit parameters

The input parameters described are required for functionality of Qualcomm Smart Transmit algorithm.

These parameters are entered through the *Embedded File System* (EFS) and cannot be accessed by the end-user.

Part 0 report documents determination of  $P_{limit}$  for sub-6 WWAN bands, and *input.power.limit* for 5G mmW NR bands using the below design targets and device related uncertainty:

- *SAR\_design\_target* of 1.0 W/kg for 1g SAR and sub-6 WWAN device design related uncertainty of 1.0 dB.
- *PD\_design\_target* of 0.631 mW/cm<sup>2</sup> 4cm<sup>2</sup>PD and mmW device design related uncertainty of 2.0 dB.




## 4.2. Qualcomm Smart Transmit parameters for the 5G mmW NR

The input.power.limit parameter for 5G mmW NR radio determined in Section 8.5 of this report are populated via EFS entry into the EUT.

## 5. Measurement System & Test Equipment

### 5.1. Measurement System

The DASY6 & 8 system used for performing compliance tests consists of the following items:



- A standard high precision 6-axis robot with controller, teach pendant and software. An arm extension for accommodating the data acquisition electronics (DAE).
- The EUmmWVx probe is based on the pseudo-vector probe design, which not only measures the field magnitude but also derives its polarization ellipse.
- A data acquisition electronics (DAE) which performs the signal amplification, signal multiplexing, AD-conversion, offset measurements, mechanical surface detection, collision detection, etc. The unit is battery powered with standard or rechargeable batteries. The signal is optically transmitted to the EOC.
- The Electro-optical converter (EOC) performs the conversion from optical to electrical signals for the digital communication to the DAE. To use optical surface detection, a special version of the EOC is required. The EOC signal is transmitted to the measurement server.
- The function of the measurement server is to perform the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- The Light Beam used is for probe alignment. This improves the (absolute) accuracy of the probe positioning.
- A computer running Win10 and the DASY6 software.
- Remote control and teach pendant as well as additional circuitry for robot safety such as warning lamps, etc.
- The phantom which is specialized for 5G other accessories according to the targeted measurement.

## 5.2. EUmmWVx / 5G Probe

### E-Field mm-Wave Probe for General Near-Field Measurements



Frequency Range  
Dynamic Range  
Position Precision

Dimensions

Applications

Compatibility

Two dipoles optimally arranged to obtain pseudo-vector information  
Minimum 3 measurements/point, 120° rotated around probe axis  
Sensors (0.8mm length) printed on glass substrate protected by high density foam  
Low perturbation of the measured field  
Requires positioner which can do accurate probe rotation

750 MHz – 110 GHz  
< 20 V/m - 10'000 V/m with PRE-10 (min < 50 V/m - 3000 V/m)  
< 0.2 mm (DASY6)  
Overall length: 337 mm (tip: 20 mm)  
Tip diameter: encapsulation 8 mm (internal sensor < 1mm)  
Distance from probe tip to dipole centers: < 2 mm  
Sensor displacement to probe's calibration point: < 0.3 mm  
E-field measurements of 5G devices and other mm-wave transmitters operating above 10GHz in < 2 mm distance from device (free-space)  
Power density, H-field and far-field analysis using total field reconstruction (cDASY6 5G or ICEy-mmW module required)  
cDASY6 + 5G-Module SW1.0 and higher

## 5.3. Data Acquisition Electronics(DAE)



Measurement Range  
Input Offset Voltage  
Input Resistance  
Input Bias Current  
Battery Power  
Dimensions (L x W x H)

Serial optical link for communication with DASY4/5 embedded system (fully remote controlled) Two-step probe touch detector for mechanical surface detection and emergency robot stop

-100 – +300 mV (16 bit resolution and two range settings: 4 mV, 400 mV)  
<5 μV (with auto zero)  
200 Mohm  
<50 fA  
>10 hours of operation (with two 9.6 V NiMH batteries)  
60 x 60 x 68 mm

## 6. Measurement Procedures

### 6.1. System Verification Scan Procedures

cDASY6 5G Module V1.2 supports “5G Scan”, a fine resolution scan performed on two different planes which is used to reconstruct the E- and H-fields as well as the power density; the average power density is derived from this measurement.

#### Step 1: Power Reference Measurement

The Power Reference Measurement and Power Drift Measurements are for monitoring the power drift of the device under test in the batch process. The minimum distance of probe sensors to surface determines the closest measurement point to device under test.

#### Step 2: 5G Scan

The steps in the X, Y, and Z directions are specified in terms of fractions of the signal wavelength,  $\lambda$ . Area Scan Parameters extracted from SPEAG, 5G Module V1.2 Application Note.

#### Recommended settings for measurement of verification sources

Frequency [GHz]	Grid step	Grid extent X/Y [mm]	Measurement points
10	0.125 ( $\frac{\lambda}{8}$ )	60/60	18 × 18
30	0.25 ( $\frac{\lambda}{4}$ )	60/60	26 × 26
45	0.25 ( $\frac{\lambda}{4}$ )	42/42	28 × 28
60	0.25 ( $\frac{\lambda}{4}$ )	32.5/32.5	28 × 28
90	0.25 ( $\frac{\lambda}{4}$ )	30/30	38 × 38

The minimum distance of probe sensors to verification source surface, horn antenna, is 10 mm.

In other case, distance is determined as  $\lambda / 5$ , details are shown in section 6.3.

#### Step 3: Power drift measurement

The Power Drift Measurement measures the field at the same location as the most recent power reference measurement within the same procedure, and with the same settings. The Power Drift Measurement gives the field difference in dB from the reading conducted within the last Power Reference Measurement. This allows a user to monitor the power drift of the device under test within a batch process. The measurement procedure is the same as Step 1.

When the drift is larger than  $\pm 5\%$ , test is repeated from step1.

### 6.2. Scan Procedures

#### Step 1: Power Reference Measurement

Same as System Verification Scan Procedures step 1.

#### Step 2: 5G Scan

Same as System Verification Scan Procedures step 2. But measurement area is defined based on TCB workshop “A sufficiently large measurement region and proper measurement spatial resolution are required to maintain field reconstruction accuracy”.

#### Step 3: Power drift measurement


Same as System Verification Scan Procedures step 3.

When the drift is smaller than  $\pm 5\%$ , it is considered in the uncertainty budget if drifts larger than 5%, uncertainty is re-calculate.

### 6.3. Total Field and Power Flux Density Reconstruction(measurement distance)

Reconstruction algorithms are used to project or transform the measured fields from the measurement surface to the evaluation surface (below fig) in order to determine power density or to compute spatial-average and/or local power density with known uncertainty.

Manufacture has developed a reconstruction approach based on the Gerchberg-Saxton algorithm, which benefits from the availability of the E-field polarization ellipse information obtained with the EummWVx probe. This reconstruction algorithm, together with the ability of the probe to measure extremely close to the source without perturbing the field, permits reconstruction of the E- and H-fields, as well as of the power density, on measurement planes located as near as  $\lambda / 5$  away.



### 6.4. Test Equipment

The measuring equipment used to perform the tests documented in this report has been calibrated in accordance with the manufacturers' recommendations, and is traceable to recognized national standards.

#### System Check

Name of Equipment	Manufacturer	Type/Model	Serial No.	Cal. Due Date
5G probe	SPEAG	EummWV4	9493	1/31/2024
5G probe	SPEAG	EummWV4	9536	2/16/2024
Data Acquisition Electronics	SPEAG	DAE4	1468	8/18/2023
Data Acquisition Electronics	SPEAG	DAE4	1670	6/7/2023
Data Acquisition Electronics	SPEAG	DAE4	1668	<b>4/27/2023</b>
Data Acquisition Electronics	SPEAG	DAE4	1343	8/18/2023
Verification kit	SPEAG	5G verification source_30GHz	1047	1/31/2024
Thermometer	Lutron	MHB-382SD	AK.12102	8/9/2023

## 6.5. Measurement Uncertainty

Measurement Uncertainty for cDASY6 Module mmWave						
Error Description	Uncertainty value ( $\pm$ dB)	Probe Dist.	Divisor	(Ci)	Std. Unc. ( $\pm$ dB)	(Vi)
<b>Uncertainty terms dependent on the measurement system</b>						
1.Probe Calibration	0.49	Normal	1	1	0.49	Infinity
2.Probe correction	0.00	Rectangular	1.73	1	0.00	Infinity
3.Frequency response (BW =< 1 GHz)	0.20	Rectangular	1.73	1	0.12	Infinity
4.Sensor cross coupling	0.00	Rectangular	1.73	1	0.00	Infinity
5.Isotropy	0.50	Rectangular	1.73	1	0.29	Infinity
6.Linearity	0.20	Rectangular	1.73	1	0.12	Infinity
7.Probe scattering	0.00	Rectangular	1.73	1	0.00	Infinity
8.Probe positioning offset	0.30	Rectangular	1.73	1	0.17	Infinity
9.Probe positioning repeatability	0.04	Rectangular	1.73	1	0.02	Infinity
10.Sensor mechanical offset	0.00	Rectangular	1.73	1	0.00	Infinity
11.Probe spatial resolution	0.00	Rectangular	1.73	1	0.00	Infinity
12.Field impedance dependance	0.00	Rectangular	1.73	1	0.00	Infinity
13.Amplitude and phase drift	0.00	Rectangular	1.73	1	0.00	Infinity
14.Amplitude and phase noise	0.04	Rectangular	1.73	1	0.02	Infinity
15.Measurement area truncation	0.10	Rectangular	1.73	1	0.06	Infinity
16.Data acquisition	0.03	Normal	1.00	1	0.03	Infinity
17.Sampling	0.00	Rectangular	1.73	1	0.00	Infinity
18.Field reconstruction	0.60	Rectangular	1.73	1	0.35	Infinity
19.Forward transformation	0.00	Rectangular	1.73	1	0.00	Infinity
20.Power density scaling	-	Rectangular	1.73	1	-	Infinity
21.Spatial averaging	0.10	Rectangular	1.73	1	0.06	Infinity
22.System detection limit	0.04	Rectangular	1.73	1	0.02	Infinity
<b>Uncertainty terms dependent on the DUT and environmental factors</b>						
23.Probe coupling with DUT	0.00	Rectangular	1.73	1	0.00	Infinity
24.Modulation response	0.40	Rectangular	1.73	1	0.23	Infinity
25.Integration time	0.00	Rectangular	1.73	1	0.00	Infinity
26.Response time	0.00	Rectangular	1.73	1	0.00	Infinity
27.Device holder influence	0.10	Rectangular	1.73	1	0.06	Infinity
28.DUT alignment	0.00	Rectangular	1.73	1	0.00	Infinity
29.RF ambient conditions	0.04	Rectangular	1.73	1	0.02	Infinity
30.Ambient reflections	0.04	Rectangular	1.73	1	0.02	Infinity
31.Immunity / secondary reception	0.00	Rectangular	1.73	1	0.00	Infinity
32.Drift of the DUT	0.22	Rectangular	1.73	1	0.13	Infinity
Combined Std. Uncertainty					0.76	Infinity
<b>Expanded Standard Uncertainty (95%)</b>					<b>1.53</b>	

## 6.6. DECISION RULE

Decision rule for statement(s) of conformity is based on Procedure 2, Clause 4.4.3 in IEC Guide 115:2021.

## 7. DUT Information

### 7.1. DUT Description

Device Dimension	Refer to Appendix A.		
Back Cover	The Back Cover is not removable		
Battery Options	The rechargeable battery is not user accessible.		
Test sample information	<b>No.</b>	<b>S/N</b>	<b>Notes</b>
	1	R3CW20P0NTK	mmWave Radiated
	2	73d3487155137eee	mmWave Radiated

### 7.2. Wireless Technologies

Wireless technologies	Frequency bands	Operating mode	Duty Cycle used for SAR testing
5G NR mmW	NR Band 258 (50MHz & 100MHz) NR Band 261 (50MHz & 100MHz) NR Band 260 (50MHz & 100MHz)	DFT-s-OFDM : QPSK, 16QAM, 64QAM CP-OFDM : QPSK, 16QAM, 64QAM	100%

### 7.3. 5G NR mmWave Test and Reporting Considerations

Item	Description		
Frequency range, Channel Bandwidth, Numbers and Frequencies	Band 258	Frequency range: 24250 – 27500 MHz	
		Channel Bandwidth	
		100MHz	
		50MHz	
		MHz / Channel	MHz / Channel
	Low	24350.04 / 2018333	24350.04 / 2018333
	Mid	24800.04 / 2025833	24800.04 / 2025833
	High	25200.00 / 2032499	25224.96 / 2032915
	Band 261	Frequency range: 27500 – 28350 MHz	
		Channel Bandwidth	
		100MHz	
		50MHz	
		MHz / Channel	MHz / Channel
	Low	27550.08 / 2071677	27525.00 / 2071249
	Mid	27924.96 / 2077915	27924.96 / 2077915
	High	28299.96 / 2084165	28324.92 / 2084581
Band 260	Frequency range: 37000 – 40000 MHz		
	Channel Bandwidth		
	100MHz		
	50MHz		
	MHz / Channel	MHz / Channel	
Low	37050.00 / 2229999	37026.00 / 2229599	
Mid	38499.96 / 2254165	38499.96 / 2254165	
High	39949.92 / 2278331	39975.00 / 2278749	
Sub carrier Spacing	120 kHz		
Total Number of Supported Uplink CCs (SISO)	4		
Total Number of Supported Uplink CCs (MIMO)	4		
Total Number of Supported DL CCs	8		
LTE Anchor Bands	n258 : B2 / 5 / 12 / 14 / 30 / 66, n261 : B2 / 4 / 5 / 12 / 13 / 48 / 66, n260 : B2 / 5 / 12 / 13 / 14 / 30 / 48 / 66		
NR FR1 Anchor Bands	n258 : B2 / 5 / 12 / 25 / 30 / 41 / 66 / 77, n261 : B2 / 5 / 25 / 41 / 48 / 66 / 77 n260 : B2 / 5 / 12 / 25 / 30 / 41 / 48 / 66 / 77		
Duplex Type (mmWave)	TDD		

## 7.4. Time-Averaging Algorithm for RF Exposure Compliance

The equipment under test(EUT) are supporting 3G/4G/5G NR and WLAN(with BT) technologies through Qualcomm® modem. Qualcomm® modem is enabled with Qualcomm® Smart Transmit feature. This feature performs time averaging algorithm in real time to control and manage transmitting power and ensure the time-averaged RF exposure is in compliance with FCC requirements all the time. Refer to Compliance Summary document for detailed description of Qualcomm® Smart Transmit feature.

The Smart Transmit algorithm maintains the time-averaged transmit power, in turn, time-averaged RF exposure of *SAR\_design\_target* or *PD\_design\_target*, below the predefined time-averaged power limit (i.e.,  $P_{limit}$  for sub-6 radio, and *input.power.limit* for 5G mmW NR), for each characterized technology and band. Smart Transmit allows the device to transmit at higher power instantaneously when needed. but manages power limiting to maintain time-averaged transmit power to *input.power.limit* listed in Section 8.5.

The purpose of this report (Part 1 test) is to demonstrate that the EUT meets FCC PD limits when transmitting in static transmission scenario at maximum allowable time-averaged power level given by *input.power.limit*.

### 7.5. Input Power Limit

All power density measurements for this device were performed at the *input.power.limit* given in below tables. Input power is per antenna element and polarization for each antenna module. When input power limit is calculated to be above the maximum input power, the device is limited to the maximum input power.

#### 5G NR n258 K Patch Input Power Limit

Antenna	Beam ID_1	Beam ID_2	input.power.limit (dBm)
K patch	0		11.7
	2		11.7
	4		12.7
	6		12.1
	8		12.6
	10		10.4
	11		8.9
	12		8.8
	13		9.0
	18		8.9
	19		9.2
	20		9.7
	24		5.4
	25		5.0
	26		4.6
	27		5.3
	28		5.3
	34		5.1
	35		5.4
	36		4.6
	37		6.0
	128		10.2
	130		9.6
	132		9.5
	134		9.5
	136		11.6
	138		7.2
	139		6.5
	140		5.9
	141		7.0
	146		6.9
	147		6.1
	148		5.8
	152		2.8
	153		2.6
	154		2.8
	155		2.0
156		1.2	
162		2.9	
163		3.0	
164		2.5	
165		1.2	
0	128		7.4
2	130		6.8
4	132		7.2
6	134		7.1
8	136		8.2
10	138		4.2
11	139		4.4
12	140		3.5
13	141		4.3
18	146		3.8
19	147		4.9
20	148		3.7
24	152		-0.8
25	153		-0.8
26	154		0.3
27	155		-0.1
28	156		-1.5
34	162		-0.5
35	163		0.3
36	164		0.0
37	165		-0.5



**5G NR n258 M Patch Input Power Limit**

Antenna	Beam ID_1	Beam ID_2	input.power.limit (dBm)
M patch	1		11.0
	3		10.6
	5		9.9
	7		11.0
	9		10.4
	14		8.3
	15		7.2
	16		7.4
	17		6.9
	21		7.6
	22		7.2
	23		6.4
	29		3.8
	30		3.0
	31		2.5
	32		2.6
	33		2.3
	38		3.2
	39		2.9
	40		2.4
	41		2.2
	129		10.1
	131		9.1
	133		9.8
	135		9.8
	137		10.7
	142		5.6
	143		5.6
	144		5.9
	145		7.0
	149		6.3
	150		5.7
	151		6.5
	157		1.6
	158		2.1
	159		2.3
	160		1.8
	161		2.0
	166		1.9
	167		2.2
	168		2.3
169		1.7	
1	129	6.4	
3	131	6.5	
5	133	6.6	
7	135	6.6	
9	137	7.6	
14	142	3.5	
15	143	2.9	
16	144	3.3	
17	145	4.0	
21	149	4.6	
22	150	3.7	
23	151	4.2	
29	157	-1.3	
30	158	-1.1	
31	159	-0.9	
32	160	-1.5	
33	161	-1.6	
38	166	-1.0	
39	167	-1.3	
40	168	-0.8	
41	169	-1.6	

**5G NR n261 K Patch Input Power Limit**

Antenna	Beam ID_1	Beam ID_2	input.power.limit (dBm)
K patch	0		11.5
	2		11.9
	4		11.8
	6		11.3
	8		13.6
	10		8.9
	11		7.9
	12		8.6
	13		9.1
	18		8.5
	19		8.4
	20		9.2
	24		4.6
	25		4.2
	26		4.1
	27		4.5
	28		6.4
	34		4.6
	35		4.4
	36		5.0
	37		4.8
	128		9.6
	130		8.7
	132		8.9
	134		8.6
	136		11.3
	138		6.8
	139		5.5
	140		5.5
	141		7.0
	146		6.3
	147		4.9
	148		5.4
	152		2.1
	153		2.0
	154		1.5
	155		1.3
156		1.5	
162		2.0	
163		1.8	
164		1.5	
165		1.2	
0	128	7.1	
2	130	6.6	
4	132	6.6	
6	134	6.5	
8	136	9.0	
10	138	4.0	
11	139	3.6	
12	140	3.8	
13	141	4.0	
18	146	3.9	
19	147	3.5	
20	148	4.3	
24	152	-0.6	
25	153	-0.4	
26	154	-0.5	
27	155	-1.1	
28	156	-0.8	
34	162	-0.6	
35	163	-0.2	
36	164	-0.5	
37	165	-1.4	

**5G NR n261 M Patch Input Power Limit**

Antenna	Beam ID_1	Beam ID_2	input.power.limit (dBm)
M patch	1		9.6
	3		9.3
	5		10.2
	7		10.4
	9		9.9
	14		6.8
	15		5.9
	16		6.8
	17		7.5
	21		6.1
	22		6.3
	23		7.1
	29		4.0
	30		3.4
	31		3.3
	32		3.5
	33		2.9
	38		3.6
	39		3.1
	40		3.2
	41		2.9
	129		11.3
	131		10.2
	133		9.9
	135		10.6
	137		11.4
	142		7.7
	143		6.3
	144		5.9
	145		8.0
	149		7.0
	150		6.2
	151		7.2
	157		3.2
	158		3.1
	159		2.7
	160		2.6
	161		2.9
	166		2.9
	167		3.0
	168		3.0
169		2.5	
1	129	7.7	
3	131	7.3	
5	133	7.3	
7	135	7.3	
9	137	7.6	
14	142	4.8	
15	143	3.5	
16	144	3.9	
17	145	5.6	
21	149	3.9	
22	150	4.0	
23	151	4.4	
29	157	1.0	
30	158	0.3	
31	159	0.5	
32	160	-0.2	
33	161	-0.5	
38	166	0.3	
39	167	0.3	
40	168	0.3	
41	169	-0.8	

**5G NR n260 K Patch Input Power Limit**

Antenna	Beam ID_1	Beam ID_2	input.power.limit (dBm)
K patch	0		11.4
	2		11.3
	4		10.7
	6		11.6
	8		11.4
	10		8.0
	11		7.3
	12		8.8
	13		8.2
	18		8.2
	19		8.2
	20		8.6
	24		3.7
	25		4.0
	26		4.3
	27		5.4
	28		5.2
	34		3.4
	35		4.3
	36		4.6
	37		5.4
	128		12.1
	130		11.1
	132		10.7
	134		11.2
	136		12.4
	138		7.9
	139		8.4
	140		8.4
	141		8.3
	146		8.7
	147		8.2
	148		8.7
	152		4.7
	153		4.7
	154		4.4
	155		5.3
156		4.5	
162		4.3	
163		5.3	
164		4.4	
165		4.2	
0	128	8.3	
2	130	8.0	
4	132	7.5	
6	134	8.0	
8	136	8.5	
10	138	5.1	
11	139	4.8	
12	140	5.4	
13	141	4.9	
18	146	5.5	
19	147	5.2	
20	148	6.5	
24	152	1.1	
25	153	1.1	
26	154	1.2	
27	155	1.5	
28	156	1.2	
34	162	1.2	
35	163	1.4	
36	164	1.3	
37	165	1.0	

**5G NR n260 M Patch Input Power Limit**

Antenna	Beam ID_1	Beam ID_2	input.power.limit (dBm)
M patch	1		11.3
	3		10.4
	5		9.5
	7		10.1
	9		10.6
	14		6.9
	15		7.3
	16		7.6
	17		8.0
	21		6.7
	22		7.7
	23		7.7
	29		3.9
	30		3.8
	31		3.6
	32		4.0
	33		4.5
	38		3.8
	39		3.5
	40		3.4
	41		4.6
	129		11.7
	131		10.4
	133		9.5
	135		9.9
	137		10.3
	142		6.8
	143		6.8
	144		6.8
	145		8.0
	149		6.5
	150		7.4
	151		6.8
	157		3.5
	158		3.7
	159		4.1
	160		3.0
	161		3.6
	166		4.0
	167		3.6
	168		4.1
169		3.7	
1	129	7.8	
3	131	7.2	
5	133	6.6	
7	135	7.0	
9	137	7.3	
14	142	3.7	
15	143	4.3	
16	144	4.3	
17	145	4.2	
21	149	3.5	
22	150	4.6	
23	151	3.6	
29	157	-0.2	
30	158	0.1	
31	159	0.8	
32	160	0.4	
33	161	0.0	
38	166	0.3	
39	167	0.2	
40	168	1.0	
41	169	0.3	

## 8. RF Exposure Conditions (Test Configurations)

### 8.1. Operating mode(s)

DUTs can transmit in operating modes and frequency bands using different signal characteristics (e.g. modulation, source coding, channel bandwidth, etc.) that require power density tests. The appropriate operating modes should be selected for testing taking into consideration differences in maximum output power and production variations, to ensure maximum power density is assessed.

Supported mode:

- |  |                                       |
|--|---------------------------------------|
| <input checked="" type="checkbox"/> CW | <input type="checkbox"/> D-QPSK       |
| <input type="checkbox"/> AM            | <input type="checkbox"/> QPSK         |
| <input type="checkbox"/> FMCW          | <input type="checkbox"/> Up to 16QAM  |
| <input type="checkbox"/> FM            | <input type="checkbox"/> Up to 64QAM  |
| <input type="checkbox"/> pi/2-BPSK     | <input type="checkbox"/> Up to 256QAM |
| <input type="checkbox"/> pi/2-QPSK     | <input type="checkbox"/> pi/2-16QAM   |

### 8.2. Measurement position(s)

Power density evaluated at worst-surfaces according to test results of Power density Part.0 report.

Band	Antenna	Folder Condition	Back Rear	Front	Top Edge 1	Bottom Edge 3	Left Edge 4	Right Edge 2
n258	K Patch	Closed	Yes	No	No	No	No	No
n258	M Patch	Closed	Yes	No	No	No	No	Yes
n261	K Patch	Closed	Yes	No	No	No	No	No
n261	M Patch	Closed	Yes	No	No	No	No	Yes
n260	K Patch	Closed	Yes	No	No	No	No	No
n260	M Patch	Closed	Yes	No	No	No	No	Yes
n258	K Patch	Open	Yes	No	No	No	No	No
n258	M Patch	Open	Yes	Yes	No	No	No	Yes
n261	K Patch	Open	Yes	No	No	No	No	No
n261	M Patch	Open	Yes	Yes	No	No	No	Yes
n260	K Patch	Open	Yes	No	No	No	No	No
n260	M Patch	Open	Yes	Yes	No	No	No	Yes

Please refer to Appendix A for Antenna's location.

## 9. Dielectric Property & System Check

### 9.1. Dielectric Property

Media is air so Relative Permittivity ( $\epsilon_r$ ) and Conductivity ( $\sigma$ ) is 1.

### 9.2. System Check

Per Nov 2017, TCB Workshop

System validation is required before a system is deployed for measurement

System check is also required before each series of continuous measurement and, as applicable, repeated at least weekly

Peak and spatially averaged power density at the peak location(s) must be compared to calibrated results according to the defined test conditions

- the same spatial resolution and measurement region used in the waveguide calibration should be applied to system validation and system check
- 4 cm<sup>2</sup> spatial averaging have been used according to FCC requirement.
- power density distribution should also be verified, both spatially (shape) and numerically (level) through visual inspection for noticeable differences
- the measured results should be within 10% of the calibrated targets

#### SAR 8 Room

SAR Lab	Date	Sorce SN	Sorce Cal. Due Data	Measured Total psPD for 4cm <sup>2</sup> (W/m <sup>2</sup> )	Target (Ref. Value) (W/m <sup>2</sup> )	Delta $\pm 10$ %	visual inspection	Plot No.
SAR 8	5/5/2023	1047	1/31/2024	65.8	71.6	-8.10	confirmed	
SAR 8	5/8/2023	1047	1/31/2024	64.9	71.6	-9.36	confirmed	1
SAR 8	5/9/2023	1047	1/31/2024	66.8	71.6	-6.70	confirmed	

#### SAR 9 Room

SAR Lab	Date	Sorce SN	Sorce Cal. Due Data	Measured Total psPD for 4cm <sup>2</sup> (W/m <sup>2</sup> )	Target (Ref. Value) (W/m <sup>2</sup> )	Delta $\pm 10$ %	visual inspection	Plot No.
SAR 9	4/20/2023	1047	1/31/2024	71.4	67.0	6.57	confirmed	
SAR 9	4/21/2023	1047	1/31/2024	71.6	67.0	6.87	confirmed	
SAR 9	4/25/2023	1047	1/31/2024	73.3	67.0	9.40	confirmed	
SAR 9	4/26/2023	1047	1/31/2024	73.0	67.0	8.96	confirmed	
SAR 9	4/27/2023	1047	1/31/2024	72.6	67.0	8.36	confirmed	
SAR 9	4/28/2023	1047	1/31/2024	72.9	67.0	8.81	confirmed	
SAR 9	5/1/2023	1047	1/31/2024	72.5	67.0	8.21	confirmed	
SAR 9	5/2/2023	1047	1/31/2024	72.2	67.0	7.76	confirmed	
SAR 9	5/3/2023	1047	1/31/2024	72.9	67.0	8.81	confirmed	
SAR 9	5/4/2023	1047	1/31/2024	73.3	67.0	9.40	confirmed	
SAR 9	5/8/2023	1047	1/31/2024	73.2	67.0	9.25	confirmed	
SAR 9	5/9/2023	1047	1/31/2024	73.0	67.0	8.96	confirmed	
SAR 9	5/10/2023	1047	1/31/2024	73.6	67.0	9.85	confirmed	2

#### Note(s):

psPD value used the  $pS_{tot}$  avg value of test result plot.

## 10. Measured and Reported (Scaled) Results

Both Normal psPD and Total psPD are record in test results according to TCB workshop October 2018 note . But Only Total psPD level are considered according to FCC requirement.

### 10.1. NR Band n258 - Closed Test Results

Antenna	Dist. (mm)	Test Position	Freq. (MHz)	Ch.	Beam ID1	Beam ID2	input.power.limit (dBm)	Tested Signal	Duty Cycle	Power Drift	Normal psPD (mW/cm <sup>2</sup> )	Total psPD (mW/cm <sup>2</sup> )	Plot No.
					V	H					Meas.	Meas.	
K patch	2 mm	Back	24800.04	Mid	26		4.6	CW	100.0%	-0.07	0.313	0.376	
	2 mm	Back	25200.00	High		165	1.2	CW	100.0%	0.02	0.323	0.415	
	2 mm	Back	25200.00	High	28	156	-1.5	CW	100.0%	-0.16	0.287	0.444	1
M patch	2 mm	Back	25200.00	High	39		2.9	CW	100.0%	-0.20	0.101	0.168	
	2 mm	Back	24800.04	Mid		169	1.7	CW	100.0%	0.04	0.178	0.216	
	2 mm	Right	25200.00	High	29		3.8	CW	100.0%	-0.05	0.353	<b>0.546</b>	2
	2 mm	Right	25200.00	High		157	1.6	CW	100.0%	-0.18	0.110	0.161	
	2 mm	Back	25200.00	High	29	157	-1.3	CW	100.0%	0.00	0.134	0.175	
	2 mm	Right	25200.00	High	29	157	-1.3	CW	100.0%	0.03	0.108	0.140	

(10 W/m<sup>2</sup> = 1.0 mW/cm<sup>2</sup>)

### 10.2. NR Band n258 - Open Test Results

Antenna	Dist. (mm)	Test Position	Freq. (MHz)	Ch.	Beam ID1	Beam ID2	input.power.limit (dBm)	Tested Signal	Duty Cycle	Power Drift	Normal psPD (mW/cm <sup>2</sup> )	Total psPD (mW/cm <sup>2</sup> )	Plot No.
					V	H					Meas.	Meas.	
K patch	2 mm	Back	25200.00	High	28		5.3	CW	100.0%	0.01	0.263	0.363	
	2 mm	Back	25200.00	High		165	1.2	CW	100.0%	-0.11	0.389	0.503	3
	2 mm	Back	25200.00	High	28	156	-1.5	CW	100.0%	-0.05	0.277	0.481	
M patch	2 mm	Back	25200.00	High	31		2.5	CW	100.0%	0.10	0.089	0.144	
	2 mm	Back	24350.04	Low		169	1.7	CW	100.0%	0.18	0.221	0.298	
	2 mm	Front	25200.00	High	41		2.2	CW	100.0%	0.07	0.180	0.274	
	2 mm	Front	24350.04	Low		161	2.0	CW	100.0%	0.19	0.022	0.028	
	2 mm	Right	25200.00	High	41		2.2	CW	100.0%	0.09	0.371	0.483	4
	2 mm	Right	24350.04	Low		161	2.0	CW	100.0%	0.06	0.143	0.233	
	2 mm	Back	25200.00	High	39	167	-1.3	CW	100.0%	-0.08	0.193	0.209	
	2 mm	Front	25200.00	High	41	169	-1.6	CW	100.0%	-0.05	0.120	0.178	
	2 mm	Right	24800.04	Mid	41	169	-1.6	CW	100.0%	-0.08	0.170	0.235	

(10 W/m<sup>2</sup> = 1.0 mW/cm<sup>2</sup>)

#### Note(s):

1. This device utilizes power reduction for some WLAN wireless modes and technologies for simultaneous transmission compliance. These mechanisms are assessed In the SAR Test Report.
2. *PD\_design\_target* of 0.631 mW/cm<sup>2</sup> was used with mmW device design related uncertainty of 2 dB.
3. *Input.power.limit* parameter for 5G mmW NR radio was calculated in RF Exposure Part 0 test report.
4. The measurement was tested by setting it to a higher Tested Power than *Input.power.limit*.
5. The device was configured to transmit CW wave signal for testing. Additional testing was not evaluated for different modulations, RB configurations, component carriers, channel configurations since the smart transmit algorithm monitors powers on a per symbol basis, which is independent of these signal characteristics.
6. *Input.power.limit* was determined as the worst *Input.power.limit* among Open and Closed, and PD was measured.



### 10.3. NR Band n261 - Closed Test Results

Antenna	Dist. (mm)	Test Position	Freq. (MHz)	Ch.	Beam ID1	Beam ID2	input.power.limit (dBm)	Tested Signal	Duty Cycle	Power Drift	Normal psPD (mW/cm <sup>2</sup> )	Total psPD (mW/cm <sup>2</sup> )	Plot No.
					V	H					Meas.	Meas.	
K patch	2 mm	Back	27924.96	Mid	26		4.1	CW	100.0%	0.19	0.297	0.359	5
	2 mm	Back	27924.96	Mid		165	1.2	CW	100.0%	-0.07	0.347	0.493	
	2 mm	Back	28229.96	High	27	155	-1.1	CW	100.0%	-0.18	0.426	0.481	
M patch	2 mm	Back	28229.96	High	41		2.9	CW	100.0%	0.13	0.077	0.112	6
	2 mm	Back	27550.08	Low		158	3.1	CW	100.0%	-0.13	0.280	0.328	
	2 mm	Right	27924.96	Mid	41		2.9	CW	100.0%	0.04	0.276	0.393	
	2 mm	Right	27550.08	Low		166	2.9	CW	100.0%	-0.13	0.214	0.301	
	2 mm	Back	27924.96	Mid	41	169	-0.8	CW	100.0%	-0.08	0.269	0.313	
	2 mm	Right	27550.08	Low	32	160	-0.2	CW	100.0%	-0.19	0.196	0.238	

(10 W/m<sup>2</sup> = 1.0 mW/cm<sup>2</sup>)

### 10.4. NR Band n261 - Open Test Results

Antenna	Dist. (mm)	Test Position	Freq. (MHz)	Ch.	Beam ID1	Beam ID2	input.power.limit (dBm)	Tested Signal	Duty Cycle	Power Drift	Normal psPD (mW/cm <sup>2</sup> )	Total psPD (mW/cm <sup>2</sup> )	Plot No.
					V	H					Meas.	Meas.	
K patch	2 mm	Back	28229.96	High	26		4.1	CW	100.0%	-0.01	0.336	0.378	7
	2 mm	Back	27924.96	Mid		165	1.2	CW	100.0%	-0.05	0.367	0.505	
	2 mm	Back	27924.96	Mid	37	165	-1.4	CW	100.0%	-0.01	0.334	0.422	
M patch	2 mm	Back	27924.96	Mid	41		2.9	CW	100.0%	-0.13	0.079	0.112	8
	2 mm	Back	27550.08	Low		169	2.5	CW	100.0%	-0.12	0.389	0.451	
	2 mm	Front	27924.96	Mid	31		2.4	CW	100.0%	-0.08	0.191	0.306	
	2 mm	Front	27924.96	Mid		167	2.1	CW	100.0%	-0.20	0.049	0.056	
	2 mm	Right	27924.96	Mid	33		2.9	CW	100.0%	0.19	0.263	0.310	
	2 mm	Right	27550.08	Low		159	2.7	CW	100.0%	-0.01	0.308	0.353	
	2 mm	Back	27550.08	Low	41	169	-1.7	CW	100.0%	0.04	0.234	0.283	
	2 mm	Front	27924.96	Mid	39	167	-0.6	CW	100.0%	-0.11	0.143	0.190	
	2 mm	Right	27550.08	Low	41	169	-0.8	CW	100.0%	0.01	0.117	0.154	

(10 W/m<sup>2</sup> = 1.0 mW/cm<sup>2</sup>)

#### Note(s):

- This device utilizes power reduction for some WLAN wireless modes and technologies for simultaneous transmission compliance. These mechanisms are assessed in the SAR Test Report.
- PD\_design\_target* of 0.631 mW/cm<sup>2</sup> was used with mmW device design related uncertainty of 2 dB.
- Input.power.limit* parameter for 5G mmW NR radio was calculated in RF Exposure Part 0 test report.
- The measurement was tested by setting it to a higher Tested Power than *Input.power.limit*.
- The device was configured to transmit CW wave signal for testing. Additional testing was not evaluated for different modulations, RB configurations, component carriers, channel configurations since the smart transmit algorithm monitors powers on a per symbol basis, which is independent of these signal characteristics.
- Input.power.limit* was determined as the worst *Input.power.limit* among Open and Closed, and PD was measured.

### 10.5. NR Band n260 - Closed Test Results

Antenna	Dist. (mm)	Test Position	Freq. (MHz)	Ch.	Beam ID1	Beam ID2	input.power.limit (dBm)	Tested Signal	Duty Cycle	Power Drift	Normal psPD (mW/cm <sup>2</sup> )	Total psPD (mW/cm <sup>2</sup> )	Plot No.
					V	H					Meas.	Meas.	
K patch	2 mm	Back	37050.00	Low	34		3.4	CW	100.0%	0.07	0.202	0.292	9
	2 mm	Back	39949.92	High		165	4.2	CW	100.0%	-0.04	0.314	0.400	
	2 mm	Back	39949.92	High	37	165	1.0	CW	100.0%	-0.01	0.150	0.192	
M patch	2 mm	Back	39949.92	High	40		3.4	CW	100.0%	0.00	0.242	0.259	10
	2 mm	Back	38499.96	Mid		167	3.6	CW	100.0%	-0.09	0.112	0.176	
	2 mm	Right	39949.92	High	40		3.4	CW	100.0%	0.13	0.317	0.340	
	2 mm	Right	38499.96	Mid		160	3.0	CW	100.0%	0.10	0.350	0.430	
	2 mm	Back	38499.96	Mid	39	167	0.2	CW	100.0%	0.00	0.175	0.219	
	2 mm	Right	38499.96	Mid	38	166	0.3	CW	100.0%	0.13	0.206	0.352	

(10 W/m<sup>2</sup> = 1.0 mW/cm<sup>2</sup>)

### 10.6. NR Band n260 - Open Test Results

Antenna	Dist. (mm)	Test Position	Freq. (MHz)	Ch.	Beam ID1	Beam ID2	input.power.limit (dBm)	Tested Signal	Duty Cycle	Power Drift	Normal psPD (mW/cm <sup>2</sup> )	Total psPD (mW/cm <sup>2</sup> )	Plot No.
					V	H					Meas.	Meas.	
K patch	2 mm	Back	37050.00	Low		34	3.4	CW	100.0%	-0.01	0.202	0.295	11
	2 mm	Back	39949.92	High	165		4.2	CW	100.0%	0.05	0.315	0.397	
	2 mm	Back	39949.92	High	165	37	1.0	CW	100.0%	-0.03	0.206	0.248	
M patch	2 mm	Back	37050.00	Low		38	3.8	CW	100.0%	0.02	0.243	0.263	12
	2 mm	Back	38499.96	Mid	160		3.0	CW	100.0%	0.10	0.108	0.171	
	2 mm	Front	38499.96	Mid		39	3.5	CW	100.0%	0.03	0.231	0.237	
	2 mm	Front	39949.92	High	160		3.0	CW	100.0%	-0.06	0.148	0.251	
	2 mm	Right	37050.00	Low		39	3.5	CW	100.0%	-0.12	0.382	0.476	
	2 mm	Right	38499.96	Mid	160		3.0	CW	100.0%	-0.01	0.418	<b>0.480</b>	
	2 mm	Back	38499.96	Mid	167	39	0.2	CW	100.0%	-0.09	0.186	0.221	
	2 mm	Front	38499.96	Mid	158	30	0.1	CW	100.0%	-0.19	0.033	0.034	
	2 mm	Right	37050.00	Low	157	29	-0.2	CW	100.0%	0.18	0.228	0.315	

10 W/m<sup>2</sup> = 1.0 mW/cm<sup>2</sup>)

**Note(s):**

1. This device utilizes power reduction for some WLAN wireless modes and technologies for simultaneous transmission compliance. These mechanisms are assessed In the SAR Test Report.
2. *PD\_design\_target* of 0.631 mW/cm<sup>2</sup> was used with mmW device design related uncertainty of 2 dB.
3. *Input.power.limit* parameter for 5G mmW NR radio was calculated in RF Exposure Part 0 test report.
4. The measurement was tested by setting it to a higher Tested Power than *Input.power.limit*.
5. The device was configured to transmit CW wave signal for testing. Additional testing was not evaluated for different modulations, RB configurations, component carriers, channel configurations since the smart transmit algorithm monitors powers on a per symbol basis, which is independent of these signal characteristics.
6. *Input.power.limit* was determined as the worst *Input.power.limit* among Open and Closed, and PD was measured.

### 11. Simultaneous Transmission Conditions

Total exposure ratio calculated by taking ratio of reported SAR divided by SAR limit and adding it to measured power density divided by power density limit. Numerical sum of the two ratios should be less than 1

$$TER = \sum_{a=1}^A \frac{SAR_a}{SAR_{a, limit}} + \sum_{b=1}^B \frac{psPD_b}{psPD_{b, limit}} < 1$$

The Total exposure ratio shall be less than unity to ensure compliance with the limits.

$$\sum_{n=1}^N \frac{4G SAR_n}{4G SAR_{n, limit}} + \sum_{m=1}^M \frac{5G mmW NR psPD_m}{5G mmW NR psPD_{m, limit}} + \sum_{p=1}^P \frac{WLAN SAR_p}{WLAN SAR_{p, limit}} < 1$$

Qualcomm Smart Transmit algorithm for WWAN adds directly the time-averaged RF exposure from 4G and time-averaged RF exposure from 5G mmW NR. Smart Transmit algorithm controls the total RF exposure from both 4G and 5G mmW NR to not exceed FCC limit. Therefore, per FCC guidance, Total Exposure Ratio does not need to be evaluated directly for the 4G and 5G simultaneous compliance via summation. The validation of the time-averaging algorithm and compliance under the Tx varying transmission scenario for WWAN technologies are reported in Part 2 report.

$$\sum_{n=1}^N \frac{4G SAR_n}{4G SAR_{n, limit}} + \sum_{p=1}^P \frac{WLAN SAR_p}{WLAN SAR_{p, limit}} < 1$$

$$\sum_{m=1}^M \frac{5G mmW NR psPD_m}{5G mmW NR psPD_{m, limit}} + \sum_{p=1}^P \frac{WLAN SAR_p}{WLAN SAR_{p, limit}} < 1$$

For 5G mmW NR, since there is total design-related uncertainty arising from TxAGC and device-to-device variation, the worst-case RF exposure should be determined by accounting for this device uncertainty of 2.0 dB. For this device, the manufacturer has added an additional permanent back-off for every beam in the calculations for input.power.limits used in the EFS files. The back-off levels can be found in the Part 0 Test report. Therefore, 5G mmW NR RF exposure for this DUT is evaluated by reported psPD calculated as;

$$Reported\_psPD = (PD\_design\_target + 2 \text{ dB}) \times 10^{(-WWAN \text{ back-off in dB}/10)}$$

Note that since not all the beams supported by this EUT are measured, reported\_psPD cannot be computed based on limited measured\_psPD data. Alternatively, since measured psPD for all the beams will be PD\_design\_target + 2.0 dB, reported\_psPD is computed based on this worst-case psPD as shown above.

The compliance analysis for simultaneous transmission scenarios of WWAN with Smart Transmit and 4G & WLAN can be found in two reports indicated in the table below.

	Simultaneous Scenario	Evaluation Report
1.	4G LTE WWAN + WLAN	FCC SAR Evaluation Report (Part 1)
2.	4G LTE WWAN + 5G mmW NR WWAN	RF Exposure Part 2 Test Report

**Simultaneous Transmission Condition**

RF Exposure Condition	Item	Capable Transmit Configurations				
Phablet-10g	1	EN-DC (LTE + 5G mmW NR)	+	UWB	+	NFC

**Note(s):**

1. 5G mmW NR Operations are limited to Non-Standalone (EN-DC) operations only.
2. 5G NR antenna arrays cannot transmit at the same time.
3. 5G NR bands cannot transmit at the same time.
4. For EN-DC mode, Qualcomm Smart Transmit algorithm in WWAN adds directly the time-averaged RF exposure from 4G(LTE) and time-averaged RF exposure from 5G NR and time-averaged RF exposure from WLAN and time-averaged RF exposure from BT. Smart Transmit algorithm controls the total RF exposure from both 4G and 5G NR and WLAN and BT to not exceed FCC limit. Therefore, simultaneous transmission compliance between 4G+5G NR+WLAN+BT operation is demonstrated in the Part 2 Report during algorithm validation. In Part 1 Report, simultaneous transmission compliance was evaluated individually with other Radios (UWB and NFC) using 5G mmW NR.

### 11.1. 5G mmW NR psPD for TER Ratio analysis

Antenna	NR Band	Surface	Evaluation Distance (mm)	Adjustment Factor due to Simulation - Closed -	Adjustment Factor due to Simulation - Open -	Adjusted Reported psPD (mW/cm <sup>2</sup> ) - Closed -	Adjusted Reported psPD (mW/cm <sup>2</sup> ) - Open -	Measured psPD (mW/cm <sup>2</sup> )	Final Reported psPD (mW/cm <sup>2</sup> )
K-patch	n258	Back	2	1.000	1.000	0.977	0.955	0.503	<b>0.977</b>
	n258	Front	2	0.045	0.146	0.044	0.139	-	0.139
	n258	Top	2	0.082	0.075	0.080	0.072	-	0.080
	n258	Right	2	0.238	0.262	0.233	0.250	-	0.250
	n258	Bottom	2	0.372	0.352	0.363	0.336	-	<b>0.363</b>
	n258	Left	2	0.616	0.156	0.602	0.149	-	<b>0.602</b>
	n261	Back	2	1.000	1.000	0.977	0.955	0.505	<b>0.977</b>
	n261	Front	2	0.068	0.093	0.066	0.089	-	0.089
	n261	Top	2	0.049	0.046	0.048	0.044	-	0.048
	n261	Right	2	0.120	0.139	0.117	0.133	-	0.133
	n261	Bottom	2	0.149	0.137	0.146	0.131	-	0.146
	n261	Left	2	0.538	0.243	0.526	0.232	-	0.526
	n260	Back	2	1.000	1.000	0.977	0.955	0.400	<b>0.977</b>
	n260	Front	2	0.020	0.028	0.020	0.027	-	0.027
	n260	Top	2	0.026	0.026	0.025	0.025	-	0.025
	n260	Right	2	0.112	0.088	0.109	0.084	--	0.109
n260	Bottom	2	0.197	0.193	0.192	0.184	-	0.192	
n260	Left	2	0.458	0.055	0.447	0.053	-	0.447	
M-patch	n258	Back	2	0.887	1.000	0.809	0.813	0.298	0.813
	n258	Front	2	0.448	0.840	0.409	0.683	0.274	<b>0.683</b>
	n258	Top	2	0.415	0.494	0.378	0.402	-	0.402
	n258	Right	2	1.000	1.000	0.912	0.813	0.546	<b>0.912</b>
	n258	Bottom	2	0.030	0.013	0.027	0.011	-	0.027
	n258	Left	2	0.028	0.016	0.026	0.013	-	0.026
	n261	Back	2	1.000	1.000	0.912	0.813	0.451	0.912
	n261	Front	2	0.360	0.791	0.328	0.643	0.306	0.643
	n261	Top	2	0.587	0.354	0.535	0.288	-	<b>0.535</b>
	n261	Right	2	1.000	1.000	0.912	0.813	0.393	<b>0.912</b>
	n261	Bottom	2	0.045	0.031	0.041	0.025	-	0.041
	n261	Left	2	0.030	0.009	0.027	0.007	-	0.027
	n260	Back	2	0.690	0.717	0.629	0.583	0.263	0.629
	n260	Front	2	0.382	0.632	0.348	0.514	0.251	0.514
	n260	Top	2	0.441	0.406	0.402	0.330	-	0.402
	n260	Right	2	1.000	1.000	0.912	0.813	0.480	<b>0.912</b>
n260	Bottom	2	0.015	0.027	0.014	0.022	-	0.022	
n260	Left	2	0.009	0.015	0.008	0.012	-	0.012	

### 11.2. 5G mmW NR Phablet Total Exposure Ratio

		psPD	UWB Ant Reported SAR	NFC Ant Reported SAR	psPD+UWB Ant Reported SAR	psPD+NFC Ant Reported SAR	psPD+UWB+NFC Ant Reported SAR
		mW/cm <sup>2</sup>	W/kg	W/kg			
		1	2	3	1+2	1+3	1+2+3
Applicable Limit		1.0	4.0	4.0	1.0	1.0	1.0
Rear	Reported Value	0.977	0.001	0.021			
	Ratio to Limit	0.977	0.000	0.005	0.977	0.982	<b>0.983</b>
Front	Reported Value	0.683	0.001	0.000			
	Ratio to Limit	0.683	0.000	0.000	0.683	0.683	0.683
Top	Reported Value	0.535	0.000	0.000			
	Ratio to Limit	0.535	0.000	0.000	0.535	0.535	0.535
Right	Reported Value	0.912	0.000	0.000			
	Ratio to Limit	0.912	0.000	0.000	0.912	0.912	0.912
Bottom	Reported Value	0.363	0.000	0.000			
	Ratio to Limit	0.363	0.000	0.000	0.363	0.363	0.363
Left	Reported Value	0.602	0.000	0.000			
	Ratio to Limit	0.602	0.000	0.000	0.602	0.602	0.602

**Note(s):**

- Adjusted factor is (simulated PD on desired exposure plane)/(PD on worst-surface at 2mm evaluation distance) out of all beams and out of all channels. See Power Density Simulation Report.
- Worst-case power density results for each test configuration among all antenna arrays and among all supported bands were considered for Total Exposure Ratio analysis.
- For power density measurements, a test separation distance of 2 mm was used for phablet configuration due to probe restraints.

## Mathematical Derivation of TER Compliance

$$\text{Total Normalized RFx} = \text{Normalized RFx}_{\text{Time Averaged WWAN}} + \text{Normalized RFx}_{\text{WLAN}} \leq 1.0 \quad (1)$$

Since WWAN Smart Transmit algorithm adds directly the time-averaged RF exposure from 4G and time-averaged RF exposure from 5G mmW NR, per chipset manufacturer's guidance, Normalized RF exposure from 4G and from 5G mmW NR could be assumed as

$$\text{Normalized RFx}_{\text{Time Averaged WWAN}} = \frac{4G \text{ SAR}}{4G \text{ SAR Limit}} + \frac{5G \text{ mmW NR psPD}}{5G \text{ mmW NR psPD Limit}} \leq 1.0 \quad (2)$$

Smart Transmit algorithm assumes that 4G and 5G mmW NR hotspots are co-located and therefore:

$$\text{Time Averaged WWAN} = [x(t) \times A] + [(1-x(t)) \times B] \leq 1.0 \text{ Normalized Limit} \quad (3)$$

$A = \text{Max normalized time-averaged SAR exposure from 4G}$

$B = \text{Max normalized time-averaged PD exposure from 5G mmW NR}$

$x(t) = \text{Ranges between } [0,1]$

$x(t) \times A = \text{Percentage of normalized time-averaged RF exposure from 4G}$

$(1-x(t)) \times B = \text{Remaining percentage of RF exposure contribution from 5G mmW NR}$

Smart Transmit controls "x" in real time such that the sum of these exposures never exceeds 1.0 Normalized Limit. If the equations below (4a, 4b) are proven, then, mathematically equation (5) would be proven.

$$A + \text{norm. SAR from WLAN} \leq 1.0 \text{ normalized limit} \quad (4a)$$

$$B + \text{norm. SAR from WLAN} \leq 1.0 \text{ normalized limit} \quad (4b)$$

$$[x(t) \times A] + [(1-x(t)) \times B] + \text{norm. SAR from WLAN} \leq 1.0 \text{ normalized limit} \quad (5)$$

Without 5G mmW NR, Smart Transmit limits the maximum RF exposure contributed from 4G to 100% normalized exposure. For this device, the manufacturer has added an additional permanent back-off for every beam in the calculations for input.power.limits used in the EFS files. therefore:

$$\text{Smart Tx WWAN: } A = \max(\text{normalized SAR exposure from 4G}) \leq 1.0 \text{ normalized limit} \quad (6a)$$

$$\text{Smart Tx WWAN: } B = \max(\text{normalized PD exposure from 5G mmW NR}) \times 10^{(-\text{WWAN backoff in dB})/10} \leq 1.0 \text{ normalized limit} \quad (6b)$$

To demonstrate simultaneous transmission compliance in equation (1), below equations (7a & 7b) obtained by combining equations (4a & 4b) and (6a & 6b), should be proven for simultaneous transmission compliance:

$$\text{Total Normalized RFx} = \text{Normalized SAR}_{4G \text{ WWAN}} + \text{Normalized SAR}_{\text{WLAN}} < 1.0 \quad (7a)$$

$$\text{Total Normalized RFx} = 10^{(-\text{WWAN backoff in dB})/10} \times \text{Normalized psPD}_{5G \text{ mmW NR WWAN}} + \text{Normalized SAR}_{\text{WLAN}} < 1.0 \quad (7b)$$

Which are re-written as:

$$\text{Total Normalized RFx} = \frac{4G \text{ SAR}}{4G \text{ SAR Limit}} + \frac{\text{WLAN SAR}}{\text{WLAN SAR Limit}} < 1 \quad (8a)$$

$$\text{Total Normalized RFx} = 10^{(-\text{WWAN backoff in dB})/10} * \frac{5G \text{ mmW NR psPD}}{5G \text{ mmW NR psPD Limit}} + \frac{\text{WLAN SAR}}{\text{WLAN SAR Limit}} < 1 \quad (8b)$$

Analysis for equation (8a) is performed in Section 12 of FCC SAR Evaluation Report (Part 1). Analysis for equation (8b) is performed in this Sec 12.

## **Appendixes**

**Refer to separated files for the following appendixes.**

**4790748041-S3 FCC Report PD\_App A\_Setup Photos**

**4790748041-S3 FCC Report PD\_App B\_System Check Plots**

**4790748041-S3 FCC Report PD\_App C\_Highest Test Plots**

**4790748041-S3 FCC Report PD\_App D\_Probe Calibration Certificates**

**4790748041-S3 FCC Report PD\_App E\_Verification source Calibration Certificates**

**END OF REPORT**