

EXHIBIT 11

RF OUTPUT POWER MEASUREMENTS

This exhibit describes the procedures employed and presents results of measurements DTSA output power, as required by and performed in accordance with § 2.1046.

Requirements

Section 24.232 of the FCC Rules and Regulations governing operation of PCS equipment provides power limitations for base and mobile/portable stations. Per § 24.232(a), base (fixed) stations are limited to 1640 W peak equivalent isotropically radiated power (e.i.r.p.) with an antenna height up to 300 meters HAAT (height above average terrain). In no case may the peak output power exceed 100 W. In § 24.232(b), mobile/portable stations are limited to 2 W e.i.r.p. peak output power.

Measurement of transmitter RF output power are described in § 2.1046 and are necessary to obtain a certification grant of equipment authorization. For all measurements of output power, the RF output port of the DTSA was loaded with a matched 50 Ω impedance.

Measurement Procedure

Measurements of DTSA output power was performed using an HP8563E Spectrum Analyzer, with a resolution bandwidth set large enough to integrate the power in the entire transmitted burst. Prior to the measurement, signal path loss of the diagnostic system (cables, attenuator, power splitter) was characterized at all frequencies at which output power was measured; this loss was then used to correct the raw readings to obtain precise measurements of DTSA RF output power. Measurements were made the lowest (channel 512, 1850.2 MHz), middle (channel 661, 1880.0), and highest (channel 810, 1908.8 MHz) PCS-1900 defined channels in the licensed PCS spectrum.

Specific procedures followed during measurements of RF output power were as follows:

1. Configure the DTSA:
 - Input Voltage 8.0 VDC
 - Mode Speech call selected using the Racal 6103
 - RF Output Power Maximum level (step 0, 30 dBm nominal) and minimum level (step 15, 0 dBm nominal) selected using the Racal 6103
 - Frequencies Channel 512 (1850.2 MHz), Channel 661 (1880.0 MHz), and Channel 810 (1908.8 MHz) selected using the Racal 6103

2. Configure the HP8953E Spectrum Analyzer:
 - Center Frequency Center of selected channel
 - Span 1 kHz
 - RBW 1 MHz
 - Sweep Time 5 sec
 - Display Max Hold
3. Record peak RF output power, correcting for diagnostic system losses
4. Perform measurement at all three channels
5. Perform measurement at minimum power level (Step 15, 0 dBm nominal)

Measurement Results

DTSA output power measurement results are given in Table E11.1. All results have been corrected to account for diagnostic system loss.

Table E11.1. RF output power measurement results.

PCS-1900 Channel	Measurement Frequency (MHz)	Maximum Output Power (dBm)	Minimum Output Power (dBm)
512	1850.2	28.67	-3.17
661	1880.0	28.33	-0.67
810	1909.8	28.5	-1.67

As the results in Table E11.1 indicate, the measured maximum RF peak output power of the DTSA is approximately 28.7 dBm, or 0.74 W. The nominal maximum RF output power of the DTSA is 1.0 W (30 dBm).

The peak RF output power of the DTSA complies with the 100 W maximum for fixed applications given in § 24.232(a); peak e.i.r.p. will not exceed 1640 W (i.e., antenna gain will not exceed 32 dBi). For mobile/portable applications, compliance with the 2 W e.i.r.p. limit given in § 24.232(b) will be ensured by limiting antenna system gain (antenna gain minus RF interconnect cable loss) to 3 dB nominally. Note that in all applications, DTSA output power is controlled by the GSM network to minimize transmit power while maintaining the quality of the link.