Exhibit B Response to Question 28 for Kalopei, Hawaii Antenna

This attachment analyzes the power-flux density near the proposed transmit antenna to be located in Kalopei, Hawaii. The antenna will be a square flat plate antenna 0.89m x 0.89m with transmit gain 22.2 dBi. The site will transmit a peak EIRP of 16.5 dBW. The power-flux density calculations in this exhibit are based on this peak EIRP value. These calculations follow the methodology outlined in OET Bulletin No. 65, "Evaluating Compliance with FCC-Specified Guidelines for Human Exposure to Radiofrequency Radiation." The power-flux density calculations are made for a transmitting frequency of 1660.5 MHz. At this frequency, the maximum permissible exposure to RF fields in a controlled environment is 5 mW/cm².

The calculations are based on data provided by the antenna manufacturer. See Figure 1. The maximum allowable exposure value of 5 mW/cm² is equal to 7 dBmW/cm². From Figure 1, it can be seen that this value is never reached for the antenna at an input power level of 1 W. For the case that this application applies to, a 16.5 dBW signal out of a 22.2 dBi gain antenna, the input power is -5.7 dBW or 0.269 W or 3.7 times smaller than the values of Figure 1. Therefore, the conclusion is the same, the maximum value of 5 mW/cm² is not reached for the case that this application applies to.

Conclusion

This site is in a controlled environment. The general public does not have access to the site where the transmit antenna is located. The maximum permissible exposure to RF fields in a controlled environment is 5 mW/cm² at L-band. The calculations show that the site will not exceed the permissible levels for exposure to RF radiation.

Figure 1: Antenna Power Density

| Aperture size | 0.89 | m | | | Near field Power density (dBmW/cm^2) | Far field Power density (dBmW/cm^2) | | | | | |
|---|------|--------------------|---------------|-----------------|--|---|--------|--------|--------|--------|--------|
| Power input | 1.00 | W | | | | Distance (m) | | | | | |
| Frequency (GHz) | | FF distance (m) | Gain (dBi) | Efficiency | 1 | 8 | 9 | 10 | 11 | 12 | 13 |
| 1.522 | | 7.95 | | 0.668 | | -27.95 | -28.98 | -29.89 | -30.72 | -31.48 | -32.17 |
| 1.542 | | 8.05 | 20.4 | 0.573 | -4.29 | -28.65 | -29.68 | -30.59 | -31.42 | -32.18 | -32.87 |
| 1.559 | | 8.14 | 20.8 | | -4.11 | -28.25 | -29.28 | -30.19 | -31.02 | -31.78 | -32.47 |
| 1.6265 | | 8.49 | 21.1 | 0.608 | -4.03 | -27.95 | -28.98 | -29.89 | -30.72 | -31.48 | -32.17 |
| 1.6435 | | 8.58 | 21.2 | 0.602 | -4.07 | -27.85 | -28.88 | -29.79 | -30.62 | -31.38 | -32.07 |
| 1.6605 | GHz | 8.67 | 22.2 | 0.79 | -2.89 | -26.85 | -27.88 | -28.79 | -29.62 | -30.38 | -31.07 |
| -5.00 -5.0025.00 -25.00 -30.00 | | | | | —————————————————————————————————————— | 1.522 GHz 1.542 GHz 1.559 GHz 1.6265 GHz 1.6435 GHz 1.6605 GHz | | | | | |
| -35.00 | | | | | - 10 | 10 | _ | | | | |
| | 0 | 2 4 | | 5 8 ance (m) | 10 | 12 | 14 | | | | |