

Sent by: JetFax M910e

5;

07/11/00 8:21AM; JetFax #851; Page 2/6

Received: 7/11/00 7:00AM;

703 470 2707 -&gt; WILLIAMS MARKETING DEPT; Page 14

JUL 11 '00 08:09AM COMSEARCH

P.2/6

EXHIBIT  
Page 1 of 5Analysis of Non-Ionizing Radiation  
for a 1.9 Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 1.9 meter earth station system. The analysis and calculations performed in this report are in compliance with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

| Frequency Range (MHz) | Power Density (mWatts/cm <sup>2</sup> ) |
|-----------------------|---|
| 30-300                | 0.2                                     |
| 300-1500              | Frequency (MHz) * (0.8/1200)            |
| 1500-100,000          | 1.0                                     |

Table 2. Limits for Occupational/Controlled Exposure (MPE)

|              |                              |
|--------------|------------------------------|
| 30-300       | 1.0                          |
| 300-1500     | Frequency (MHz) * (4.0/1200) |
| 1500-100,000 | 5.0                          |

Table 3 contains the parameters that are used to calculate the various power densities for the earth stations.

Sent by: JaiFax M910a

5;

07/11/00 8:21AM; JaiFax #851; Page 3/6

Received: 7/11/00 7:00AM;

700 476 2767 -&gt; WILLIAMS MARKETING DEPT; Page 16

JUL 11 '00 08:10AM COMSEARCH

P.3/6

EXHIBIT  
Page 2 of 6

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

| Parameter            | Abbreviation | Value               | Units     |
|----------------------|--------------|---------------------|-----------|
| Antenna Diameter     | D            | 1.9                 | meters    |
| Antenna Surface Area | Sa           | $\pi * D^{**2}/4$   | meters**2 |
| Feed Flange Diameter | Df           | 19.0                | cm        |
| Area of Feed Flange  | Fa           | $\pi * Df^{**2}/4$  | cm**2     |
| Frequency            | Frequency    | 14250               | MHz       |
| Wavelength           | lambda       | 300/frequency (MHz) | meters    |
| Transmit Power       | P            | 350.00              | Watts     |
| Antenna Gain         | Ges          | 46.5                | dBi       |
| Pi                   | II           | 3.1415927           | n/a       |
| Antenna Efficiency   | n            | 0.56                | n/a       |

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation: (1)

$$\begin{aligned} \text{Distance to the Far Field Region, (Rf)} &= 0.60 * D^{**2} / \text{lambda} \\ &= \underline{102.9} \text{ meters} \end{aligned} \quad (1)$$

The maximum main beam power density in the Far Field can be determined from the following equation: (2)

$$\begin{aligned} \text{On-Axis Power Density in the Far Field, (Wf)} &= \text{Ges} * P / 4 * \text{II} * \text{Rf}^{**2} \\ &= 117.531 \text{ Watts/meters**2} \\ &= \underline{11.753} \text{ mWatts/cm**2} \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation: (3)

$$\begin{aligned} \text{Extent of the Near Field, (Rn)} &= D^{**2} / (4 * \text{lambda}) \\ &= \underline{42.9} \text{ meters} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation: (4)

$$\begin{aligned} \text{Near Field Power Density, (Wn)} &= 16.0 * n * P / \text{II} * D^{**2} \\ &= 274.370 \text{ Watts/meters**2} \\ &= \underline{27.437} \text{ mWatts/cm**2} \end{aligned} \quad (4)$$

Sent by: JetFax M910e

5;

07/11/00 8:21AM; JetFax #R51; Page 4/6

Received: 7/11/00 7:00AM;

708 476 2767 -&gt; WILLIAMS MARKETING DEPT; Page 18

JUL 11 '00 08:10AM COMSEARCH

P.4/6

EXHIBIT  
Page 3 of 53. Transition Region Calculations

The Transition region is located between the Near and Far Field regions. As stated in Section 2. above the power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1. above is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance  $R_t$  can be determined from the following equation: (5)

$$\text{Transition region Power Density, (Tt)} = W_n * R_n / R_t \quad (5)$$

4. Region between Feed Assembly and Antenna Reflector

Transmissions from the feed assembly are directed toward the antenna reflector surface, and are confined within a conical shape defined by the type of feed assembly. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the feed assembly and reflector surface can be calculated by determining the power density at the feed assembly surface. This can be determined from the following equation: (6)

$$\begin{aligned} \text{Power Density at Feed Flange, (Wf)} &= 4 * P / F_a \\ &= \underline{4937.771} \text{ mWatts/cm}^{**2} \end{aligned} \quad (6)$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the feed assembly, in 4. above, but the area is now the area of the reflector aperture can be determined from the following equation: (7)

$$\begin{aligned} \text{Power Density at the Reflector Surface, (Ws)} &= 4 * P / S_a \\ &= \underline{493.777} \text{ Watts/meters}^{**2} \\ &= \underline{49.378} \text{ mWatts/cm}^{**2} \end{aligned} \quad (7)$$

6. Region between Reflector and Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and ground can be determined from the following equation: (8)

$$\begin{aligned} \text{Power Density between Reflector and Ground, (Wg)} &= P / S_a \\ &= \underline{123.444} \text{ Watts/meters}^{**2} \\ &= \underline{12.344} \text{ mWatts/cm}^{**2} \end{aligned} \quad (8)$$

Sent by: JetFax M910e

5;

07/11/00 8:21AM; JetFax #851; Page 5/6

Received: 7/11/00 7:00AM;

703 478 2787 -&gt; WILLIAMS MARKETING DEPT; Page 17

JUL 11 '00 08:10AM COMSEARCH

P.5/6

EXHIBIT  
Page 4 of 5

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

| Region  | Calculated Maximum Radiation<br>Power Density Level (mWatts/cm**2) | Hazard Assessment |
|---|--|-------------------|
| 1. Far Field (Rf) = <u>102.9</u> meters           | <u>11.753</u>  | Potential Hazard  |
| 2. Near Field (Rn) = <u>42.9</u> meters           | <u>27.437</u>  | Potential Hazard  |
| 3. Transition Region<br>Rn < Rt < Rf, (Rt)        | <u>27.437</u>  | Potential Hazard  |
| 4. Between Feed Assembly<br>and Antenna Reflector | <u>4937.771</u>  | Potential Hazard  |
| 5. Main Reflector                                 | <u>49.378</u>  | Potential Hazard  |
| 6. Between Reflector<br>and Ground                | <u>12.344</u>  | Potential Hazard  |

Table 5. Summary of Expected Radiation levels for Controlled Environment

| Region  | Calculated Maximum Radiation<br>Power Density Level (mWatts/cm**2) | Hazard Assessment |
|---|--|-------------------|
| 1. Far Field (Rf) = <u>102.9</u> meters           | <u>11.753</u>  | Potential Hazard  |
| 2. Near Field (Rn) = <u>42.9</u> meters           | <u>27.437</u>  | Potential Hazard  |
| 3. Transition Region<br>Rn < Rt < Rf, (Rt)        | <u>27.437</u>  | Potential Hazard  |
| 4. Between Feed Assembly<br>and Antenna Reflector | <u>4937.771</u>  | Potential Hazard  |
| 5. Main Reflector                                 | <u>49.378</u>  | Potential Hazard  |
| 6. Between Reflector<br>and Ground                | <u>12.344</u>  | Potential Hazard  |

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

Sent by: JetFax M910e

5;

07/11/00 8:22AM; JetFax #851; Page 6/6

Received: 7/11/00 7:10AM;

708 476 2787 -&gt; WILLIAMS MARKETING DEPT; Page 18

JUL 11 '00 08:11AM COMSEARCH

P.6/6

EXHIBIT A  
Page 5 of 5

## 7. Conclusions

Based on the above analysis it is concluded that the FCC MPE guidelines have been exceeded (or met) in the regions of Table 4. The applicant proposes to comply with the FCC MPE limits by one or more of the following methods.

The antenna will be roof mounted at a minimum elevation of 2.4 meters above ground level and since one diameter removed from the center of main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured for the near and far field regions. The antenna transmitter will be turned off during maintenance in order to comply with the FCC MPE limit of 5 mW/cm<sup>2</sup> at the Reflector Surface.