

RADIATION HAZARD STUDY

This radiation hazard study describes the R.F. radiation environment of the permanent fixed Ku-band uplink operated by Christian Ministries of the Valley, Inc. This fixed earth station uplink is located at a latitude of 26d - 09m - 54s North and a longitude of 98d - 00m - 55s West, in Weslaco, Texas.

This study is done to comply with the requirements of Section 1.1307(b) of the rules of the Federal Communications Commission. All calculations conform to the procedures presented in OET Bulletin No. 65 for aperture antennas.

Transmit antenna: Prodelin 2.4 meter KU-band

Antenna Diameter $D := 2.4 \cdot \text{m}$

Antenna Efficiency $\eta := 67\%$

Transmitter: 4 watt output flange SSPA, operated at 50% power

Transmit Power $P := 4 \cdot \text{watt} \cdot 50\%$
 $P = 2 \cdot \text{watt}$
 $\text{mw} := \frac{\text{watt}}{1000}$

	at 14.0 GHz	at 14.5 GHz
Antenna Gain	$G_1 := 49.10$	$G_2 := 49.30$
Wavelength	$\lambda_1 := 2.14285 \cdot \text{cm}$	$\lambda_2 := 2.06896 \cdot \text{cm}$

Calculations for the Near Field (Fresnel Region)

Extent of the Near Field

$$R_{n1} := \frac{D^2}{4 \cdot \lambda_1} \qquad R_{n2} := \frac{D^2}{4 \cdot \lambda_2}$$
$$R_{n1} = 67.2 \cdot \text{m} \qquad R_{n2} = 69.6 \cdot \text{m}$$

Maximum Near Field
Power Density

$$S_n := \frac{16 \cdot \eta \cdot P}{\pi \cdot D^2}$$
$$S_n = 0.118 \cdot \frac{\text{mw}}{\text{cm}^2}$$

	at 14.0 GHz	at 14.5 GHz
Distance to Far Field	$R_{f1} := \frac{0.6 \cdot D^2}{\lambda_1}$ $R_{f1} = 161.281 \cdot \text{m}$	$R_{f2} := \frac{0.6 \cdot D^2}{\lambda_2}$ $R_{f2} = 167.04 \cdot \text{m}$
Absolute Gain of Antenna	$G_{a1} := 10^{\frac{G_1}{10}}$	$G_{a2} := 10^{\frac{G_2}{10}}$
Maximum Far Field Power Density	$S_{f1} := \frac{P \cdot G_{a1}}{4 \cdot \pi \cdot R_{f1}^2}$ $S_{f1} = 0.05 \cdot \frac{\text{mw}}{\text{cm}^2}$	$S_{f2} := \frac{P \cdot G_{a2}}{4 \cdot \pi \cdot R_{f2}^2}$ $S_{f2} = 0.049 \cdot \frac{\text{mw}}{\text{cm}^2}$

Calculations for the Transition Zone

The farthest point in the near field is the beginning of the transition zone -

$$R_{t1} := R_{n2}$$

$$R_{t1} = 69.6 \cdot \text{m}$$

The end of the Transition Zone is the beginning of the Far Field -

$$R_{t2} := R_{f2}$$

$$R_{t2} = 167.04 \cdot \text{m}$$

	Beginning	End
Transition Zone Power Density	$S_{t1} := \frac{S_n \cdot R_{n2}}{R_{t1}}$ $S_{t1} = 0.118 \cdot \frac{\text{mw}}{\text{cm}^2}$	$S_{t2} := \frac{S_n \cdot R_{n2}}{R_{t2}}$ $S_{t2} = 0.049 \cdot \frac{\text{mw}}{\text{cm}^2}$

Calculations at the Reflector Surface:

(Page 3 of 3)

$$\begin{aligned}\text{Area of Reflector} \quad A &:= \pi \cdot \left(\frac{D}{2}\right)^2 \\ A &= 4.524 \cdot \text{m}^2\end{aligned}$$

$$\begin{aligned}\text{Power Density at the} \quad S_{\text{ref}} &:= \left(2 \cdot \frac{P}{A}\right) \\ \text{Reflector Surface} \quad S_{\text{ref}} &= 0.088 \cdot \frac{\text{mw}}{\text{cm}^2}\end{aligned}$$

Calculations between the Antenna and the Ground:

$$\begin{aligned}\text{Power Density between} \quad S_{\text{ga}} &:= \frac{P}{A} \\ \text{Antenna and Ground} \quad S_{\text{ga}} &= 0.044 \cdot \frac{\text{mw}}{\text{cm}^2}\end{aligned}$$

Conclusions

The power densities in the Near Field, Far Field, Transition Zone, at the Surface of the Reflector, and between the Reflector and the Ground are all below the allowable limit. Nowhere do they exceed the level of 5 mw/cm² as listed in OET Bulletin No. 65. Thus, this transmit earth terminal meets FCC requirements for human exposure to radio frequency energy.