

RF RADIATION HAZARD ANALYSIS

Exhibit #B

Antenna Dia. (D)=1.5 Meters 4.922 Feet
Antenna Surface Area (SA)=1.767 sq meters
Subreflector Dia. (DS)=N/A (prime focus offset)
Subreflector Surface Area (AS)=N/A
KU Wavelength at 14.250 GHz (LAMBDA)=.0211 meters
Power at output of HPA flange=20.969 dB
Path Loss to OMT (IL)=.6 dB
Power at OMT Flange (P)=130.645 watts
Antenna Gain at 14.250 GHz (G)=45.9 dBi (2 port antenna gain)
Antenna Gain given in Power Ratio (GES)=3.89E+04
Antenna Aperture Efficiency (N)=.7764

<u>Region</u>	<u>Radiation Level</u>	<u>Hazard Assessment</u>
Far Field (Rf) 63.981 m 209.922 ft	9.88 mW/cm sq	Potential Hazard
Near Field (Wf) 26.659m 87.467 ft	22.96 mW/cm sq	Potential Hazard
Transition Region (Rt) Ru<Rt<Rf	equal to or less than 22.96 mW/cm sq	Potential Hazard
Between Main Reflector and Subreflector (Ws)	N/A (no subreflector)	
Main Reflector Region (Wm)	14.3786 mW/cm sq	Potential Hazard
Power Density Between Reflector and Ground	7.393 mW/cm sq	Potential Hazard
Far Field Off Axis (WF)	.099 mW/cm sq	Meets ANSI Requirements
Near Field Off Axis (WN)	.23 mW/cm sq	Meets ANSI Requirements

Conclusion: Based on the above analysis, harmful areas of Radiation do exist in areas around the antenna and in the path of the antenna toward the satellite that it is pointed at. The Area occupied by the general public will not exceed the ANSI limit of 1 mW cm sq. because the antenna is mounted on top of the truck, which is at least 10 feet above the ground, and safety increases with look angles used by the Satellites in the United States on Dom. Sat. arch. The areas on the ground and behind the antenna are 100 times less power (20 dB) when at a min. of the dia. of the reflector, this is reflected in the Off Axis figures as seen above (WF) & (WN). The SNG will be marked with the standard radiation hazard warnings, and on the antenna itself. The warning signs will warn personnel to avoid the area around and in front of the reflector when the transmitter is operating. To ensure compliance with safety limits, the earth station transmitter will be turned off and marked to remain off whenever maintenance and repair personnel are required to work in the areas of potential hazard as defined in the above study. Additionally the earth station personnel will be trained to insure that the antenna path is clear at all times while the transmitter is in operation. The only access to the roof of the truck, is a stored ladder which will only be used when the transmitter is off and not accessible by the general public.

Note: See Exhibit #Ba for how the above calculations were made.

Exhibit Ba Analysis of Non-Ionizing Radiation

Antenna Diameter, (D)=.....	$D := 1.5$ meters	$D \cdot 3.281 = 4.922$	Feet
Antenna Surface Area, (Sa)=	$Sa := \pi \cdot \frac{D \cdot D}{4}$	$Sa = 1.767$	sq meters
Subreflector Diameter, (Ds)=.....	$Ds := 0$	cm	$Ds \cdot .3937 = 0$ Inch's
Area of Subreflector, (As)=.....	$As := \pi \cdot \frac{Ds \cdot Ds}{4}$	$As = 0$	sq cm
Center Frequency, (Cf)=.....	$CF := 14.250$	GHz	
Wavelength at (Cf), (Lambda)=.....	$\text{Lambda} := .0211$	meters	
	C-Band=.049	Ku-Band=.0211	
Transmit Power at HPA or VPC Flange, (P1)=..	$P1 := 150$	watts	$P2 := \log(P1) \cdot 10$ $P2 = 21.761$ dB
Path Loss from HPA or VPC to OMT, (Loss)=..	$\text{Loss} := .6$	dB	
Power at OMT, (P)=.....	$P3 := P2 - \text{Loss}$	$P3 = 21.161$	OMT Pwr in dB
	$P := 10^{\frac{P3}{10}}$	$P = 130.645$	OMT Pwr in watts
Antenna Gain at (Cf), (Gain)=.....	$\text{Gain} := 45.9$	dBi	
Antenna Gain Converted to Power Ratio, (Ges).	$\text{Ges} := 10^{\frac{\text{Gain}}{10}}$	$\text{Ges} = 3.89 \cdot 10^4$	Ratio
Antenna Aperture Efficiency, (n)=.....	$n := .7764$		

Far Field (Rf)=	$Rf := \frac{60 \cdot (D \cdot D)}{\text{Lambda}}$	$Rf = 63.981$	meters	$Rf \cdot 3.281 = 209.922$	Feet
Far Field Pwr Density (Wf)=	$Wf := \frac{\text{Ges} \cdot P}{4 \cdot \pi \cdot (Rf \cdot Rf)}$	$Wf = 9.88$			mw sq cm
Near Field (Rn)=	$Rn := \frac{D \cdot D}{4 \cdot \text{Lambda}}$	$Rn = 26.659$	meters	$Rn \cdot 3.281 = 87.467$	Feet
Near Field Pwr Density (Wn)=	$Wn := \frac{16 \cdot n \cdot P}{\pi \cdot (D \cdot D)}$	$Wn = 22.96$			mw sq cm
Transition Region (Rt)=	$Rt := Wn \cdot 1$	$Rt = 22.96$			mw sq cm (Equal to or less then)
Pwr Density at Sub Reflector (Ws)=	(N/A No Sub Reflector)				
Main Reflector Region Pwr Density (Wm)=	$Wm := \frac{2 \cdot P}{Sa}$	$Wm = 14.786$			mw sq cm
Pwr Density between main reflector and ground (Wg)=	$Wg := \frac{P}{Sa}$	$Wg = 7.393$			mw sq cm
Far Field Off Axis (WF)=	$WF := Wf \cdot .01$	$WF = 0.099$			mw sq cm
Near Field Off Axis (WN)=	$WN := Wn \cdot .01$	$WN = 0.23$			mw sq cm