

## RF RADIATION HAZARD ANALYSIS

### Exhibit #B

Antenna Diameter, (D) = 1.5 meters / 4.922 Feet  
Antenna Surface Area, (Sa) = 1.767 sq meters  
Subreflector Diameter, (Ds) = 0 centimeters  
KU Wavelength at 14.25 GHz (LAMBDA) = 0.0211 meters  
Power at output of VPC flange = 25.563 dB  
Path Loss to OMT (IL) = 0.8 dB  
Power at OMT, (P) = 302.9 Watts  
Antenna Gain at 14.250 GHz, (G)= 45.5 dBi (2 port antenna gain)  
Antenna Gain given in Power Ratio, (Ges) = 3.548E+04  
Antenna Aperture Efficiency (N) = 0.776

<b>Region</b>	<b>Radiation Level</b>	<b>Hazard Assessment</b>
Far Field, (Rf) = 63.981 meters / 209.922 Feet	20.892 mW/cm sq	Potential Hazard
Near Field, (Wf) = 26.659 meters / 87.467 Feet	53.232 mW/cm sq	Potential Hazard
Transition Region (Rt) Ru<Rt<Rf	equal to or less than 53.232 mW/cm sq	Potential Hazard
Between Main Reflector and Subreflector (Ws)	N/A (no subreflector)	
Main Reflector Region (Wm)	34.282 mW/cm sq	Potential Hazard
Power Density Between Reflector and Ground	17.141 mW/cm sq	Potential Hazard
Far Field Off Axis (WF)	0.209 mW/cm sq	Meets ANSI Requirements
Near Field Off Axis (WN)	0.532 mW/cm sq	Meets ANSI Requirements

**Conclusion:** Based on the above analysis, harmful areas of Radiation do exist in areas around the antenna and in the path of the antenna toward the satellite that it is pointed at. The Area occupied by the general public will not exceed the ANSI limit of 1 mW cm sq. because the antenna is mounted on top of the truck, which is at least 8 feet above the ground, and safety increases with look angles used by the Satellites in the United States on Dom. Sat. arch. The areas on the ground and behind the antenna are 100 times less power (20dB) when at a min. of the dia. of the reflector. This is reflected in the Off Axis figures as seen above (WF) & (WN). The SNG will be marked with the standard radiation hazard warnings, and on the antenna itself. The warning signs will warn personnel to avoid the area around and in front of the reflector when the transmitter is operating. To ensure compliance with safety limits, the earth station transmitter will be turned off and marked to remain off whenever maintenance and repair personnel are required to work in the areas of potential hazard as defined in the above study. Additionally the earth station personnel will be trained to insure that the antenna path is clear at all times while the transmitter is in operation. The only access to the roof of the truck is a stored ladder which will only be used when the transmitter is off and not accessible by the general public.

Note: See Exhibit #Ba for how the above calculations were made.

## Exhibit Ba Analysis of Non-Ionizing Radiation

Antenna Diameter, ( $D$ ) =	$D := 1.5$ meters	$D \cdot 3.281 =$	4.922 Feet
Antenna Surface Area, ( $Sa$ ) =	$Sa := \pi \cdot \frac{D \cdot D}{4}$	$Sa =$	1.767 sq meters
Subreflector Diameter, ( $Ds$ ) =	$Ds := 0$ cm	$Ds \cdot .3937 =$	0.000 Inches
Area of Subreflector, ( $As$ ) =	$As := \pi \cdot \frac{Ds \cdot Ds}{4}$	$As =$	0.000 sq cm
Center Frequency, ( $Cf$ ) =	$Cf := 14.250$ GHz		
Wavelength at ( $Cf$ ), ( $Lambda$ ) =	$Lambda := 0.0211$ meters C-Band = .049 Ku-Band = .0211		
Transmit Power at HPA or VPC Flange, ( $P1$ ) =	$P1 := 360.00$ watts	$P2 := \log(P1) \cdot 10$	$P2 = 25.563$ dB
Path Loss from HPA or VPC to OMT, ( $IL$ ) =	$Loss := 0.75$ dB		
Power at OMT, ( $P$ )=	$P3 := P2 - Loss$	$P3 =$	24.813 OMT Pwr in dB
	$P := 10^{\frac{P3}{10}}$	$P =$	302.90 OMT Pwr in watts
Antenna Gain at ( $Cf$ ), ( $Gain$ )=	$Gain := 45.50$ dBi		
Antenna Gain Converted to Power Ratio, ( $Ges$ )=	$Ges := 10^{\frac{Gain}{10}}$	$Ges =$	3.548E+04 Ratio
Antenna Aperture Efficiency, ( $n$ )=	$n := 0.7764$		
<hr/>			
Far Field ( $Rf$ )=	$Rf := \frac{.60 \cdot (D \cdot D)}{Lambda}$	$Rf =$	63.981 meters
		$Rf \cdot 3.281 =$	209.92 feet
Far Field Power Density ( $Wf$ )=	$Wf := \frac{Ges \cdot P}{4 \cdot \pi \cdot (Rf \cdot Rf)} \cdot .1$	$Wf =$	20.892 mw sq cm
Near Field ( $Rn$ ) =	$Rn := \frac{(D \cdot D)}{4 \cdot Lambda}$	$Rn =$	26.659 meters
		$Rf \cdot 3.281 =$	87.467 feet
Near Field Power Density ( $Wn$ )=	$Wn := \frac{16 \cdot n \cdot P}{\pi \cdot (D \cdot D)} \cdot .1$	$Wn =$	53.232 mw sq cm
Transition Region ( $Rt$ )=	$Rt := Wn \cdot 1$	$Rt =$	53.232 mw sq cm (Equal to or less than)
Pwr Density at Sub Reflector ( $Ws$ )=	$Ws := \frac{2 \cdot P}{As} \cdot 1000$		N/A
Main Reflector Region Pwr Density ( $Wm$ )=	$Wm := \frac{2 \cdot P}{Sa} \cdot .1$	$Wm =$	34.282 mw sq cm
Pwr Density between main reflector and ground ( $Wg$ )=	$Wg := \frac{P}{Sa} \cdot .1$	$Wg =$	17.141 mw sq cm
Far Field Off Axis ( $WF$ )=	$WF := Wf \cdot .01$	$WF =$	0.209 mw sq cm
Near Field Off Axis ( $WN$ )=	$WN := Wn \cdot .01$	$WN =$	0.532 mw sq cm