

EXHIBIT A - ANALYSIS OF ENVIRONMENTAL IMPACT

RF NON-IONIZING RADIATION ANALYSIS:

A DETAILED RF NON-IONIZING RADIATION HAZARD ANALYSIS WAS CONDUCTED AND IS ATTACHED AS EXHIBIT B.

USING THE ASSUMPTION THAT ALL AVAILABLE TRANSMITTER POWER IS APPLIED TO THE IFL INPUT, HARMFUL LEVELS OF RADIATION WILL NOT EXIST IN REGIONS NORMALLY OCCUPIED BY PERSONNEL AS DEFINED BY ANSI CRITERIA (ANSI SPECIFICATIONS REQUIRE THAT PERSONNEL NOT BE EXPOSED TO LEVELS OF NON-IONIZING RADIATION EXCEEDING 5 mW / cm².)

ANTENNA SIZE AND DESCRIPTION OF SURROUNDING AREA:

THE EARTH STATION IS LESS THAN 24' IN DIAMETER AND IS LOCATED WITHIN A BROADCAST STUDIO COMPLEX WITH AN EXISTING SATELLITE ANTENNA FARM PREVIOUSLY AUTHORIZED FOR THIS LOCATION. MOST OF THE RESIDENTIAL HOMES WITHIN VIEW ARE OWNED AND USED BY THIS FACILITY AS STUDIO GUEST QUARTERS.

ADDITIONAL PRECAUTIONARY SAFETY MEASURES:

PROTECTIVE FENCING WILL BE INSTALLED AND APPROPRIATE WARNING SIGNS WILL BE POSTED.

PREPARED AND SUBMITTED BY:

BASIL F. PINZONE, JR. 05/19/2010
TECHNICAL CONSULTANT

EXHIBIT B - ANALYSIS OF NON-IONIZING RADIATION

HARMFUL LEVELS OF RADIATION WILL NOT EXIST IN REGIONS NORMALLY OCCUPIED BY PERSONNEL.

CRITERIA: ANSI SPECIFICATIONS REQUIRE THAT PERSONNEL NOT BE EXPOSED TO LEVELS OF NON-IONIZING RADIATION EXCEEDING 5 mW / cm².

THE FOLLOWING ANALYSES SUPPORT THIS DETERMINATION:

FAR FIELD ANALYSIS:

EFFICIENCY = $\eta = G/(\pi * D/\lambda)^2 = 0.586$
ANTENNA GAIN = 58.3 dBi (lin 676,083)
ANTENNA DIAMETER = 7.2 Meters
LAMBDA = $3 * 10^8$ Meters / $14.25 * 10^9$ Hz = 0.0210526
POWER MAX AT FLANGE = 1130 Watts (30.5 dBW)
DISTANCE TO FAR FIELD = $2 * D^2/\lambda$
= 103.68 / 0.0210526
= 4925 Meters
ON-AXIS POWER DENSITY = $G * P/4 * \pi * \text{Far Field Distance}^2$
= $676,083 * 1130 / 12.56637 * 24,255,625$
= 2.506 W/m²
= 0.251 mW/cm²

LEVEL IS LESS THAN THE 5 mW/cm² MAXIMUM ANSI LEVEL PERMITTED

NEAR FIELD ANALYSIS (Parallel Beam Region & Transition Region):

PARALLEL BEAM REGION ANALYSIS:

DISTANCE TO END OF PARALLEL BEAM (CYLINDER) REGION:
= $\text{DIAMETER}^2 / 2.5 * \lambda$
= 51.84 / 0.0526315
= 984 Meters
POWER DENSITY AT END OF PARALLEL BEAM REGION
= P / CYLINDRICAL PARALLEL BEAM AREA
= 1130 / 40.715
= 27.75 W / m²
= 2.78 mW / cm²

LEVEL IS LESS THAN THE 5 mW/m² MAXIMUM ANSI LEVEL PERMITTED

ADDITIONAL PRECAUTION: Personnel will not be permitted within 1 meter of the aperture cylinder during normal operations

TRANSITION REGION ANALYSIS:

THIS REGION WILL DECREASE INVERSELY WITH DISTANCE BEGINNING AT THE END OF THE PARALLEL BEAM REGION AND WILL NOT EXCEED 2.78 mW / cm² LEVEL IS LESS THAN THE 5 mW/m² MAXIMUM ANSI LEVEL PERMITTED

ADDITIONAL PRECAUTION: Personnel will not be permitted within 1 meter of the aperture cylinder during normal operations

MAIN REFLECTOR ANALYSIS:

$$\begin{aligned} &= P / \text{REFLECTOR AREA} \\ &= 1130 / 40.715 \\ &= 27.75 \text{ W / m}^2 \\ &= 2.78 \text{ mW / cm}^2 \end{aligned}$$

LEVEL IS LESS THAN THE 5 mW/m² MAXIMUM ANSI LEVEL PERMITTED

ADDITIONAL PRECAUTION: Personnel will not be permitted within 1 meter of the aperture cylinder during normal operations

FEED TO SUB-REFLECTOR / REFLECTOR ANALYSIS:

$$\begin{aligned} \text{POWER DENSITY AT FEED FLANGE} &= P / \text{FEED AREA} \\ &= 1130 / 0.159 \\ &= 7107 \text{ W/m}^2 \\ &= 711 \text{ mW/cm}^2 \end{aligned}$$

! POTENTIAL HAZARD FROM FEED TO SUB-REFLECTOR TO REFLECTOR !

RF POWER WILL BE TURNED OFF DURING ANTENNA MAINTENANCE REQUIRING PERSONNEL TO OCCUPY THE HAZARDOUS CONICAL REGION BETWEEN THE FEED HORN, SUB-REFLECTOR, AND REFLECTOR.

PREPARED AND SUBMITTED BY:

BASIL F. PINZONE, JR. 05/19/2010
TECHNICAL CONSULTANT