

## RF RADIATION HAZARD ANALYSIS

### Exhibit #B

Antenna Dia. (D)=1.2 Meters 3.937 Feet  
Antenna Surface Area (SA)=1.131 sq meters  
Subreflector Dia. (DS)=N/A (prime focus offset)  
Subreflector Surface Area (AS)=N/A  
KU Wavelength at 14.250 GHz (LAMBDA)=.0211 meters  
Power at output of HPA flange=18.451 dB  
Path Loss to OMT (IL)=.6 dB  
Power at OMT Flange (P)=60.967 watts  
Antenna Gain at 14.250 GHz (G)=43.5 dBi (2 port antenna gain)  
Antenna Gain given in Power Ratio (GES)=2.239E+04  
Antenna Aperture Efficiency (N)=.6982

| <u>Region</u>                                   | <u>Radiation Level</u>                   | <u>Hazard Assessment</u> |
|---|--|--------------------------|
| Far Field (Rf) 40.948 m 134.35 ft               | 6.478 mW/cm sq                           | Potential Hazard         |
| Near Field (Wf) 17.062m 55.979 ft               | 15.055 mW/cm sq                          | Potential Hazard         |
| Transition Region (Rt)<br>Ru<Rt<Rf              | equal to or less than<br>15.055 mW/cm sq | Potential Hazard         |
| Between Main Reflector and<br>Subreflector (Ws) | N/A (no subreflector)                    |                          |
| Main Reflector Region (Wm)                      | 10.781 mW/cm sq                          | Potential Hazard         |
| Power Density Between Reflector<br>and Ground   | 5.391 mW/cm sq                           | Potential Hazard         |
| Far Field Off Axis (WF)                         | ..065 mW/cm sq                           | Meets ANSI Requirements  |
| Near Field Off Axis (WN)                        | .151 mW/cm sq                            | Meets ANSI Requirements  |

**Conclusion:** Based on the above analysis, harmful areas of Radiation do exist in areas around the antenna and in the path of the antenna toward the satellite that it is pointed at. The Area occupied by the general public will not exceed the ANSI limit of 1 mW cm sq. because the antenna is mounted on top of the truck, which is at least 8 feet above the ground, and safety increases with look angles used by the Satellites in the United States on Dom. Sat. arch. The areas on the ground and behind the antenna are 100 times less power (20 dB) when at a min. of the dia. of the reflector, this is reflected in the Off Axis figures as seen above (WF) & (WN). The SNG will be marked with the standard radiation hazard warnings, and on the antenna itself. The warning signs will warn personnel to avoid the area around and in front of the reflector when the transmitter is operating. To ensure compliance with safety limits, the earth station transmitter will be turned off and marked to remain off whenever maintenance and repair personnel are required to work in the areas of potential hazard as defined in the above study. Additionally the earth station personnel will be trained to insure that the antenna path is clear at all times while the transmitter is in operation. The only access to the roof of the truck, is a stored ladder which will only be used when the transmitter is off and not accessible by the general public.

Note: See Exhibit #Ba for how the above calculations were made.

**Exhibit Ba Analysis of Non-Ionizing Radiation**

|   |   |                             |                                 |
|---|---|-----------------------------|---------------------------------|
| Antenna Diameter, (D)=.....                   | D := 1.2 meters                         | D·3.281 = 3.937             | Feet                            |
| Antenna Surface Area, (Sa)= .....             | $Sa := \pi \cdot \frac{D \cdot D}{4}$   | Sa = 1.131                  | sq meters                       |
| Subreflector Diameter, (Ds)=.....             | Ds := 0                                 | cm                          | Ds·3.937 = 0 Inch's             |
| Area of Subreflector, (As)=.....              | $As := \pi \cdot \frac{Ds \cdot Ds}{4}$ | As = 0                      | sq cm                           |
| Center Frequency, (Cf)=.....                  | CF := 14.250                            | GHz                         |                                 |
| Wavelength at (Cf), (Lambda)=.....            | Lambda := .0211                         | meters                      |                                 |
|   | C-Band=.049                             | Ku-Band=.0211               |                                 |
| Transmit Power at HPA or VPC Flange, (P1)=..  | P1 := 70                                | watts                       | P2 := log(P1)·10 P2 = 18.451 dB |
| Path Loss from HPA or VPC to OMT, (Loss)=..   | Loss := .6                              | dB                          |                                 |
| Power at OMT, (P)=.....                       | P3 := P2 - Loss                         | P3 = 17.851                 | OMT Pwr in dB                   |
|   | $P := 10^{\frac{P3}{10}}$               | P = 60.967                  | OMT Pwr in watts                |
| Antenna Gain at (Cf), (Gain)=.....            | Gain := 43.5                            | dBi                         |                                 |
| Antenna Gain Converted to Power Ratio, (Ges). | $Ges := 10^{\frac{Gain}{10}}$           | Ges = 2.239·10 <sup>4</sup> | Ratio                           |
| Antenna Aperture Efficiency, (n)=.....        | n := .6982                              |                             |                                 |

|   |   |             |          |                         |      |
|---|---|-------------|----------|-------------------------|------|
| Far Field (Rf)=                                     | $Rf := \frac{.60 \cdot (D \cdot D)}{\text{Lambda}}$         | Rf = 40.948 | meters   | Rf·3.281 = 134.35       | Feet |
| Far Field Pwr Density (Wf)=                         | $Wf := \frac{Ges \cdot P}{4 \cdot \pi \cdot (Rf \cdot Rf)}$ | Wf = 6.478  | mw sq cm |                         |      |
| Near Field (Rn)=                                    | $Rn := \frac{D \cdot D}{4 \cdot \text{Lambda}}$             | Rn = 17.062 | meters   | Rn·3.281 = 55.979       | Feet |
| Near Field Pwr Density (Wn)=                        | $Wn := \frac{16 \cdot n \cdot P}{\pi \cdot (D \cdot D)}$    | Wn = 15.055 | mw sq cm |                         |      |
| Transition Region (Rt)=                             | Rt := Wn·1  | Rt = 15.055 | mw sq cm | (Equal to or less then) |      |
| Pwr Density at Sub Reflector (Ws)=                  | (N/A No Sub Reflector)                                      |             |          |                         |      |
| Main Reflector Region Pwr Density (Wm)=             | $Wm := \frac{2 \cdot P}{Sa}$                                | Wm = 10.781 | mw sq cm |                         |      |
| Pwr Density between main reflector and ground (Wg)= | $Wg := \frac{P}{Sa}$  | Wg = 5.391  | mw sq cm |                         |      |
| Far Field Off Axis (WF)=                            | WF := Wf·.01  | WF = 0.065  | mw sq cm |                         |      |
| Near Field Off Axis (WN)=                           | WN := Wn·.01  | WN = 0.151  | mw sq cm |                         |      |