

## RF RADIATION HAZARD ANALYSIS

### Exhibit #B

Antenna Dia. (D)=1.5 Meters 4.922 Feet  
Antenna Surface Area (SA)=1.767sq meters  
Subreflector Dia. (DS)=N/A (prime focus offset)  
Subreflector Surface Area (AS)=N/A (prime focus offset)  
KU Wavelength at 14.250 GHz (LAMBDA)=.0211 meters  
Power at output of HPA flange=25.441 dB  
Path Loss to OMT (IL)=1.0 dB  
Power at OMT Flange (P)=278.015 watts  
Antenna Gain at 14.250 GHz (G)=45.9 dBi  
Antenna Gain given in Power Ratio (GES)=.3890E+05  
Antenna Aperture Efficiency (N)=.7902

<u>Region</u>	<u>Radiation Level</u>	<u>Hazard Assessment</u>
Far Field (RF) 63.981 m 209.922 ft	21.026 mW/cm sq	Potential Hazard
Near Field (WF) 26.659 m 87.467 ft	49.727 mW/cm sq	Potential Hazard
Transition Region (RT) Ru<Rt<Rf	equal to or less than 49.727 mW/cm sq	Potential Hazard
Between Main Reflector and Subreflector (WS)	N/A	
Main Reflector Region (WM)	31.465 mW/cm sq	Potential Hazard
Power Density Between Reflector and Ground	15.732 mW/cm sq	Potential Hazard

**Conclusion:** Based on the above analysis, harmful areas of Radiation do exist in areas around the antenna and in the path of the antenna toward the satellite that it is pointed at. The Area occupied by the general public will not exceed the ANSI limit of 1 mW cm sq. because the antenna is mounted on top of the truck, which is at least 8 feet above the ground, and safety increases with look angles used by the Satellites in the United States on Dom. Sat. arch. The SNG will be marked with the standard radiation hazard warnings, and on the antenna itself. The warning signs will warn personnel to avoid the area around and in front of the reflector when the transmitter is operating. To ensure compliance with safety limits, the earth station transmitter will be turned off and marked to remain off whenever maintenance and repair personnel are required to work in the areas of potential hazard as defined in the above study. Additionally the earth station personnel will be trained to insure that the antenna path is clear at all times while the transmitter is in operation

Note: See Exhibit #Ba for how the above calculations were made.

### Exhibit Ba Analysis of Non-Ionizing Radiation

Antenna Diameter, (D)=.....	D := 1.5 meters    D·3.281 = 4.922 Feet
Antenna Surface Area, (Sa)= .....	$Sa := \pi \cdot \frac{D \cdot D}{4}$ Sa = 1.767 sq meters
Subreflector Diameter, (Ds)=.....	Ds := 0 cm    Ds·.3937 = 0 Inch's
Area of Subreflector, (As)=.....	$As := \pi \cdot \frac{Ds \cdot Ds}{4}$ As = 0 sq cm
Center Frequency, (Cf)=.....	CF := 14.250 GHz
Wavelength at (Cf), (Lambda)=.....	Lambda := .0211 meters
	C-Band=.049 Ku-Band=.0211
Transmit Power at HPA or VPC Flange, (P1)=..	P1 := 350 watts    P2 := log(P1)·10    P2 = 25.441dB
Path Loss from HPA or VPC to OMT, (Loss)=..	Loss := 1.0 dB
Power at OMT, (P)=.....	P3 := P2 - Loss    P3 = 24.441 OMT Pwr in dB
	$P := 10^{\frac{P3}{10}}$ P = 278.015 OMT Pwr in watts
Antenna Gain at (Cf), (Gain)=.....	Gain := 45.9 dBi
Antenna Gain Converted to Power Ratio, (Ges).	$Ges := 10^{\frac{Gain}{10}}$ Ges = 3.89·10 <sup>4</sup> Ratio
Antenna Aperture Efficiency, (n)=.....	n := .7902

Far Field (Rf)=	$Rf := \frac{.60 \cdot (D \cdot D)}{\text{Lambda}}$ Rf = 63.981 meters    Rf·3.281 = 209.922 Feet
Far Field Pwr Density (Wf)=	$Wf := \frac{Ges \cdot P}{4 \cdot \pi \cdot (Rf \cdot Rf)} \cdot .1$ Wf = 21.026 mw sq cm
Near Field (Rn)=	$Rn := \frac{D \cdot D}{4 \cdot \text{Lambda}}$ Rn = 26.659 meters    Rn·3.281 = 87.467 Feet
Near Field Pwr Density (Wn)=	$Wn := \frac{16 \cdot n \cdot P}{\pi \cdot (D \cdot D)} \cdot .1$ Wn = 49.727 mw sq cm
Transition Region (Rt)=	Rt := Wn·1    Rt = 49.727 mw sq cm (Equal to or less then)
Pwr Density at Sub Reflector (Ws)=	N/A <span style="background-color: black; color: black;"> </span> = N/A mw sq cm
Main Reflector Region Pwr Density (Wm)=	$Wm := \frac{2 \cdot P}{Sa} \cdot .1$ Wm = 31.465 mw sq cm
Pwr Density between main reflector and ground (Wg)=	$Wg := \frac{P}{Sa} \cdot .1$ Wg = 15.732 mw sq cm