

Exhibit B - Radiation Hazard Study

When applying for a license to construct and operate, modify, or renew an earth station, it is understood that the applicant must certify whether grant of the application will have significant environmental impact as defined in the Federal Communications Commission's (FCC) rules, 47 C.F.R. § 1.1307.

In this report Spacenet analyzes the maximum radiofrequency (RF) levels emitted from the satellite communications antenna described below. The reference document for this study is OET Bulletin No.65, Edition 97-01, *Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields*, August 1997.

1. Antenna Near-Field Power Density Calculation

The extent of the near-field is defined by the following equation¹:

$$R_{near} = (D_{antenna})^2 / (4 \lambda)$$

where: R_{near} = extent of the near-field (in meters)

$D_{antenna}$ = diameter of the antenna main reflector (in meters)

λ = wavelength of the RF transmit frequency (in meters)

The maximum on-axis power density within near-field is defined by the following equation²:

$$S_{near} = \{(16\eta P_{feed}) / [\pi (D_{antenna})^2]\} / 10$$

where: S_{near} = maximum on-axis power density within the near-field (in milliwatts per square centimeter)

η = antenna aperture efficiency

P_{feed} = maximum power into antenna feed flange (in watts)

$D_{antenna}$ = diameter of the antenna main reflector (in meters)

¹ See OET 65 page 27 formula (12).

² See OET 65 page 28 formula (13). The right side of the equation is divided by 10 so that the power spectral density units on the left side will be mW/cm².

Exhibit B - Radiation Hazard Study

2. Antenna Far-Field Power Density Calculation

The distance to the beginning of the far-field region is defined by the following equation³:

$$R_{far} = [0.6(D_{antenna})^2] / \lambda$$

where: R_{far} = distance to beginning of far-field (in meters)
 $D_{antenna}$ = diameter of the antenna main reflector (in meters)
 λ = wavelength of the transmit frequency (in meters)

The maximum on-axis power density within the far-field is defined by the following equation⁴:

$$S_{far} = [(P_{feed} G_{antenna}) / 4 \pi (R_{far})^2] / 10$$

where: S_{far} = maximum on-axis power density in the far-field (in milliwatts per square centimeter)
 P_{feed} = maximum power into antenna feed flange (in watts)
 $G_{antenna}$ = antenna main beam gain at AF transmit frequency (in numeric value)
 R_{far} = distance to beginning of far-field (in meters)

The on-axis power densities calculated from the above formulas represent the maximum exposure levels that the system can produce. Off-axis power densities will be considerably less.

3. Antenna Transition Region Power Density Calculation

The on-axis power spectral density for the transition region is defined by the following formula⁵:

$$S_{tr} = S_{near} R_{near} / R$$

where: S_{tr} = maximum on-axis power density in the transition region (in milliwatts per square centimeter)
 S_{near} = maximum on-axis power density in the near-field (in milliwatts per square centimeter)
 R_{near} = is the distance that defines the end of the near field region.
 R = is the distance within in the transition region between the near field and far field regions.

³ See OET 65 page 29 formula (16).

⁴ See OET 65 Section 2, page 19, formula (3) and page 29, formula (18). The right side of the equation is divided by 10 so that the power spectral density units on the left side will be mW/cm².

⁵ See OET 65 page 34, formula (17).

Exhibit B - Radiation Hazard Study

Since the distance within the transition region “R” will always be greater than the distance to the end of the near field region “R_{near}” then $S_{tr} \leq S_{near}$.

4. Antenna Feed-Flange Power Density Calculation

The maximum power density at the antenna feed-flange is defined by the following equation⁶:

$$S_{feed} = 1000 \{ [4(P_{feed})] / \{ [\pi (D_{feed})^2] / 4 \} \}$$

where: S_{feed} = maximum power density at the antenna feed-flange (in milliwatts per square centimeter)

P_{feed} = maximum power into antenna feed flange (in watts)

D_{feed} = diameter of the antenna feed-flange (in centimeters)

5. Antenna Main Reflector Power Density Calculation

The maximum power density in the main reflector region of the antenna is defined by the following equation⁷:

$$S_{antenna} = \{ [4(P_{feed})] / \{ [\pi \{ (D_{antenna})^2 \} / 4 \} \} / 10$$

where: $S_{antenna}$ = maximum power density in the antenna main reflector region (in milliwatts per square centimeter)

P_{feed} = maximum power into antenna feed flange (in watts)

$D_{antenna}$ = diameter of the antenna main reflector (in meters)

6. Power Density Calculation between the Antenna Main Reflector and the Ground

The maximum power density between the antenna main reflector and the ground is defined by the following equation:

$$S_{ground} = \{ P_{feed} / \{ [\pi \{ (D_{antenna})^2 \} / 4 \} \} / 10$$

where: S_{ground} = maximum power density between the antenna main reflector and the ground (in milliwatts per square centimeter)

P_{feed} = maximum power into antenna feed flange (in watts)

⁶ The formula is multiplied by 1,000 on the right side of the equation to change the units from watts on the right side of the equation to milliwatts on the left side.

⁷ See OET 65 equation (11) which is “S = 4 P / A”, where “A” is the area of the reflector and for a circular reflector $A = \pi (D_{antenna})^2 / 4$. The formula is divided by 10 on the right side to change the units from meters and watts on the right side of the formula to cm and mW on the left side.

Exhibit B - Radiation Hazard Study

$D_{antenna}$ = diameter of the antenna main reflector (in meters)

7. Calculation of Radiation Levels and FCC Standards

Spacenet understands that a licensee must ensure that people are not exposed to harmful levels of radiation. Spacenet plans to utilize the 1.2 meter Andrew fixed and temporary-fixed antennas with 1, 2 or 4-watt transmitters. The transmitters will be operated at full output power. The preceding formulas were used to calculate the power densities shown on the following page.

The Commission's maximum permissible exposure (MPE) limits at the transmit frequency band for the earth stations included in this application are provided in the table set forth below.

Maximum Permissible Exposure (MPE) Limits at 14,000-14,500 MHz

Exposure Criteria	Power Density (mW/cm ²)	Averaging Time (minutes)	Reference
general population/uncontrolled exposure	1	6	OET 65 page 67 Appendix A Table 1 (A)
occupational/controlled exposure	5	30	OET 65 page 67 Appendix A Table 1 (B)

Exhibit B - Radiation Hazard Study

Radiation Hazard Calculations

Site ID	REMOTE 1	REMOTE 2	HUB
Antenna ID	1.2C	1.2P	7.6M
Antenna main reflector diameter	1.2 m	1.2 m	7.6 m
Feed flange diameter	14.63 cm	14.63 cm	16.50 cm
RF transmit frequency	14.250 GHz	14.250 GHz	14.250 GHz
Maximum power into antenna feed-flange	2.0 W	2.0 W	70 W
Main-beam gain of antenna	43.3 dBi	43.2 dBi	59.0 dBi
Antenna aperture efficiency	0.67	0.65	0.62
Antenna main reflector surface area	1.131 m ²	1.131 m ²	45.36 m ²
Feed flange surface area	168.1 cm ²	168.1 cm ²	213.8 cm ²
Wavelength at RF transmit frequency	0.021 m	0.021 m	0.021 m
Distance to beginning of far-field region	41.0 m	41.0 m	1647.3 m
Distance to extent of near-field region	17.1 m	17.1 m	386.4 m

Max. on-axis power density in far-field	0.20 mW/cm² Satisfies MPE Limits	0.20 mW/cm² Satisfies MPE Limits	0.16 mW/cm² Satisfies MPE Limits
Max. on-axis power density in near-field	0.47 mW/cm² Satisfies MPE Limits	0.46 mW/cm² Satisfies MPE Limits	0.38 mW/cm² Satisfies MPE Limits
Max. on-axis power density in transition region	0.47 mW/cm² Satisfies MPE Limits	0.46 mW/cm² Satisfies MPE Limits	0.38 mW/cm² Satisfies MPE Limits
Max. power density at feed-flange (see note 1)	47.6 mW/cm² Potential Hazard	47.6 mW/cm² Potential Hazard	1309.5 mW/cm² Potential Hazard
Max. power density at main reflector	0.71 mW/cm² Satisfies All MPE Limits	0.71 mW/cm² Satisfies All MPE Limits	0.62 mW/cm² Satisfies All MPE Limits
Max. power density between main reflector and ground	0.18 mW/cm² Satisfies All MPE Limits	0.18 mW/cm² Satisfies All MPE Limits	0.15 mW/cm² Satisfies All MPE Limits

Note 1: Feed flange power density exceeds both uncontrolled MPE limit of 1 mW/cm² and controlled MPE limit of 5 mW/cm²

Exhibit B - Radiation Hazard Study

8. Results Analysis

1.2 meter Antennas

The calculations provided in this exhibit indicate that MPE limits are exceeded at the antenna feed flange for the 1.2 meter earth stations. The antennas exceed the MPE limits for occupational/controlled and general population/uncontrolled exposure at the feed horn and in the area between the feed horn and reflector.

All 1.2 meter fixed antennas are and will be installed such that the area where the MPE is exceeded will not be readily accessible to humans. Additionally, all transmissions will be terminated whenever the technical staff is required, for maintenance or other activities, to occupy the regions where potentially hazardous power density levels can exist.

The 1.2 meter earth stations will have an automatic shut-off mechanism that will terminate transmissions if the receive signal is lost, which will occur if there is blockage of the area between the feed horn and reflector.

7.6 meter Antenna

The calculations provided in this exhibit indicate that MPE limits are exceeded at the antenna feed flange for the 7.6 meter earth station. The antenna exceeds the MPE limits for occupational/controlled and general population/uncontrolled exposure at the feed horn and in the area between the feed horn and reflector.

The 7.6 meter antenna is installed such that the area where the MPE is exceeded will not be readily accessible to humans. Additionally, all transmissions will be terminated whenever the technical staff is required, for maintenance or other activities, to occupy the regions where potentially hazardous power density levels can exist.

9. Conclusion

Dollar General Corporation, and its VSAT network supplier Spacenet, understand that Dollar General must ensure that people are not exposed to harmful levels of radiation and have and will continue to act to ensure that people are not exposed to harmful levels of radiation in the operation of the Dollar General VSAT Network.

Exhibit B - Radiation Hazard Study

10. Certification

I hereby certify that I am the technically qualified person responsible for preparation of the engineering information contained in this radiation hazard assessment, that I have reviewed the engineering information submitted, and that it is complete and accurate to the best of my knowledge.

Paul Holland
RF Engineering Chief Engineer
Spacenet Inc.
June 24, 2013