

EXHIBIT WITH RADIATION HAZARD REPORTS

INCLUDES RADIATION HAZARD REPORTS FOR:

INTELLIAN 0.60 METER KU-BAND ANTENNA (MODEL V60G) WITH 16 WATT BUC

INTELLIAN 0.83 METER KU-BAND ANTENNA (MODEL V80G) WITH 16 WATT BUC

INTELLIAN 2.4 METER C-BAND ANTENNA (Model V240K) WITH 100 WATT BUC

SEA TEL 0.9 METER KU-BAND ANTENNA (Model 3612) WITH 16 WATT BUC

SEA TEL 1.0 METER KU-BAND ANTENNA (Model 4006/4009/4010) WITH 16 WATT BUC

SEA TEL 1.06 METER KU-BAND ANTENNA (Model 4012) WITH 16 WATT BUC

SEA TEL 1.2 METER KU-BAND ANTENNA (MODEL 5009/5010/5012 WITH 25 WATT BUC

SEA TEL 2.4 METER KU-BAND ANTENNA (Model 9797 AND 9711) WITH 100 WATT BUC

Analysis of Non-Ionizing Radiation for a 0.6-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 0.6-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	0.6	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	0.28	m ²
Subreflector Diameter	D _{sr}	Input	6.8	cm
Area of Subreflector	A _{sr}	$\pi D_{sr}^2 / 4$	36.32	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	$300 / F$	0.021053	m
Transmit Power	P	Input	11.59	W
Antenna Gain (dBi)	G _{es}	Input	38.3	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	6760.8	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2 / (\pi^2 D^2)$	0.84	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 10.3 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 59.235 \text{ W/m}^2 \\ &= 5.924 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 4.3 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 138.281 \text{ W/m}^2 \\ &= 13.828 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 13.828 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Main Reflector and the Subreflector

Transmissions from the feed assembly are directed toward the subreflector surface, and are reflected back toward the main reflector. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the subreflector and the reflector surfaces can be calculated by determining the power density at the subreflector surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Subreflector} \quad S_{sr} &= 4000 P / A_{sr} & (6) \\ &= 1276.544 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the subreflector. The area is now the area of the main reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Main Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 163.965 \text{ W/m}^2 \\ &= 16.396 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Main Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 40.991 \text{ W/m}^2 \\ &= 4.099 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 10.3$ m)	S_{ff}	5.924	Potential Hazard
2. Near Field ($R_{nf} = 4.3$ m)	S_{nf}	13.828	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	13.828	Potential Hazard
4. Between Main Reflector and Subreflector	S_{sr}	1276.544	Potential Hazard
5. Main Reflector	$S_{surface}$	16.396	Potential Hazard
6. Between Main Reflector and Ground	S_g	4.099	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 10.3$ m)	S_{ff}	5.924	Potential Hazard
2. Near Field ($R_{nf} = 4.3$ m)	S_{nf}	13.828	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	13.828	Potential Hazard
4. Between Main Reflector and Subreflector	S_{sr}	1276.544	Potential Hazard
5. Main Reflector	$S_{surface}$	16.396	Potential Hazard
6. Between Main Reflector and Ground	S_g	4.099	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that harmful levels of radiation may exist in those regions noted for the Uncontrolled (Table 4) and Controlled (Table 5) environments.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to insure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working, or otherwise present on the roof, deck, and in or near, the main beam of the antenna.

Finally, occupational exposure will be limited, and the transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mW/cm^2 will be complied with for those regions in close proximity to the main reflector, and subreflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.

Analysis of Non-Ionizing Radiation for a 0.83-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 0.83-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	0.83	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	0.54	m ²
Subreflector Diameter	D _{sr}	Input	5.0	cm
Area of Subreflector	A _{sr}	$\pi D_{sr}^2 / 4$	19.63	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	$300 / F$	0.021053	m
Transmit Power	P	Input	11.59	W
Antenna Gain (dBi)	G _{es}	Input	39.8	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	9549.9	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2 / (\pi^2 D^2)$	0.62	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 19.6 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 22.849 \text{ W/m}^2 \\ &= 2.285 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 8.2 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 53.340 \text{ W/m}^2 \\ &= 5.334 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 5.334 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Main Reflector and the Subreflector

Transmissions from the feed assembly are directed toward the subreflector surface, and are reflected back toward the main reflector. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the subreflector and the reflector surfaces can be calculated by determining the power density at the subreflector surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Subreflector} \quad S_{sr} &= 4000 P / A_{sr} & (6) \\ &= 2361.095 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the subreflector. The area is now the area of the main reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Main Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 85.684 \text{ W/m}^2 \\ &= 8.568 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Main Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 21.421 \text{ W/m}^2 \\ &= 2.142 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 19.6$ m)	S_{ff}	2.285	Potential Hazard
2. Near Field ($R_{nf} = 8.2$ m)	S_{nf}	5.334	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	5.334	Potential Hazard
4. Between Main Reflector and Subreflector	S_{sr}	2361.095	Potential Hazard
5. Main Reflector	$S_{surface}$	8.568	Potential Hazard
6. Between Main Reflector and Ground	S_g	2.142	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 19.6$ m)	S_{ff}	2.285	Satisfies FCC MPE
2. Near Field ($R_{nf} = 8.2$ m)	S_{nf}	5.334	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	5.334	Potential Hazard
4. Between Main Reflector and Subreflector	S_{sr}	2361.095	Potential Hazard
5. Main Reflector	$S_{surface}$	8.568	Potential Hazard
6. Between Main Reflector and Ground	S_g	2.142	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that harmful levels of radiation may exist in those regions noted for the Uncontrolled (Table 4) and Controlled (Table 5) environments.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to insure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working, or otherwise present on the roof, deck, and in or near, the main beam of the antenna.

Finally, occupational exposure will be limited, and the transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mW/cm^2 will be complied with for those regions in close proximity to the main reflector, and subreflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.

Analysis of Non-Ionizing Radiation for a 2.4-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 2.4-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	2.4	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	4.52	m ²
Feed Flange Diameter	D _{fa}	Input	2.9	cm
Area of Feed Flange	A _{fa}	$\pi D_{fa}^2 / 4$	6.61	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	$300 / F$	0.021053	m
Transmit Power	P	Input	72.44	W
Antenna Gain (dBi)	G _{es}	Input	48.0	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	63095.7	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2 / (\pi^2 D^2)$	0.49	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 164.2 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 13.497 \text{ W/m}^2 \\ &= 1.350 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 68.4 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 31.508 \text{ W/m}^2 \\ &= 3.151 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 3.151 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Feed Assembly and the Antenna Reflector

Transmissions from the feed assembly are directed toward the antenna reflector surface, and are confined within a conical shape defined by the type of feed assembly. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the feed assembly and reflector surface can be calculated by determining the power density at the feed assembly surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Feed Flange} \quad S_{fa} &= 4000 P / A_{fa} & (6) \\ &= 43868.476 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the feed assembly. The area is now the area of the reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 64.051 \text{ W/m}^2 \\ &= 6.405 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 16.013 \text{ W/m}^2 \\ &= 1.601 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 164.2$ m)	S_{ff}	1.350	Potential Hazard
2. Near Field ($R_{nf} = 68.4$ m)	S_{nf}	3.151	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	3.151	Potential Hazard
4. Between Feed Assembly and Antenna Reflector	S_{la}	43868.476	Potential Hazard
5. Main Reflector	$S_{surface}$	6.405	Potential Hazard
6. Between Reflector and Ground	S_g	1.601	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 164.2$ m)	S_{ff}	1.350	Satisfies FCC MPE
2. Near Field ($R_{nf} = 68.4$ m)	S_{nf}	3.151	Satisfies FCC MPE
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	3.151	Satisfies FCC MPE
4. Between Feed Assembly and Antenna Reflector	S_{la}	43868.476	Potential Hazard
5. Main Reflector	$S_{surface}$	6.405	Potential Hazard
6. Between Reflector and Ground	S_g	1.601	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that FCC RF Guidelines have been exceeded in the specified region(s) of the Uncontrolled (Table 4) and Controlled (Table 5) environments. The applicant proposes to comply with the Maximum Permissible Exposure (MPE) limits of 1.0 mW/cm² for the Uncontrolled Areas, and the MPE limits of 5.0 mW/cm² for the Controlled Areas.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to ensure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working or otherwise present on the deck, and in or near, the main beam of the antenna.

Finally, the earth station's operating personnel will not have access to areas that exceed the MPE levels, while the earth station is in operation. The transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mW/cm² will be complied with for those regions in close proximity to the main reflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.

Analysis of Non-Ionizing Radiation for a 0.9-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 0.9-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	0.9	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	0.65	m ²
Feed Flange Diameter	D _{fa}	Input	3.8	cm
Area of Feed Flange	A _{fa}	$\pi D_{fa}^2 / 4$	11.34	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	$300 / F$	0.021053	m
Transmit Power	P	Input	15.14	W
Antenna Gain (dBi)	G _{es}	Input	40.5	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	11220.2	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2 / (\pi^2 D^2)$	0.61	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 23.6 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 24.269 \text{ W/m}^2 \\ &= 2.427 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 9.8 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 56.656 \text{ W/m}^2 \\ &= 5.666 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 5.666 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Feed Assembly and the Antenna Reflector

Transmissions from the feed assembly are directed toward the antenna reflector surface, and are confined within a conical shape defined by the type of feed assembly. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the feed assembly and reflector surface can be calculated by determining the power density at the feed assembly surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Feed Flange} \quad S_{fa} &= 4000 P / A_{fa} & (6) \\ &= 5339.847 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the feed assembly. The area is now the area of the reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 93.114 \text{ W/m}^2 \\ &= 9.311 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 23.278 \text{ W/m}^2 \\ &= 2.328 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 23.6$ m)	S_{ff}	2.427	Potential Hazard
2. Near Field ($R_{nf} = 9.8$ m)	S_{nf}	5.666	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	5.666	Potential Hazard
4. Between Feed Assembly and Antenna Reflector	S_{fa}	5339.847	Potential Hazard
5. Main Reflector	$S_{surface}$	9.311	Potential Hazard
6. Between Reflector and Ground	S_g	2.328	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 23.6$ m)	S_{ff}	2.427	Satisfies FCC MPE
2. Near Field ($R_{nf} = 9.8$ m)	S_{nf}	5.666	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	5.666	Potential Hazard
4. Between Feed Assembly and Antenna Reflector	S_{fa}	5339.847	Potential Hazard
5. Main Reflector	$S_{surface}$	9.311	Potential Hazard
6. Between Reflector and Ground	S_g	2.328	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that harmful levels of radiation may exist in those regions noted for the Uncontrolled (Table 4) and Controlled (Table 5) environments.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to insure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working, or otherwise present on the ship, and in or near, the main beam of the antenna.

Finally, occupational exposure will be limited, and the transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mW/cm^2 will be complied with for those regions in close proximity to the main reflector, and subreflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.

Analysis of Non-Ionizing Radiation for a 1.0-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 1.0-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	1.0	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	0.79	m ²
Subreflector Diameter	D _{sr}	Input	5.1	cm
Area of Subreflector	A _{sr}	$\pi D_{sr}^2 / 4$	20.43	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	300 / F	0.021053	m
Transmit Power	P	Input	13.46	W
Antenna Gain (dBi)	G _{es}	Input	40.6	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	11481.5	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2/(\pi^2 D^2)$	0.52	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 28.5 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 15.141 \text{ W/m}^2 \\ &= 1.514 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 11.9 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 35.345 \text{ W/m}^2 \\ &= 3.535 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 3.535 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Main Reflector and the Subreflector

Transmissions from the feed assembly are directed toward the subreflector surface, and are reflected back toward the main reflector. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the subreflector and the reflector surfaces can be calculated by determining the power density at the subreflector surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Subreflector} \quad S_{sr} &= 4000 P / A_{sr} & (6) \\ &= 2635.572 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the subreflector. The area is now the area of the main reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Main Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 68.551 \text{ W/m}^2 \\ &= 6.855 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Main Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 17.138 \text{ W/m}^2 \\ &= 1.714 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 28.5$ m)	S_{ff}	1.514	Potential Hazard
2. Near Field ($R_{nf} = 11.9$ m)	S_{nf}	3.535	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	3.535	Potential Hazard
4. Between Main Reflector and Subreflector	S_{sr}	2635.572	Potential Hazard
5. Main Reflector	$S_{surface}$	6.855	Potential Hazard
6. Between Main Reflector and Ground	S_g	1.714	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 28.5$ m)	S_{ff}	1.514	Satisfies FCC MPE
2. Near Field ($R_{nf} = 11.9$ m)	S_{nf}	3.535	Satisfies FCC MPE
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	3.535	Satisfies FCC MPE
4. Between Main Reflector and Subreflector	S_{sr}	2635.572	Potential Hazard
5. Main Reflector	$S_{surface}$	6.855	Potential Hazard
6. Between Main Reflector and Ground	S_g	1.714	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that harmful levels of radiation may exist in those regions noted for the Uncontrolled (Table 4) and Controlled (Table 5) environments.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to insure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working, or otherwise present on the ship, and in or near, the main beam of the antenna.

Finally, occupational exposure will be limited, and the transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mW/cm^2 will be complied with for those regions in close proximity to the main reflector, and subreflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.

Analysis of Non-Ionizing Radiation for a 1.06-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 1.06-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	1.06	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	0.88	m ²
Feed Flange Diameter	D _{fa}	Input	5.1	cm
Area of Feed Flange	A _{fa}	$\pi D_{fa}^2 / 4$	20.43	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	$300 / F$	0.021053	m
Transmit Power	P	Input	14.79	W
Antenna Gain (dBi)	G _{es}	Input	41.8	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	15135.6	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2 / (\pi^2 D^2)$	0.60	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 32.0 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 17.372 \text{ W/m}^2 \\ &= 1.737 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 13.3 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 40.553 \text{ W/m}^2 \\ &= 4.055 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 4.055 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Feed Assembly and the Antenna Reflector

Transmissions from the feed assembly are directed toward the antenna reflector surface, and are confined within a conical shape defined by the type of feed assembly. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the feed assembly and reflector surface can be calculated by determining the power density at the feed assembly surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Feed Flange} \quad S_{fa} &= 4000 P / A_{fa} & (6) \\ &= 2895.996 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the feed assembly. The area is now the area of the reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 67.039 \text{ W/m}^2 \\ &= 6.704 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 16.760 \text{ W/m}^2 \\ &= 1.676 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 32.0$ m)	S_{ff}	1.737	Potential Hazard
2. Near Field ($R_{nf} = 13.3$ m)	S_{nf}	4.055	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	4.055	Potential Hazard
4. Between Feed Assembly and Antenna Reflector	S_{ia}	2895.996	Potential Hazard
5. Main Reflector	$S_{surface}$	6.704	Potential Hazard
6. Between Reflector and Ground	S_g	1.676	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm²)		Hazard Assessment
1. Far Field ($R_{ff} = 32.0$ m)	S_{ff}	1.737	Satisfies FCC MPE
2. Near Field ($R_{nf} = 13.3$ m)	S_{nf}	4.055	Satisfies FCC MPE
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	4.055	Satisfies FCC MPE
4. Between Feed Assembly and Antenna Reflector	S_{ia}	2895.996	Potential Hazard
5. Main Reflector	$S_{surface}$	6.704	Potential Hazard
6. Between Reflector and Ground	S_g	1.676	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that harmful levels of radiation may exist in those regions noted for the Uncontrolled (Table 4) and Controlled (Table 5) environments.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to insure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working, or otherwise present on the ship, and in or near, the main beam of the antenna.

Finally, occupational exposure will be limited, and the transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mw/cm² will be complied with for those regions in close proximity to the main reflector, and subreflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.

Analysis of Non-Ionizing Radiation for a 1.2-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 1.2-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	1.2	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	1.13	m ²
Feed Flange Diameter	D _{fa}	Input	5.1	cm
Area of Feed Flange	A _{fa}	$\pi D_{fa}^2 / 4$	20.43	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	$300 / F$	0.021053	m
Transmit Power	P	Input	21.19	W
Antenna Gain (dBi)	G _{es}	Input	43.0	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	19952.6	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2 / (\pi^2 D^2)$	0.62	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 41.0 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 19.976 \text{ W/m}^2 \\ &= 1.998 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 17.1 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 46.633 \text{ W/m}^2 \\ &= 4.663 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 4.663 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Feed Assembly and the Antenna Reflector

Transmissions from the feed assembly are directed toward the antenna reflector surface, and are confined within a conical shape defined by the type of feed assembly. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the feed assembly and reflector surface can be calculated by determining the power density at the feed assembly surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Feed Flange} \quad S_{I_a} &= 4000 P / A_{I_a} & (6) \\ &= 4149.165 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the feed assembly. The area is now the area of the reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 74.944 \text{ W/m}^2 \\ &= 7.494 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 18.736 \text{ W/m}^2 \\ &= 1.874 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 41.0$ m)	S_{ff}	1.998	Potential Hazard
2. Near Field ($R_{nf} = 17.1$ m)	S_{nf}	4.663	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	4.663	Potential Hazard
4. Between Feed Assembly and Antenna Reflector	S_{fa}	4149.165	Potential Hazard
5. Main Reflector	$S_{surface}$	7.494	Potential Hazard
6. Between Reflector and Ground	S_g	1.874	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 41.0$ m)	S_{ff}	1.998	Satisfies FCC MPE
2. Near Field ($R_{nf} = 17.1$ m)	S_{nf}	4.663	Satisfies FCC MPE
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	4.663	Satisfies FCC MPE
4. Between Feed Assembly and Antenna Reflector	S_{fa}	4149.165	Potential Hazard
5. Main Reflector	$S_{surface}$	7.494	Potential Hazard
6. Between Reflector and Ground	S_g	1.874	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that harmful levels of radiation may exist in those regions noted for the Uncontrolled (Table 4) and Controlled (Table 5) environments.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to ensure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working, or otherwise present on the roof, deck, and in or near, the main beam of the antenna.

Finally, occupational exposure will be limited, and the transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mW/cm^2 will be complied with for those regions in close proximity to the main reflector, and subreflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.

Analysis of Non-Ionizing Radiation for a 2.4-Meter Earth Station System

This report analyzes the non-ionizing radiation levels for a 2.4-meter earth station system. The analysis and calculations performed in this report comply with the methods described in the FCC Office of Engineering and Technology Bulletin, No. 65 first published in 1985 and revised in 1997 in Edition 97-01. The radiation safety limits used in the analysis are in conformance with the FCC R&O 96-326. Bulletin No. 65 and the FCC R&O specifies that there are two separate tiers of exposure limits that are dependant on the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The Maximum Permissible Exposure (MPE) limits for persons in a General Population/Uncontrolled environment are shown in Table 1. The General Population/Uncontrolled MPE is a function of transmit frequency and is for an exposure period of thirty minutes or less. The MPE limits for persons in an Occupational/Controlled environment are shown in Table 2. The Occupational MPE is a function of transmit frequency and is for an exposure period of six minutes or less. The purpose of the analysis described in this report is to determine the power flux density levels of the earth station in the far-field, near-field, transition region, between the subreflector or feed and main reflector surface, at the main reflector surface, and between the antenna edge and the ground and to compare these levels to the specified MPEs.

Table 1. Limits for General Population/Uncontrolled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	0.2
300-1500	Frequency (MHz)*(0.8/1200)
1500-100,000	1.0

Table 2. Limits for Occupational/Controlled Exposure (MPE)

Frequency Range (MHz)	Power Density (mW/cm ²)
30-300	1.0
300-1500	Frequency (MHz)*(4.0/1200)
1500-100,000	5.0

Table 3. Formulas and Parameters Used for Determining Power Flux Densities

Parameter	Symbol	Formula	Value	Units
Antenna Diameter	D	Input	2.4	m
Antenna Surface Area	A _{surface}	$\pi D^2 / 4$	4.52	m ²
Feed Flange Diameter	D _{fa}	Input	19.0	cm
Area of Feed Flange	A _{fa}	$\pi D_{fa}^2 / 4$	283.53	cm ²
Frequency	F	Input	14250	MHz
Wavelength	λ	$300 / F$	0.021053	m
Transmit Power	P	Input	84.14	W
Antenna Gain (dBi)	G _{es}	Input	48.4	dBi
Antenna Gain (factor)	G	$10^{G_{es}/10}$	69984.2	n/a
Pi	π	Constant	3.1415927	n/a
Antenna Efficiency	η	$G\lambda^2 / (\pi^2 D^2)$	0.55	n/a

1. Far Field Distance Calculation

The distance to the beginning of the far field can be determined from the following equation:

$$\begin{aligned} \text{Distance to the Far Field Region} \quad R_{ff} &= 0.60 D^2 / \lambda \\ &= 164.2 \text{ m} \end{aligned} \quad (1)$$

The maximum main beam power density in the far field can be determined from the following equation:

$$\begin{aligned} \text{On-Axis Power Density in the Far Field} \quad S_{ff} &= G P / (4 \pi R_{ff}^2) \\ &= 17.388 \text{ W/m}^2 \\ &= 1.739 \text{ mW/cm}^2 \end{aligned} \quad (2)$$

2. Near Field Calculation

Power flux density is considered to be at a maximum value throughout the entire length of the defined Near Field region. The region is contained within a cylindrical volume having the same diameter as the antenna. Past the boundary of the Near Field region, the power density from the antenna decreases linearly with respect to increasing distance.

The distance to the end of the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Extent of the Near Field} \quad R_{nf} &= D^2 / (4 \lambda) \\ &= 68.4 \text{ m} \end{aligned} \quad (3)$$

The maximum power density in the Near Field can be determined from the following equation:

$$\begin{aligned} \text{Near Field Power Density} \quad S_{nf} &= 16.0 \eta P / (\pi D^2) \\ &= 40.592 \text{ W/m}^2 \\ &= 4.059 \text{ mW/cm}^2 \end{aligned} \quad (4)$$

3. Transition Region Calculation

The Transition region is located between the Near and Far Field regions. The power density begins to decrease linearly with increasing distance in the Transition region. While the power density decreases inversely with distance in the Transition region, the power density decreases inversely with the square of the distance in the Far Field region. The maximum power density in the Transition region will not exceed that calculated for the Near Field region. The power density calculated in Section 1 is the highest power density the antenna can produce in any of the regions away from the antenna. The power density at a distance R_t can be determined from the following equation:

$$\begin{aligned} \text{Transition Region Power Density} \quad S_t &= S_{nf} R_{nf} / R_t \\ &= 4.059 \text{ mW/cm}^2 \end{aligned} \quad (5)$$

4. Region between the Feed Assembly and the Antenna Reflector

Transmissions from the feed assembly are directed toward the antenna reflector surface, and are confined within a conical shape defined by the type of feed assembly. The most common feed assemblies are waveguide flanges, horns or subreflectors. The energy between the feed assembly and reflector surface can be calculated by determining the power density at the feed assembly surface. This can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Feed Flange} \quad S_{fa} &= 4000 P / A_{fa} & (6) \\ &= 1187.040 \text{ mW/cm}^2 \end{aligned}$$

5. Main Reflector Region

The power density in the main reflector is determined in the same manner as the power density at the feed assembly. The area is now the area of the reflector aperture and can be determined from the following equation:

$$\begin{aligned} \text{Power Density at the Reflector Surface} \quad S_{\text{surface}} &= 4 P / A_{\text{surface}} & (7) \\ &= 74.396 \text{ W/m}^2 \\ &= 7.440 \text{ mW/cm}^2 \end{aligned}$$

6. Region between the Reflector and the Ground

Assuming uniform illumination of the reflector surface, the power density between the antenna and the ground can be determined from the following equation:

$$\begin{aligned} \text{Power Density between Reflector and Ground} \quad S_g &= P / A_{\text{surface}} & (8) \\ &= 18.599 \text{ W/m}^2 \\ &= 1.860 \text{ mW/cm}^2 \end{aligned}$$

7. Summary of Calculations

Table 4. Summary of Expected Radiation levels for Uncontrolled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 164.2$ m)	S_{ff}	1.739	Potential Hazard
2. Near Field ($R_{nf} = 68.4$ m)	S_{nf}	4.059	Potential Hazard
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	4.059	Potential Hazard
4. Between Feed Assembly and Antenna Reflector	S_{fa}	1187.040	Potential Hazard
5. Main Reflector	$S_{surface}$	7.440	Potential Hazard
6. Between Reflector and Ground	S_g	1.860	Potential Hazard

Table 5. Summary of Expected Radiation levels for Controlled Environment

Region	Calculated Maximum Radiation Power Density Level (mW/cm ²)		Hazard Assessment
1. Far Field ($R_{ff} = 164.2$ m)	S_{ff}	1.739	Satisfies FCC MPE
2. Near Field ($R_{nf} = 68.4$ m)	S_{nf}	4.059	Satisfies FCC MPE
3. Transition Region ($R_{nf} < R_t < R_{ff}$)	S_t	4.059	Satisfies FCC MPE
4. Between Feed Assembly and Antenna Reflector	S_{fa}	1187.040	Potential Hazard
5. Main Reflector	$S_{surface}$	7.440	Potential Hazard
6. Between Reflector and Ground	S_g	1.860	Satisfies FCC MPE

It is the applicant's responsibility to ensure that the public and operational personnel are not exposed to harmful levels of radiation.

8. Conclusions

Based upon the above analysis, it is concluded that FCC RF Guidelines have been exceeded in the specified region(s) of the Uncontrolled (Table 4) and Controlled (Table 5) environments. The applicant proposes to comply with the Maximum Permissible Exposure (MPE) limits of 1.0 mW/cm² for the Uncontrolled Areas, and the MPE limits of 5.0 mW/cm² for the Controlled Areas.

The earth station will be mounted aboard a ship, and it is recommended that the lower edge of the antenna should be at least 2 meters above the deck. If this is not the case, additional procedures will be instituted to ensure the safety of the Public in the vicinity of the antenna.

The applicant will ensure that the main beam of the antenna will be pointed at least one diameter away from any buildings, or other obstacles in those areas that exceed the MPE levels. Since one diameter removed from the center of the main beam the levels are down at least 20 dB, or by a factor of 100, public safety will be ensured.

The earth station will be marked with the standard radiation hazard warnings, as well as the area in the vicinity of the earth station, to inform those in the general population, who may be working or otherwise present on the deck, and in or near, the main beam of the antenna.

Finally, the earth station's operating personnel will not have access to areas that exceed the MPE levels, while the earth station is in operation. The transmitter will be turned off during periods of maintenance, so that the MPE standard of 5.0 mW/cm² will be complied with for those regions in close proximity to the main reflector, which could be occupied by operating personnel.

The applicant agrees to abide by the conditions specified in Condition 5208 provided below:

Condition 5208 - The licensee shall take all necessary measures to ensure that the antenna does not create potential exposure of humans to radiofrequency radiation in excess of the FCC exposure limits defined in 47 CFR 1.1307(b) and 1.1310 wherever such exposures might occur. Measures must be taken to ensure compliance with limits for both occupational/controlled exposure and for general population/uncontrolled exposure, as defined in these rule sections. Compliance can be accomplished in most cases by appropriate restrictions such as fencing. Requirements for restrictions can be determined by predictions based on calculations, modeling or by field measurements. The FCC's OET Bulletin 65 (available on-line at www.fcc.gov/oet/rfsafety) provides information on predicting exposure levels and on methods for ensuring compliance, including the use of warning and alerting signs and protective equipment for worker.