



METER

Equivalent Isotropically Radiated Power (EIRP) Calculation

$$P_{Tmax} = P_R + 20\log_{10}f + 20\log_{10}(30 + d) - 27.55 \quad (\text{from NTIA 8.3.28})$$

For the proposed repeaters,

$$P_R = P_{GPS} + G_{antenna} + G_{repeater,adjustable} + G_{repeater,antenna} - G_{dipole} - L_{cable} - L_{free\ space}$$

Where: P_{GPS} is the average power received from GPS satellites in North America (-130 dBm)

$G_{antenna}$ is the gain of the GPS antenna (35 dB)

$G_{repeater,adjustable}$ is the adjustable gain in the repeater (30 dB)

$G_{repeater,antenna}$ is the gain from the repeater antenna (3 dB)

G_{dipole} is the gain dipole antenna and is subtracted to represent isotropic antenna (2.2 dB)

L_{cable} is the cable loss (-12.8 dB)

$L_{free\ space}$ is free space loss

d is the distance from the repeater

f is the frequency of the repeater (1575.42 MHz for L1)

$$L_{free\ space} = 20\log_{10}d + 20\log_{10}f + 32.44$$

$$L_{free\ space} = 20\log_{10}(30) + 20\log_{10}(1575.42) + 32.44$$

$$L_{free\ space} = 66.1\ \text{dB}$$

$$P_R = -130 + 35 + 30 + 3 - 2.2 - 12.8 - 66.1$$

$$P_R = -143.1\ \text{dBm} = 0.000005\ \text{pW}$$

Thus, we can determine P_{Tmax} at $d = 0\ \text{meters}$:

$$P_{Tmax} = -143.1 + 20\log_{10}(1575.42) + 20\log_{10}(30 + 0) - 27.55$$

$$P_{Tmax} = -77.16\ \text{dBm} = 19.23\ \text{pW}$$

Therefore, the proposed repeaters comply to NTIA 8.3.28 because:

$$P_R < -140\ \text{dBm} \text{ and } P_{Tmax} < 39.3\ \text{pW at } d = 0\ \text{meters}$$