FCC §15.247 (i), §2.1091 - RF Exposure

FCC ID: 2A7G5-Z1

Applied procedures / limit

According to FCC §15.247(i) and §1.1307(b)(1), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess of the Commission's guidelines.

Limits for Occupational / Controlled Exposure

Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/ cm²)	Averaging Time E ² , H ² or S (minutes)	
0.3-3.0	614	1.63	(100)*	6	
3.0-30	1842 / f	4.89 / f	(900 / f)*	6	
30-300	61.4	0.163	1.0	6	
300-1500			F/300	6	
1500-100,000			5	6	

Note: *f* is frequency in MHz

Limits for General Population / Uncontrolled Exposure

Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/ cm²)	Averaging Time E ² , H ² or S (minutes)	
0.3-1.34	614	1.63	(100)*	30	
1.34-30	824/f	2.19/f	(180/f)*	30	
30-300	27.5	0.073	0.2	30	
300-1500			F/1500	30	
1500-100,000			1.0	30	

Note: f = frequency in MHz

^{* =} Power density limit is applicable at frequencies greater than 100 MHz

^{* =} Plane-wave equivalent power density

MPE PREDICTION

Predication of MPE limit at a given distance, Equation from OET Bulletin 65, Edition 97-01

$$S = PG/4\pi R^2$$

Where: S = power density

P = power input to antenna

G = power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna, R=20cm

Test Result of RF Exposure Evaluation

	Modes& Channel Freq. (MHz)	Tune up Produce power	Maximu m peak output power (dBm)	Output power to antenna (mW)	Antenna Gain (numeric)	Power Density (S) (mW/ cm2)	Limit (mW / cm2	Result
EDR	8DPSK & HCH	4±1	5	3.1623	0.687 (-1.63dBi)	0.00043	1	Pass
5.2G WIFI	802.11ac2 0&5200	5±1	6	3.9811	1.6866 (2.27dBi)	0.00134	1	Pass
5.8G WIFI	802.11n(H T20)& 5825	5±1	6	3.9811	0.798 (-0.98dBi)	0.00063	1	Pass

BT+WIFI supported simultaneous transmission:

EDR+5GWIFI: Σ MPE Ratio =0.00043+0.00134 =0.00177≤1, So passed.