

Wireless Controlled 0 -10V Dual Channel Dimming DC Device

WCD2CS is a wireless controlled dual channel dimming module powered by 12-24V DC and controlled or monitored via mobile device or cloud platform.




Key Features

- Analog 2Channel (0-10V) independent output to control intensity and color
- BLE4.2 based non-flooding intelligent Mesh
- Zero downtime Over the Air firmware (OTA) updates

Table of Contents

1.	Block Diagram	3
	Specifications	
	Device Dimensions (mm)	
	Connector Description	
5.	Wiring Diagram	5
	Use Cases	
7.	User Precautions	6

1. Block Diagram



2. Specifications

Electrical	Symbol	Min	Тур.	Max.	Unit.	Remarks
Input Voltage	Vin	12		24	Vdc	Rated Input voltage
Input Current	lin1		10	15	mA	@24Vdc, Max RF transmitting
Analogue Dimming Output						
Dimming Output1	Vadimol	0		10	V	Max output tolerance ±5%
Dimming Output2	Vadimo2	0		10	V	Max output tolerance ±5%
Output Current				15	mA	For dimming max output
Dimming Range		0		100	%	
Dimming Resolution			8		bit	100 steps
Dimming Curve			Linear			
Cut Off Voltage			1		V	Programmable

RI	 	 •1	L


Frequency Range	2400		2483.5	MHz	
TX Power	6	8		dBm	Conductive
Frequency Drift(Max)	-25		25	kHz	dF2
Frequency Deviation	±225		±275	kHz	
Carrier Frequency offset		30	150	kHz	
TX current			48	mA	Total current@ Max Tx power
Receive Frequency	2400		2483	kHz	
Rx Current			-37	mA	Total Current @Rx Mode
Receiver Sensitivity	-86		-75	dBm	

Environmental	Symbol	Min	Тур.	Max.	Unit.	Remarks
Ambient Temperature	t _a	-20		50	°C	
Storage Temperature	ts	-20		70	°C	
Relative Humidity				85	%	
IP Rating			IP20		-	Indoor use only
Dimensions			66*47*29		mm	L x W x H (mm)
Net Weight		80	90	100	g	T.B.D

Dimming	Type	Note
Dimming Control 1	0 – 10V	Analog

3. Device Dimensions (mm)


Case Material: 5VA



4. Wire Description


PIN	SYMBOL	COLOR	DESCRIPTION
1	CH1+	Purple	CHI 0 to 10V Analog Output
2	CH2+	Blue	CH2 0 to 10V Analog Output
3	GND	Grey	12V Ground
4	12V	Red	12V(Input)

5. Wiring Diagram




6. Use Cases

1. Controlling Intensity and CCT of LED bulb



2. Controlling LED bulb with Sensor Inputs



7. User Precautions

- Observe the correct polarity of output terminal.
- Avoid input voltage exceeds the maximum rating, which will cause damage to the circuit and result in malfunction
- Static electricity or surge voltage may damage the components inside LED Driver, to avoid this
 please follow the proper anti-electrostatic working process.

8. FCC Statement

• This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.
- Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.
- This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Information

• The device has been evaluated to meet general RF exposure requirement. The device can be use d in portable exposure condition without restriction.