SPECIFICATION

Shenzhen Strongpower Communication Co., Ltd

ShenzhenStrongpowerCommunicationCo., Ltd. E108DC Bluetooth Aatenna SPECIFICATION

Customer		Frequency	2402MHz-2480MHz	
Model	E108DC	Band	27021VII 12-27001VII 12	
Serial No		Color		
RF	Zou Lijun	Structural	Zhou Jun	
designer	Zou Lijuii	engineer	Ziiou Juii	
Technical	Fu Yicheng	Date	2023/10/26	
director	Tu Ticheng	Date	2023/10/20	


Confirm by customer:

INDEXES

1. The equipment of Active&Passive test	3-4
2. Passive test	5-6
2.1 S Parameters	5
2.2 Passive Efficiency and Gain	5
2.3 Passive pattern	6
3.Active test	6-8
3.1 TRP&TIS test	6
4.Matching Circuit	

1. The Equipment of Active&Passive Test


chamber




Satimo



Airlink




Guang Ping



GTS

equipment


















2. Passive Test

2.1 S Parameters, VSWR, Return loss, Smith Chart



2.2 Passive Efficiency and Gain


R

L

频率(MHz)	Efficiency%	Gain dBi
2400	23.01%	-1.92
2410	23.25%	-1.79
2420	22.71%	-1.83
2430	22.47%	-1.87
2440	22.49%	-1.84
2450	22.80%	-1.71
2460	22.82%	-1.58
2470	22.37%	-1.59
2480	22.50%	-1.53

频率(MHz)	Efficiency%	Gain dBi	
2400	29.99%	-0.04	
2410	30.97%	0.11	
2420	30.87%	0.06	
2430	31.17%	0.10	
2440	31.19%	0.06	
2450	31.53%	0.10	
2460	31.39%	0.08	
2470	30.58%	0.08	
2480	30.27%	0.16	

2.3 Passive pattern



3.Active test

3.1 TRP&TIS

FS-R

信道	TRP	TIS
СН	(dBm)	(dBm
0	2.08	-88.65
39	2	-89.45
78	1.75	-89.82

HR

信道	TRP	TIS
СН	(dBm)	(dBm
0	-3.04	-84.49
39	-3.02	-85.05
78	-3.09	-85.03

FS-L

信道	TRP	TIS
СН	(dBm)	(dBm
0	2.36	-88.7
39	2.42	-90.12
78	1.83	-90.43

Confidentiality requirements

Strongpower Communication Co., Ltd. has the information provided by proprietary technology, which shall be kept strictly confidential and shall not be disclosed to any person or company without the prior written consent of Strongpower Communication Technology Co., Ltd.

HL				
信道	TRP	TIS		
СН	(dBm)	(dBm		
0	-3.49	-84.83		
39	-3.41	-84.99		
78	-3.4	-85.08		

4. Matching Circuit

Left&Right are the same

Element	E1	E2	E3
Value	NC	0 Ω	NC

