

Confidential

FCC ID: APYHRO00298

TUNE UP PROCEDURE For GSM850/PCS1900

PCS1900 Output Power

All channels are common.

PCL	Target [dBm]		Spec. [dBm]	
	Burst Ave.		Burst Average	
	Typical	Min.	Max.	
0	29.5	28.2	30.5	
1	27.5	25.5	29.5	
2	25.5	23.5	27.5	
3	23.5	21.5	25.5	
4	21.5	19.5	23.5	
5	19.5	17.5	21.5	
6	17.5	15.5	19.5	
7	15.5	13.5	17.5	
8	13.5	11.5	15.5	
9	11.5	8.5	14.5	
10	9.5	6.5	12.5	
11	7.5	4.5	10.5	
12	5.5	2.5	8.5	
13	3.5	0.5	6.5	
14	1.5	-2.5	5.5	
15	0.0	-4.0	4.0	

The Maximum Output Power in a multislot configuration
(GPRS MultiSlot Class = 12 ,
GMSK_MULTISLOT_POWER_PROFILE = 0)

The Number of Timeslots in uplink assignment	Max. Limit of Typ. Output Power [dBm]		Spec. [dBm]	
	Burst Ave.	Max.	Burst Ave.	Max.
1	29.5	30.5		
2	27.2	28.2		
3	25.3	26.3		
4	24.3	25.3		

The difference between the transmitter output power at two adjacent power control levels,
measured at the same channel, is not less than 0,5 dB and not be more than 3,5 dB.

If one or both of the adjacent output power levels are reduced according to
GMSK_MULTISLOT_POWER_PROFILE 0 and the number of timeslots, the difference between the
transmitter output power at two adjacent power control levels, measured at the same frequency, shall not be less
than -1dB and not be more than 3.5 dB.

GSM850 Output Power

All channels are common.

PCL	Target [dBm]		Spec. [dBm]	
	Burst Ave.		Burst Average	
	Typical	Min.	Max.	
5	32.5	31.2	33.5	
6	30.5	28.5	32.5	
7	28.5	26.5	30.5	
8	26.5	24.5	28.5	
9	24.5	22.5	26.5	
10	22.5	20.5	24.5	
11	20.5	18.5	22.5	
12	18.5	16.5	20.5	
13	16.5	14.5	18.5	
14	14.5	12.5	16.5	
15	12.5	10.5	14.5	
16	10.5	6.5	14.5	
17	8.5	4.5	12.5	
18	6.5	2.5	10.5	
19	4.5	0.5	8.5	

The Maximum Output Power in a multislot configuration
(GPRS MultiSlot Class = 12 ,
GMSK_MULTISLOT_POWER_PROFILE = 0)

The Number of Timeslots in uplink assignment	Max. Limit of Typ. Output Power [dBm]		Spec. [dBm]	
	Burst Ave.	Max.	Burst Ave.	Max.
1	32.5	33.5		
2	30.2	31.2		
3	28.3	29.3		
4	27.3	28.3		