

Exhibit 12**SECTION 2.1046****MEASUREMENT OF RADIO FREQUENCY POWER OUTPUT**

The test arrangements used to measure the radio frequency power output of the **ULAM / AS5CMP-34** Ultra Linear Amplifier Module is on the following page. Measurements were made respectively at each frequency where Occupied Bandwidth measurements were performed. The use of the ULAM requires that the J4 power level be calibrated for each specific channel of use. The test configuration, Figure 12a, allowed the measurement of output power for each channel investigated for Occupied Bandwidth. These included the "Left" and "Right" Edge of Block and at a center channel for each Block.

The ULAM system has a maximum power output at the antenna terminals of 16.0 Watts (42.04 dBm) +2 / -4 dB per Carrier or 48 Watts total. It also has a minimum power output at the antenna terminals of 0.16 Watts (+2 / -4 dB, across the PCS downlink Band (1930.00-1990.00 MHz). The signal applied to the ULAM is defined in Table 12.1. The power was reset to 16.0 Watts/carrier at each measurement frequency to verify the spectral performance at that power level at each specific frequency of interest. The attenuation range was also verified. The specific Frequencies, channels and set power level was documented on each "Occupied Bandwidth" data sheet. These were performed for single dual and three carrier configurations.

The applied signal met the recommended characteristics per ANSI J-STD-008 section 3.1.4 as defined below.

Type	Number of Channels	Fraction of Power (Linear)	Fraction of Power (dB)	Comments
Pilot	1	0.1490	-8.3	Walsh 0
Sync	1	0.015/p	-18.3	Walsh 32, always 1/8 rate
Paging	1	0.054	-12.7	Walsh 1, full rate only
Traffic	6	0.13 each	-8.8 each	Variable Walsh Assignments, full rate only

TABLE 12.1 Base Station Test Model, Nominal

Figure 12A Test Configuration for Occupied Bandwidth and Power




Exhibit 12**Equipment used in Figure 12 For Measurement of RF Power**

Modular Cell	Fully Populated PCS Modular Cell
OM 1&2 :	Oscillator Module, 15 MHz Rubidium and Crystal types
CBR: 1-9	CDMA Baseband Radio (FCC ID: AS5CMP-26)
ULAM: 1-9	Ultra Linear Amplifier Module (FCC ID: AS5CMP-34)
Transmit Filter:	PCS Block Transmit Filter appropriate for the investigated Block
Directional Coupler:	HP 778D and 772D Dual Directional Coupler
Power Meter:	HP E4419A Power Meter with EPC-E18A Power Head
Plotter:	HP Model 7470A Plotter
Attenuators, Variable	HP 8494B and 8495B digital attenuators
Attenuators, Fixed	Weinschel Corp DC-18 GHz, various values
Spectrum Analyzer:	Rohde & Schwarz ESMI EMI Test Receiver

Exhibit 12**RESULTS:**

The **ULAM/ AS5CMP-34** was configured in the test setup shown in Figure 12A. For each of the PCS channels tested the **ULAM/ AS5CMP-34** delivered a minimum of 16.0 Watts per carrier +2/-0 dB when measured at the J4 output connection.

This data is recorded on the Occupied Bandwidth Data Sheets for “Left edge”, “Center”, and “Right Edge” of each frequency Block. Data is presented for Blocks “A”, and “B” .

Note: The **ULAM/ AS5CMP-34** can be operated as a single carrier or as a Multiple Carrier CDMA amplifier. The maximum power level are verified at each cell site during setup of the PCS CDMA Modular Cell and installation of the **CBR, FCC ID: AS5CMP-26**.