

RF Exposure / MPE Calculation

No. : 11463343H
Applicant : FUJITSU TEN LIMITED
Type of Equipment : Car Audio
Model No. : FT0106B (WLAN part)
FCC ID : BABFT0106B

FUJITSU TEN LIMITED declares that Model: FT0106B complies with FCC radiation exposure requirement specified in the FCC Rule 2.1091 (for mobile).

RF Exposure Calculations:

The following information provides the minimum separation distance for the highest gain antenna provided with the "FT0106B" as calculated from (B) Limits for General Population / Uncontrolled Exposure of TABLE 1- LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE) of §1.1310 Radiofrequency radiation exposure limits.

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

$P =$ 25.82 mW (Maximum average output power)

Time average was used for the above value in consideration of 6-minutes time-averaging

Burst power average was used for the above value in consideration of worst condition.

$G =$ 1.114 Numerical Antenna gain; equal to 0.47dBi

$r =$ 20 cm (Separation distance)

Power Density Result $S = 0.00572 \text{ mW/cm}^2$

Even taking into account the tolerance, this device can be satisfied with the limits.

UL Japan, Inc.

Ise EMC Lab.

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8999

Facsimile : +81 596 24 8124