

BZ5DTR10SC
Application for FCC Certification
10 Watt Digital Television Translator

Spurious Emissions

Spurious output from the transmitter and mask filter was measured as shown below. Because the spectrum analyzer used did not have a Resolution Bandwidth setting of 500kHz, a setting of 300kHz was used. A correction factor of -2.2dB is applied to all readings (note: relative readings all remain the same) and is calculated by the following equation:

$$A = A_{alt} + 10 * \log \left(\frac{BW_{alt}}{500} \right)$$

Note that these measurements **do not** include the external GPS filter (one supplied with every transmitter) which also provides an additional 85dB within the GPS frequency bands. Typical tuning of this filter found in Figures 11 and 12.

Figure 6 shows the fundamental frequency at a span of 50MHz, showing the spectrum for three channels above and below the channel. Spurious emissions in the 2nd and 3rd adjacent channel are better than -65dB referenced to the fundamental (reference).




Figure 6: Fundamental

BZ5DTR10SC
Application for FCC Certification
10 Watt Digital Television Translator

Figure 7 shows the second harmonic level of the transmitter. The reference is the same as for the previous filter.




Figure 7: Second harmonic.

Figure 8 shows the spectral emissions from the transmitter across the band up to 2.9GHz (beyond the 5th Harmonic) again, prior to a GPS filter. All emissions up to the second harmonic are better than -60dB relative to the fundamental, and beyond the second harmonic are further attenuated by the GPS filter, should this be required, as shown in the filter response plots.

BZ5DTR10SC
Application for FCC Certification
10 Watt Digital Television Translator




Figure 8: Frequency Spectrum up to 2.9GHz

Shown in Figure 9 is the emission mask tests for the simple mask and Figure 10 is the emission mask with a stringent mask filter.




Figure 9: Simple mask test.

BZ5DTR10SC
Application for FCC Certification
10 Watt Digital Television Translator




Figure 10: Stingent Mask Test

BZ5DTR10SC
Application for FCC Certification
10 Watt Digital Television Translator

GPS filters are required when the second or third harmonics of the operating channel fall within the GPS frequency range (1164-1240 MHz and 1559-1610 MHz). This is not the case for VHF products. The GPS filter tuning is given in Figures 11, and 12, showing a minimum attenuation of 65dB within the GPS frequency bands.




Figure 11: GPS Filter typical response (in band)

BZ5DTR10SC
Application for FCC Certification
10 Watt Digital Television Translator




Figure 12: GPS Filter typical response (GPS Bands)