

UT-9 TRANSMITTER PROCEDURE

1. Audio from the microphone is coupled through IC BA4510 applied to Audio amplifier and buffer stage. Adjust VR R4 to control audio amplify level.
2. (Variable Capacitance Diode) of the VCO modulate the audio signal into RF signal
3. The RF signal of 630MHz to 660MHz is generated from VCO and is locked via PLL IC U4 when selected. Adjust VC C31 to correct the exact frequency..
4. The locked RF signal is coupled to buffer (Q13) and amplifiers (Q12 & Q11) .
5. After RF pre-amplify and final amplify, L7,L8,C41 & L9,L10,C50 to filter the spurious and harmonics and have the correct frequency pass through the maximum pass-point of the filter to transmit out. At this stage, the RF level is about 7dBm.

MASCOT ELECTRIC CO . , LTD .

DATE : APR 15 2004

UT-9 TRANSMITTER PROCEDURE

1. Audio from the microphone is coupled through IC BA4510 applied to Audio amplifier and buffer stage. Adjust VR R4 to control audio amplify level.
2. (Variable Capacitance Diode) of the VCO modulate the audio signal into RF signal
3. The RF signal of 740MHz to 770MHz is generated from VCO and is locked via PLL IC U4 when selected. Adjust VC C31 to correct the exact frequency..
4. The locked RF signal is coupled to buffer (Q13) and amplifiers (Q12 & Q11) .
5. After RF pre-amplify and final amplify, L7,L8,C41 & L9,L10,C50 to filter the spurious and harmonics and have the correct frequency pass through the maximum pass-point of the filter to transmit out. At this stage, the RF level is about 7dBm.

MASCOT ELECTRIC CO . , LTD .

DATE : APR 15 2004