

VX-920/VX-970 series

Address	Device name	Description	Application
[MAIN-UNIT]			
D 1001	Diode	PTZ TE25 15A	Protect
D 1002	Diode	1SS400	SW
D 1003	Diode	1SS400	SW
D 1004	Diode	1SS400	SW
D 1005	Diode	1SS400	SW
D 1006	Diode	DA221	Protect
D 1007	Diode	DA221	Protect
D 1008	Diode	DA221	Protect
D 1009	Diode	DA221	Protect
D 1010	Diode	DA221	Protect
D 1011	Diode	HVU131	ANT SW
D 1012	Diode	HVU131	ANT SW
D 1013	Diode	DA221	Protect
D 1014	Diode	1SV323	BPF Tune
D 1015	Diode	1SV323	BPF Tune
D 1016	Diode	1SS400	SW
D 1017	Diode	1SS400	RF AMP
D 1018	Diode	1SV323	BPF Tune
D 1019	Diode	1SV323	BPF Tune
D 1020	Diode	DAN222	SW
D 1021	Diode	1SS400	Ripple Filter
D 1022	Diode	DA221	Limiter
D 1023	Diode	DA221	Limiter
D 1024	Diode	DAN222	SW
D 1025	Diode	1SS400	Limiter
D 1026	Not use		
D 1027	Diode	1SV286	VCO
D 1028	LED	KL-157T01	TX/BUSY Indicator
D 1029	Diode	1SS400	Ripple Filter
D 1030	Diode	1SV282	VCO
D 1031	Diode	1SV282	VCO
D 1032	Diode	1SV282	VCO
D 1033	Diode	1SV286	VCO
D 1034	Diode	1SV286	VCO
D 1035	Diode	1SV282	VCO
D 1036	Diode	1SV286	VCO
D 1037	Diode	1SV286	VCO
D 1038	Diode	1SS400	Reverse Protect
D 1039	Diode	DA221	IF AMP
D 1040	Diode	DA221	Limiter
D 1041	Zener Diode	HZU5ALL	Protect
D 1042	Diode	1SS400	SW
D 1043	Diode	DAN222	SW
D 1044	Diode	DAN222	SW
D 1045	Diode	1SS400	Limiter
D 1046	Diode	DAN222	SW
D 1047	Diode	DA221	Limiter
D 1048	Diode	DA221	Limiter
D 1049	Diode	1SV323	BPF Tune
D 1050	Diode	1SV323	BPF Tune
D 1051	Diode	1SV323	BPF Tune
D 1052	Diode	1SV323	BPF Tune
Q 1001	IC	CD4053BPWR	Selector
Q 1002	Transistor	XP1501	TX 5V Regulator
Q 1003	Transistor	CPH6102	TX 5V Regulator
Q 1004	Transistor	DTC144EE	SW
Q 1005	IC	TAR5S50U	5V Regulator
Q 1006	Transistor	UMD5N	SW
Q 1007	Transistor	CPH6102	SW
Q 1008	IC	TDA2822D013	AF PA
Q 1009	Transistor	DTC114TE	SW
Q 1010	FET	2SK3476	Current Limiter

VX-920/VX-970 series

Address	Device name	Description	Application
Q 1011	Transistor	UMD12N	SW
Q 1012	Transistor	2SA1774 R	SW
Q 1013	Transistor	DTC114TE	AF PA
Q 1014	Transistor	UMD12N	Selector
Q 1015	IC	TDA2822D013	SW
Q 1016	IC	CD4053BPWR	SW
Q 1017	Transistor	DTC144EE	SW
Q 1018	Transistor	DTC144EE	SW
Q 1019	Transistor	DTC144EE	SW
Q 1020	IC	M62364FP 600D	Level Control
Q 1021	FET	2SK3475	TX Driver AMP
Q 1022	Transistor	2SC5226-4/5	RX RF AMP
Q 1023	IC	LA8630M-B-TE-R	De-emphasis / Expander
Q 1024	Transistor	DTC144EE	SW
Q 1025	IC	CD4052BPWR	Audio Equalizer
Q 1026	Transistor	UN911F	SW
Q 1027	Transistor	2SC3356 R24	TX Pre-Drive AMP
Q 1028	IC	BD6111FV-E2	VCV/TUNE Control
Q 1029	IC	CD4052BPWR	Audio Equalizer
Q 1030	IC	CD4053BPWR	Selector
Q 1031	IC	NJM2130F	VCV Control
Q 1032	IC	AK2345	AF Base-Band
Q 1033	Transistor	2SC5226-4	Buffer AMP
Q 1034	IC	SPM5001	
Q 1035	Transistor	DTC144EE	SW
Q 1036	Transistor	2SA1774 R	Ripple Filter
Q 1037	Transistor	DTC144EE	SW
Q 1038	Transistor	DTA144EE	SW
Q 1039	Transistor	DTC114TE	SW
Q 1040	Transistor	DTC114TE	SW
Q 1041	IC	LC73881M-TLM	DTMF Receiver
Q 1042	Transistor	2SC5226-4	Buffer AMP
Q 1043	Transistor	DTC144EE	SW
Q 1044	Transistor	DTC144EE	SW
Q 1045	Transistor	UN911F	SW
Q 1046	Transistor	DTC114TE	SW
Q 1047	FET	2SK508 K52	RX VCO
Q 1048	Transistor	DTC114TE	SW
Q 1049	Transistor	DTC144EE	SW
Q 1050	Transistor	DTC114TE	SW
Q 1051	Transistor	2SC5226-4	Buffer AMP
Q 1052	Transistor	2SC4227 R32	TX VCO
Q 1053	Transistor	DTC114TE	SW
Q 1054	Transistor	DTC114TE	SW
Q 1055	Transistor	2SD1767 Q	LED Driver
Q 1056	Transistor	2SC4617 R	Ripple Filter
Q 1057	Transistor	DTC114TE	SW
Q 1058	Transistor	2SC5226-4	IF AMP
Q 1059	Transistor	DTC114TE	SW
Q 1060	Transistor	UMD5N	SW
Q 1061	IC	S-80835CNMC-B8U	Power Down
Q 1062	IC	TAR5S35U	3.5V Regulator
Q 1063	IC	TAR5S35U	Reset Control
Q 1064	Transistor	DTC114TE	SW
Q 1065	IC	BR93L66RFVM	EEPROM
Q 1066	Transistor	2SC4617 R	Reset Control
Q 1067	IC	TA31136FN	IF Subsystem
Q 1068	FET	2SK880GR	VCV Detect
Q 1069	IC	LC87F72C8A-F5N19	Microprocessor
Q 1070	IC	SA7025DK	PLL Subsystem
Q 1071	Transistor	2SC4617 R	Noise AMP
Q 1072	IC	LM2902PWR	Current Detect/Power Control
Q 1073	IC	LM2902PWR	AF Control

VX-920/VX-970 series

Address	Device name	Description	Application
Q 1074	IC	LM2902PWR	AF Control
Q 1075	IC	LM2902PWR	AF Control
Q 1076	IC	LM2904PWR	AF Control
Q 1077	IC	LM2902PWR	AF Control
Q 1078	IC	CD4066BPWR	AF SW
Q 1079	Transistor	DTC144EE	SW
Q 1080	IC	LM2904PWR	AF Control
Q 1081	Transistor	DTC144EE	SW
Q 1082	IC	LM2902PWR	AF Control
Q 1083	IC	LM2902PWR	AF Control

[DISPLAY-UNIT]

D 2001	LED	FA1101F	Backlight for LCD
D 2002	LED	FA1101F	Backlight for LCD
D 2003	LED	LNJ808K8SRA	Backlight for LCD
D 2004	LED	LNJ808K8SRA	Backlight for LCD
D 2005	LED	LNJ808K8SRA	Backlight for KEY
D 2006	LED	LNJ808K8SRA	Backlight for KEY
D 2007	LED	LNJ808K8SRA	Backlight for KEY
D 2008	LED	LNJ808K8SRA	Backlight for KEY
D 2009	Diode	1SS400	SW
D 2010	Diode	1SS400	SW
D 2011	Diode	1SS400	SW
D 2012	Diode	1SS400	SW
Q 2001	Transistor	DTC114TE	LCD Backlight SW
Q 2002	Transistor	DTC114TE	KEY Backlight SW
Q 2003	IC	TAR5S50U	Regulator for LED
Q 2004	Transistor	XP1501	Regulator for LED
Q 2005	Transistor	2SA1602A	Regulator for LED
Q 2006	IC	NJU6624AFG1	LCD Driver