

VX-6000L COMPONENT APPLICATIONS

Address	Device name	Description	Applications
[MAIN-UNIT]			
Q 1003	Transistor	2SB1201STP	9V Regulator
Q 1005	Transistor	DTB123EK	Rx 9V Switch
Q 1006	Transistor	2SB1132R	Tx 9V Switch
Q 1007	IC	NJM2902V	RX Tune Buff/APC COMP
Q 1008	Transistor	2SC4154E	VCO 8V Regulator
Q 1009	Transistor	IMH6	Tx/Rx Switch
Q 1011	Transistor	RT1N241M	MOD Mute Switch
Q 1012	Transistor	3SK228	RF Amplifier
Q 1014	Transistor	2SC4226	TX Voltage Control Oscillator
Q 1015	Transistor	2SK508	RX Voltage Control Oscillator
Q 1016	Transistor	RT1N241M	Rx VCO Switch
Q 1017	Transistor	IMH6A	Tx VCO Switch
Q 1018	Transistor	2SC5107-O	Buff AMP
Q 1019	Transistor	2SC4215	Buff AMP
Q 1021	Transistor	2SC5415E	RF AMP
Q 1023	IC	NJM78L05UA	5V Regulator
Q 1024	IC	SA7025DK	PLL Subsystem
Q 1025	Transistor	3SK240	1st MIX
Q 1026	IC	TA31136FN	IF Subsystem
Q 1027	Transistor	2SC4154E	Reference Oscillator
Q 1029	Transistor	2SC4226	IF AMP
Q 1030	IC	MM1216ENRE	9V Regulator
Q 1034	Transistor	2SK2035	PLL Filter
Q 1035	Transistor	2SA1602A-F	PLL Filter
Q 1036	Transistor	2SC4154E	PLL Filter
Q 1037	Transistor	2SC4154E	PLL Filter
Q 1038	IC	TA75S01F	sub-audio AMP
Q 1501	Transistor	3SK131	Noise AMP
Q 1502	Transistor	3SK131	Noise AMP
Q 1503	Transistor	IMD3	Switch
Q 1504	Transistor	2SC4215	Pulse AMP
Q 1505	Transistor	2SC4215	Pulse AMP
Q 1507	Transistor	2SK508	IF Switch
Q 1508	Transistor	2SK508	IF Switch
Q 1509	Transistor	2SC4215	Pulse AMP
Q 2001	IC	NJM2902V	Emphasis/IDC/LPF/MIX
Q 2002	Transistor	IMZ1	Analog Switch
Q 2003	IC	NJM2902V	RSSI/SQL/LPF
Q 2004	Transistor	RT1N241M	Analog Switch
Q 2006	Transistor	DTC323TK	Mute Switch
Q 2007	IC	BU4066BF	Analog Switch
Q 2008	Transistor	RT1N241M	MIC Mute Switch
Q 2009	Transistor	IMX1	Analog Switch
Q 2011	Transistor	RT1N241M	AF Mute
Q 2012	Transistor	DTC323TK	AF Mute
Q 2013	IC	MX165CDW	CTCSS Encoder/Decoder
Q 2014	IC	CXA1846N	AF Volume
Q 2015	Transistor	DTB123EK	Analog Switch
Q 2016	IC	BU4053BCF	Analog Switch
Q 2018	Transistor	2SC4154E	Clock Freq. Shift switch
Q 2019	IC	MB90F583B	Microprocessor
Q 2020	Transistor	2SJ327-Z	Power Supply Switch
Q 2024	IC	NJM78L05UA	5V Regulator
Q 2025	Transistor	2SA1602A-F	Power Down detect
Q 2026	Transistor	RT1N241M	Power Down detect
Q 2027	IC	S-80735SN-DZ	CPU Reset
Q 2028	IC	HN58X2432TI	Programmable Data Store
Q 2029	IC	TDA7240AV	AF Power AMP
Q 2108	IC	NJM2902V	Emphasis /AF AMP
Q 2110	IC	NJM2902V	LPF
Q 2111	Transistor	DTB123EK	PTT Switch
Q 2112	Transistor	IMD3	Analog Switch
Q 2114	Transistor	RT1N241M	EXT SQ Switch
Q 2115	Transistor	IMD3	Analog Switch

VX-6000L COMPONENT APPLICATIONS

Address	Device name	Description	Applications
Q 2116	Transistor	RT1N241M	Analog Switch
Q 2117	IC	TC4W53FU	Analog Switch
Q 2118	Transistor	RT1N241M	Analog Switch
Q 2119	Transistor	RT1N241M	AF Switch
Q 2120	Transistor	RT1N241M	Analog Switch
Q 2121	Transistor	RT1N241M	Analog Switch
Q 2122	Transistor	RT1N241M	Analog Switch
Q 2125	Transistor	RT1N241M	DCS SW
Q 2127	Transistor	RT1N241M	Analog Switch
Q 2130	Transistor	2SC4215	AGC AMP
Q 2131	Transistor	DTC124EK	TX Power Control
Q 2132	Transistor	DTB123EK	TX Power Control
D 1001	Diode	RLS135	RF Limitting
D 1002	Diode	BAS316	RF Limitting
D 1003	Diode	P6KA18	Reverse Voltage Protecion
D 1005	Diode	BAS316	Switch
D 1009	Varactor Diode	HVU356	BPF Tune
D 1010	Varactor Diode	1SV229	BPF Tune
D 1012	Varactor Diode	HVU356	BPF Tune
D 1013	Varactor Diode	1SV229	BPF Tune
D 1015	Varactor Diode	HVU300A	TX VCO
D 1016	Varactor Diode	HVU300A	TX VCO
D 1017	Varactor Diode	HVU306A	RX VCO
D 1018	Varactor Diode	HVU306A	RX VCO
D 1019	Varactor Diode	HVU359	TX VCO MOD
D 1020	Varactor Diode	HVU356	BPF Tune
D 1021	Varactor Diode	1SV229	BPF Tune
D 1022	Varactor Diode	HVU356	BPF Tune
D 1023	Varactor Diode	1SV229	BPF Tune
D 1024	Diode	1SS321	Tx/Rx RF Switch
D 1026	Diode	MC2848	2nd IF Filter Switch
D 1027	Diode	HZM5.6NB2	5V Supply
D 1028	Diode	MC2848	2nd IF Filter Switch
D 1029	Varactor Diode	HVU359	DCS MOD
D 1030	Varactor Diode	1SV230	Temp. Control for PLL REF
D 1033	Diode	MC2850	Temp. Control for PLL REF
D 1034	Diode	HVU300A	TX VCO
D 1035	Varactor Diode	HVU300A	TX VCO
D 1036	Varactor Diode	HVU306A	BPF Tune
D 1038	Varactor Diode	HVU306A	BPF Tune
D 1039	Varactor Diode	HVU356	BPF Tune
D 1040	Varactor Diode	HVU306A	BPF Tune
D 1041	Diode	HSB88WS	DBM Mixer
D 1042	Diode	BAS316	Switch
D 1043	Varactor Diode	HVU300A	PLL VCO Filter Tuning
D 1044	Varactor Diode	HVU300A	PLL VCO Filter Tuning
D 1501	Diode	HSM88AS	Noise DET
D 1510	Diode	HSM88AS	AGC DET
D 1511	Diode	BAS316	Switch
D 2001	Diode	MC2846	Switch
D 2002	Diode	MC2850	Detector
D 2003	Diode	MC2850	SQ Noise Detector
D 2004	Diode	MC2850	Temp. Comp.
D 2005	Diode	BAS316	CTCSS Detector
D 2006	Diode	MC2850	limitter
D 2007	Diode	MC2846	DC Switch
D 2010	Diode	MC2850	Protection
D 2011	Diode	BAS316	Reverse Current Protecion
D 2012	Diode	BAS316	Reverse Current Protecion
D 2014	Diode	BAS316	Switch
D 2015	Diode	BAS316	Switch
[DISPLAY-UNIT]			
Q 3001	IC	LC75823W	LCD Driver
Q 3003	Transistor	RT1N241M	Mic Mute

VX-6000L COMPONENT APPLICATIONS

Address	Device name	Description	Applications
Q 3004	Transistor	IMZ1	Line Buff
Q 3005	Transistor	RT1N241M	DATA Line Mute
Q 3008	Transistor	RT1N241M	Mic Mute
Q 3009	Transistor	RT1N241M	Mic Mute
Q 3010	Transistor	IMX1	Line Buff
Q 3011	Transistor	IMZ1	Buff
Q 3012	IC	S-93C46AMFN	Programmable Data Store
Q 3013	Transistor	IMD3	Buff
Q 3014	IC	HD64F3642AH	Microprocessor
Q 3015	Transistor	IMH6A	Switch for flash mode
Q 3016	IC	S-80735SN	Microprocessor Reset
Q 3017	Transistor	2SA1602A	Power Down Detect
Q 3019	Transistor	2SC4154	Clock Freq. Shift switch
Q 3020	Transistor	RT1N241M	AF MUTE
Q 3021	IC	NJM78L05UA	5V Regulator
Q 3022	Transistor	RT1N241M	Switch for flash mode
Q 3024	Transistor	RT1N241M	Panel Interface Detect
Q 3025	Transistor	RT1N241M	Volume Control ON/OFF
Q 3026	Transistor	RT1N241M	Power Switch Control
Q 3027	Transistor	RT1N241M	Power Down Detect
Q 3028	Transistor	2SB1132	Power Switch
Q 3029	Transistor	2SB1132	LED Switch
Q 3030	Transistor	UMW1N	Brightness Control
Q 3031	Transistor	2SB1132	Power Switch
Q 3033	Transistor	IMH6A	Power Switch Control
Q 3038	Transistor	IMX1	AGC AMP
Q 3039	IC	NJM2902V	MIC AMP
Q 3040	Transistor	IMZ1	BUFF
Q 3043	IC	TC4S66F	Analog Switch
D 3005	Diode	1SS226	AGC rectification
D 3006	Diode	DAP202U	FLASH MPU Writing
D 3008	Diode	MC2848	DC Switch
D 3010	LED	TLOU1008	LED for illumination
D 3011	LED	TLOU262	LED for illumination
D 3012	LED	TLOU1008	LED for illumination
D 3013	LED	TLOU262	LED for illumination
D 3015	LED	GL3HS44	LED Indicator
D 3016	LED	GL3PR8	LED Indicator
D 3017	LED	GL3KG8	LED Indicator
D 3018	Diode	MC2850	Protection of Static electricity
D 3019	Diode	MC2850	Protection of Static electricity
D 3020	Diode	BAS316	Reverse Voltage Protecion
D 3021	Diode	BAS316	Reverse Voltage Protecion
D 3022	Diode	BAS316	Reverse Voltage Protecion
D 3023	Diode	BAS316	Reverse Voltage Protecion
[KEY-UNIT]			
Q 3401	Transistor	2SA1602A	Switch
D 3401	LED	TLOU1008	LED Indicator
D 3402	LED	TLOU1008	LED Indicator
D 3403	LED	TLOU1008	LED Indicator
D 3404	LED	TLOU1008	LED Indicator
D 3405	LED	TLOU1008	LED Indicator
[PA-UNIT]			
Q 6001	Transistor	2SC1971	Pre Drive Amplifire
Q 6002	IC	KIA7808PI	8V Regulator
Q 6003	Transistor	2SD882Q	Bias Control
Q 6004	Transistor	2SC1971	Drive Amplifire
Q 6005	Transistor	2SC1971	Drive Amplifire
Q 6006	Transistor	SD1405	Power Amplifier
Q 6007	Transistor	SD1405	Power Amplifier
Q 6008	Transistor	2SA1213Y	Bias Switch
Q 6009	Transistor	DTC114EK	Bias Switch
D 6001	Diode	BAS316	Reverse Voltage Protecion
D 6002	Diode	1SS357	Bias
D 6003	Diode	1SS357	Bias

VX-6000L COMPONENT APPLICATIONS

Address	Device name	Description	Applications
D 6004	Diode	1SS357	Bias
D 6005	Diode	1SS357	Bias
D 6006	Diode	MA729	Detector
D 6007	Diode	MA729	Detector