

**Compliance Certification Services Inc.** 

Report No: C121026Z01-RP1\_MPE FCC ID: MSQ-RTN12D Date of Issue: November 25, 2012

## **RADIO FREQUENCY EXPOSURE**

# LIMIT

Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines. See §15.247(b)(4) and §1.1307(b)(1) of this chapter.

### EUT Specification

	r
EUT	Wireless-N Router
	🛛 WLAN: 2.412GHz ~ 2.462GHz
Frequency band	WLAN: 5.18GHz ~ 5.32GHz / 5.50GHz ~ 5.70GHz
(Operating)	WLAN: 5.745GHz ~ 5825GHz
	Others _
	Portable (<20cm separation)
Device category	Mobile (>20cm separation)
	Others
	Occupational/Controlled exposure ( $S = 5mW/cm^2$ )
Exposure classification	General Population/Uncontrolled exposure
	$(S=1mW/cm^2)$
	Single antenna
	Multiple antennas
Antenna diversity	🔀 Tx diversity
	Rx diversity
	Tx/Rx diversity
Max. output power	18.69dBm (73.96mW)
Antenna gain (Max)	5.00dBi (Numeric gain:3.16)
Evaluation applied	MPE Evaluation
	SAR Evaluation
Note:	

1. The maximum output power is 18.69dBm (73.96mW) at 2437MHz (with 3.16 numeric antenna gain.)

2. For mobile or fixed location transmitters, no SAR consideration applied. The minimum separation generally be used is at least 20 cm, even if the calculations indicate that the MPE distance would be lesser.

## **TEST RESULT**

No non-compliance noted.



**Compliance Certification Services Inc.** 

Report No: C121026Z01-RP1\_MPE FCC ID: MSQ-RTN12D Date of Issue: November 25, 2012

ulation

Given 
$$E = \frac{\sqrt{30 \times P \times G}}{d}$$
 &  $S = \frac{E^2}{3770}$ 

Combining equations and re-arranging the terms to express the distance as a function of the remaining variables yields:

$$S = \frac{30 \times P \times G}{3770d^2}$$
 Equation 1

Where d = distance in cmP = Power in mWG = Numeric antenna gain  $S = Power Density in mW / cm^2$ 

#### Maximum Permissible Exposure

EUT Output Power=73.96mW

Numeric antenna gain=3.16

Substituting the MPE safe distance using d=20 cm into *Equation 1* :

Yields

The power density S =  $30 \times 73.96 \times 3.16 / (3770 \times 400) \text{ cm}^2 = 4.600 \text{ X} 10^{-4} \text{mW/cm}^2$ 

(For mobile or fixed location transmitters, the maximum power density is  $1.0 \ mW/cm^2$  even if the calculation indicates that the power density would be larger.)