

Theory of Operation on Proline 2.5/3

The Proline3 Handheld Radio Transceivers are comprised of one main PCB.

The main PCB contains the transmitter, receiver, and control circuits.

1) Receiver

The receiver circuit adopts dual conversion super heterodyne with 1st IF 45.1MHz and 2nd IF 455kHz

A. Front-end

Front-end consists of pre-selector filter, RF Amplifier, Post-selector filter. The receive signal is routed through C71 and selected by C72, C28, L6, L18, L16, L19 to amplified around 13dB at RF amp. Q1. Front-end adjusts bandwidth by varicap diode tuning.

This circuit removes unnecessarily spurious 1st Image.

B. First Mixer

The signal from Front-end is input to Q2 base of 1st mixer. 1st local signal generated from VCO is input to Q2, emitter. These two signals are mixed at Mixer into 1st IF signal 45.1Mhz, which is resonated in parallel at C61, L14 and inputted to XF1, Pair crystal filter.

C. IF Amplifier

1st IF signal from XF1 is amplified about 15dB at IF amp Q3 and inputted to IC1, IF IC.

2nd Local Oscillator is 44.645MHz. The signal from 2nd Mixer is refined removing unnecessary spurious signal and detected through high gain linear amp. This detected signal is inputted to IC1 pin9.

D. AF Amplifier

300Hz High Pass Filter U2 removes the signal under 300Hz of the demodulated signal from IC1 so that noise under sub tone use is removed.

De-emphasis functions to get 6dB/oct by R55, C91 and this signal controls volume of sound by RV1.

IC5 can operate a speaker as audio current amplifier amplifying the signal. The operating current can be reduced by mute signal.

E. Squelch

The demodulated signal from IC1 is coupled of noise to C12. The noise

is filtered and amplified by C9,10, R16, 127 and rectified by double voltage at D2, C11 and transformed to DC level. And this DC signal is used as the signal to mute RV2 audio.

F. Audio AMP

After CTCSS,DCS signal is removed at 300Hz High Pass Filter and de-emphasized to -6 dB/Oct at R55, C91, the volume of sound is controlled by RV1.

IC5 is doing low frequency current amplify as audio amplifier to operate a speaker.

IC5 has mute function and if Pin 2, mute port is high, it's on mute. If it is low, it's unmute.

2) Transmitter

The transmitter consists of Buffer, Power Amplifier, Low-Pass Filter, Antenna Switch, Auto-Power Control.

2-1) Buffer

-6 dBm TX RF signal from VCO is amplified to around $+25$ dBm by buffer Q7,9 to have desired output power at final Amp.

Pie style resister attenuator is used between VCO and Buffer Amp. To minimize the effect of load caused by transmit amplifier in TX.

2-2) Power Amplifier

TX RF Signal form buffer Amp. Gains 3Watt output by final Amp Q6.

Collect impedance of Q6 states in low so that it is matching to 50ohm by C47, L10, C46 and inputted to 5th Low Pass Filter.

2-3) Low Pass Filter

5th Low Pass Filter reduces the unwanted spurious for TX output power from final Amp.

L8, 9, C45, 46, 53, 85 are Chebisheve Filter.

2-4) Antenna Switch

Ant. Switch is to share the antenna in TX and RX. It prevents TX

sensitivity from degradation by LPF. Also, it protects receive circuit by blocking TX signal to receive end, turning on D5, 6.

Flow of the signal in RX is designed to minimize the loss of the signal using the character of series resonance of L7, C71.

2-5) Auto-Power Control

This circuit controls TX Power by detection on the current through R34, 178, 179.

The voltage difference from these resistors is amplified by U4-B and gets the voltage comparing the this signal with the reference voltage from R95, 100 at U4-A.

This voltage difference is kept to stable value by RV5 changing Gate voltage of Final Amp.

3) PLL Synthesizer

Reference frequency is 21.25Mhz and this oscillated frequency is compensated in temperature by the variation of D21 capacitor according to the voltage changes from thermistor.

The frequency from VCO is inputted to PLL IC and this inputted signal is divided by the ratio set by data and compared with reference step frequency.

Then, the difference comes to IC2 pin18,20 Port. Proline3 consists of external charge pump.

Charge pump output turns into DC by PLL LPF R28, 29, 168, C33, 41, 68, 160 so that it can vary VCO control voltage to have set frequency.

For TX and RX switch, Q36 and Q37 base switch to control voltage.(TXEN1)

4) Audio and Control circuit

IC4 controls all factions of the radio as Microprocessor.

It detects outer condition such as function data on frequency, Power supply switching and make it operate correctly.

IC U1 consists of 250Hz LPF to function CTCSS,DCS decoding correctly and the output of this filter is amplified at U1-A. Then, it goes to Q24 to be changed to

logic signal so that CTCSS,DCS Decoding is enabled.

U5-C is CTCSS,DCS Encode Filter. It mixes the signals from 3 ports and this mixed signal goes through this filter to get clear CTCSS,DCS signal.

U5-A, B, and D is TX Audio Amp and limiter. It amplifies the voice signal from C-Mic and have the character of 6dB/Oct Pre-Emphasis.

This voice signal is controlled by U5-A for the volume.

U5-B is 3KHz LPF and has the character that reduces to 18dB/Oct.

This character minimizes the interference of adjacent channel by voice signal.