

888 Car Alarm System Technical Information:

Description and Specification

Function description:

- 1、 Two-way remote controller with pager function
- 2、 Color LCD remote display
- 3、 Alarm with sound,tremble and colour logo by remote controller
- 4、 Remote control arming/disarming
- 5、 Engine immobilization
- 6、 Alarm armed mode
- 7、 Mute armed mode
- 8、 Anti-jamming
- 9、 Auto re-arming
- 10、 Anti-hijacking
- 11、 Code learning
- 12、 Emergency alarm
- 13、 Warning for unlocked vehicle
- 14、 Warning for disarmed vehicle
- 15、 Locating with sound and light
- 16、 Remote trunk release
- 17、 Emergency override
- 18、 Automatic lock/unlock
- 19、 Trigger memory and report

Technical Information:

1. Control box

Voltage: 12V \pm 2V

Static current: <20mA(Emitter, LED included)

Current (max): direction indicator: 15A \times 2

Siren: 5A

Door lock: 10A

Frequency: 433.92MHz

Power: <10mW

2. LCD remote

Voltage: $12V \pm 2V$

Static current: 400uA

Battery size: AAA

Frequency: 433.92MHz

Power: <10mW

3. Siren

Volume: 105~110DB

Power: 15W