

**Prediction of MPE Limit
47 CFR § 2.1091/ § 2.1093**

$$S_{20} = \frac{P_A G_N}{4\pi R_{20}^2}$$

$$S_C = \frac{P_A G_N}{4\pi R_C^2}$$

$$R_C = \sqrt{\frac{P_A G_N}{4\pi S_L}}$$

$$S_L = \frac{f}{1500} \text{ (mW/cm}^2\text{)}$$

S₂₀ = Power Density of the Device at 20cm

S_L = Power Density Limit

S_C = Power Density of the Device at the Compliance Distance R_C

R₂₀ = 20cm

R_C = Minimum Distance to the Radiating Element to Meet Compliance

P_T = Power Input to Antenna

P_A = Adjust Power

G_N = Numeric Gain of the Antenna

f = Transmit Frequency

Transmit Duty Cycle = 100%


Use Group = General Population

Transmit Duty Cycle:	100.00	(%)
Tx Frequency (f):	928.00	(MHz)
RF Power at Antenna Input Port (P _T):	79.00	(mW)
Antenna Gain:	11.00	(dBi)
Numeric Antenna Gain (G _N):	12.59	(numeric)
Cable or Other Loss:	0.00	(dB)
Duty Cycle/Loss Adjusted Power (P _A):	79.00	(mW)

S_L =	0.619	(mW/cm ²)
S₂₀ at 20cm =	0.198	(mW/cm ²)
R_C =	11.3	(cm)
S_C =	0.62	(mW/cm ²)

RESULT **PASS**

Art Voss



Senior Engineer

Celltech Labs Inc.