



Appendix A

RF Test Data for BT LE (Conducted Measurement)

Product Name: Smart LED Wall Light

Test Model: WL1-8

Environmental Conditions

Temperature:	23.8° C
Relative Humidity:	52.1%
ATM Pressure:	100.0 kPa
Test Engineer:	Joker Hu
Supervised by:	Nick Peng





A.1 -6dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	BLE 1M	2402	Ant1	0.633	≥ 0.5	Pass
NVNT	BLE 1M	2440	Ant1	0.629	≥ 0.5	Pass
NVNT	BLE 1M	2480	Ant1	0.636	≥ 0.5	Pass
NVNT	BLE 2M	2402	Ant1	1.083	≥ 0.5	Pass
NVNT	BLE 2M	2440	Ant1	1.08	≥ 0.5	Pass
NVNT	BLE 2M	2480	Ant1	1.095	≥ 0.5	Pass






Test Graphs

-6dB Bandwidth NVNT BLE 1M 2402MHz Ant1




-6dB Bandwidth NVNT BLE 1M 2440MHz Ant1






-6dB Bandwidth NVNT BLE 1M 2480MHz Ant1




-6dB Bandwidth NVNT BLE 2M 2402MHz Ant1






-6dB Bandwidth NVNT BLE 2M 2440MHz Ant1



-6dB Bandwidth NVNT BLE 2M 2480MHz Ant1





A.2 Occupied Channel Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	99% OBW (MHz)
NVNT	BLE 1M	2402	Ant1	1.029
NVNT	BLE 1M	2440	Ant1	1.035
NVNT	BLE 1M	2480	Ant1	1.031
NVNT	BLE 2M	2402	Ant1	2.025
NVNT	BLE 2M	2440	Ant1	2.059
NVNT	BLE 2M	2480	Ant1	2.028






Test Graphs

OBW NVNT BLE 1M 2402MHz Ant1




OBW NVNT BLE 1M 2440MHz Ant1






OBW NVNT BLE 1M 2480MHz Ant1




OBW NVNT BLE 2M 2402MHz Ant1






OBW NVNT BLE 2M 2440MHz Ant1



OBW NVNT BLE 2M 2480MHz Ant1





A.3 Maximum Peak Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE 1M	2402	Ant1	7.43	30	Pass
NVNT	BLE 1M	2440	Ant1	6.56	30	Pass
NVNT	BLE 1M	2480	Ant1	5.64	30	Pass
NVNT	BLE 2M	2402	Ant1	7.35	30	Pass
NVNT	BLE 2M	2440	Ant1	6.42	30	Pass
NVNT	BLE 2M	2480	Ant1	5.48	30	Pass

EIRP


Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Antenna Gain	Report EIRP Power(dBm)	Limit (dBm)	Verdict
NVNT	BLE 1M	2402	Ant1	7.43	4.54	11.97	36	Pass
NVNT	BLE 1M	2440	Ant1	6.56	4.54	11.10	36	Pass
NVNT	BLE 1M	2480	Ant1	5.64	4.54	10.18	36	Pass
NVNT	BLE 2M	2402	Ant1	7.35	4.54	11.89	36	Pass
NVNT	BLE 2M	2440	Ant1	6.42	4.54	10.96	36	Pass
NVNT	BLE 2M	2480	Ant1	5.48	4.54	10.02	36	Pass








Test Graphs



Power NVNT BLE 1M 2402MHz Ant1



Power NVNT BLE 1M 2440MHz Ant1









A.4 Maximum Power Spectral Density Level


Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	BLE 1M	2402	Ant1	-11.08	8	Pass
NVNT	BLE 1M	2440	Ant1	-10.54	8	Pass
NVNT	BLE 1M	2480	Ant1	-10.27	8	Pass
NVNT	BLE 2M	2402	Ant1	-12.9	8	Pass
NVNT	BLE 2M	2440	Ant1	-12.58	8	Pass
NVNT	BLE 2M	2480	Ant1	-12.58	8	Pass






Test Graphs

PSD NVNT BLE 1M 2402MHz Ant1




PSD NVNT BLE 1M 2440MHz Ant1






PSD NVNT BLE 1M 2480MHz Ant1




PSD NVNT BLE 2M 2402MHz Ant1






PSD NVNT BLE 2M 2440MHz Ant1



PSD NVNT BLE 2M 2480MHz Ant1





A.5 Band Edge


Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-56.08	-20	Pass
NVNT	BLE 1M	2480	Ant1	-57.52	-20	Pass
NVNT	BLE 2M	2402	Ant1	-45.21	-20	Pass
NVNT	BLE 2M	2480	Ant1	-57.6	-20	Pass






Test Graphs

Band Edge NVNT BLE 1M 2402MHz Ant1 Ref




Band Edge NVNT BLE 1M 2402MHz Ant1 Emission






Band Edge NVNT BLE 1M 2480MHz Ant1 Ref




Band Edge NVNT BLE 1M 2480MHz Ant1 Emission






Band Edge NVNT BLE 2M 2402MHz Ant1 Ref




Band Edge NVNT BLE 2M 2402MHz Ant1 Emission






Band Edge NVNT BLE 2M 2480MHz Ant1 Ref



Band Edge NVNT BLE 2M 2480MHz Ant1 Emission





A.6 Conducted RF Spurious Emission

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-58.39	-20	Pass
NVNT	BLE 1M	2440	Ant1	-57.51	-20	Pass
NVNT	BLE 1M	2480	Ant1	-58.13	-20	Pass
NVNT	BLE 2M	2402	Ant1	-58.4	-20	Pass
NVNT	BLE 2M	2440	Ant1	-59.32	-20	Pass
NVNT	BLE 2M	2480	Ant1	-58.35	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Tx. Spurious NVNT BLE 1M 2402MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2402MHz Ant1 Emission






Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Emission






Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Emission






Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Ref




Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Emission






Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Ref




Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Emission






Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Ref



Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Emission





A.7 Duty Cycle


Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	BLE 1M	2402	Ant1	83.98	0.76	0.48
NVNT	BLE 1M	2440	Ant1	83.96	0.76	0.48
NVNT	BLE 1M	2480	Ant1	83.98	0.76	0.48
NVNT	BLE 2M	2402	Ant1	56.67	2.47	0.94
NVNT	BLE 2M	2440	Ant1	56.68	2.47	0.94
NVNT	BLE 2M	2480	Ant1	56.69	2.46	0.94






Test Graphs

Duty Cycle NVNT BLE 1M 2402MHz Ant1




Duty Cycle NVNT BLE 1M 2440MHz Ant1






Duty Cycle NVNT BLE 1M 2480MHz Ant1




Duty Cycle NVNT BLE 2M 2402MHz Ant1






Duty Cycle NVNT BLE 2M 2440MHz Ant1



Duty Cycle NVNT BLE 2M 2480MHz Ant1





A.8 Restrict Band

Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	Correction Factor (dB)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	BLE 1M	2402	Ant1	2310	-50.85	4.54	-	48.92	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2310	-58.96	4.54	0.76	41.57	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2353.68	-47.25	4.54	-	52.52	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2379.792	-57.27	4.54	0.76	43.26	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2390	-48.65	4.54	-	51.12	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2390	-58.57	4.54	0.76	41.96	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-50.58	4.54	-	49.19	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-58.28	4.54	0.76	42.25	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2486.896	-46.23	4.54	-	53.54	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2493.256	-57.13	4.54	0.76	43.40	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2500	-49.13	4.54	-	50.64	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2500	-58.21	4.54	0.76	42.32	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2310	-50.62	4.54	-	49.15	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2310	-58.71	4.54	2.47	43.53	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2350.032	-46.65	4.54	-	53.12	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2383.536	-57.52	4.54	2.47	44.72	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2390	-52.13	4.54	-	47.64	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2390	-58.61	4.54	2.47	43.63	Average	54	Pass





NVNT	BLE 2M	2480	Ant1	2483.5	-48.56	4.54	-	51.21	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2483.5	-57.35	4.54	2.46	44.88	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2494.192	-47.59	4.54	-	52.18	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2483.656	-57.24	4.54	2.47	45.0	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2500	-50.47	4.54	-	49.30	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2500	-58.24	4.54	2.47	44.0	Average	54	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
 Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
 Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
 Scan code to check authenticity




Test Graphs

Restrict Band NVNT BLE 1M 2402MHz Ant1 Peak




Restrict Band NVNT BLE 1M 2402MHz Ant1 Average






Restrict Band NVNT BLE 1M 2480MHz Ant1 Peak




Restrict Band NVNT BLE 1M 2480MHz Ant1 Average






Restrict Band NVNT BLE 2M 2402MHz Ant1 Peak




Restrict Band NVNT BLE 2M 2402MHz Ant1 Average





Restrict Band NVNT BLE 2M 2480MHz Ant1 Peak



Restrict Band NVNT BLE 2M 2480MHz Ant1 Average

