VONZTEK




Any questions, please contact: support@vonztek.net

Packaging Contents

- Wireless Headset *1
- User Manual *1
- Type-C Cable *1
- USB Dongle *1



- Adjustable headband
- 4 Mic mute button
- 2 Comfortable ear cushions
- 6 Answer/Reject button
- 3 180° swivel ear cups
 Noise canceling mic
- Type-C charge port
 270-degree boom mic
- Charge indicator light



Operating Instructions

2.1 Charging

- $\ensuremath{\mathbb{D}} Plug$ the USB cable into the headset and the computer, or put the headset into the charging base correctly to start charging.
- ② In the charging status, the charging indicator is solid Red. After fully charged, the charging indicator light is solid Blue.
- 3 When the battery is low, the indicator light will flash red.

2.2 Start

 \oplus In the off status, slide the power switch of the headset to the 'middle' gear, and then the headset is power-on. When there is no pairing record, it will automatically enter the pairing mode(Red/Blue flashes) when it is turned on, and enter the re-connection mode(Blue light flashes) when there is a pairing record.

2.3 Shutdown

①In the power-on status, slide the power switch of the headset to the 'right' gear, and the headset will be power-off.

2.4 Pairing

①In the power-on status and non-calling status, slide the power switch of the headset to the 'left' gear, and hold it for about 2 seconds until the indicators turn to flash 'Red/Blue' alternately. Then release the switch, now the headset can be found by Bluetooth devices.

② Turn on the Bluetooth of the mobile phone/laptop or other Bluetooth devices. When the device finds the headset, select the 'BT-88' device. When the pairing of the device and the headset is completed, the indicator light will change from an alternately red/blue flash to a slow blue flash.

2.5 Answer/reject/hang up calls

- ①First, pair the headset with the Bluetooth device successfully.
- ②When there is an incoming call, click the 'Answer\Reject Call\Siri' button on the headset to answer the current call.
- ③When there is an incoming call, press and hold the 'Answer\Reject Call\Siri' button of the headset for 1-2 seconds, and the current call will be rejected.

2.6 Volume adjustment

- ①First, pair the headset with the Bluetooth device successfully.
- ②When you need to increase the volume, click the 'Volume +' button on the headset to increase the volume.
- ③When you need to lower the volume, click the 'Volume -' button on the headset to decrease the volume.

2.7 Play/Pause

- ①First, pair the headset with the Bluetooth Device successfully.
- 2When you are playing music, dick the 'Play\Pause' button on the headset, and the music being played will be paused.
- ③When the music is paused, click the 'Play\Pause' button on the headset, and the paused music will be played.

2.8 Previous/Next

- ①First, pair the headset with the Bluetooth Device successfully.
- ②When you are playing music, press and hold the 'Volume +' button on the headset until the music is changed, then release the button, and the next music will be played.
- ®When you are playing music, press and hold the 'Volume -' button on the headset until the music is changed, then release the button, and the previous music will be played.


2.9 The voice control function (Siri voice control function of Apple devices)

- ①First, pair the headset with the Bluetooth device successfully.
- ②When the device is not in a call status, quickly double-click the 'Answer\Reject Cal\Siri' button of the headset, and the mobile phone will start the voice control function

2.10 Mute the microphone

- 1) First, pair the headset with the Bluetooth device successfully.
- When the headset is in the status of talking or recording, dick the 'Mic Mute' button of the headset, and the microphone will be muted. The microphone mute indicator light is on.
- ③ When the microphone is in the mute status, click the 'Mic Mute' button of the headset, and the microphone will unmute. The microphone mute indicator is off.

How to charge with charge cable?



Connection Guide

1. Connection without Dongle PAIRING MODE



- 1.In off status, slide the power switch to the middle, headset turned on
- 2.Slide and hold power switch to 'PAIR' side, until circle indicator flashes Blue & Red, enter pairing mode, you will hear 'Pairing' through the headset. Then release the power switch.



- 3. Go to the Bluetooth menu on your device. Search and click to connect 'BT-88' on your Phone/PC/laptop Bluetooth lists, circle indicator change to Blue flashes once after connected. You can hear 'Connected' through the headset. Now you can play music/make phone calls from device to headphone. (IF ASKED FOR PIN CODE, TYPE 0000)
- 4. Click PC/MAC sound icon(Bottom right side of Windows/Top right side of MAC) choose BT-88 Stereo' when only listen to music. 'BT-88Hands-free AG Audio' when online meetings or using mic &speakers.

- 5. You can enter PAIRING MODE at any time needed, just simply slide and hold power switch to 'PAIR' side.
- 6. Make sure 'BT-88' is set as playback and recording device in your computer's setting.
- 7. Make sure 'BT-88' is set as default audio device for your softphone such as MS Teams.


RECONNECT MODE

- 1.In off status, slide power switch to the middle, enter reconnect mode with LED Blue flash, the headset will start to search the devices connected before.
- 2. Once the headset connected with the remembered devices, you will hear 'Connected' through the speaker and the LED change to Blue light slow flash.
- 3. Make sure 'BT-88' is set as playback and recording device in your computer's setting.
- 4.Make sure 'BT-88' is set as default audio device for your softphone such as MS Teams.



2. Connection with Dongle

- 1.In off status, slide power switch to the middle, enter reconnect mode with LED Blue flash, the headset will start to search the devices connected before.
- 2.Plug in the 'BT-88' Dongle (included in package) into your PC/laptop 's USB-A port.
- 3.The Headset and the Dongle will pair automatically, you can hear 'Connected' through the headset.
- 4.Make sure 'BT-88 Dongle' is set as playback and recording device in your computer's setting.
- 5.Make sure 'BT-88 Dongle' is set as default audio device for your softphone such as MS Teams.



Dual Connection

- a. Connection with 2 Devices
- (Dongle+Bluetooth Device)
- Please connect to the Bluetooth device first, then connect to the USB Dongle. First, make sure the USB Dongle is not plug in.
- 2. In off status, slide the power switch to the middle, headset turned on
- 3. Slide and hold power switch to 'PAIR' side, until circle indicator flashes Blue & Red, enter pairing mode, you will hear 'Pairing' through the headset, then release the power
- switch.

 4. Go to the Bluetooth menu on your Device. Search and click to connect 'BT-88' on your Phone/PC/laptop Bluetooth
- lists, circle indicator change to Blue flashes once after connected. You can hear 'Connected' through the headset.

 Now you can play music/make phone calls from device to
- headphone. (IF ASKED FOR PIN CODE, TYPE 0000)
- 5. Plug in the 'BT-88' Dongle (included in package) into your PC/laptop 's USB-A port.
- ${\it 6.} \, {\it The Dongle will connect} \, {\it to the headset automatically}.$
- 7. Now the Dongle and your Bluetooth device are connected to the 'RT-88' headset







FREQUENTLY ASKED QUESTIONS

headset normally after connected.

Q: Not ABLE TO USE THE HEADSET ON PC?
A: You can switch different mode of the headset on PC setting of the AUDIO, click the bottom right side speaker icon, you can find 2 choices of the BT-88

If you can not HEAR others on the online meeting, please choose 'BT-88 Hands-free AG Audio'

If you need to only listen to music or videos without using MIC, please choose 'BT-88 Stereo'.

If you connected to the Bluetooth DONGLE, please choose 'BT-88 Dongle,'

Q: HOW TO GET IN PC BLUETOOTH LIST?
A: WINDOWS: When the headset is flashing red & blue light.

GO TO SETTINGS>DEVICES>Add Bluetooth or other Devices>Bluetooth





Standby Time ———— 200H+

Battery Capacity

Talking Time

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference, and

This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the PCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no quarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by uniming the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following

Recrient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.