

WIRELESS TOWING & TRAILER LIGHT KIT

100% Cable-Free Solution

Complete Kit Includes

- (2) Wireless Trailer Lights
- Convenient Carrying Case ■ Vertical And Horizontal Mount Brackets
- USB Cigarette Plug Charger
- 7-Wire Blade Wireless Transmitter
- Dual USB Charging Cable



INSTRUCTIONS

Read The Following Information Carefully Before Use

Charging Instructions

Charging Time: 2 – 2.5 Hours


Dual USB cable charges both lights at once.



Battery Life

100% Charge: 8 Hours of Run Time

50% Charge: 4 Hours of Run Time





The battery life indicator is for reference only. Run times may depend on road conditions and driving patterns.

Installation Instructions



- 1. Insert transmitter into the receptacle on your vehicle.
- 2. Attach tow lights to the rear of the towed vehicle or trailer.

Operating Instructions

Turn On: Press the on/off button for 1 second. When the white power indicator light illuminates, the unit is powered on.


Turn Off: Press the on/off button for about 1 second $until\,the\,white\,power\,indicator\,light\,turns\,off.$




NOTES: The blue battery indicator light will illuminate for 15 seconds before turning off, but the unit is still on. The blue battery indicator light will also remain on for 15 seconds before turning off.

License Plate Light Instructions

Turn On: Hold the power button for 3 seconds, the license plate light will illuminate.





Pairing Instructions

To pair, turn on your vehicle, turn on your headlights, and plug in the transmitter.



Testing Instructions



Always test prior to use.





PRL - Rear Position Lamp (Low brightness) 1234 - Rear LED/Red lens

DI - Direction Indicator Lamp (Stobe) 1234 - Red LED



Mounting Instructions

- \bullet Use the strong rubber-coated magnet/suction cup bases to mount to any fla smooth surface on the back of the trailer or towed vehicle.
- Position the left and right wireless lights appropriately.
- Place the lamps as far apart as possible for maximum visibility.










Specifications

Input Voltage	DC 5V
Working Frequency	2.4GHz
Radio Communication Range	100 Feet
Battery Capacity	2,600MAH
Charging Time	2 to 2.5 Hours
Waterproof Level	IP67
Operating Temperature	-13°F to 150°F (-25°C to 65°C)
Dimensions	See Drawings Be l ow ↓





Important Safety Instructions

- **1.** Fully charge battery before use.
- 2. Check battery life before use.
- 3. Test all light functions before use.
- **4.** Charge the battery every 6 months if not in use.
- 5. Test lights frequently when using for long periods of time.
- **6.** Always consult your vehicle's owners manual before use. **7.** Replacement or additional lights must be paired before use.
- **8.** Great for trailering and towing, always mount on a flat, smooth surface.
- 9. Intended for intermittent use only. Not intended for speeds exceeding 35mph.



FCC Warning:

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and

found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.