

T609DL	
<b>2G Bands</b>	
2G Bands	900MHz
2G Bands	1800MHz
2G Bands	1900MHz
2G Bands	850MHz
<b>3G Bands</b>	
3G Bands	B1
3G Bands	B2
3G Bands	B4
3G Bands	B5
3G Bands	B8
<b>4G Bands</b>	
4G Bands	B2
4G Bands	B3
4G Bands	B4
4G Bands	B5
4G Bands	B7
4G Bands	B12 (MFB1)
4G Bands	B13
4G Bands	B20
4G Bands	B25
4G Bands	B26
4G Bands	B28
4G Bands	B66
4G Bands	B71
4G Bands	B41(HPUe)
4G Bands	B48
<b>5G NR</b>	
NSA,SA	n25(40MHz)
NSA only	n2
NSA only	n5
NSA only	n66(40MHz)
NSA,SA	n71
NSA only	n77(100MHz)(HPUe)
NSA,SA	n30
NSA,SA	n41(100MHz)(HPUe)
<b>4x4 MIMO DL</b>	
4*4 MIMO-LTE	B2
4*4 MIMO-LTE	B4
4*4 MIMO-LTE	B25
4*4 MIMO-LTE	B66
4*4 MIMO-LTE	B41
4*4 MIMO-LTE	B48
4*4 MIMO-5G	n66
4*4 MIMO-5G	n2
4*4 MIMO-5G	n25
4*4 MIMO-5G	n41
4*4 MIMO-5G	n77
<b>E 2CA for LTE UL CA</b>	
LTE CA	Not supported
<b>E 2CA for LTE DL CA</b>	
Category	Feature
LTE CA	CA 2A[2]-2A[2]
LTE CA	CA 2A[2]-4A[2]
LTE CA	CA 2A[2]-5A[2]
LTE CA	CA 2A[2]-12A[2]
LTE CA	CA 2A[2]-13A[2]
LTE CA	CA 2A[2]-66A[2]
LTE CA	CA 2A[2]-71A[2]
LTE CA	CA 4A[2]-4A[2]
LTE CA	CA 4A[2]-5A[2]
LTE CA	CA 4A[2]-12A[2]
LTE CA	CA 4A[2]-13A[2]
LTE CA	CA 4A[2]-71A[2]
LTE CA	CA 5A[2]-5A[2]
LTE CA	CA 5B[2]
LTE CA	CA 5A[2]-66A[2]
LTE CA	CA 5A[2]-41A[2]
LTE CA	CA 12A[2]-66A[2]
LTE CA	CA 13A[2]-66A[2]
LTE CA	CA 25A[2]-26A[2]
LTE CA	CA 41A[2]-41A[2]
LTE CA	CA 41A[2]-48A[2]
LTE CA	CA 66A[2]-66A[2]
LTE CA	CA 66B[2]
LTE CA	CA 66C[2]
LTE CA	CA 66A[2]-71A[2]
LTE CA	CA 2C[2]
LTE CA	CA 41C[2]
LTE CA	CA 25A[2]-25A[2]
LTE CA	CA 25A[2]-41A[2]
<b>EN-DC x LTE + 1 NR</b>	
5G EN-DC	DC 12A[2]_n66A[4]
5G EN-DC	DC 12A[2]_n2A[4]
5G EN-DC	DC 12A[2]_n30A[2]
5G EN-DC	DC 12A[2]_n77A[4]
5G EN-DC	DC 12A[2]-66A[2]_n2A[4]
5G EN-DC	DC 12A[2]-66A[2]_n30A[2]
5G EN-DC	DC 12A[2]-66A[2]_n66A[4]
5G EN-DC	DC 12A[2]-66A[2]_n77A[4]
5G EN-DC	DC 13A[2]_n2A[4]
5G EN-DC	DC 13A[2]_n66A[4]
5G EN-DC	DC 13A[2]_n77A[4]

T609L_20230419_ID Card v1.3.0	
<b>2G Bands</b>	
2G Bands	900MHz
2G Bands	1800MHz
2G Bands	1900MHz
2G Bands	850MHz
<b>3G Bands</b>	
3G Bands	B1
3G Bands	B2
3G Bands	B4
3G Bands	B5
3G Bands	B8
<b>4G Bands</b>	
4G Bands	B2
4G Bands	B4
4G Bands	B5
4G Bands	B7
4G Bands	B12
4G Bands	B13
4G Bands	B25
4G Bands	B26
4G Bands	B66
4G Bands	B71
4G Bands	B41(PC2 HPUE)
4G Bands	B48(PC3)
<b>5G NR Bands</b>	
NSA, SA	n2
NSA, SA	n5
NSA, SA	n12
NSA, SA	n25
NSA, SA	n41(PC2 HPUE)
NSA, SA	n48(PC3)
NSA, SA	n66
NSA, SA	n71
NSA, SA	n77(PC2 HPUE)
<b>4x4 MIMO Band</b>	
4*4 MIMO-LTE	B2
4*4 MIMO-LTE	B4
4*4 MIMO-LTE	B25
4*4 MIMO-LTE	B66
4*4 MIMO-LTE	B41
4*4 MIMO-LTE	B48
4*4 MIMO-5G	n2
4*4 MIMO-5G	n25
4*4 MIMO-5G	n41
4*4 MIMO-5G	n48
4*4 MIMO-5G	n66
4*4 MIMO-5G	n77
<b>LTE 2CA for LTE UL CA</b>	
LTE CA	not support
<b>LTE 2CA for LTE DL CA</b>	
Category	Feature[only support MIMO [2]*[2] for each cc
LTE CA	CA 2A-2A
LTE CA	CA 2A-4A
LTE CA	CA 2A-5A
LTE CA	CA 2A-12A
LTE CA	CA 2A-66A
LTE CA	CA 2A-48A
LTE CA	CA 2A-71A
LTE CA	CA 4A-4A
LTE CA	CA 4A-5A
LTE CA	CA 4A-12A
LTE CA	CA 4A-48A
LTE CA	CA 4A-71A
LTE CA	CA 5A-48A
LTE CA	CA 5A-66A
LTE CA	CA 12B
LTE CA	CA 12A-48A
LTE CA	CA 12A-66A
LTE CA	CA 48A[2]-66A[2]
LTE CA	CA 48A[2]-71A[2]
LTE CA	CA 66A-66A
LTE CA	CA 66A-71A
<b>5G EN-DC x LTE + 1 NR</b>	
5G EN-DC for n2	DC 5A_n2A(UL&DL)
5G EN-DC for n2	DC 12A_n2A(UL&DL)
5G EN-DC for n2	DC 13A_n2A(UL&DL)
5G EN-DC for n2	DC 66A_n2A(UL&DL)
5G EN-DC for n2	DC 5A-48A_n2A(partial, B48 only SCC)(DL)
5G EN-DC for n2	DC 66A-5A_n2A(DL)
5G EN-DC for n2	DC 66A-12A_n2A(DL)
5G EN-DC for n5	DC 2A_n5A(UL&DL)
5G EN-DC for n5	DC 66A_n5A(UL&DL)
5G EN-DC for n5	DC 2A-48A_n5A(partial, B48 only SCC)(DL)
5G EN-DC for n5	DC 2A-66A_n5A(DL)
5G EN-DC for n5	DC 48A-66A_n5A(partial, B48 only SCC)(DL)
5G EN-DC for n12	DC 2A_n12A(UL&DL)
5G EN-DC for n12	DC 66A_n12A(UL&DL)
5G EN-DC for n12	DC 2A-66A_n12A(DL)
5G EN-DC for n25	DC 12A_n25A(UL&DL)
5G EN-DC for n41	DC 2A_n41A(UL&DL)
5G EN-DC for n41	DC 5A_n41A(UL&DL)
5G EN-DC for n41	DC 12A_n41A(UL&DL)
5G EN-DC for n41	DC 66A_n41A(UL&DL)
5G EN-DC for n41	DC 2A_66A_n41A(DL)
5G EN-DC for n48	DC 5A_n48A(UL&DL)

5G EN-DC	DC 13A[2]-66A[2]_n2A[4]
5G EN-DC	DC 13A[2]-66A[2]_n66A[4]
5G EN-DC	DC 13A[2]-66A[2]_n77A[4]
5G EN-DC	DC 2A[2]-12A[2]_n66A[2]
5G EN-DC	DC 2A[2]-66A[2]_n41A[4]
5G EN-DC	DC 2A[2]-66A[2]_n71A[2]
5G EN-DC	DC 2A[2]-71A[2]_n71A[2] B71 only SCC
5G EN-DC	DC 2A[4]_n41A[4]
5G EN-DC	DC 2A[4]_n71A[2]
5G EN-DC	DC 2A[4]_n2A[4]
5G EN-DC	DC 2A[4]_n30A[2]
5G EN-DC	DC 2A[4]_n5A[2]
5G EN-DC	DC 2A[4]_n66A[4]
5G EN-DC	DC 2A[4]_n77A[4]
5G EN-DC	DC 2A[2]-12A[2]_n2A[4]
5G EN-DC	DC 2A[2]-12A[2]_n30A[2]
5G EN-DC	DC 2A[2]-12A[2]_n77A[4]
5G EN-DC	DC 2A[2]-13A[2]_n2A[4]
5G EN-DC	DC 2A[2]-13A[2]_n66A[4]
5G EN-DC	DC 2A[2]-2A[2]_n30A[2]
5G EN-DC	DC 2A[2]-2A[2]_n5A[2]
5G EN-DC	DC 2A[2]-2A[2]_n66A[4]
5G EN-DC	DC 2A[2]-2A[2]_n77A[4]
5G EN-DC	DC 2A[2]-5A[2]_n2A[4]
5G EN-DC	DC 2A[2]-5A[2]_n30A[2]
5G EN-DC	DC 2A[2]-5A[2]_n5A[2] B5 only SCC
5G EN-DC	DC 2A[2]-5A[2]_n66A[4]
5G EN-DC	DC 2A[2]-5A[2]_n77A[4] for UL 5A[2]_n77A[4]
5G EN-DC	DC 2A[4]-5A[2]_n77A[4] for UL 2A[4]_n77A[4]
5G EN-DC	DC 2A[2]-66A[2]_n2A[4]
5G EN-DC	DC 2A[2]-66A[2]_n30A[2]
5G EN-DC	DC 2A[2]-66A[2]_n5A[2]
5G EN-DC	DC 2A[2]-66A[2]_n66A[4]
5G EN-DC	DC 2A[2]-66A[2]_n77A[4]
5G EN-DC	DC 2C[2]_n41A[4]
5G EN-DC	DC 2C[2]_n71A[2]
5G EN-DC	
5G EN-DC	DC 5A[2]_n2A[4]
5G EN-DC	DC 5A[2]_n30A[2]
5G EN-DC	DC 5A[2]_n66A[4]
5G EN-DC	DC 5A[2]_n77A[4]
5G EN-DC	DC 5A[2]-66A[2]_n2A[4]
5G EN-DC	DC 5A[2]-66A[2]_n30A[2]
5G EN-DC	DC 5A[2]-66A[2]_n5A[2] B5 only SCC
5G EN-DC	DC 5A[2]-66A[2]_n66A[4]
5G EN-DC	DC 5A[2]-66A[2]_n77A[4] for UL DC 5A[2]_n77A[4]
5G EN-DC	DC 5A[2]-66A[2]_n77A[4] for UL DC 66A[2]_n77A[4]
5G EN-DC	DC 66A[2]-66A[2]_n71A[2]
5G EN-DC	DC 66A[2]-71A[2]_n71A[2] B71 only SCC
5G EN-DC	DC 66A[4]_n25A[4]
5G EN-DC	DC 66A[4]_n41A[4]
5G EN-DC	DC 66A[4]_n71A[2]
5G EN-DC	DC 66A[4]_n2A[4]
5G EN-DC	DC 66A[4]_n30A[2]
5G EN-DC	DC 66A[4]_n5A[2]
5G EN-DC	DC 66A[4]_n66A[4]
5G EN-DC	DC 66A[4]_n77A[4]
5G EN-DC	DC 66A[2]-66A[2]_n30A[2]
5G EN-DC	DC 66A[2]-66A[2]_n5A[2]
5G EN-DC	DC 66A[2]-66A[2]_n77A[4]
5G EN-DC	DC 66C[2]_n71A[2]
5G EN-DC	DC 2A[4]_n25A[4]
5G EN-DC	DC 2A[4]_n71B[2]
5G EN-DC	DC 66A[4]_n71B[2]
5G EN-DC	DC 2A[2]-2A[2]_n71A[2]
5G EN-DC	DC 12A[2]-66A[2]_n25A[4]
5G EN-DC	DC 2A[2]-2A[2]_n41A[4]
5G EN-DC	DC 2A[2]-13A[2]_n77A[4]
5G EN-DC	DC 5A[2]-5A[2]_n2A[4]
5G EN-DC	DC 5A[2]-5A[2]_n66A[4]
5G EN-DC	DC 5B[2]_n2A[4]
5G EN-DC	DC 5B[2]_n66A[4]
5G EN-DC	DC 66B[2]_n2A[4]
5G EN-DC	DC 66B[2]_n5A[2]
5G EN-DC	DC 66C[2]_n2A[4]
5G EN-DC	DC 66C[2]_n5A[2]
5G EN-DC	DC 66A[2]-66A[2]_n2A[4]
5G EN-DC	DC 12A[2]_n25A[4]
<b>G EN-DC 1LTE+2NR</b>	
5G EN-DC	DC 2A[4]_n66A[4]-n71A[2]
5G EN-DC	DC 66A[4]_n41A[4]-n71A[2]
5G EN-DC	DC 2A[4]_n41A[4]-n71A[2]
5G EN-DC	DC 2A[2]_n41A[4]-n66A[2] (Partial, N66 only SCC)
5G EN-DC	DC 66A[4]_n25A[4]-n71A[2]
5G EN-DC	DC 66A[2]_n25A[2]-n41A[4]
5G EN-DC	DC 2A[2]-66A[2]_n41C[2]
5G EN-DC	DC 66A[4]_n41C[2]
5G EN-DC	DC 2A[4]_n41C[2]
5G EN-DC	DC 2A[4]_n71B
5G EN-DC	DC 66A[4]_n71B

5G EN-DC for n66	DC 2A_n66A(UL&DL)
5G EN-DC for n66	DC 5A_n66A(UL&DL)
5G EN-DC for n66	DC 12A_n66A(UL&DL)
5G EN-DC for n66	DC 13A_n66A(UL&DL)
5G EN-DC for n66	DC 2A-5A_n66A(DL)
5G EN-DC for n66	DC 2A_12A_n66A(DL)
5G EN-DC for n66	DC 2A-48A_n66A(partial, B48 only SCC)(DL)
5G EN-DC for n71	DC 2A_n71A(UL&DL)
5G EN-DC for n71	DC 66A_n71A(UL&DL)
5G EN-DC for n71	DC 2A-66A_n71A(DL)
5G EN-DC for n77	DC 2A_n77A(UL&DL)
5G EN-DC for n77	DC 12A_n77A(UL&DL)
5G EN-DC for n77	DC 5A_n77A(UL&DL)
5G EN-DC for n77	DC 5A-66A_n77A(DL)
5G EN-DC for n77	DC 66A_n77A(UL&DL)
5G EN-DC for n77	DC 66A-66A_n77A(DL)
5G EN-DC for n77	DC 2A-2A_n77A(DL)
5G EN-DC for n77	DC 2A-5A_n77A(DL)
5G EN-DC for n77	DC 2A-66A_n77A(DL)
<b>5G NR SA CA</b>	
5G NR SA CA	CA_n71A-n77A
5G NR SA CA	CA_n66A-n77A
5G NR SA CA	CA_n2A-n77A
5G NR SA CA	CA_n5A-n77A
5G NR SA CA	CA_n66A-n71A
5G NR SA CA	CA_n48A-n66A
5G NR SA CA	CA_n48A-n71A
5G NR SA CA	CA_n2A-n41A only support CA_n41A[4+4]_n2A[2*2](only n41 as PCC)
5G NR SA CA	CA_n66A-n41A
5G NR SA CA	CA_n5A-n41A
5G NR SA CA	CA_n71A-n41A
5G NR SA CA	CA_n77A-n41A

5G NR SA CA	
5G NR SA CA	CA_n66A[4]-n77A[4]
5G NR SA CA	CA_n41A[4]-n71A[2]
5G NR SA CA	CA_n41(2A)[4]
5G NR SA CA	CA_n25A[4]-n71A[2]
5G NR SA CA	CA_n25A[4]-n41A[4]
5G NR SA CA	CA_n41C[4]
5G NR SA CA	CA_n41A[4]-n66A[4]
5G NR SA CA	CA_n66A[4]-n71A[2]
5G NR SA CA	CA_n71B[2]
5G NR SA CA	CA_n25(2A)[4]
5G NR SA CA	CA_n25A[4]-n66A[4]
5G NR SA CA	CA_n71(2A)[2]
5G NR SA CA	CA_n25A[4]-n77A[4]
5G NR SA CA	CA_n41A[4]-n77A[4]

FCC 测试频段

LTE		SA		ENDC	
T609DL	T609L	T609DL	T609L	T609DL	T609L
FDD2	FDD2	n25	n2	DC_12A_n66A	DC_5A_n2A
FDD4	FDD4	n41	n5	DC_12A_n2A	DC_12A_n2A
FDD5	FDD5	n66	n12	DC_12A_n30A	DC_13A_n2A
FDD7	FDD7	n71	n25	DC_12A_n77A	DC_66A_n2A
FDD12	FDD12	n77	n41	DC_13A_n2A	DC_2A_n5A
FDD13	FDD13	n2	n48	DC_13A_n66A	DC_66A_n5A
FDD25	FDD25	n5	n66	DC_13A_n77A	DC_12A_n25A
FDD26	FDD26	n30	n71	DC_2A_n41A	DC_2A_n41A
TDD41	TDD41		n77	DC_2A_n71A	DC_5A_n41A
TDD41HPUE	TDD41HPUE			DC_2A_n2A	DC_12A_n41A
TDD48	TDD48			DC_2A_n30A	DC_66A_n41A
FDD66	FDD66			DC_2A_n5A	DC_2A_n66A
FDD71	FDD71			DC_2A_n66A	DC_5A_n66A
				DC_2A_n77A	DC_12A_n66A
				DC_5A_n2A	DC_13A_n66A
				DC_5A_n30A	DC_2A_n71A
				DC_5A_n66A	DC_66A_n71A
				DC_5A_n77A	DC_2A_n77A
				DC_66A_n25A	DC_12A_n77A
				DC_66A_n41A	DC_5A_n77A
				DC_66A_n71A	DC_66A_n77A
				DC_66A_n2A	DC_5A_n48A
				DC_66A_n30A	
				DC_66A_n5A	
				DC_66A_n66A	
				DC_66A_n77A	
				DC_2A_n25A	
				DC_12A_n25A	

T609L

T609L新增

仅考虑SAR/RSE