



Feature

- ※ High gain
- ※ Omani-directional
- ※ Wide bandwidth

Application


※GSM850/900/DCS/PCS/WCDMA B1/B2/B4/B5/B8

LTE B1/B2/B3/B4/B5/B7/B8/B12/B17/B13/B28/B38/B40/B41/B66


Name and address of the antenna manufacturer	Model number of the antenna
Huizhou Shuobide Wireless Technology Co., Ltd Suzhou Industrial Park, No. 99 Weixin Road, Zhongke Intelligence	3IN1: KJ5-ANT1 DIV: KJ5-ANT2 MAIN: KJ5-ANT3 5G WIFI: KJ5-ANT4

Transmitter Frequency		GSM 850/WCDMA B5/LTE B5: 824 - 849 MHz
		GSM 900/WCDMA B8/LTE B8: 880 - 915 MHz
		DCS /WCDMA B4/LTE B3/B4/B66: 1710 - 1785 MHz
		PCS/WCDMA B2/LTE B2: 1850-1910MHz
		WCDMA B1/LTE B1: 1920 - 1980MHz
		LTE B7: 2496-2565MHz
		LTE B40: 2300-2400MHz
		LTE B38: 2570-2620MHz
		LTE B41: 2535-2655MHz
		LTE B12/B17/B28/B13: 710-755MHz
Receiver Frequency		GSM 850/WCDMA B5/LTE B5: 869 - 894 MHz
		GSM 900/WCDMA B8/LTE B8: 925 - 960 MHz
		DCS/LTE B3/B66: 1805 - 1880 MHz
		WCDMA 4/LTE B4: 2110-2155 MHz
		PCS/WCDMA B2/LTE B2: 1930-1990MHz
		WCDMA B1/LTE B1: 2110 - 2170MHz
		LTE B7: 2620-2690MHz
		LTE B40: 2300-2400MHz
		LTE B38: 2570-2620MHz
		LTE B41: 2535-2655MHz
LTE B12/B17/B28/B13 :758-803MHz		
Antenna Gain	ANT3	GSM 850/WCDMA B5/LTE B5 : -4.7dBi
		GSM 900/WCDMA B8/LTE B8 : -4.8dBi
		DCS /WCDMA B4/LTE B3/B4/B66 : -1.2dBi
		PCS/WCDMA B2/LTE B2: -1.4dBi
		WCDMA B1/LTE B1 : -1.3dBi
		LTE B7/B38/B41 : -0.4dBi
		LTE B40 : -0.7dBi
		LTE B12/B17/B28/B13: -5.6dBi
	ANT1	Bluetooth/2.4G Wi-Fi:-3.3dBi
	ANT4	5G Wi-Fi:-1.1dBi


※ Antenna Gain
ANT1 2.4GWIFI&BT



2.4G WIFI&BT $\Phi = 0^\circ$




2.4G WIFI&BT $\Phi = 90^\circ$




2.4G WIFI&BT Theta=90deg


※ Antenna Gain
ANT3
Main Antenna



GSM850 / WCDMA B5 / LTE B5 Phi=0deg




GSM850 / WCDMA B5 / LTE B5 Phi=90deg




GSM850 / WCDMA B5 / LTE B5 Theta=90deg


※ Antenna Gain
Main Antenna



LTE B40 $\Phi=0^\circ$




LTE B40 $\Phi=90^\circ$




LTE B40 Theta=90deg


※ Antenna Gain
Main Antenna



GSM900 / WCDMA B8 / LTE B8 Phi=0deg




GSM900 / WCDMA B8 / LTE B8 Phi=90deg




GSM900 / WCDMA B8 / LTE B8 Theta=90deg


※ Antenna Gain
Main Antenna



DCS1800/PCS1900/WCDMA B1/B2LTE B1/B2/B3/B4/B66Phi=0deg




DCS1800/PCS1900/WCDMA B1/B2LTE B1/B2/B3/B4/B66 Phi=90deg




DCS1800/PCS1900/WCDMA B1/B2LTE B1/B2/B3/B4/B66Theta=90deg


※ Antenna Gain
Main Antenna



LTE B7/B38/41 Phi=0deg




LTE B7/B38/41 $\Phi = 90^\circ$




LTE B7/B38/41 $\Theta = 90^\circ$


※ Antenna Gain
Main Antenna



LTE B12/B17/ B28/B13 $\Phi=0^\circ$




LTE B12/B17/B28/B13 $\Phi=90^\circ$




LTE B12/B7/B28/B13 Theta=90deg


※ Antenna Gain
ANT4



5G WIFI Phi=0deg




5G WIFI $\Phi=90\text{deg}$



5G WIFI $\Theta=90\text{deg}$

Antenna Photo



PREPARED BY	CHECKEDBY	APPROVAL BY	S.R.NO	
	Yuehua.sun		DATE:	2023/07/26