
User Manual

Model name: H-08

Brand name: JOWAY

FCC ID: 2AEZ4JOWAYH-08

Security Precautions

Security Precautions: In order to have a proper and safety use of the headset, please read this user manual in detail and save it.

■ **Be sure to aware the following guidelines when using your headset.**

1. Should adjust Volume and time reasonably when using the headset.
2. Please stop using the headset in potentially hazardous situation to ensure your safety.
3. Please avoid using headset to listen to music, make or receive calls to avoid distraction while driving.
4. Put this product and its accessories somewhere out of the reach of children, to avoid a fatal dander caused by inappropriate use.
5. Should keep water from entering the headset during grooming, which may cause damage to the sound quality or the headset.
6. Should avoid turning the volume so high that you can't hear anything around you. If you feel a tinnitus or the volume is too high, please reduce the volume.
7. Stop using the headset if you feel obvious discomfort, irritation or have other adverse reactions.
8. The headset should not be stored or use at temperatures below -15 °C or above 55°C which may shorten headset or battery life.

Overview of the headset

■ Overview of I5 Bluetooth stereo headset:



■ H-08 Bluetooth headset in the box:

- Hostx1
- USB charging cable x1
- warranty card x1
- Qualification x1
- Ear clip x1
- User's manual x1
- Overhand hook x2

■ Charger and battery:

Please check the charging cable is original or bot before charging the Bluetooth headset.

Warning:

Must use original charge cable to charge for the Bluetooth headset, otherwise it may damage the headset. Thus, voltage of charger must be 5V, electric current exceed 100mA(5V/100mA).

Technical specification

■ Bluetooth Specification

- Support agreement: A2DP, AVRCP, HSP, HFP
- Frequency: 2.400GHz-2.480GHz
- Working scope: $\geq 10\text{m}$
- Talking time: 6 hours
- Music time: 5 hours (80% volume)
- Standby time: 200 hours
- Charging standard: Micro USB, DC5V,500mA
- Charging time: about 1.5 hours
- Working environment: $-10\sim 50^{\circ}\text{C}$
- Frequency of volume: 20Hz-22KHz

■ Specification

- Product Net Weight: 15g
- Product Dimension: 61x15x9.5mm

indicator light

Matching status: red and blue light quick blinks alternately

Music Status: all lights turn off

Charging Status: red light keep flashing

Charging Finished: red light turns off, or blue light keep flashing

Low-power Status: red light turns on with indicate voice

Operation Description

Turn on: Put the button to "turn on" status

Turn off: Put the button to "turn off" status

- Matching mode: It will automatically enter into matching status while firstly turn on (or keep pressing the multi-functional button into matching status).
- Answer/hang up: single press the multi-functional button
- Repeat dial the last no.: double press the multi-functional button
- Voice dial(need mobile support): double press the lower volume button
- Up/down song: press the side button once
- Volume big/small: keep pressing the side button for 2 seconds
- Turn to mobile answer the phone: keep pressing the upper volume button
- Headphone power indicate: double press the upper volume button, 100% power with once blinking of red light, 75% power with twice blinking of red light, 50% power with three blinking of red light, 25% power with four blinking of red light. (Note: it must be operated under stand-by status and IOS system can show the power directly on the screen.)
- Language swift (Chinese or English): when the headphone was matched, press the multi-functional button and lower volume button at the same time for 3 seconds, then it will have indicate voice to show OK.
- Sound effect swift: when the headphone was matched, press the upper volume button and lower.
- Voice calls: answer YES, reject NO, note (on the Caller ID After the broadcast will open voice).

Bluetooth matching steps 1

1. Please keep as close as possible from Bluetooth headphone to mobile phone (or other connecting devices) within 1 meter.
2. Turn on the Bluetooth headphone and make sure it enters into matching status. Then red and blue light blinks alternately which shows wait for matched.
3. Open the user's mobile Bluetooth function and search or scan, which will find all of the closed Bluetooth devices. Then click the headphone name H-08 and enter code 0000. After connected successfully, the headphone will turn to blue light blinking which means matched finished. Now you can listen to the phone music and take a phone call.

Warm Prompt:

1. Mobile already matched will no need to match again, the headphone will automatically match the previous device and make connection.
2. There are some phones after matching connection, they still need to choose headphones service function. If the cell phone bluetooth version is 2.1 or higher, when matching, you don't need to pair password (0000).
3. The maximum of matching time is 240 seconds. If you exceeded such time it will drop out the matching status. If you still can't match successfully, please repeat the above steps to match again.
4. The headphone will automatically shut down when it being no-connection over 10 minutes.
5. Built-in three kinds of sound effects can be switched headphones.

Bluetooth matching steps 2

Matching 2: One with two function(connect two bluetooth devices at the same time)

1. Ensure the headset has already connected the first mobile phone(already had the connect memory)
2. Please close the bluetooth earphone and restart it waiting to the condition of matching connection . Activate another mobile phone bluetooth function and searching for bluetooth device, select H-08 and matched (as the first matching connection method)
3. Open the first mobile phone bluetooth function, click and connect the type of H-08 which has the connect memory, at this time, H-08 already connected with two mobile phones, one with two function.

Steps of connecting computer

First download a universal driver software.Installed successfully , you will have a little gray icon (Bluetooth icon) in the bottom right corner of your computer. Then plug in the Bluetooth adapter, at this time, the gray Bluetooth icon will turn to blue. Note: notebook computer with Bluetooth function does not need external Bluetooth adapter which need to buy separately. Right click on the (bluetooth icon), select "show the classic interface" When the bluetooth headset turned off, press the multifunctional key long, until red and blue lights flashing (matching), headset has entered the searched state at this time.

Right click on the computer interface, select the "search" equipment, the headset must be in pairs (red and blue lights flashing), then the computer will search for all nearby bluetooth devices. Double-click the computer and search for H-08 bluetooth headset. Right-click the H-08 and select "bluetooth audio high quality", enter the password "0000" (0000) initial passwords. Here, congratulations, bluetooth headset has been successfully connect with computer, and now can listening to the music and voice chat from computer!

FAQ

1:Headset can't pare with mobile phone.

Ans:please check whether your headset is in pairing mode or reconnect ion mode, check whether Bluetooth search function of your mobile phone has been opened. Thus, check your mobile device's Bluetooth menu and delete/forget the headset,reconnect the headset following instructions of use manual

2:headset can't be switch on

Ans:Please check the battery status of your headset.

3:Can I change battery for the headset?

Ans: No, this headset use a built-in-non detachable Li-Polymer battery. It can't be removed.

4:can I use headset while driving?

Ans: For safety reason, we strongly recommend not to use over-ear headset to avoid distraction while driving.

5: Headset disconnect with your Mobile phone within 10 meter.

Ans: please check if there is metal or other material within relatively close range may interfere Bluetooth connection, as Bluetooth is a radio technology that is sensitive to objects between the headset and connected devices.

6: Can't hearing a sound from your computer or mobile phone.

Ans: Please check whether the output channel of your computer is Bluetooth Audio Device and Bluetooth function of your computer support A2DP profile. And please check volume of your headset, and computer/ mobile phone.

7: can't use the headset to control volume of select track of APP of your mobile phone.



想要浏览更多资讯
可关注乔威官方微信

FCC Caution.

§ 15.19 Labelling requirements.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

§ 15.21 Changes or modification warning

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

§ 15.105 Information to the user.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

* RF warning for Portable device:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.