使用说明书

X1无线双耳迷你蓝牙耳机

参数配置

*真正无线蓝牙双耳,左右声道分离。

*充电:磁吸试充电顶针

*充电时间:1.5小时。

*主机功耗:20豪安左右,副机在17-18豪安。

*左右耳均具有完整蓝牙耳机功能,可单独使用,也可成对

*蓝牙发射距离:空旷处15-25米;背向10-15米;信号稳定。

*电池容量:左右耳均为40毫安;充电盒内置容量450毫安。

*持续听歌打电话:单耳使用2小时,双耳成对使用2小时。

附文:请尽量按照本图示的方式和角度佩戴蓝牙耳机,以获

*待机时间:单耳使用35小时,双耳成对使用35小时。

V1.0

User's Manual

Product Name:earphone

ModelName:X1,X2,X3,X5,X6,X7,X8,X9,X10,X11,X12, X13,X15,X16,X17,X18,X19,X20,X21,X22,X23,X25,X26, X27,X28,X29,X30,X31,X32,X33,X35,X36,X37,X38,X39.

Brand Name:BYM

Parameter configuration

- * Real dual wireless bluetooth headset, it has left and right channel. * Left and right headset have a complete bluetooth headset function which can be used with single headset and can also be used in pairs.
- * Bluetooth connection distance: When there is no obstacle, its bluetooth 's working distance is 15-25 meters; When there are obstacles, its bluetooth 's working distance is 10-15 meters; The signal
- * Power consumption of one headset with answering calls function is about 20 mAh ,another one 's power consumption is about the 17-18 mAh.
- * Battery capacity: left and right headset are 40 mAh; Charging box with built-in capacity is 450 mAh.
- * Charging: Magnetic charging thimble. Keep listening songs or make calls: 2 hours for one headset and
- * Standby time: 35 hours with one headset and 35 hours with two
- * Charging time: 1.5 hours.

Enclosure: Please follow as the way and angle of the picture to wear bluetooth headset to get the best



蓝牙配对

- 1、长按开机键产品开机,默认进入双耳模式,左右耳自动 连接。耳机LED灯变成蓝灯闪状态即连接成功(每隔5秒闪
- 2、左右耳连接成功后,手机可以搜索到蓝牙耳机名,手机 连接成功,源端播放音版会自动切换至蓝牙耳机传输,在耳 机端实现音频播放。
- 3、长按开机键5秒,产品开启进入单耳模式,手机可以搜索 到蓝牙耳机名,手机连接成功,源端播放音频会自动切换至 蓝牙耳机传输,在耳机端实现音频播放。

关机

长按耳机功能键然后松开,LED灯将熄灭,然后关机。

打电话

- 1、当耳机开机并于手机连接成功,即可接听电话(只有一边 耳机工作)。
- 2、当来电时,耳机将有来电提示。此时按来电音乐耳机的功 能键,即可接听电话;双击功能键,即可拒绝接听来电。 3、电话中按下功能键,将挂断电话。
- 4、电话过程中,可通过手机调节通话音量。

听音乐

- 1、当耳机开机并于手机连接成功,即可使用手机的音乐播放
- 2、播放过程中按下功能键,将暂停播放,再次按下功能键将 继续音乐播放。 3、请通过手机调节音乐播放音量。

给耳机充电

- *请使用本产品附带的专用充电器给耳机充电。
- *将耳机放入指定的充电盒内,短按充电盒按键即可充电,充 电盒LED长亮显示电量。
- *充电时,耳机的LED灯会红灯长亮。充电完成,LED灯会自 动熄灭。
- *两台耳机都充满电量后,充电盒自动关闭充电,即LED灯熄 灭。

X1充电盒操作说明

- 1、USB充电输入电压: DC4.5~5V
- 2、最大充电电流:1A
- 3、充电状态指示灯如下图

电量C(%)	L1	L2	L3	L4
充满	亮	亮	亮	亮
75%≤C	亮	亮	亮	1.5Hz闪烁
50%≤C<75%	亮	亮	1.5Hz闪烁	灭
25%≤C<50%	亮	1.5Hz闪烁	灭	灭
C<25%	1.5Hz闪烁	灭	灭	灭

短按按键为开机	,电量指示灯	点亮,	电量状态指	『示如下图:
电量C(%)	L1	L2	L3	L4
C≥75%	亮	亮	亮	亮
50%≤C<75%	亮	亮	亮	灭
25%≤C<50%	亮	亮	灭	灭
3%≤C<25%	亮	灭	灭	灭
0%≤C<3%	1.5Hz闪烁	灭	灭	灭

- 5、升压输出电压:5V
- 6、升压最大输出电流:1A

注意事项

- 1.请不要使劲摔打产品,也不要重物挤压
- 2.本产品严禁进水,请在淋浴时和雨中时不要使用本产品 3.请远离WiFi路由器及其它蓝牙设备,以避免其它使用信号的
- 设备对本产品形成干扰。 4.请在有效距离(15M无遮挡)内使用。
- 5.本产品出厂时已1对1配对,请不要混用两对蓝牙耳机

Bluetooth pairing

- 1: Press the power button, headset will enter the using two headsets mode by default, left and right headset will connect with each other automatically. Headset LED lights will become a blue light which means they connected successfully. (Light will flash every 5 seconds). 2: When right and left headset 's connection is successful, the mobile phone can search and connect with the bluetooth headset successfully, the audio player will switch to bluetooth headset transmission and
 - headset audio will play it automatically. 3: Press the power button for 5 seconds, the product will enter into single headset mode and mobile phone can search and connect with its bluetooth, the audio player will switch to bluetooth headset transmission and headset audio will play it automatically.

Shut down

Press the headset function button and then release. LED lights will be

Make calls

When the headset is turned on and connected with mobile phone successfully, you can answer the phones. (only one headset works.) When there is a call, the headset will give users a reminder. At this point users could press headset function key to answer the call; Double-click the function key, users can refuse to answer the call. Press the function key on the phone to hang up.

During the call, the call volume can be adjusted by the phone.

Listen to the music

When the headset is turned on and connected with mobile phone successfully, you can use the phone's music player to listen to music Press the function key during playback and it will be paused, and press function again to play the music again. Please adjust the music playing volume by the phone

Charge the headset

Use the special charger that comes with the product to charge the

Put the headset into the specified charging box, press the charging box button to charge it, LED bright and display the electricity. When it is charged, the headset's LED light will be red and bright.
When the charging is completed, the charging box LED will be off

automatically.

After two headsets are fully charged, the charging box turns off charging automatically which is that LED lights will be off.

X1 Charging box operating instructions

- 1, USB charging input voltage: DC4.5 ~ 5V
- 2, Maximum charging electric current: 1A 3, Charging status indicator as shown below

electricity C(%)	L1	L2	L3	L4
Full	Bright	Bright	Bright	Bright
75%≤C	Bright	Bright	Bright	1.5Hz Flashing
50%≤C<75%	Bright	Bright	1.5Hz Flashing	Lights off
25%≤C<50%	Bright	1.5Hz Flashing	Lights off	Lights off
C<25%	1.5Hz Flashing	Lights off	Lights off	Lights off

4, Short press the button to power headset on, power indicator

electricity C(%)	L1	L2	L3	L4
C≥75%	Bright	Bright	Bright	Bright
50%≤C<75%	Bright	Bright	Bright	Lights off
25%≤C<50%	Bright	Bright	Lights off	Lights off
3%≤C<25%	Bright	Lights off	Lights off	Lights off
0%≤C<3%	1.5Hz Flashing	Lights off	Lights off	Lights off

- 5, Boost output voltage: 5V.
- 6, Boost the maximum output current: 1A.
- 7, Double-click the power button to turn off the machine

Precautions

- 1. Do not beat the product hard, do not squeeze heavy objects.
- 2. This product is strictly prohibited water, please do not use this product when showering and in the rain
- 3.Stay it away from WiFi routers and other bluetooth devices to avoid other devices interfering signal .
- 4. Please use it within effective distance (15M without cover).
- 5. This product has been paired one to one at the factory, please do not mix two pairs of bluetooth headset.

Manufacture: Shenzhen Buzz Tech Co., Ltd

FCC Caution.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- -Reorient or relocate the receiving antenna.
- -Increase the separation between the equipment and receiver.
- -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.