

Bluetooth Headphone

BT69

User Manual

SPECIFICATIONS

Bluetooth version: Bluetooth V4.2

Support: HFPV1.2, A2DPV1.3, AVRCPV1.4, HSP1.6, GAVDP1.2, IOP

SNR: 96dB SNR stereo ADC and stereo DAC

Sensitivity: -80dBm<0.1%BER

Transmission distance: 10m

Frequency: 2.402 -2.480GHZ

Transmission power: CLASS2 ,

Audio SNR: \geq 75dB

Audio performance: SBC decoding

Battery capacity: 3.7V/200mAH Li-polymer battery

Charging voltage: DC5V 250mA

Charging time: about 2 hour

Working currency: \leq 40mA

Standby currency: <500uA

Working temperature: -40°C to +85°C

Play time: about 4 hours

Working time: about 3.5 hours

Standby time: about 40 hours

OPERATION GUIDE

Power On: Long press ►|| for 3 seconds, sound prompt.

Power Off : Long press ►|| for 3 seconds, sound prompt.

Answer/Hang up Calls: Single press ►||

Re-dial Last Phone Call: Double press ►||

Play/ Pause Music: Single press ►||

Volume +/-: Long press | ← / → +

Previous/Next Song: Single press | ← / → +

PAIRING

1. Initial Pairing: Bluetooth headset will enter pairing mode automatically, sound prompt. Turn on Bluetooth function on device and select BT69, no PIN code needed. Sound prompt when pairing successfully.

2. Re-Pairing: Long press ►|| for about 3 seconds in power off mode, headset enter pairing mode when red and blue LED indicator lights flash quickly.

3. Bluetooth headset will pairing connected device automatically when power on.

LED INDICATOR LIGHT

1. Charging: Red light keeps on in charging mode, light off when fully charged.
2. Power on: Blue light keeps on.
3. Pairing mode: Green and blue lights flashing alternately.
4. Standby mode: Blue light keeps on.
5. Paired mode: Blue light keeps on.
6. Play mode: Blue light flash every 1 second.

ATTENTION

1. Please charge the Bluetooth headset when sound prompt.
2. The port at the button of headset is for audio input only, please DO NOT connect other headphones.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment

HARMFUL INTERFERENCE TO RADIO COMMUNICATIONS. HOWEVER, THERE IS NO
guarantee that interference will not occur in a particular installatio
If this equipment does cause harmful interference to radio or
television reception, which can be determined by turning the
equipment off and on, the user is encouraged to try to correct the
interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from
that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for he

This device complies with part 15 of the FCC Rules. Operation is
subject to the following two conditions:(1) This device may not cau
harmful interference, and (2) this device must accept any
interference received, including interference that may cause
undesired operation.

Changes or modifications not expressly approved by the party
responsible for compliance could void the user's authority to opera