

The Stealth Elite User's Guide



Pro Ears Amplification & Protection Devices

Improve Hearing amplifying what you want to hear and filtering out noise.

Thank you for choosing the Stealth Elite.

We at Pro Ears strive to provide our customers with quality products at an affordable price. If for any reason you are not satisfied please contact us and we will be happy find a solution.

Please read this User Guide carefully before use. You'll find instructions on the use and care of your electronic ear buds.

* * *

COMPONENTS

- * 1 Pair of Stealth Elite earbuds
- * Stealth Elite MMCX bluetooth lanyard
- * 4 Pairs foam tips (XS,S,M,L)
- * 3 Pairs silicon tips (S,M,L)
- * 3 Pairs of earhooks (S,M,L)
- * Detachable security lanyard
- * 4 x A10 Battery
- * Charging carry case
- * USB-C charging cable

FITTING INSTRUCTIONS





NOTE: ALWAYS TEST FIT EARTIP WITH THE SOUND TURNED OFF

- 1. Select one of the 3 sizes of ear hooks and place the hook on the housing prior to putting the ear tip on the housing. The ear hook should fit securely in the fossa of the outer ear as per the image.
- Select one of the enclosed ear tips based on size of ear canal and intended purpose of use. The foam tips are intended for maximum hearing protection and isolation. The silicone tips are primarily for listening to media or phone calls. You may need to experiment with each size ear tip to find the most comfortable and secure fit.
- Select the proper size ear tip and ear hook to fit your ear and ear canal. Use the largest size that fits comfortably for most protection. The ear tip should form a complete seal blocking out sound. This is critical to achieve the highest NRR rating and protect your hearing.
- Compress the foam tip by rolling between your fingers as much as possible before inserting into the ear canal.
- Hold in place and gently rotate the ear bud until external sound is muffled.

6.

Test with earphone turned off. Clap your hands and listen to the sound level. If the ear bud tips are the correct size and properly inserted outside sound should be significantly muted. If not, repeat steps 1-4 with an alternative size ear tip.

7.

To attach security lanyard ,snap the optional security lanyard in the port above the MMCX connector port on both earbuds.

BATTERY INSTALLATION



A #10 battery is required. Expected battery life is approximately 80 - 100 hours.

Remove the sticker from the battery. To insert battery, open battery compartment by pulling down on the rim of compartment door. The battery is held in place by a small lip on the bottom of the compartment. Place the battery into the compartment so that the (+) sign side of the battery is facing up; when battery is inserted correctly, compartment door will close with ease. The Battery door will not close easily if the battery is not properly inserted.

DO NOT FORCE THE DOOR. A BROKEN DOOR WILL VOID THE WARRANTY!

Please remove the battery when the Stealth Elite is not in use. Any moisture on the battery should be wiped off.

WARNING: Button Cell Batteries are Dangerous if Swallowed

- Keep batteries out of the reach of children.
- · Discard batteries very carefully.
- Never allow children to play with batteries.
- Never change batteries in front of children.
- Never put batteries in your mouth for any reason, as they are slippery and easy to swallow by accident.
- Always check medication before swallowing, as batteries have been confused as medications.

In the event a battery is swallowed call: **The National Button Battery Ingestion Hotline**(202) 625-3333 for counsel or treatment

OPERATING INSTRUCTIONS



NOTE: THE STEALTH ELITE HAS A BUILT-IN "SAFETY"
CIRCUIT WHICH LIMITS THE OUTPUT OF THE
INSTRUMENT TO A MAXIMUM OF 110dB SPL

For the Stealth Elite Ear Buds

Turnina the Unit On and Off

Flip the MODE SWITCH from 0 to I or II to turn on the unit.

When not in use flip the MODE SWITCH back to 0 to conserve battery.

Operatina Control

- 1. Flip the MODE SWITCH to I to use Pass Through sound. In position I hear ambient sound naturally while still providing z compression of loud sounds. Position I is recommended in high wind or situations where echoes are present.
- Flip the MODE SWITCH to II to use Amplification Mode. In position II ambient sounds are fully amplified allowing the wearer to hear faint sounds more clearly.
- 3. Always start with the unit set to 0 or Isolation Mode.

For the Stealth Elite Bluetooth Lanyard

Turning On and Off

- 1. Connect the BLUETOOTH LANYARD to the EARBUDS by gently snapping the MMCX connectors together until you hear a snap.
- 2. Press and hold BLUETOOTH BUTTON for 3 seconds and INDICATOR LIGHT will flash blue.
- 3. The earphone will then enter automatic pairing and the INDICATOR LIGHT will flash alternately red and blue. Enter your Bluetooth settings on your device and connect earphone by choosing Stealth Elite from the list of devices. Once connected the INDICATOR LIGHT will flash slowly blue and your ear buds will be ready to use.

To Make Calls

- 1. Tap BLUETOOTH BUTTON once to pick up or end calls
- 2. Tap BLUETOOTH BUTTON twice to redial last incoming or outgoing number.
- 3. When there is another incoming call during another call, tap BLUETOOTH BUTTON once to end original call and pick up incoming call.. Tap BLUETOOTH BUTTON twice to put original call on hold and receive incoming call. Tap BLUETOOTH BUTTON twice to alternate between the two calls.

For Media

1.Tap BLUETOOTH BUTTON once to play/pause music

- 2.Tap VOLUME UP/DOWN BUTTON once to increase/decrease media volume
- 3. Press and hold VOLUME UP/DOWN BUTTON for 2 seconds t skip to previous/next track
- 4. Press and hold BLUETOOTH BUTTON to activate SIRI/BIXBY/ALEXA etc. platforms.

CARING FOR YOUR STEALTH ELITE

Remember that your Stealth Elite is a quality instrument and should be treated in the same careful manner as any other precision-engineered device.

- Never allow any liquid to enter the Stealth Elite as this may damage the components within the device. If the battery door is closed the unit is water resistant to IPX Rating 5.
- 2. Do not store your device in any location which would expose it to excessive heat (e.g. direct sunlight, heaters, or radiators.)
- 3. Be careful not to drop the device as this may damage its components.
- 4. Never insert any foreign objects into your device; this could result in serious damage to the instrument.
- 5. Never permit solvents to come into contact with your device as this can damage the unit.
- 6. Clean your device by wiping with a damp (not wet) cloth moistened with an antiseptic liquid.
- Remember to clean your ear after showering or swimming before inserting the ear bud.
- 8. Use a qualified battery to guarantee proper functioning.
- 9. Remember to remove the battery while your ear buds are not in use. 10. Do not try to repair or disassemble the Stealth Elite yourself.
- 11. We recommend replacing your foam ear tips periodically as the foam maybe come hard or unsanitary. Use Pro Ears ear tips as not all replacement tips have the same dimensions and may not provide the same attenuation.
- 12. For any other questions about maintenance, please contact Customer Service.

SERVICE AND WARRANTY

Your Stealth Elite is covered by a manufacturer's limited warranty. This covers all manufacturing and material defects. Problems arising from improper handling or repairs made by unauthorized party are not covered and may void the warranty.

 $\label{please contact Customer Service for details of this warranty. \\$

Toll-free customer support 800-891-3660 or www.altusbrands.com

LIMITED WARRANTY

Altus Brands warrants this product to the original purchaser to be free from defects in materials and workmanship, under normal use and conditions for a period of one-year parts/90 days labor from the date of the original purchase. Under this warranty, this unit will be replaced or repaired at our option, without charge for parts or labor, excluding batteries, for a period of 90 days after the purchase. After 90 days, the cost of labor with Shipping/Handling and Insurance of \$29.95 is the customer's responsibility.

This warranty is void if any of the following occur:

- 1. The warranty card was not sent in at the time or purchase
- 2. The unit is not owned by the original purchaser at the time of the warranty claim
- 3. The unit has been tampered with, opened or punctured
- 4. The unit has been immersed in water or other liquids, allowed to be filled with dirt or dust, or otherwise physically abused
- 5. The 12-month limited warranty has expired

This shall be the exclusive written warranty of the original purchaser and neither this warranty or any other warranty, expressed or implied, shall extend beyond the 12-month period listed above. In no event shall Altus Brands, LLC be liable for consequential damages, consequential property damage, or consequential personal injury. (Some states do not allow limitations on implied warranties or exclusions of consequential damages, so that these restrictions may not apply to you). This warranty gives you specific legal rights, and you may have other rights, which vary from state to state.

Record serial # for future reference:

necord Serial # 101 future referen

Request an RMA from Altus Brands. • 6873 Sullivan Road • Grawn, MI 49637 Tel 800.891.3660 Register your product online at: www.Proears.com

Model: Stealth Elite

Warranty Registration

Model: Stealth El

Date of Purchase:

The Stealth Elite is used to reduce harmful loud sounds like gunshot noise. Gunfire is a hazardous exposure noise. Altus Brands carries no implied guarantee for over-exposure to noise. We recommend hearing tests to insure the continued health of your hearing.

FCC STATEMENT

- 1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
- (1) This device may not cause harmful interference.
 (2) This device must accept any interference received, including interference that may
- (2) This device must accept any interference received, including interference that ma cause undesired operation.

 2 Changes or modifications not expressly approved by the party responsible for
- Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

RF WARNING STATEMENT

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction

NOTE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no quarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: Reorient or relocate the receiving antenna. Increase the separation between the equipment and receiver. Connect the equipment on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radiotic kentician for help.