# **FCC Test Report**

Report No.: AGC01824170203FE03

FCC ID : 2AHYV-UNIVERS

**APPLICATION PURPOSE**: Class II Permissive Change

**PRODUCT DESIGNATION** : BTJLABMIC

**BRAND NAME** : JLAB

**MODEL NAME** : See Page 4

**CLIENT** : PEAG, LLC dba JLab Audio

**DATE OF ISSUE** : Mar.27, 2017

STANDARD(S)

TEST PROCEDURE(S) : FCC Part 15 Rules

**REPORT VERSION** : V1.1

Attestation of Global Compliance (Shenzhen) Co., Ltd

# **CAUTION:**

This report shall not be reproduced except in full without the written permission of the test laboratory and shall not be quoted out of context.



Report No.: AGC01824170203FE03 Page 2 of 29

# **Report Revise Record**

Report Version	Revise Time	Issued Date	Valid Version	Notes
V1.0	/	Jan.07, 2017	Valid	Original Report
V1.1	1	Mar.27, 2017	Valid	Revise Report

Note: Owing to the product under testing was identical with the AGC01824161201FE03's product except for the battery. So the test data may refer to the AGC01824161201FE03 except for test data below 1GHz in the report.

# **TABLE OF CONTENTS**

1. VERIFICATION OF CONFORMITY	
2. GENERAL INFORMATION	5
2.1. PRODUCT DESCRIPTION	5
2.2. TABLE OF CARRIER FREQUENCYS	5
3. MEASUREMENT UNCERTAINTY	6
4. DESCRIPTION OF TEST MODES	6
5. SYSTEM TEST CONFIGURATION	7
5.1. CONFIGURATION OF EUT SYSTEM	7
5.2. EQUIPMENT USED IN EUT SYSTEM	7
5.3. SUMMARY OF TEST RESULTS	7
6. TEST FACILITY	8
7 TEST METHODOLOGY	8
8. ALL TEST EQUIPMENT LIST	8
9. RADIATED EMISSION	9
9.1TEST LIMIT	g
9.2. MEASUREMENT PROCEDURE	
9.3. TEST SETUP	12
9.4. TEST RESULT	13
APPENDIX A: PHOTOGRAPHS OF TEST SETUP	17
APPENDIX B: PHOTOGRAPHS OF EUT	18

Page 4 of 29

### 1. VERIFICATION OF CONFORMITY

Applicant	PEAG, LLC dba JLab Audio		
Address	3402 Piazza DOro Way Suite 230 Oceanside, CA, United States, 92056		
Manufacturer	Dongguan Siyoto Electronics Co., Ltd.		
Address Hecheng Industrial District, Dongjiang, Qiaotou Town, Donggua Guangdong, China			
Product Designation	BTJLABMIC		
Brand Name	JLAB		
Test Model	BTJLABMIC		
Series Model	Metal BT, JBuds Pro BT, Metal Plus BT, Metal Mini BT, JBuds Elite BT, Metal Neon BT		
Model difference	All the same except for the appearance and color.		
Date of test	Mar.05, 2017 to Mar.10, 2017		
Deviation	None		
Condition of Test Sample	Normal		
Report Template	AGCRT-US-BR/RF		

We hereby certify that:

The above equipment was tested by Dongguan Precise Testing Service Co., Ltd. The test data, the energy emitted by the sample tested as described in this report is in compliance with the requirements of FCC Rules Part 15.249.

Tested By	Strive Liang	
	Strive Liang(Liang Faqiang)	Mar.10, 2017
Reviewed By	foresto ei	
	Forrest Lei(Lei Yonggang)	Mar.27, 2017
Approved By	Solya Zhang	
-	Solger Zhang(Zhang Hongyi)  Authorized Officer	Mar.27, 2017

Page 5 of 29

# 2. GENERAL INFORMATION

### 2.1. PRODUCT DESCRIPTION

A major technical description of EUT is described as following

Operation Frequency 2.402 GHz to 2.480GHz		
RF Output Power	0.68dBm(Max EIRP Power=Max radiation field-95.2)	
Bluetooth Version	V4.1	
Modulation	GFSK, π /4-DQPSK, 8DPSK	
Number of channels	79	
Hardware Version	HDV3.0_1	
Software Version	HDV3.0_1	
Antenna Designation	Ceramic Antenna	
Antenna Gain	2dBi	
Power Supply	DC 3.7V by battery	

Note: The EUT didn't support BLE.

### 2.2. TABLE OF CARRIER FREQUENCYS

Frequency Band	Channel Number	Frequency
	0	2402MHz
	1	2403MHz
	:	:
	38	2440 MHz
2400~2483.5MHz	39	2441 MHz
	40	2442 MHz
	:	:
	77	2479 MHz
	78	2480 MHz

Page 6 of 29

### 3. MEASUREMENT UNCERTAINTY

The reported uncertainty of measurement y  $\pm U$ , where expended uncertainty U is based on a standard uncertainty multiplied by a coverage factor of k=2, providing a level of confidence of approximately 95 %  $\circ$ 

No.	Item	Uncertainty
1	Conducted Emission Test	±3.18dB
2	All emissions,radiated	±3.91dB
3	Temperature	±0.5°C
4	Humidity	±2%

### 4. DESCRIPTION OF TEST MODES

NO.	TEST MODE DESCRIPTION	
1	BT Link	

Page 7 of 29

### 5. SYSTEM TEST CONFIGURATION

### **5.1. CONFIGURATION OF EUT SYSTEM**

Configure 1: (Normal hopping)

EUT

### **5.2. EQUIPMENT USED IN EUT SYSTEM**

Item	Equipment	Model No.	ID or Specification	Remark
1	lpod	APPLE	A1367	A.E

### **5.3. SUMMARY OF TEST RESULTS**

FCC RULES	DESCRIPTION OF TEST	RESULT	
§15.249(a) §15.209	Radiated Emission	Compliant	

Report No.: AGC01824170203FE03 Page 8 of 29

### 6. TEST FACILITY

Site Dongguan Precise Testing Service Co., Ltd.	
Location  Building D,Baoding Technology Park,Guangming Road2,Dongcheng District, Dongguan, Guangdong, China,	
FCC Registration No.	371540
Description	The test site is constructed and calibrated to meet the FCC requirements in documents ANSI C63.4:2014.

### **7 TEST METHODOLOGY**

All measurements contained in this report were conducted with ANSI C63.10-2013.

### 8. ALL TEST EQUIPMENT LIST

FOR RADIATED EMISSION TEST (BELOW 1GHz)

Radiated Emission Test Site						
Name of Equipment	Manufacturer	Model Number	Serial Number	Last Calibration	Due Calibration	
EMI Test Receiver	ROHDE & SCHWARZBECK	ESCI	101417	July 4, 2016	July 3, 2017	
Trilog Broadband Antenna (25M-1GHz)	SCHWARZBECK	VULB9160	9160-3355	July 4, 2016	July 3, 2017	
Signal Amplifier	SCHWARZBECK	BBV 9475	9745-0013	July 4, 2016	July 3, 2017	
RF Cable	SCHWARZBECK	AK9515E	96221	July 4, 2016	July 3, 2017	
3m Anechoic Chamber	CHENGYU	966	PTS-001	June 6, 2016	June 5, 2017	
Multi-Device Positioning Controller	MAX-FULL	MF-7802	MF780208339	N/A	N/A	
Active loop antenna (9K-30MHz)	SCHWARZBECK	FMZB1519	1519-038	June 6, 2016	June 5, 2017	
Spectrum Analyzer	AGILENT	E4407B	MY46185649	June 6, 2016	June 5, 2017	
Radiation Cable 1	MXT	RS1	R005	June 6, 2016	June 5, 2017	
Radiation Cable 2	MXT	RS1	R006	June 6, 2016	June 5, 2017	

Page 9 of 29

### 9. RADIATED EMISSION

### 9.1TEST LIMIT

#### Standard FCC15.249

Fundamental Frequency	Field Strength of Fundamental	Field Strength of Harmonics			
	(millivolts/meter)	(microvolts/meter)			
900-928MHz	50	500			
2400-2483.5MHz	50	500			
5725-5875MHz	50	500			
24.0-24.25GHz	250	2500			

#### Standard FCC 15.209

Frequency	Distance	Field Strei	ngths Limit				
(MHz)	Meters	μ V/m	dB(μV)/m				
0.009 ~ 0.490	300	2400/F(kHz)					
0.490 ~ 1.705	30	24000/F(kHz)					
1.705 ~ 30	30	30					
30 ~ 88	3	100	40.0				
88 ~ 216	3	150	43.5				
216 ~ 960	3	200	46.0				
960 ~ 1000	3	500	54.0				
Above 1000	3	Other:74.0 dB(μV)/m (Peak) 54.0 dB(μV)/m (Average)					

Remark:

- (1) Emission level dB $\mu$  V = 20 log Emission level  $\mu$  V/m
- (2) The smaller limit shall apply at the cross point between two frequency bands.
- (3) Distance is the distance in meters between the measuring instrument, antenna and the closest point of any part of the device or system.

Report No.: AGC01824170203FE03 Page 10 of 29

#### 9.2. MEASUREMENT PROCEDURE

- 1. The measuring distance of 3m shall be used for measurements. The EUT was placed on the top of a rotating table 0.8 meter above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation(below 1GHz)
- 2. The height of the test antenna shall vary between 1m to 4m.Both horizontal and vertical polarization Of the antenna are set to make the measurement.
- 3. The initial step in collecting radiated emission data is a receive peak detector mode. Pre-scanning the measurement frequency range. Significant peaks are then marked and then Quasi Peak detector mode re-measured.
- 4. All readings are peak unless otherwise stated QP in column of Note. Peak denoted that the Peak reading compliance with the QP limits and then QP Mode measurement didn't perform(Bleow 1GHz)

Report No.: AGC01824170203FE03 Page 11 of 29

The following table is the setting of spectrum analyzer and receiver.


Spectrum Parameter	Setting
Start ~Stop Frequency	9KHz~150KHz/RB 200Hz for QP
Start ~Stop Frequency	150KHz~30MHz/RB 9KHz for QP
Start ~Stop Frequency	30MHz~1000MHz/RB 120KHz for QP

Receiver Parameter	Setting
Start ~Stop Frequency	9KHz~150KHz/RB 200Hz for QP
Start ~Stop Frequency	150KHz~30MHz/RB 9KHz for QP
Start ~Stop Frequency	30MHz~1000MHz/RB 120KHz for QP


Report No.: AGC01824170203FE03 Page 12 of 29

### 9.3. TEST SETUP

# Radiated Emission Test-Setup Frequency Below 30MHz



### RADIATED EMISSION TEST SETUP 30MHz-1000MHz



Page 13 of 29

### 9.4. TEST RESULT


### **BTJLABMIC**

### **RADIATED EMISSION BELOW 30MHz**

No emission found between lowest internal used/generated frequencies to 30MHz.

### **RADIATED EMISSION BELOW 1GHz**

RADIATED EMISSION TEST- (30MHz-1GHz)-LOW CHANNEL-HORIZONTAL



Site: site #1 Polarization: Horizontal Temperature: 22.2
Limit: FCC Class B 3M Radiation Power: Humidity: 54.3 %

EUT: BTJLABMIC Distance:

M/N: BTJLABMIC Mode: BT Link Note:


No.	Mk	Freq.	Reading	Factor	Measurement	Limit	Over	Detector	Antenna Height	Table Degree	Comment
	-	MHz	dBu∀	dB/m	dBu∀/m	dBu√/m	dB		cm	degree	
1		72.0333	4.66	8.28	12.94	40.00	-27.06	peak			
2		141.5500	0.97	14.82	15.79	43.50	-27.71	peak			
3		513.3832	4.61	21.49	26.10	46.00	-19.90	peak			
4		749.4167	0.75	26.61	27.36	46.00	-18.64	peak			
5		869.0500	0.30	27.81	28.11	46.00	-17.89	peak		·	
6	*	957.9667	1.73	29.92	31.65	46.00	-14.35	peak			

Temperature: 22.2

Humidity: 54.3 %

Page 14 of 29

### RADIATED EMISSION TEST- (30MHz-1GHz)-LOW CHANNEL -VERTICAL



Polarization:

Power:

46.00

46.00

46.00

46.00

-26.74

-20.88

-17.76

-13.94

peak

peak

peak

peak

Distance:

Vertical

Site: site #1

Limit: FCC Class B 3M Radiation

Reading

dBu∀

12.79

1.70

0.46

1.32

1.13

2.65

Factor

dB/m

1.84

14.76

18.80

23.80

27.11

29.41

19.26

25.12

28.24

32.06

EUT: BTJLABMIC M/N: BTJLABMIC Mode: BT Link

Freq.

MHz

80.1167

169.0333

359.8000

647.5667

784.9833

928.8667

Note:

Mk No.

> 1 2

3

4

5

6

	Measurement	Limit	Over	Detector	Antenna Height	Table Degree	Comment
	dBuV/m	dBu∀/m	dB		cm	degree	
	14.63	40.00	-25.37	peak			
1	16.46	43.50	-27.04	peak			

# **RESULT: PASS**

Note: 1. Factor=Antenna Factor + Cable loss, Margin=Measurement-Limit.

2. The "Factor" value can be calculated automatically by software of measurement system.

Page 15 of 29


### **JBuds Elite BT**

### **RADIATED EMISSION BELOW 30MHz**

No emission found between lowest internal used/generated frequencies to 30MHz.

### **RADIATED EMISSION BELOW 1GHz**

### RADIATED EMISSION TEST- (30MHz-1GHz)-LOW CHANNEL-HORIZONTAL



Site: site #1 Polarization: Horizontal Temperature: 23.6 Limit: FCC Class B 3M Radiation Power: Humidity: 52.9 %

EUT: BTJLABMIC Distance:


M/N: JBuds Elite BT
Mode: BT Link

Note:

No.	Mk	Freq.	Reading	Factor	Measurement	Limit	Over	Detector	Antenna Height		Comment
	-	MHz	dBu∀	dB/m	dBu∀/m	dBu√/m	dB		cm	degree	
1		76.8833	10.30	3.54	13.84	40.00	-26.16	peak			
2		215.9167	10.24	10.38	20.62	43.50	-22.88	peak			
3		358.1833	10.69	18.79	29.48	46.00	-16.52	peak			
4		453.5667	10.31	20.63	30.94	46.00	-15.06	peak			
5	*	521.4667	10.25	21.71	31.96	46.00	-14.04	peak			
6		962.8167	1.92	29.88	31.80	54.00	-22.20	peak			

Page 16 of 29

### RADIATED EMISSION TEST- (30MHz-1GHz)-LOW CHANNEL -VERTICAL



Site: site #1 Limit: FCC Class B 3M Radiation

EUT: BTJLABMIC M/N: JBuds Elite BT Mode: BT Link

Note:

Polarization: Vertical Temperature: 23.6 Power: Humidity: 52.9 %

Distance:

No.	Mk	Freq.	Reading	Factor	Measurement	Limit	Over	Detector	Antenna Height	Table Degree	Comment
	-	MHz	dBu∀	dB/m	dBu∀/m	dBu∀/m	dB		cm	degree	
1		165.8000	9.62	14.96	24.58	43.50	-18.92	peak			
2		366.2667	6.21	18.85	25.06	46.00	-20.94	peak			
3		468.1167	10.46	20.79	31.25	46.00	-14.75	peak			
4		515.0000	9.19	21.53	30.72	46.00	-15.28	peak			
5		730.0167	2.88	26.05	28.93	46.00	-17.07	peak			
6	*	896.5333	4.04	28.52	32.56	46.00	-13.44	peak			

### **RESULT: PASS**


**Note:** 1. Factor=Antenna Factor + Cable loss, Margin=Measurement-Limit.

2. The "Factor" value can be calculated automatically by software of measurement system.

Report No.: AGC01824170203FE03 Page 17 of 29

# **APPENDIX A: PHOTOGRAPHS OF TEST SETUP**


FCC RADIATED EMISSION TEST SETUP




Page 18 of 29

### **APPENDIX B: PHOTOGRAPHS OF EUT**


TOP VIEW OF EUT



**BOTTOM VIEW OF EUT** 




FRONT VIEW OF EUT




**BACK VIEW OF EUT** 



LEFT VIEW OF EUT




RIGHT VIEW OF EUT




VIEW OF EUT (PORT)




**OPEN VIEW OF EUT** 



**INTERNAL VIEW OF EUT-1** 




**INTERNAL VIEW OF EUT-2** 



Page 23 of 29

### **INTERNAL VIEW OF EUT-3**



SERIES Model

TOP VIEW OF EUT(JBuds Elite BT)



BOTTOM VIEW OF EUT(JBuds Elite BT)



TOP VIEW OF EUT(Metal BT)



# BOTTOM VIEW OF EUT(Metal BT)



TOP VIEW OF EUT(JBuds Pro BT)



BOTTOM VIEW OF EUT(JBuds Pro BT)



TOP VIEW OF EUT(Metal Plus BT)



BOTTOM VIEW OF EUT(Metal Plus BT)



TOP VIEW OF EUT(Metal Mini BT)




BOTTOM VIEW OF EUT(Metal Mini BT)



TOP VIEW OF EUT(Metal Neon BT)



# BOTTOM VIEW OF EUT(Metal Neon BT)



----END OF REPORT----