

www.fulham.com  
**120V**  
**277V**  
 Ph: (223) 599-8001  
 MADE IN CHINA

**FULHAM**  
**WORKHORSE LED™**

RoHS COMPLIANT

UL LISTED E342838

PROGRAMMABLE CONSTANT CURRENT DRIVER  
**MODEL: T1R1UNV210P-60C**  
 SUITABLE FOR LED's USE ONLY  
 SUITABLE FOR DRY OR DAMP LOCATIONS

100% - 1%, 0%

IP65

L BLK  
 N WHT

ANT

INPUT 120-277 VAC  
 WHT (L)  
 ANT

LED DRIVER

R-SET +  
 NTC -

ORG +  
 YLW -

RED +  
 BLUE -

OUTPUT

ANT

ORG +  
 YLW -

RED +  
 BLUE -

INPUT VOLTAGE 120-277VAC, 50/60Hz  
 INPUT CURRENT 0.6A Max.  
 INPUT POWER 72W  
 POWER FACTOR >0.95@Full Load  
 OUTPUT CURRENT 500-2100mA  
 OUTPUT VOLTAGE 10-57VDC  
 OUTPUT POWER 60W Max.  
 U-OUT 60V  
 ta -40°C To 60°C

OUTPUT CHANNELS 1  
 DIMMING WIRELESS  
 THD <20%  
 EFFICIENCY 85% Typical@Full Load  
 RFI/EMI FCC PART 15B  
 OUTPUT TYPE Class 2  
 SOUND RATING A  
 Class P

This device complies with Part 15 of the FCC Rules.  
 FCC ID: 2AJ9LT1R1UNV210P60W  
 See www.fulham.com for installation, operation and maintenance instructions.

Tc, 90°C Max.

**TVILIGHT**

**WARNING:** Install In Accordance With The National And Local Electrical Code. Disconnect Power Before Servicing. Driver Must Be Grounded.

**ATTENTION:** L'installation doit être conforme aux normes du Code National Électrique. Débranchez l'alimentation avant l'entretien. Pilote doivent être mis à la terre.

R-SET / 500mA

