



FCC TEST REPORT

FCC ID: 2AJFC-174M

On Behalf of

Light Speed Vision (Beijing) Co.,Ltd.

Camera

Model No.: QHY174M, QHY174C, QHY178M, QHY178C, QHY163C,
QHY224C, QHY163M, QHY183C, QHY290M, QHY290C

Prepared for : Light Speed Vision (Beijing) Co.,Ltd.

Address : R&D Plaza, Tsinghua Science Park, Shuangqing Road, Haidian
District, Beijing, China

Prepared By : Shenzhen Alpha Product Testing Co., Ltd.

Address : Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China

Report Number : T1861032 02

Date of Receipt : June 13, 2016

Date of Test : June 13-August 30, 2016

Date of Report : September 14, 2016

Version Number : REV0

TABLE OF CONTENTS

<u>Description</u>	<u>Page</u>
1. Summary of standards and results	4
1.1. Description of Standards and Results	4
2. GENERAL INFORMATION	5
2.1. Description of Device (EUT).....	5
2.2. Tested Supporting System Details.....	6
2.3. Block Diagram of connection between EUT and simulators	6
2.4. Test mode Description	7
2.5. Test Facility	7
2.6. Measurement Uncertainty.....	7
3. POWER LINE CONDUCTED Emission test.....	8
3.1. Test Equipment.....	8
3.2. Block Diagram of Test Setup.....	8
3.3. Power Line Conducted Emission Test Limits	8
3.4. Configuration of EUT on Test.....	9
3.5. Operating Condition of EUT	9
3.6. Test Procedure	9
3.7. Conducted Disturbance at Mains Terminals Test Results	10
4. Radiated emission Test	13
4.1. Test Equipment.....	13
4.2. Block Diagram of Test Setup.....	13
4.3. Radiated Emission Limit	14
4.4. Configuration of EUT on Test.....	15
4.5. Operating Condition of EUT	15
4.6. Test Procedure	15
4.7. Radiated Disturbance Test Results	16
5. Photograph.....	21
5.1. Photos of Radiated Emission Test (In Semi Anechoic Chamber).....	21
5.2. Photos of Power Line Conducted Emission Test	22
6. Photos of the EUT	23

TEST REPORT DECLARATION

Applicant : Light Speed Vision (Beijing) Co.,Ltd.
Manufacturer : Light Speed Vision (Beijing) Co.,Ltd.
EUT Description : Camera

(A) Model No. : QHY174M, QHY174C, QHY178M, QHY178C, QHY163C, QHY224C, QHY163M, QHY183C, QHY290M, QHY290C

(B) Trademark :  **QHYCCD**

(C) Ratings Supply : DC 12V


(D) Test Voltage : DC 12V from DC source

Measurement Standard Used:

FCC Rules and Regulations Part 15 Subpart B Class B 2016, ANSI C63.4:2014

The device described above is tested by Shenzhen Alpha Product Testing Co., Ltd. to determine the maximum emission levels emanating from the device and the severe levels of the device can endure and its performance criterion. The test results are contained in this test report and Shenzhen Alpha Product Testing Co., Ltd. is assumed full responsibility for the accuracy and completeness of test. Also, this report shows that the EUT is technically compliant with the FCC Part15 requirements.

This report applies to above tested sample only. This report shall not be reproduced in parts without written approval of Shenzhen Alpha Product Testing Co., Ltd.

Tested by (name + signature).....: Reak Yang
Test Engineer


Approved by (name + signature).....: Simple Guan
Project Manager


Date of issue.....: September 18, 2016

1. SUMMARY OF STANDARDS AND RESULTS

1.1. Description of Standards and Results

The EUT have been tested according to the applicable standards as referenced below:

EMISSION			
Description of Test Item	Standard	Limits	Results
Power Line Conducted Emission Test	FCC Part 15:2016 ANSI C63.4:2014	Class B	P
Radiated Emission Test	FCC Part 15:2016 ANSI C63.4:2014	Class B	P
Note: 1. P is an abbreviation for Pass. 2. F is an abbreviation for Fail. 3. N/A is an abbreviation for Not Applicable.			

2. GENERAL INFORMATION

2.1. Description of Device (EUT)

Description : Camera

Model Number : QHY174M, QHY174C, QHY178M, QHY178C, QHY163C, QHY224C, QHY163M, QHY183C, QHY290M, QHY290C

Diff : There is no difference between all the models, except the appearance color and model name, so this report performs the model QHY174M.

Test Voltage : DC 12V from DC source

AC Adapter : N/A

Highest frequency : 200MHz

Software version : /

Hardware version : /

Trademark :  QHYCCD

Applicant : Light Speed Vision (Beijing) Co.,Ltd.

Address : R&D Plaza, Tsinghua Science Park, Shuangqing Road, Haidian District, Beijing, China

Manufacturer : Light Speed Vision (Beijing) Co.,Ltd.


Address : R&D Plaza, Tsinghua Science Park, Shuangqing Road, Haidian District, Beijing, China

Sample Type : Prototype production

2.2. Tested Supporting System Details

No.	Description	Manufacturer	Model	Serial Number	Certification or DOC
1	Personal Computer	DELL	D11M	CN-0LV772-C088 7-378-H8UR	DOC
2	Monitor	DELL	E2014Hf	CN-011HFV-7287 2-397-CHEM	DOC
3	USB Keyboard	ACER	SK-9625	KBUSB15805000 37E0100	DOC
4	USB Mouse	ACER	MS.11200.014	M-UAY-ACR2	DOC
5.	Printer	HP	HP1020	CNCJ410726	DOC
6.	DC Power	Longwei	TPR-12010D	/	VOC

2.3. Block Diagram of connection between EUT and simulators



Signal Cable Description of the above Support Units					
No.	Port Name	Cable	Length	Shielded (Yes or No)	Detachable (Yes or No)
(a)	USB Port	USB Cable	150CM	Yes(Shielding and foil shields)	Yes
(b)	VGA Port	VGA Cable	120CM	Yes(Shielding)	Yes
(C)	Serial Port	Serial Cable	150CM	Yes(Shielding)	Yes

EUT: Camera

2.4. Test mode Description

No.	Test Mode
※1.	Take Photo
2.	Standby
Note: ※ is worst case mode for, so this report only reflected the worst mode.	

2.5. Test Facility

Shenzhen Alpha Product Testing Co., Ltd.
 Building B, East Area of Nanchang Second, Industrial Zone, Gushu 2nd Road,
 Bao'an, Shenzhen, China

March 25, 2015 File on Federal Communication Commission
 Registration Number: 203110

July 18, 2014 Certificated by IC
 Registration Number: 12135A

2.6. Measurement Uncertainty

(95% confidence levels, k=2)


Test Item	Uncertainty
Uncertainty for Conduction emission test	2.71dB
Uncertainty for Radiation Emission test (<1G)	3.90 dB (Distance: 3m Polarize: V)
	3.92 dB (Distance: 3m Polarize: H)
Uncertainty for Radiation Emission test (>1G)	4.26 dB (Distance: 3m Polarize: V)
	4.28 dB (Distance: 3m Polarize: H)

3. POWER LINE CONDUCTED EMISSION TEST

3.1. Test Equipment

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Test Receiver	Rohde & Schwarz	ESCI	101165	2016.01.17	1 Year
2.	L.I.S.N.#1	Schwarzbeck	NSLK8126	8126466	2016.01.17	1 Year
3.	L.I.S.N.#2	ROHDE&SCHWARZ	ENV216	101043	2016.01.17	1 Year
4.	Pulse Limiter	Schwarzbeck	9516F	9618	2016.01.17	1 Year
5	Cable	Resenberger	SUCOFLEX 104	MY6562/4	2016.01.17	1 Year

3.2. Block Diagram of Test Setup



3.3. Power Line Conducted Emission Test Limits

Frequency	Maximum RF Line Voltage	
	Quasi-Peak Level dB(μV)	Average Level dB(μV)
150kHz ~ 500kHz	66 ~ 56*	56 ~ 46*
500kHz ~ 5MHz	56	46
5MHz ~ 30MHz	60	50

Notes:

1. Emission level=Read level + LISN factor-Preamp factor + Cable loss
2. * Decreasing linearly with logarithm of frequency.
3. The lower limit shall apply at the transition frequencies.

3.4. Configuration of EUT on Test

The following equipment are installed on Power Line Conducted Emission Test to meet the commission requirement and operating regulations in a manner which tends to maximize its emission characteristics in a normal application.

3.5. Operating Condition of EUT

- (1) Setup the EUT as shown as Section 3.2.
- (2) Turn on the power of all equipment.
- (3) Let the EUT work in test mode and 15 minutes before taking the test.

3.6. Test Procedure

- (1) The EUT was placed on a non-metallic table, 80cm above the ground plane. The EUT Power connected to the power mains through a line impedance stabilization network (L.I.S.N. 1#). This provided a 50-ohm coupling impedance for the EUT (Please refer to the block diagram of the test setup and photographs). The other peripheral devices power cord connected to the power mains through a line impedance stabilization network (L.I.S.N.#2). Both sides of power line were checked for maximum conducted interference. In order to find the maximum emission, the relative positions of equipments and all of the interface cables were changed according to ANSI C63.4:2014 on conducted Emission test.
- (2) The frequency range from 150kHz to 30MHz is checked, the bandwidth of test receiver (R&S TEST RECEIVER ESCI) is set at 9kHz.
- (3) The frequency range from 30MHz to 1000MHz was pre-scanned with a Peak detector and all final readings of measurement from Test Receiver are Quasi-Peak and Average values.
- (4) The test results are reported on Section 3.7.


3.7. Conducted Disturbance at Mains Terminals Test Results

EUT	: Camera	Test Date	: 2016.08.29
M/N	: QHY174M	Temperature	: 25°C
Test Engineer	: Reak Yang	Humidity	: 51%
Test Mode	: Communicate with PC		
Test Results	: PASS		
Note: 1. The test results are listed in next pages. 2. This mode is worst case mode, so this report only reflected the worst mode. 3. If the limits for the measurement with the average detector are met when using a receiver with a peak detector, the test unit shall be deemed to meet both limits and the measurement with the average detector and quasi-peak detector need not be carried out. 4. If the limits for the measurement with the average detector are met when using a receiver with a quasi-peak detector, the test unit shall be deemed to meet both limits and the measurement with the average detector need not be carried out.			



Shenzhen Alpha Product Testing Co., Ltd.
 Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: +86-755-29766001 FAX: +86-755-86375565
 Website: <http://www.a-lab.cn> Email: service@a-lab.cn

Data: 11



Condition : FCC PART 15 B QP POL: LINE Temp: 25°C Hum: 51 %


Item	Freq	Read Level	LISN Factor	Preamp Factor	Cable Loss	Level	Limit	Margin	Remark
	MHz	dBuV	dB	dB	dB	dBuV	dBuV	dBuV	
1	0.22	29.23	9.61	-9.52	0.10	48.46	62.88	-14.42	Peak
2	0.46	29.19	9.62	-9.58	0.10	48.49	56.67	-8.18	QP
3	0.46	20.20	9.62	-9.58	0.10	39.50	46.67	-7.17	Average
4	1.01	25.88	9.54	-9.63	0.10	45.15	56.00	-10.85	Peak
5	3.76	20.99	9.67	-9.87	0.12	40.65	56.00	-15.35	Peak
6	5.22	11.16	9.67	-9.94	0.12	30.89	60.00	-29.11	Peak
7	15.72	22.18	9.72	-9.83	0.26	41.99	60.00	-18.01	Peak

Remark: Level = Read Level + LISN Factor - Preamp Factor + Cable Loss



Shenzhen Alpha Product Testing Co., Ltd.
 Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: +86-755-29766001 FAX: +86-755-86375565
 Website: <http://www.a-lab.cn> Email: service@a-lab.cn

Data: 9



Condition : FCC PART 15 B QP POL: NEUTRAL Temp: 25°C Hum: 51 %

Item	Freq MHz	Read Level dBuV	LISN Factor dB	Preamp Factor dB	Cable Loss dB	Level dBuV	Limit dBuV	Margin dBuV	Remark
1	0.21	29.40	9.60	-9.52	0.10	48.62	63.10	-14.48	Peak
2	0.47	28.52	9.61	-9.58	0.10	47.81	56.58	-8.77	QP
3	0.47	21.30	9.61	-9.58	0.10	40.59	46.58	-5.99	Average
4	0.78	25.32	9.60	-9.60	0.10	44.62	56.00	-11.38	Peak
5	3.76	20.06	9.62	-9.87	0.12	39.67	56.00	-16.33	Peak
6	15.72	19.97	9.76	-9.83	0.26	39.82	60.00	-20.18	Peak
7	20.16	18.71	9.68	-9.80	0.35	38.54	60.00	-21.46	Peak

Remark: Level = Read Level + LISN Factor - Preamp Factor + Cable Loss

4. RADIATED EMISSION TEST


4.1. Test Equipment

For frequency range 30MHz~1GHz (At Semi Anechoic Chamber)						
Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1	Test Receiver	Rohde&Schwarz	ESCI	101165	2016.01.17	1 Year
2	Amplifier	HP	HP8347A	2834A00455	2016.01.19	1 Year
3	Bilog Antenna	Schwarzbeck	VULB 9168	9168-438	2016.01.19	2 Year
4	Cable	Resenberger	SUCOFLEX 104	309972/4	2016.01.17	1 Year


For frequency range above 1GHz (At Semi Anechoic Chamber (3m))						
Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1	Spectrum Analyzer	Agilent	E4407B	MY49510055	2016.01.17	1 Year
2	Horn Antenna	Schwarzbeck	BBHA 9120 D	BBHA 9120 D(1201)	2016.01.21	1 Year
3	Amplifier	Agilent	8449B	3008A02664	2016.01.19	1 Year
4	Cable	Resenberger	SUCOFLEX 104	329112/4	2016.01.17	1 Year

4.2. Block Diagram of Test Setup

In Semi Anechoic Chamber (3m) Test Setup Diagram for 30MHz~1000MHz



In Semi Anechoic Chamber (3m) Test Setup Diagram for Above 1GHz



4.3.Radiated Emission Limit

Frequency MHz	Distance (Meters)	Field Strengths Limits dB(μ V)/m
30 ~ 88	3	40.0
88 ~ 216	3	43.5
216 ~ 960	3	46.0
960 ~ 1000	3	54.0
Above 1GHz	3	74(Peak) 54(Average)

Notes:

1. Emission level = Read level + Antenna Factor - Preamp Factor + Cable Loss
2. The smaller limit shall apply at the cross point between two frequency bands.
3. Distance is the distance in meters between the measuring instrument, antenna and the closest point of any part of the device or system.
4. Frequency range of radiated measurements:

Highest frequency generated or used in the device or on which the device operates or tunes (MHz)	Upper frequency of measurement range (MHz)
Below 1.705	30
1.705-108	1000
108-500	2000
500-1000	5000
Above 1000	5th harmonic of the highest frequency or 40 GHz, whichever is lower.

4.4. Configuration of EUT on Test

The following equipment are installed on Radiated Emission Test to meet the commission requirements and operating regulations in a manner that tends to maximize its emission characteristics in normal application.

4.5. Operating Condition of EUT

- (1) Setup the EUT as shown as Section 4.2.
- (2) Turn on the power of all equipment.
- (3) Let the EUT work in test mode and 15 minutes before taking the test.

4.6. Test Procedure

- (1) The EUT was placed on a non-metallic table, 80 cm above the ground plane inside a semi-anechoic chamber. An antenna was located 3m from the EUT on an adjustable mast. A pre-scan was first performed in order to find prominent radiated emissions. For final emissions measurements at each frequency of interest, the EUT were rotated and the antenna height was varied between 1m and 4m in order to maximize the emission. Measurements in both horizontal and vertical polarities were made and the data was recorded. In order to find the maximum emission, the relative positions of equipments and all of the interface cables were changed according to ANSI C63.4:2014 on Radiated Emission test.
- (2) For the radiated emission test above 1GHz:
Place the measurement antenna away from each area of the EUT determined to be a source of emissions at the specified measurement distance, while keeping the measurement antenna aimed at the source of emissions at each frequency of significant emissions, with polarization oriented for maximum response. The measurement antenna may have to be higher or lower than the EUT, depending on the radiation pattern of the emission and staying aimed at the emission source for receiving the maximum signal. The final measurement antenna elevation shall be that which maximizes the emissions. The measurement antenna elevation for maximum emissions shall be restricted to a range of heights of from 1 m to 4 m above the ground or reference ground plane.
- (3) The frequency range from 30MHz to 1000MHz is checked, the bandwidth of test receiver (R&S TEST RECEIVER ESCI) is set at 120kHz.
- (4) The frequency range from above 1GHz is checked, the bandwidth of spectrum analyzer (Analyzer Spectrum Analyzer E4407B) is set at 1MHz.
- (5) The frequency range from 30MHz to 1000MHz was pre-scanned with a peak detector and all final readings of measurement from Test Receiver are Quasi-Peak values, the frequency range from 1GHz to 6GHz was pre-scanned with a peak detector and all final readings of measurement from Spectrum Analyzer are peak and average values checked, all measurement distance is 3m in 3m semi anechoic chamber.
- (6) The test results are reported on Section 4.7.


4.7.Radiated Disturbance Test Results

Frequency Range : 30MHz~1000MHz	
EUT : Camera	Test Date : 2016.08.30
M/N : QHY174M Test Engineer : Reak Yang	Temperature : 24.5°C
Test Mode : Communicate with PC	Humidity : 56%
Test Results : PASS	
Note: 1. The test results are listed in next pages. 2. This mode is worst case mode, so this report only reflected the worst mode. 3. If the limits for the measurement with the quasi-peak detector are met when using a receiver with a peak detector, the test unit shall be deemed to meet both limits and the measurement with the quasi-peak detector need not be carried out.	

Frequency Range : Above 1GHz	
EUT : Camera	Test Date : 2016.08.30
M/N : QHY174M Test Engineer : Reak Yang	Temperature : 24.5°C
Test Mode : Communicate with PC	Humidity : 56%
Test Results : PASS	
Note: 1. The test results are listed in next pages. 2. This mode is worst case mode, so this report only reflected the worst mode. 3. If the limits for the measurement with the average detector are met when using a receiver with a peak detector, the test unit shall be deemed to meet both limits and the measurement with the average detector need not be carried out.	



Shenzhen Alpha Product Testing Co., Ltd.
 Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: +86-755-29766001 FAX: +86-755-86375565
 Website: <http://www.a-lab.cn> Email: service@a-lab.cn




Temp : 24.5°C
 Hum : 56%

Item	Freq	Read	Antenna	Preamp	Cable	Level	Limit	Margin	Remark
		Level	Factor	Factor	Loss	dBuV	dBuV	dBuV	
	MHz	dBuV	dB	dB	dB				
1	74.92	54.74	9.90	30.09	0.25	34.80	40.00	-5.20	Peak
2	199.99	53.30	9.90	28.84	0.43	34.79	43.50	-8.71	Peak
3	300.37	52.20	12.85	28.02	0.64	37.67	46.00	-8.33	Peak
4	375.94	53.68	14.35	27.42	0.96	41.57	46.00	-4.43	Peak
5	526.40	49.72	16.99	27.22	1.00	40.49	46.00	-5.51	Peak
6	601.43	47.23	18.36	25.89	1.07	40.77	46.00	-5.23	Peak

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Alpha Product Testing Co., Ltd.
 Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: +86-755-29766001 FAX: +86-755-86375565
 Website: <http://www.a-lab.cn> Email: service@a-lab.cn



Temp : 24.5c
 Hum : 56%


Item	Freq	Read Level	Antenna Factor	Preamp Factor	Cable Loss	Level	Limit	Margin	Remark
	MHz	dBuV	dB	dB	dB	dBuV	dBuV	dBuV	
1	37.55	50.84	13.73	30.83	0.08	33.82	40.00	-6.18	Peak
2	99.88	53.75	10.15	30.15	0.46	34.21	43.50	-9.29	Peak
3	150.01	50.31	14.16	29.45	0.39	35.41	43.50	-8.09	Peak
4	374.62	51.41	14.32	27.43	1.07	39.37	46.00	-6.63	Peak
5	451.14	49.03	15.99	27.54	1.08	38.56	46.00	-7.44	Peak
6	675.21	42.70	19.40	25.76	1.22	37.56	46.00	-8.44	Peak

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Alpha Product Testing Co., Ltd.
 Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: +86-755-29766001 FAX: +86-755-86375565
 Website: <http://www.a-lab.cn> Email: service@a-lab.cn

Data: 15



Condition : FCC PART 15_18G PEAK POL: VERTICAL

Temp : 24.5c
 Hum : 56%


Item	Freq	Read Level	Antenna Factor	Preamp Factor	Cable Loss	Level	Limit	Margin	Remark
	MHz	dBuV	dB	dB	dB	dBuV	dBuV	dBuV	
	11235.00	50.74	24.58	34.90	2.38	42.80	74.00	-31.20	Peak
	21665.00	46.82	24.75	34.77	3.18	39.98	74.00	-34.02	Peak
	32540.00	46.73	27.67	34.98	4.06	43.48	74.00	-30.52	Peak
	42840.00	45.22	27.94	34.98	4.29	42.47	74.00	-31.53	Peak
	53585.00	46.65	28.74	34.89	4.92	45.42	74.00	-28.58	Peak
	63990.00	45.63	29.66	34.71	5.17	45.75	74.00	-28.25	Peak

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Alpha Product Testing Co., Ltd.
 Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: +86-755-29766001 FAX: +86-755-86375565
 Website: <http://www.a-lab.cn> Email: service@a-lab.cn

Data: 16



Condition : FCC PART 15_18G PEAK POL: HORIZONTAL



Temp : 24.5c
 Hum : 56%

Item	Freq	Read Level	Antenna Factor	Preamp Factor	Cable Loss	Level	Limit	Margin	Remark
	MHz	dBuV	dB	dB	dB	dBuV	dBuV	dBuV	
	11235.00	48.74	24.58	34.90	2.38	40.80	74.00	-33.20	Peak
	21665.00	47.82	24.75	34.77	3.18	40.98	74.00	-33.02	Peak
	32145.00	44.72	27.37	34.95	3.73	40.87	74.00	-33.13	Peak
	42540.00	44.73	27.67	34.98	4.06	41.48	74.00	-32.52	Peak
	53480.00	42.55	28.40	34.91	4.83	40.87	74.00	-33.13	Peak
	64135.00	40.51	29.89	34.64	5.26	41.02	74.00	-32.98	Peak

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss

5. PHOTOGRAPH

5.1. Photos of Radiated Emission Test (In Semi Anechoic Chamber)




5.2.Photos of Power Line Conducted Emission Test




6. PHOTOS OF THE EUT



Full Load




Front View




Rear View




Top View




Bottom View





Left View




Right View




Inside View


**Inside View****Inside View**




Inside View



Inside View



Inside View



Inside View

----END OF REPORT----