


dodocool

Instruction Manual

DA109

dodocool Wireless Stereo
Sports In-Ear Headphone

Overview



EN How to use

Button	Function	Operation
Multifunction button	Power on	When the power is off, press and hold the multifunction button for about 2 seconds.
	Pair	When the power is off, press and hold the multifunction button for about 6 seconds.
	Power off	When the power is on, press and hold the multifunction button for about 5 seconds.
Volume up/down button	Answer a call	When there is an incoming call, press the multifunction button once.
	End a call	During a call, press the multifunction button once.
	Reject a call	When there is an incoming call, press and hold the multifunction button for about 1 second.
	Activate voice control function	Press and hold the multifunction button for about 1 second.
	Recall the last number	Press the multifunction button twice.
	Play the music	When your device is playing the music, press the multifunction button once.
	Pause the music	When your device is playing the music, press the multifunction button once.

Volume up button	Increase the volume	When your device is playing the music, press the volume up button once.
	Previous track	When your device is playing the music, press and hold the volume up button for about 1 second.
	Mute the Microphone	During a call, press and hold the volume up button for about 1 second.
Volume down button	Decrease the volume	When your device is playing the music, press the volume down button once.
	Next track	When your device is playing the music, press and hold the volume down button for about 1 second.
	Call transfer	During a call, press and hold the volume down button for about 1 second.

Specifications

Wireless chipset: CSR8645
Wireless profile: APT-X, A2DP, AVRCP, HSP, HFP
Theoretical range in open field: 10m without obstrucer
Frequency range: 2.4 Ghz
RF power / RF grade: Max 7 dBm / Class II
Battery: 3.7 V, 110 mAh lithium polymer battery
Standby time: 360 hours
Play time: Up to 8 hours
Charging time: 1.5 hours
Mylar thickness: PEEK composites diaphragm 6 μ
Driver diameter: 10 mm (dynamic)
Impedance: 32 Ohms
Output S.P.L: 100 \pm 3 dB SPL
Frequency response: 20 Hz ~ 20,000 Hz
Microphone sensitivity: -42 \pm 3 dB

FCC Notice

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

WARNING: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.



support@dodocool.com www.dodocool.com

FCC ID: 2AJOUA109

Made in China

