

FCC Test Report

Report No.: AGC07811200301FE03

FCC ID : 2AJZYSA307

APPLICATION PURPOSE : Original Equipment

PRODUCT DESIGNATION: Promo Wireless Charger with Phone Stand

BRAND NAME : N/A

MODEL NAME : SA307, IT147

APPLICANT: NINGBO GECEN PROMOTION & GIFT CO.,LTD.

DATE OF ISSUE : Apr. 16, 2020

STANDARD(S)

TEST PROCEDURE(S) : FCC Part 15 Rules

REPORT VERSION : V1.0

Attestation of Global Compliance (Shenzhen) Co., Ltd

CAUTION:

This report shall not be reproduced except in full without the written permission of the test laboratory and shall not be quoted out of context.





Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community, Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China



Page 2 of 30

REPORT REVISE RECORD

Report Version	Revise Time	Issued Date	Valid Version	Notes
V1.0	1	Apr. 16, 2020	Valid	Initial Release








TABLE OF CONTENTS

1. VERIFICATION OF CONFORMITY	4
2. GENERAL INFORMATION	
2.1. PRODUCT DESCRIPTION	5
3. MEASUREMENT UNCERTAINTY	6
4. DESCRIPTION OF TEST MODES	7
5. SYSTEM TEST CONFIGURATION	
5.1. CONFIGURATION OF EUT SYSTEM	
5.2. EQUIPMENT USED IN EUT SYSTEM	
5.3. SUMMARY OF TEST RESULTS	
6. TEST FACILITY	9
7. RADIATED EMISSION	10
7.1TEST LIMIT	
7.2. MEASUREMENT PROCEDURE	
7.3. TEST SETUP	
7.4. TEST RESULT	
8. 20DB BANDWIDTH	16
8.1. MEASUREMENT PROCEDURE	
8.2. TEST SET-UP (BLOCK DIAGRAM OF CONFIGURATION)	16
8.3. MEASUREMENT RESULTS	17
9. FCC LINE CONDUCTED EMISSION TEST	
9.1. LIMITS OF LINE CONDUCTED EMISSION TEST	
9.2. BLOCK DIAGRAM OF LINE CONDUCTED EMISSION TEST	18
9.3. PRELIMINARY PROCEDURE OF LINE CONDUCTED EMISSION TEST	19
9.4. FINAL PROCEDURE OF LINE CONDUCTED EMISSION TEST	
9.5. TEST RESULT OF LINE CONDUCTED EMISSION TEST	
APPENDIX A: PHOTOGRAPHS OF TEST SETUP	22
APPENDIX B: PHOTOGRAPHS OF EUT	C a
APPENDIX B: PHOTOGRAPHS OF EUT	24





Page 4 of 30

1. VERIFICATION OF CONFORMITY

NINGBO GECEN PROMOTION & GIFT CO., LTD.
B106-109, NO.535 QINGSHUIQIAO ROAD, HI-TECH ZONE, NINGBO, CHINA
NINGBO GECEN PROMOTION & GIFT CO.,LTD.
NO. 178, JINMAO ROAD, JIAOCHUAN STREET, ZHENHAI DISTRICT, NINGBO, CHINA
NINGBO GECEN PROMOTION & GIFT CO., LTD.
B106-109, NO.535 QINGSHUIQIAO ROAD, HI-TECH ZONE, NINGBO, CHINA
Promo Wireless Charger with Phone Stand
N/A
SA307
IT147
All the same except for the model name and appearance color
Mar. 27, 2020 to Apr. 16, 2020
No any deviation from the test method
Normal
Pass
AGCRT-US-BR/RF

We hereby certify that:

The above equipment was tested by Attestation of Global Compliance (Shenzhen) Co., Ltd. The test data, data evaluation, test procedures, and equipment configurations shown in this report were made in accordance with the procedures given in ANSI C63.10 (2013) and the energy emitted by the sample EUT tested as described in this report is in compliance with Section 15.207, 15.209, 15.203 of the FCC Part 15, Subpart C Rules. The results of testing in this report apply to the product/system which was tested only.

Reviewed By

Sky Dong
(Project Engineer)

Max. 2hang
(Reviewer)

Apr. 16, 2020

Forrest Lei
(Authorized Officer)

Apr. 16, 2020



 $Attestation\ of\ Global\ Compliance (Shenzhen) Co., Ltd.$

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community, Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China



Page 5 of 30

2. GENERAL INFORMATION

2.1. PRODUCT DESCRIPTION

A major technical description of EUT is described as following

A major technical description of EOT is described as following			
116.9kHz			
54.09dBuV/m(PK)@3m			
FSK			
1			
0dBi			
Integrated Antenna (Met 15.203 Antenna requirement)			
V4			
V1.0			
DC 5V by adapter			





Page 6 of 30

3. MEASUREMENT UNCERTAINTY

The uncertainty is calculated using the methods suggested in the "Guide to the Expression of Uncertainty in measurement" (GUM) published by CISPR and ANSI.

- Uncertainty of Conducted Emission, Uc = ±3.2 dB
- Uncertainty of Radiated Emission below 1GHz, Uc = ±3.9 dB
- Uncertainty of Radiated Emission above 1GHz, Uc = ±4.8 dB



Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China Tel: +86-755 2523 4088 E-mail: agc@agc-cert.com Service Hotline:400 089 2118



Page 7 of 30

4. DESCRIPTION OF TEST MODES

NO.	TEST MODE DESCRIPTION		
1		Wireless charging Mode(Full load)	
2		Wireless charging Mode(half load)	10
3	2.0	Wireless charging Mode(Null load)	

Note:

1. The mode 1 was the worst case and only the data of the worst case record in this report.



Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,




Page 8 of 30

5. SYSTEM TEST CONFIGURATION

5.1. CONFIGURATION OF EUT SYSTEM

Configure:



5.2. EQUIPMENT USED IN EUT SYSTEM

Item	Equipment	Model No.	ID or Specification	Remark
1	Promo Wireless Charger with Phone Stand	SA307	2AJZYSA307	EUT
2	Adapter	DYS618-19094W-1	DC 5V	AE
3	Wireless Load	N/A	5W	AE

5.3. SUMMARY OF TEST RESULTS

FCC RULES	DESCRIPTION OF TEST	RESULT
§15.209	Radiated Emission	Compliant
§15.215	20dB bandwidth	Compliant
§15.207	Conducted Emission	Compliant



Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,



Page 9 of 30

6. TEST FACILITY

Test Site Attestation of Global Compliance (Shenzhen) Co., Ltd	
Location	1-2/F, Building 19, Junfeng Industrial Park, Chongqing Road, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China
Designation Number CN1259	
FCC Test Firm Registration Number	975832
A2LA Cert. No.	5054.02
Description	Attestation of Global Compliance(Shenzhen) Co., Ltd is accredited by A2LA

TEST EQUIPMENT OF CONDUCTED EMISSION TEST

Equipment	Manufacturer	Model	S/N	Cal. Date	Cal. Due
TEST RECEIVER	R&S	ESCI	10096	Jun. 12, 2019	Jun. 11, 2020
LISN	R&S	ESH2-Z5	100086	Aug. 26, 2019	Aug. 25, 2020
Test software	R&S	ES-K1(Ver.V1.71)	N/A	N/A	N/A

TEST EQUIPMENT OF RADIATED EMISSION TEST

Equipment	Manufacturer	Model	S/N	Cal. Date	Cal. Due
TEST RECEIVER	R&S	ESCI	10096	Jun. 12, 2019	Jun. 11, 2020
EXA Signal Analyzer	Aglient	N9010A	MY53470504	Dec. 12, 2019	Dec. 11, 2020
Active loop antenna (9K-30MHz)	ZHINAN	ZN30900C	18051	Jun. 14, 2018	Jun. 13, 2020
ANTENNA	SCHWARZBECK	VULB9168	D69250	Jan. 09, 2019	Jan. 08, 2021
Test software	FARA	EZ_EMC (Ver.RA-03A)	N/A	N/A	N/A



Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,



Page 10 of 30

7. RADIATED EMISSION

7.1TEST LIMIT

Standard FCC 15.209

Frequency	Distance	Field	Field Strengths Limit		
(MHz)	Meters	μ V/m	dB(μV)/m		
0.009 ~ 0.490	300	2400/F(kHz)	GY 2G 2		
0.490 ~ 1.705	30	24000/F(kHz)			
1.705 ~ 30	30	30	0		
30 ~ 88	3	100	40.0		
88 ~ 216	3	150	43.5		
216 ~ 960	3	200	46.0		
960 ~ 1000	3	500	54.0		
Above 1000	3	Other:74.0 dB(µV)/m	ı (Peak) 54.0 dB(μV)/m (Average)		

Remark:

- (1) Emission level dB μ V = 20 log Emission level μ V/m
- (2) The smaller limit shall apply at the cross point between two frequency bands.
- (3) Distance is the distance in meters between the measuring instrument, antenna and the closest point of any part of the device or system.



Page 11 of 30

7.2. MEASUREMENT PROCEDURE


- The EUT was placed on the top of the turntable 0.8 or 1.5 meter above ground. The phase center of the receiving antenna mounted on the top of a height-variable antenna tower was placed 3 meters far away from the turntable.
- 2. Power on the EUT and all the supporting units. The turntable was rotated by 360 degrees to determine the position of the highest radiation.
- 3. The height of the broadband receiving antenna was varied between one meter and four meters above ground to find the maximum emissions field strength of both horizontal and vertical polarization.
- 4. For each suspected emissions, the antenna tower was scan (from 1 M to 4 M) and then the turntable was rotated (from 0 degree to 360 degrees) to find the maximum reading.
- 5. Set the test-receiver system to Peak or CISPR quasi-peak Detect Function with specified bandwidth under Maximum Hold Mode.
- 6. In case the emission is lower than 30MHz, loop antenna has to be used for measurement and the recorded data should be QP measured by receiver. High Low scan is not required in this case.

The following table is the setting of spectrum analyzer and receiver.

Spectrum Parameter	Setting		
Start ~Stop Frequency	9KHz~150KHz/RB 200Hz for QP		
Start ~Stop Frequency	150KHz~30MHz/RB 9KHz for QP		
Start ~Stop Frequency	30MHz~1000MHz/RB 120KHz for QP		

Receiver Parameter	Setting
Start ~Stop Frequency	9KHz~150KHz/RB 200Hz for QP
Start ~Stop Frequency	150KHz~30MHz/RB 9KHz for QP
Start ~Stop Frequency	30MHz~1000MHz/RB 120KHz for QP









7.3. TEST SETUP

Radiated Emission Test-Setup Frequency Below 30MHz



RADIATED EMISSION TEST SETUP 30MHz-1000MHz





 $Attestation\ of\ Global\ Compliance (Shenzhen) Co., Ltd.$

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,



Page 13 of 30

7.4. TEST RESULT

RADIATED EMISSION BELOW 30MHZ

	Frequency MHz	Polarization	Reading dB(uV) PK	Factor dB (1/m)	Level dB(uV/m) PK	Limit dB(uV/m) PK	Margin dB	Pass/Fail
Ī	0.1169	Face	43.69	10.40	54.09	100.53	-46.44	Pass
Γ	0.1169	Side	35.94	10.40	46.34	100.53	-54.19	Pass

Note1: No other emissions found between lowest internal used/generated frequencies to 30MHz. The peak level of the emission is less than the average limit, so the average level shall be less than the limit without test.

Note 2: Level(dBuV/m)=Reading(dBuV)+Factor(dB/m)

Factor(dB/m)=Antenna Factor(dB/m)+Cable loss(dB)+Attenuation(dB)for Attenuator

Margin=Level-Limit

Limit(dBuV/m)=20log(2400/F(kHz))+40log(300/3)=100.53 dBuV/m.






Page 14 of 30

RADIATED EMISSION 30MHz-1GHz

EUT:	Promo Wireless Charger with Phone Stand	Model Name. :	SA307
Temperature:	20 ℃	Relative Humidtity:	48%
Pressure:	1010 hPa	Test Voltage :	DC19V
Test Mode :	Mode 1	Polarization:	Horizontal



No.	Mk	Freq.	Reading	Factor	Measurement	Limit	Over	Detector	Antenna Height	Table Degree	Comment
	•	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		cm	degree	
1	*	141.5500	17.93	19.23	37.16	43.50	-6.34	peak			
2		162.5667	16.77	18.93	35.70	43.50	-7.80	peak			
3		337.1666	10.10	20.77	30.87	46.00	-15.13	peak			
4		626.5500	3.26	27.27	30.53	46.00	-15.47	peak			
5		802.7667	2.73	30.45	33.18	46.00	-12.82	peak			
6		927.2500	3.30	31.93	35.23	46.00	-10.77	peak			

RESULT: PASS



Attestation of Global Compliance(Shenzhen)Co.,Ltd.


Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,

Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China
Tel: +86-755 2523 4088 E-mail:agc@agc-cert.com Service Hotline:400 089 2118



Page 15 of 30

FUI.	Promo Wireless Charger with Phone Stand	Model Name. :	SA307
Temperature:	20 ℃	Relative Humidtity:	48%
Pressure:	1010 hPa	Test Voltage :	DC19V
Test Mode :	Mode 1	Polarization :	Vertical



	No.	Mk	Freq.	Reading	Factor	Measurement	Limit	Over	Detector	Antenna Height	Table Degree	Comment
		•	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		cm	degree	
	1	*	31.6167	18.20	18.22	36.42	40.00	-3.58	peak			
I	2		139.9333	17.25	19.23	36.48	43.50	-7.02	peak			
	3		249.8667	12.99	18.49	31.48	46.00	-14.52	peak			
	4		453.5667	6.60	24.06	30.66	46.00	-15.34	peak			
	5		739.7167	1.87	29.05	30.92	46.00	-15.08	peak			
	6		943.4167	2.31	32.07	34.38	46.00	-11.62	peak			

RESULT: PASS

Note:

Factor=Antenna Factor + Cable loss, Margin=Result-Limit.

The "Factor" value can be calculated automatically by software of measurement system.



Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,

Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China Tel: +86-755 2523 4088 E-mail: agc@agc-cert.com Service Hotline:400 089 2118




Page 16 of 30

8. 20DB BANDWIDTH

8.1. MEASUREMENT PROCEDURE

- 1. The EUT was placed on the top of the turntable 0.8 meter above ground. The phase center of the receiving antenna mounted on the top of a height-variable antenna tower was placed 3 meters far away from the turntable.
- 2, Set the EUT Work on operation frequency.
- 3. Set Span = approximately 2 to 5 times the 20 dB bandwidth, centered on a channel
 The nominal IF filter bandwidth (3 dB RBW) shall be in the range of 1% to 5% of the OBW and video
 bandwidth (VBW) shall be approximately three times RBW; Sweep = auto; Detector function = peak
- 4. Set SPA Trace 1 Max hold, then View.

8.2. TEST SET-UP (BLOCK DIAGRAM OF CONFIGURATION)





 $Attestation\ of\ Global\ Compliance (Shenzhen) Co., Ltd.$

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community, Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China

Tel: +86-755 2523 4088 E-mail: agc@agc-cert.com Service Hotline:400 089 2118



Page 17 of 30

8.3. MEASUREMENT RESULTS

TEST ITEM	20DB BANDWIDTH	70	~GC	-6	©	
TEST MODULATION	FSK	8		70	10°C	0

Test Data (Hz)	Criteria	
Operate Channel	836	PASS

TEST PLOT OF BANDWIDTH





Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,

Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China Tel: +86-755 2523 4088 E-mail: agc@agc-cert.com Service Hotline:400 089 2118



Page 18 of 30

9. FCC LINE CONDUCTED EMISSION TEST


9.1. LIMITS OF LINE CONDUCTED EMISSION TEST

F	Maximum RF Line Voltage			
Frequency	Q.P.(dBuV)	Average(dBuV)		
150kHz~500kHz	66-56	56-46		
500kHz~5MHz	56	46		
5MHz~30MHz	60	50		

Note:

- 1. The lower limit shall apply at the transition frequency.
- 2. The limit decreases linearly with the logarithm of the frequency in the range 0.15 MHz to 0.50MHz.

9.2. BLOCK DIAGRAM OF LINE CONDUCTED EMISSION TEST





Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,

Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China Tel: +86-755 2523 4088 E-mail: agc@agc-cert.com Service Hotline:400 089 2118



Page 19 of 30

9.3. PRELIMINARY PROCEDURE OF LINE CONDUCTED EMISSION TEST

- 1. The equipment was set up as per the test configuration to simulate typical actual usage per the user's manual. When the EUT is a tabletop system, a wooden table with a height of 0.8 meters is used and is placed on the ground plane as per ANSI C63.10 (see Test Facility for the dimensions of the ground plane used). When the EUT is a floor-standing equipment, it is placed on the ground plane which has a 3-12 mm non-conductive covering to insulate the EUT from the ground plane.
- 2. Support equipment, if needed, was placed as per ANSI C63.10.
- 3. All I/O cables were positioned to simulate typical actual usage as per ANSI C63.10.
- 4. All support equipments received AC120V/60Hz power from a LISN, if any.
- 5. The EUT received charging voltage by adapter which received 120V/60Hzpower by a LISN..
- 6. The test program was started. Emissions were measured on each current carrying line of the EUT using a spectrum Analyzer / Receiver connected to the LISN powering the EUT. The LISN has two monitoring points: Line 1 (Hot Side) and Line 2 (Neutral Side). Two scans were taken: one with Line 1 connected to Analyzer / Receiver and Line 2 connected to a 50 ohm load; the second scan had Line 1 connected to a 50 ohm load and Line 2 connected to the Analyzer / Receiver.
- 7. Analyzer / Receiver scanned from 150 kHz to 30MHz for emissions in each of the test modes.
- 8. During the above scans, the emissions were maximized by cable manipulation.
- 9. The test mode(s) were scanned during the preliminary test.

Then, the EUT configuration and cable configuration of the above highest emission level were recorded for reference of final testing.

9.4. FINAL PROCEDURE OF LINE CONDUCTED EMISSION TEST

- 1. EUT and support equipment was set up on the test bench as per step 2 of the preliminary test.
- 2. A scan was taken on both power lines, Line 1 and Line 2, recording at least the six highest emissions. Emission frequency and amplitude were recorded into a computer in which correction factors were used to calculate the emission level and compare reading to the applicable limit. If EUT emission level was less –2dB to the A.V. limit in Peak mode, then the emission signal was re-checked using Q.P and Average detector.
- 3. The test data of the worst case condition(s) was reported on the Summary Data page.




Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community, Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China



9.5. TEST RESULT OF LINE CONDUCTED EMISSION TEST

LINE CONDUCTED EMISSION TEST-L



MEASUREMENT RESULT:

2020/4/1 2 Frequenc MF	cy Level	Transd dB	Limit dBµV	Margin dB	Detector	Line	PE
0.63000	00 43.40	11.3	56	12.6	QP	Ll	FLO
0.95000	00 41.20	11.3	56	14.8	QP	L1	FLO
1.58600	00 41.60	11.3	56	14.4	QP	L1	FLO
2.15800	00 40.90	11.3	56	15.1	QP	L1	FLO
2.81000	00 40.40	11.4	56	15.6	QP	L1	FLO
4.71400	00 38.70	11.4	56	17.3	QP	Ll	FLO

MEASUREMENT RESULT: "agc fin2"

2020/4/1 22 Frequency MHz		Transd dB	Limit dBµV	Margin dB	Detector	Line	PE
0.526000	30.30	11.3	46	15.7	AV	Ll	FLO
0.630000	33.40	11.3	46	12.6	AV	L1	FLO
1.002000	31.30	11.3	46	14.7	AV	L1	FLO
1.530000	31.00	11.3	46	15.0	AV	Ll	FLO
2.110000	30.30	11.3	46	15.7	AV	L1	FLO
2.754000	30.10	11.4	46	15.9	AV	L1	FLO

RESULT: PASS




Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community, Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China Tel: +86-755 2523 4088 E-mail: agc@agc-cert.com Service

Service Hotline: 400 089 2118



LINE CONDUCTED EMISSION TEST-N



MEASUREMENT RESULT:

2020/4/1 22:49 Frequency MHz		Transd dB	Limit dBµV	Margin dB	Detector	Line	PE
0.634000	38.60	11.3	56	17.4	QP	N	FLO
0.902000	36.90	11.3	56	19.1	QP	N	FLO
1.594000	37.40	11.3	56	18.6	QP	N	FLO
2.154000	36.90	11.3	56	19.1	QP	N	FLO
2.694000	36.50	11.4	56	19.5	QP	N	FLO
4.770000	35.10	11.4	56	20.9	QP	N	FLO

MEASUREMENT RESULT: "agc fin2"


2020/4/1 22:49 Frequency MHz		Transd dB	Limit dBµV	Margin dB	Detector	Line	PE
0.530000	26.20	11.3	46	19.8	AV	N	FLO
0.634000	27.50	11.3	46	18.5	AV	N	FLO
0.954000	27.10	11.3	46	18.9	AV	N	FLO
1.562000	26.30	11.3	46	19.7	AV	N	FLO
2.222000	27.70	11.3	46	18.3	AV	N	FLO
2.754000	27.80	11.4	46	18.2	AV	N	FLO

RESULT: PASS



Attestation of Global Compliance(Shenzhen)Co.,Ltd.


Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community, Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China
Tel: +86-755 2523 4088 E-mail:agc@agc-cert.com Service Hotline:400 089 2118






APPENDIX A: PHOTOGRAPHS OF TEST SETUP

FCC RADIATED EMISSION TEST SETUP BELOW 1GHZ








Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,





Page 23 of 30


FCC LINE CONDUCTED EMISSION TEST SETUP





Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,






APPENDIX B: PHOTOGRAPHS OF EUT

ALL VIEW OF EUT




TOP VIEW OF EUT






Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,






BOTTOM VIEW OF EUT



FRONT VIEW OF EUT






Attestation of Global Compliance(Shenzhen)Co.,Ltd.


Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,



BACK VIEW OF EUT




LEFT VIEW OF EUT






Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,





RIGHT VIEW OF EUT



VIEW OF EUT(PORT)






Attestation of Global Compliance(Shenzhen)Co.,Ltd.


Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,

Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China
Tel: +86-755 2523 4088 E-mail:agc@agc-cert.com Service Hotline:400 089 2118






OPEN VIEW OF EUT-1



OPEN VIEW OF EUT-2






Attestation of Global Compliance(Shenzhen)Co.,Ltd.


Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,

Hangcheng Street, Bao'an District, Shenzhen, Guangdong, China
Tel: +86-755 2523 4088 E-mail:agc@agc-cert.com Service Hotline:400 089 2118






OPEN VIEW OF EUT-3



INTERNAL VIEW OF EUT-1






Attestation of Global Compliance(Shenzhen)Co.,Ltd.


Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,



INTERNAL VIEW OF EUT-2



INTERNAL VIEW OF EUT-3



----END OF REPORT----



Attestation of Global Compliance(Shenzhen)Co.,Ltd.

Add: 2/F., Building 2, Sanwei Chaxi Industrial Park, Sanwei Community,