

Main item name	Main part specification	Level	Unit name	Unit specification	Package method	unit	Composition	Location number
Aqara\Door and Window Sensor T1	White\zigbee3.0	1	Packaging material\Aqara\door and window sensor T1	White		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara door and window sensor T1 box	Zigbee3.0/77*70*30mm/350g Huaxia Sun White Card Matte Film/V1		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara door and window sensor T1	Zigbee3.0/74*68*23mm/350g white card over dumb rubber / V1		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara door and window sensor T1 manual	Zigbee3.0/65*65mm/105g space shuttle powder / V1		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Packaging seal	Φ20mm/packing box sealing paste, transparent (sticky)		PCS	2	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Outer box red fragile labeling - Chinese and English version	General / 148.5 * 82.5mm / 80g coated paper / printing die cutting		PCS	2	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Zigbee3.0 variable barcode - YJ	24.5*11mm/80g non-transportable coated paper adhesive/V1		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Zigbee3.0 Install Code Sticker - YJ	15*15mm/80g non-transportable coated paper adhesive/V1		PCS	3	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Lithium metal fireproof label (UN3091)	UN3091, red border 5.5mm/120*110mm/80g semi-high gloss coated paper with matte film adhesive / stickers outside box / V2		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara universal outer box (Zigbee3.0)	Zigbee3.0/455*363*363mm/K5K5K/V1		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara Universal Flat Card (Zigbee3.0)	Zigbee3.0/417*325mm/B3B/V1		PCS	5	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara wireless switch T1 knife card	417*325*62mm/B3B/General temperature and humidity sensor, door and window sensor, water immersion sensor/Zigbee3.0/V1		PCS	5	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Door and window sensor body adhesive tape (own brand)	37.80mm*18.85mm*1.0mm\Germany Romance Sticker (White)\V1\LM8729		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Door and window sensor with body adhesive tape (own brand)	21.8*7.8*1.0mm\Germany Romance Sticker (White)\V1\LM8729		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Door and window sensor body adhesive tape (own brand)	Aqara\37.8*18.85*1.0mm \Germany Romance stickers (white)\V1\LM8729		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Door and window sensor with body adhesive tape (own brand)	Aqara\21.8*7.8*1.0mm \Germany Romance stickers (white)\V1\LM8729		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara universal four-week EPE (Zigbee3.0)	Zigbee3.0/383*346*13mm/20KG white EPE/V1		PCS	4	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Aqara General Up and Down EPE (Zigbee3.0)	Zigbee3.0/417*325*13mm/20KG white EPE/V1		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	1	Bare metal \Aqara\door and window sensor T1	White		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	Structural parts\Aqara\door and window sensor T1	White		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	3	Window magnetic guide column\transparent PC	2mm*3.6mm		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	3	Aqara door and window body battery bracket	PC+ABS\anti-UV\grey\texture\38mm*20mm*6.2mm\V0		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	3	Aqara door and window body side button	PC+ABS\anti-UV\white\texture\7mm*2.9mm*3.4mm\V0		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	3	Aqara door and window sub-body cover	PC+ABS\anti-UV\white\texture\25mm*11mm*6mm\V0		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	3	Aqara door and window sub-body under cover	PC+ABS\anti-UV\grey\pattern\25.2mm*11.2mm*5.9mm\V0		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	3	Aqara door and window sensor T1-body cover	PC+ABS\anti-UV\white\pattern\41mm*22mm*7.5mm\V0		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	3	Aqara door and window sensor T1-main battery cover	PC+ABS\0 anti-UV\grey\texture\41.2mm*22.2mm*3.5mm\V0		PCS	1	
Aqara\Door and Window Sensor T1	White\zigbee3.0	2	PCBA\door and window sensor T1\LM18-DW	Aqara\door and window sensor T1\LM18-DW		PCS	1	

Aqara\Door and Window Sensor T	White\zigbee3.0	3	PCB\door and window sensor T1\LM18-DW	door and window sensor T1\LM18-DW\V1.3\4L\16.1*34.56*1mm\FR4\Matt Black\Non-Pb Plating Tin	PCS		1	
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Resistor\Yageo:RC0402JR-0720ML	20MΩ\1/16W\±5%\SMD0402	PCS		1	R7
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Resistor\Yageo:RC0201JR-0743KL	43K\±5%\1\20W\SMD0201	PCS		3	R10,R12,R13
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Resistor\Yageo:RC0201JR-070RL	0R\±5%\1\20W\SMD0201	PCS		1	R11
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Resistor\Yageo:RC0201JR-071K5L	1.5kΩ\±5%\1\20W\SMD0201	PCS		1	R6
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Resistor\YAGEO:RC0201JR-071ML	1MΩ\1/20W\±5%\SMD0201	PCS		2	R3,R9
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Inductor\Sunlord : MPH201210S4R7MT	4.7uH\±20%\0.250Ω\230mA\SMD0805	PCS		1	L1
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Inductor\Sunlord:SDCL0603Q3N2ST02B03	3.2nH\±0.3nH\450mA\SMD0201	PCS		1	L3
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\AVX:TAJC227K006RNJ	220uF\6.3V\±10%\CAP TANT\SMD6032	PCS		1	C17
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\AVX:TAJC227M006RNJ	220uF\6.3V\±20%\CAP TANT\SMD6032\AVX:TAJC227M006RNJ	PCS		1	C17
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\XINGRI:XRCA45227K006CT	220uF\6.3V\±10%\CAP TANT\SMD6032	PCS		1	C17
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\AVX:TAJC227K006RNJ	220uF\6.3V\±10%\CAP TANT\SMD6032	PCS		1	C17
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0603MRX5R6BB106	10uF\10V\±20%\X5R\SMD0603	PCS		2	C5,C8
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201KRX5R5BB104	0.1uF\6.3V\±10%\X5R\SMD0201	PCS		5	C6,C9,C15,C16,C20
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201JRNPO9BN470	47pF\50V\±5%\NPO\SMD0201	PCS		3	C7,C10,C18
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201CRNPO9BN1R8	1.8pF\50V\±0.25pF\NPO\SMD0201	PCS		1	C13A
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201CRNPO9BN3R3	3.3pF\50V\±0.25pF\NPO\SMD0201	PCS		1	L2
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201CRNPO9BN4R7	4.7pF\50V\±0.25pF\NPO\SMD0201	PCS		2	C1,C2
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201CRNPO9BN2R0	2.0pF\50V\±0.25pF\NPO\SMD0201	PCS		2	C1,C2
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201JRNPO9BN100	10pF\50V\±5%\NPO\SMD0201	PCS		2	C1,C2
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201BRNPO9BNR30	0.3pF\50V\±0.1pF\NPO\SMD0201	PCS		1	C12A
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Capacitor\Yageo:CC0201KRX5R6BB103	10nF\10V\±10%\X5R\SMD0201	PCS		1	C19
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Crystal\32MHz,CL 9pF\TXC:7M32000044	SEAM SEALINGE,SR50Ω,-40-85°C,4pins,L*W3.2*2.5mm,XTAL3.2*2.5	PCS		1	Y1
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Crystal\32MHz,CL9pF\Murata:XRCGB32M000F2P41R0	ESR 70Ω,-30-85°C,4pins,XTAL 2.0x1.6x0.65	PCS		1	Y1
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Crystal\32MHz,CL 12pF \Hosonic:E3SB32.0000F12G11MGR	ESR 40Ω, -30-85 °C, 4pins,XTAL_3.2x2.5x0.7	PCS		1	Y1
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Reed Sensor\OKI:RES08-H24B	SENSOR REED-SWITCH SPST-NO\10 to 15AT,200V,0.5A\SMD_2.2x14mm	PCS		1	S1
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Reed Sensor\Standex-Meder Electronics : MK23-66-B-2	Reed Switch,10~15AT\Standex-MederElect.:MK23-66-B-2	PCS		1	S1
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Reed Sensor	REED-SW SPST-NO\MKA14103\>=24mm@D6x20mm N40 NdFeB\SMD2.3x14mm	PCS		1	S1

Aqara\Door and Window Sensor T	White\zigbee3.0	3	LED indicator	Blue\Vmin2.5V@5mA\SMD0603\EVERLIGHT:19-217/BHC-ZL1M2RY/3T	PCS	1	D2
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Switch\SMD 4.6*2.3*1.8mm SPST\250gf\CKC Electronics:112	Side SMD 4pin with Registration Mast,30000 Cycles,50mA/12V	PCS	1	S2
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Magnet\HONGDA:20150413-N40	magnet\NdFeB N40,Size 6*20,Dia x L_6x20mmG156:G156:G171	PCS	1	
Aqara\Door and Window Sensor T	White\zigbee3.0	3	magnet	NdFeB/46mm*20mm/nickel plating	PCS	1	
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Magnet\Thousands of electroacoustic: R	NdFeB N40,Size 6*20\R	PCS	1	
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Battery\Panasonic: CR1632	CR1632 Lithium Battery, 3V, 120mAh,Dia*H 16*3.2mm	PCS	1	
Aqara\Door and Window Sensor T	White\zigbee3.0	3	Battery\Panasonic: CR1632/BN/JHZ	CR1632 Lithium Battery, 3V, 120mAh,Dia*H 16*3.2mm	PCS	1	
Aqara\Door and Window Sensor T	White\zigbee3.0	3	SMD CR2032 metal negative shrapnel	SMD CR2032 Battery Neg Poda Contract Spring0.2mm\LMSA,LMTHS	PCS	1	J2
Aqara\Door and Window Sensor T	White\zigbee3.0	3	LMWD Battery Shrapnel Positive\CR1632 Battery Positive To	T=0.2mm,Phosphor Copper Base,Pinchbeck(Cu-Sn) Plating,CR1632	PCS	1	J1
Aqara\Door and Window Sensor T	White\zigbee3.0	3	PCB_IC\Aqara\Door and window sensor T1\LM18-DW	Firmware\Aqara\door and window sensor T1\LM18-DW\JN518X Chip	PCS	1	U1
Aqara\Door and Window Sensor T	White\zigbee3.0	4	IC\MCU2.4GZIGBEE\NXP:JN5189HN	Cortex-M4\32Bit\32MHz\640kB Flash\152kB\128kB\Tx Power 10dBm,Rx Sensitivity:-100dBm\Tx Current: 7.4mA@0dBm,Rx Current:4.3mA\HVQFN40\NO-NTAG	PCS	1	U1