



**DONGGUAN LINPA ACOUSTIC TECHNOLOGY CO., LTD**

Application  
For  
Certification

**FCC ID: 2AKZ8-LE34**

**Sports Headphones With Bluetooth**

**Model: LEB34**  
**Additional Model: LE34**

**Brand name: LINPA WORLD for M/N: LEB34;**  
**BAUHN for M/N: LE34;**

2.4GHz Transceiver

Report No.: 170217097GZU-001

We hereby certify that the sample of the above item is considered to comply with the requirements of FCC Part 15, Subpart C for Intentional Radiator, mention 47 CFR [10-1-15]

Prepared and Checked by:

Approved by:

Sign on file

*Jackson Yang*  
*Engineer*

---

*Kidd Yang*  
*Senior Project Engineer*  
*Date: 07 March 2017*

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to copy or distribute this report. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results referenced from this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

TRF No.: FCC 15C\_TX\_b

**Intertek Testing Services Shenzhen Ltd. Guangzhou Branch**

Block E, No.7-2 Guang Dong Software Science Park, Caipin Road, Guangzhou Science City, GETDD Guangzhou, China

Tel / Fax: 86-20-8213 9688/86-20-3205 7538 Website: www.china.intertek-etlsemko.com

---

# INTERTEK TESTING SERVICES

---

## LIST OF EXHIBITS

### *INTRODUCTION*

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information
<i>EXHIBIT 9:</i>	Confidentiality Request
<i>EXHIBIT 10:</i>	Test Equipment List

**INTERTEK TESTING SERVICES**

---

**MEASUREMENT/TECHNICAL REPORT**

**DONGGUAN LINPA ACOUSTIC TECHNOLOGY CO., LTD Co., LTD**  
**MODEL:LEB34**  
**Additional Models: LE34**

**Brand name: LINPA WORLD for M/N: LEB34; BAUHN for M/N: LE34;**

**FCC ID: 2AKZ8-LE34**

This report concerns (check one:)      Original Grant       Class II Change

Equipment Type: DXX - Part 15 Low Power Communication Device Transmitter

---

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes       No

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

---

Transition Rules Request per 15.37?      Yes       No

If no, assumed Part 15, Subpart C for intentional radiator – the new 47 CFR [10-1-15 Edition] provision.

---

Report prepared by:

Jackson Yang  
Intertek Testing Services Shenzhen Ltd.  
Guangzhou Branch  
Block E, No.7-2 Guang Dong Software Science  
Park, Caipin Road, Guangzhou Science City,  
GETDD Guangzhou, China  
Phone: 86-20-8213 9688  
Fax: 86-20-3205 7538

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: 2AKZ8-LE34  
Report No.: 170217097GZU-001

---

---

# INTERTEK TESTING SERVICES

---

---

## Table of Contents

<b>1.0 General Description</b> .....	2
1.1 Product Description .....	2
1.2 Related Submittal(s) Grants .....	2
1.3 Test Methodology .....	2
1.4 Test Facility .....	2
<b>2.0 System Test Configuration</b> .....	4
2.1 Justification .....	4
2.2 EUT Exercising Software .....	4
2.3 Special Accessories .....	4
2.4 Equipment Modification .....	4
2.5 Measurement Uncertainty .....	5
2.6 Support Equipment List and Description .....	5
<b>3.0 Emission Results</b> .....	7
3.1 Radiated Test Results .....	8
3.1.1 Field Strength Calculation .....	8
3.1.2 Radiated Emission Configuration Photograph .....	9
3.1.3 Radiated Emissions .....	9
3.1.4 Transmitter Spurious Emissions .....	11
<b>4.0 Equipment Photographs</b> .....	16
<b>5.0 Product Labelling</b> .....	18
<b>6.0 Technical Specifications</b> .....	20
<b>7.0 Instruction Manual</b> .....	22
<b>8.0 Miscellaneous Information</b> .....	24
8.1 Bandedge Plot .....	25
8.2 Discussion of Pulse Desensitization .....	27
8.3 Transmitter Duty Cycle Calculation .....	28
8.4 Emissions Test Procedures .....	29
<b>9.0 Confidentiality Request</b> .....	32
<b>10.0 Test Equipment Specifications</b> .....	34

---

## INTERTEK TESTING SERVICES

---

List of attached file

Exhibit type	File Description	Filename
Test Report	Test Report	report.pdf
Test Setup Photo	Radiated Emission	radiated photos.pdf
Test Report	Bandedge Plot	bandedge.pdf
Test Report	20dB BW Plot	bw.pdf
External Photo	External Photo	external photos.pdf
Internal Photo	Internal Photo	internal photos.pdf
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
Operation Description	Technical Description	descri.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Cover Letter	Confidentiality Letter	request.pdf
Cover Letter	Letter of Agency	agency.pdf

**EXHIBIT 1**  
**GENERAL DESCRIPTION**

# INTERTEK TESTING SERVICES

---

## 1.0 General Description

### 1.1 Product Description

The equipment under test (EUT) is a Sports Headphones With Bluetooth. The EUT was powered by DC 3.7V, 110mAh rechargeable battery which can be charged by USB port(DC 5V). The EUT cannot operate when charging. For more detail information pls. refer to the user manual.

Bluetooth Version: 4.1(Without BLE)

Antenna Type: Integral antenna

Modulation Type: GFSK,  $\pi/4$ DQPSK, 8DPSK

The Model: LE34 is the same as the Model: LEB34 in hardware aspect (circuitry and electrical, mechanical and physical construction), the differences are appearance and model no. for trading purpose.

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

### 1.2 Related Submittal(s) Grants

This is an application for certification of a transceiver for the Sports Headphones With Bluetooth BT 4.1 and for the charging function was tested and demonstrated in report 170217096GZU-001.

### 1.3 Test Methodology

Radiated emission measurements were performed according to the procedures in ANSI C63.10 (2013). Radiated emission measurement was performed in Semi-anechoic chamber. For radiated emission measurement, preliminary scans were performed in the semi-anechoic chamber only to determine the worst case modes. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application. All other measurements were made in accordance with the procedures in part 2 of CFR 47.

### 1.4 Test Facility

The Semi-anechoic chamber used to collect the radiated data is **Intertek Testing Services Shenzhen Ltd. Guangzhou Branch** and located at Block E, No.7-2 Guang Dong Software Science Park, Caipin Road, Guangzhou Science City, GETDD Guangzhou, China. This test facility and site measurement data have been fully placed on file with the FCC (Registration Number: 549654).

**EXHIBIT 2**  
**SYSTEM TEST CONFIGURATION**



# INTERTEK TESTING SERVICES

---

## 2.0 System Test Configuration

### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.10 (2013).

The EUT was powered by fully-charged DC 3.7V new rechargeable battery during the test.

All packets DH1, DH3 & DH5 mode in modulation type GFSK,  $\pi/4$ DQPSK, 8DPSK were tested, only the worst data was reported in this report.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data reported in Exhibit 3.

The unit was operated standalone and placed at the center of table.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on a turn table, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

### 2.2 EUT Exercising Software

The EUT exercise program (provided by client) used during testing was designed to exercise the various system components in a manner similar to a typical use.

### 2.3 Special Accessories

No special accessories used.

### 2.4 Equipment Modification

Any modifications installed previous to testing by DONGGUAN LINPA ACOUSTIC TECHNOLOGY CO., LTD will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services Shenzhen Ltd Guangzhou Branch.

## INTERTEK TESTING SERVICES

---

### 2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

### 2.6 Support Equipment List and Description

N/A

**EXHIBIT 3**  
**EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

### 3.0 Emission Results

Data is included worst-case configuration (the configuration which resulted in the highest emission levels).

---

---

## INTERTEK TESTING SERVICES

---

---

### 3.1 Radiated Test Results

A sample calculation, configuration photographs and data tables of the emissions are included.

#### 3.1.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG$$

Where            FS = Field Strength in dB $\mu$ V/m  
                    RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V  
                    CF = Cable Attenuation Factor in dB  
                    AF = Antenna Factor in dB  
                    AG = Amplifier Gain in dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG$$

Assume a receiver reading of 62.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The net field strength for comparison to the appropriate emission limit is 42 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

RA = 62.0 dB $\mu$ V  
AF = 7.4 dB  
CF = 1.6 dB  
AG = 29.0 dB

$$FS = 62 + 7.4 + 1.6 - 29 + 0 = 42 \text{ dB}\mu\text{V/m}$$

$$\text{Level in } \mu\text{V/m} = \text{Common Antilogarithm} [(42 \text{ dB}\mu\text{V/m})/20] = 125.9 \mu\text{V/m}$$

## INTERTEK TESTING SERVICES

---

### 3.1.2 Radiated Emission Configuration Photograph

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos. pdf.

### 3.1.3 Radiated Emissions

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Worst Case Radiated Emission  
at  
672.153 MHz

Judgement: Passed by 13.9 dB

#### **TEST PERSONNEL:**

*Sign on file*

Jackson Yang Engineer  
*Typed/Printed Name*

07 March 2017  
*Date*

## INTERTEK TESTING SERVICES

---

Applicant: DONGGUAN LINPA ACOUSTIC TECHNOLOGY CO., LTD

Date of Test: 07 March 2017

Worst Case Operating Mode: BT Link

Table 1

### Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	207.788	37.1	20.0	11.2	28.3	43.5	-15.2
Horizontal	400.245	32.1	20.0	15.7	27.8	46.0	-18.2
Horizontal	672.153	32.4	20.0	19.7	32.1	46.0	-13.9
Vertical	39.655	29.1	20.0	12.7	21.8	40.0	-18.2
Vertical	45.366	30.2	20.0	13.6	23.8	40.0	-16.2
Vertical	401.251	28.8	20.0	15.8	24.6	46.0	-21.4

- NOTES:
1. Quasi-Peak detector is used except for others stated.
  2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
  3. Negative value in the margin column shows emission below limit.
  4. All emissions are below the QP limit.

## INTERTEK TESTING SERVICES

---

### 3.1.4 Transmitter Spurious Emissions (Radiated)

Worst Case Radiated Emission  
at  
7440.000 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos. pdf.

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 9.5 dB

#### **TEST PERSONNEL:**

*Sign on file*

Jackson Yang Engineer  
*Typed/Printed Name*

07 March 2017  
*Date*



## INTERTEK TESTING SERVICES

---

Applicant: DONGGUAN LINPA ACOUSTIC TECHNOLOGY CO., LTD

Date of Test: 07 March 2017

Worst Case Operating Mode: Transmitting

Table 2

### Radiated Emissions

(2402MHz)

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Peak Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	2402.000	103.6	41.4	29.1	91.3	114.0	-22.7
Horizontal	4804.000	59.5	41.3	33.5	51.7	74.0	-22.3
Horizontal	7206.000	66.2	40.7	35.7	61.2	74.0	-12.8
Horizontal	9608.000	64.5	40.8	36.8	60.5	74.0	-13.5

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Average Factor (-dB)	Net at 3m (dB $\mu$ V/m)	Average Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	2402.000	103.6	41.4	29.1	22.5	68.8	94.0	-25.2
Horizontal	4804.000	59.5	41.3	33.5	22.5	29.2	54.0	-24.8
Horizontal	7206.000	66.2	40.7	35.7	22.5	38.7	54.0	-15.3
Horizontal	9608.000	64.5	40.8	36.8	22.5	38.0	54.0	-16.0

Notes: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Jackson Yang

---

TRF No.: FCC 15C\_TX\_b

FCC ID: 2AKZ8-LE34

Report No.: 170217097GZU-001

## INTERTEK TESTING SERVICES

---

Applicant: DONGGUAN LINPA ACOUSTIC TECHNOLOGY CO., LTD

Date of Test: 07 March 2017

Worst Case Operating Mode: Transmitting

Table 3

### Radiated Emissions

(2441MHz)

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Peak Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	2441.000	106.7	41.4	29.2	94.5	114.0	-19.5
Horizontal	4882.000	60.1	41.2	33.4	52.3	74.0	-21.7
Horizontal	7323.000	68.7	40.5	35.8	64.0	74.0	-10.0
Horizontal	9764.000	64.4	40.8	37.0	60.6	74.0	-13.4

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Average Factor (-dB)	Net at 3m (dB $\mu$ V/m)	Average Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	2441.000	106.7	41.4	29.2	22.5	72.0	94.0	-22.0
Horizontal	4882.000	60.1	41.2	33.4	22.5	29.8	54.0	-24.2
Horizontal	7323.000	68.7	40.5	35.8	22.5	41.5	54.0	-12.5
Horizontal	9764.000	64.4	40.8	37.0	22.5	38.1	54.0	-15.9

Notes: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Jackson Yang

---

TRF No.: FCC 15C\_TX\_b

FCC ID: 2AKZ8-LE34

Report No.: 170217097GZU-001

## INTERTEK TESTING SERVICES

Applicant: DONGGUAN LINPA ACOUSTIC TECHNOLOGY CO., LTD

Date of Test: 07 March 2017

Worst Case Operating Mode: Transmitting

Table 4

### Radiated Emissions

(2480MHz)

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Peak Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	2480.000	104.6	41.4	29.3	92.5	114.0	-21.5
Horizontal	4960.000	60.2	41.2	33.3	52.3	74.0	-21.7
Horizontal	7440.000	68.7	40.3	36.1	64.5	74.0	-9.5
Horizontal	9920.000	64.7	41.1	37.5	61.1	74.0	-12.9

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Average Factor (-dB)	Net at 3m (dB $\mu$ V/m)	Average Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	2480.000	104.6	41.4	29.3	22.5	70.0	94.0	-24.0
Horizontal	4960.000	60.2	41.2	33.3	22.5	29.8	54.0	-24.2
Horizontal	7440.000	68.7	40.3	36.1	22.5	42.0	54.0	-12.0
Horizontal	9920.000	64.7	41.1	37.5	22.5	38.6	54.0	-15.4

Notes: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Jackson Yang

TRF No.: FCC 15C\_TX\_b

FCC ID: 2AKZ8-LE34

Report No.: 170217097GZU-001

**EXHIBIT 4**  
**EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

### 4.0 Equipment Photographs

For electronic filing, the photographs of the tested EUT are saved with filename: external photos.pdf & internal photos.pdf.

**EXHIBIT 5**  
**PRODUCT LABELLING**

## INTERTEK TESTING SERVICES

---

### 5.0 **Product Labelling**

For electronic filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

**EXHIBIT 6**  
**TECHNICAL SPECIFICATIONS**



## INTERTEK TESTING SERVICES

---

### 6.0 Technical Specifications

For electronic filing, the block diagram and schematics of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

# **INTERTEK TESTING SERVICES**

---

## **EXHIBIT 7**

### **INSTRUCTION MANUAL**

## INTERTEK TESTING SERVICES

---

### 7.0 **Instruction Manual**

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

**EXHIBIT 8**  
**MISCELLANEOUS INFORMATION**

## INTERTEK TESTING SERVICES

---

### 8.0 **Miscellaneous Information**

This miscellaneous information includes details of the measured bandedge, the test procedure and calculation of factor such as pulse desensitization.

## INTERTEK TESTING SERVICES

---

### 8.1 Bandedge Plot

For electronic filing, the plot shows the fundamental emission when modulated is saved with filename: bandedge.pdf. From the plot, the field strength of any emissions outside of the specified frequency band are attenuated to the general radiated emission limits in section 15.209. It fulfils the requirement of 15.249(d).

#### Peak Measurement

Bandedge compliance is determined by applying marker-delta method, i.e (Bandedge Plot).

#### **(i) Lower channel 2402MHz:**

Peak Resultant field strength = Fundamental emissions (peak value) – delta from the bandedge plot

$$\begin{aligned} &= 91.3 \text{ dB}\mu\text{V/m} - 51.4 \text{ dB} \\ &= 39.9 \text{ dB}\mu\text{V/m} \end{aligned}$$

Average Resultant field strength = Fundamental emissions (Average value) – delta from the bandedge plot

$$\begin{aligned} &= 68.8 \text{ dB}\mu\text{V/m} - 51.4 \text{ dB} \\ &= 17.4 \text{ dB}\mu\text{V/m} \end{aligned}$$

#### **(ii) Upper channel 2480MHz:**

Peak Resultant field strength = Fundamental emissions (peak value) – delta from the bandedge plot

$$\begin{aligned} &= 92.5 \text{ dB}\mu\text{V/m} - 66.0 \text{ dB} \\ &= 26.5 \text{ dB}\mu\text{V/m} \end{aligned}$$

Average Resultant field strength = Fundamental emissions (Average value) – delta from the bandedge plot

$$\begin{aligned} &= 70.0 \text{ dB}\mu\text{V/m} - 66.0 \text{ dB} \\ &= 4.0 \text{ dB}\mu\text{V/m} \end{aligned}$$

The resultant field strength meets the general radiated emission limit in section 15.209, which does not exceed 74dB $\mu$ V/m (Peak Limit) and 54dB $\mu$ V/m (Average Limit).

## INTERTEK TESTING SERVICES

---

### 8.1 Bandedge Plot (cont'd)

Pursuant to FCC part 15 Section 15.215(c), the 20dB bandwidth of the emission was contained within the frequency band designated (mentioned as above) which the EUT operated. The effects, if any, from frequency sweeping, frequency hopping, other modulation techniques and frequency stability over excepted variations in temperature and supply voltage were considered.

Figure 8.1 Bandwidth

## INTERTEK TESTING SERVICES

---

### 8.2 Discussion of Pulse Desensitization

Pulse desensitivity is not applicable for this device. The effective period ( $T_{\text{eff}}$ ) is approximately 625 $\mu\text{s}$  for Bluetooth. With a resolution bandwidth (3dB) of 1MHz, so the pulse desensitivity factor is 0dB.



## INTERTEK TESTING SERVICES

---

### 8.3 Transmitter Duty Cycle Calculation, FCC Rule 15.35(b, c)

Based on the Bluetooth Specification Version 4.1, and worst case AFH mode, transmitter ON time is independent of packet type (DH5) and packet length, the AFH mode Duty cycle connection factor as below:

Channel hop rate = 800 hops/second (AFH Mode)

Adjusted channel hop rate for DH5 mode = 133.33 hops/second

Time per channel hop =  $1 / 133.33 \text{ hops/second} = 7.5 \text{ ms}$

Time to cycle through all channels =  $7.5 \times 20 \text{ channels} = 150 \text{ ms}$

Number of times transmitter hits on one channel =  $100 \text{ ms} / 150 \text{ ms} = 1 \text{ time(s)}$

Worst case dwell time = 7.5 ms

Duty cycle connection factor =  $20\log_{10}(7.5\text{ms} / 100\text{ms}) = -22.5 \text{ dB}$

## INTERTEK TESTING SERVICES

---

### 8.4 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of transmitters operating under Part 15, Subpart C rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.10 - 2013.

The transmitting equipment under test (EUT) is placed on a styrene turntable which is four feet in diameter, up to 1GHz 0.8m and above 1GHz 1.5m in height above the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjusted through all three orthogonal axes to obtain maximum emission levels. The antenna height and polarization are varied during the testing to search for maximum signal levels.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower.

## INTERTEK TESTING SERVICES

---

### 8.4 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

The IF bandwidth used for measurement of radiated signal strength was 10 kHz for emission below 30 MHz and 120 kHz for emission from 30 MHz to 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. Above 1000 MHz, a resolution bandwidth of 1 MHz (RBW 3MHz for fundamental emission) is used.

Transmitter measurements are normally conducted at a measurement distance of three meters. However, to assure low enough noise floor in the restricted bands and above 1 GHz, signals are acquired at a distance of one meter or less. All measurements are extrapolated to three meters using inverse scaling, but those measurements taken at a closer distance are so marked.

**EXHIBIT 9**  
**CONFIDENTIALITY REQUEST**

## INTERTEK TESTING SERVICES

---

### 9.0 **Confidentiality Request**

For electronic filing, the confidentiality request of the tested EUT is saved with filename: request.pdf.

# INTERTEK TESTING SERVICES

---

## EXHIBIT10 TEST EQUIPMENT LIST

## INTERTEK TESTING SERVICES

### 10.0 Test Equipment List

Equipment No.	Equipment	Model	Manufacturer	Cal. Due date	Calibration
				(MM-DD-YYYY)	Interval
EM030-04	3m Semi-Anechoic Chamber	9×6×6 m <sup>3</sup>	ETS•LINDGREN	5/9/2017	1Y
EM031-02	EMI Test Receiver (9 kHz~7 GHz)	R&S ESR7	R&S	6/7/2017	1Y
EM031-03	Signal and Spectrum Analyzer (10 Hz~40 GHz)	R&S FSV40	R&S	6/3/2017	1Y
EM011-04	Loop antenna (9 kHz-30 MHz)	HFH2-Z2	R&S	6/6/2017	1Y
EM061-03	TRILOG Super Broadband test Antenna (30 MHz-1.5 GHz) (TX)	VULB 9161	SCHWARZBECK	6/6/2017	1Y
EM033-01	TRILOG Super Broadband test Antenna(30 MHz-3 GHz) (RX)	VULB 9163	SCHWARZBECK	9/8/2017	1Y
EM033-02	Bouble-Ridged Waveguide Horn Antenna (800 MHz-18 GHz)(RX)	R&S HF907	R&S	6/6/2017	1Y
EM033-03	High Frequency Antenna & preamplifier(18 GHz~26.5 GHz) (RX)	R&S SCU-26	R&S	4/1/2017	1Y
EM033-04	High Frequency Antenna & preamplifier (26 GHz-40 GHz)	R&S SCU-40	R&S	4/1/2017	1Y
EM031-02-01	Coaxial cable(9 kHz-1 GHz)	N/A	R&S	5/30/2017	1Y
EM033-02-02	Coaxial cable(1 GHz-18 GHz)	N/A	R&S	5/30/2017	1Y
EM033-04-02	Coaxial cable(18 GHz~40 GHz)	N/A	R&S	4/1/2017	1Y
EM022-03	2.45 GHz Filter	BRM50702	Micro-Tronics	5/9/2017	1Y