



Warranty

Welcome, your satisfaction with our products and services is the greatest encouragement for our continuous improvement.
us: sales@ec-tek.com.

お客様に良い体験をしていただくことは、私たちの責任と使命であります、もし万が一、お客様がお買い上げになったものが故障していました際には、万全なアフターサービス、迅速な修理、良品との交換を実施しております。商品の保証期間中に問題が発生した場合、購入履歴を弊社アフターサービスまでご連絡をいただければ、弊社で速やかに対応させていただきますので、ご安心ください。 biz@ec-tek.com

Vielen Dank, dass Sie sich für unser Produkt entschieden haben. Wir hoffen, dass Sie zufrieden mit Ihrem Einkauf sind. Sollte dennoch ein Problem mit dem Produkt innerhalb der Gewährleistungszeit auftreten, können Sie unseren After Sales Service für eine Reparatur oder Ersatz unter eu@ec-tek.com kontaktieren

Contents

English 1~7
日本語 8~15
Deutsch 16~22

Tips:

1. Please follow the instructions for use provided in this Manual.
2. Do not charge the headset with a charger that exceeds the rated current of the headset (1A) and the voltage of 5V (5V1A). Otherwise, the battery of the headset may be easily damaged. Burning out of the unit due to the failure to follow the instructions is beyond the warranty scope.
3. Do not use the product near water and do not immerse it in any liquid. Do not either spill any liquid onto the product.
4. Avoid using this product near heat sources, such as radiators, hot-blast regulators, stoves, or other heat-generating instruments.
5. Do not block the opening of the headset, such as the charging port, indicator, and microphone.
6. Avoid excessive volume or long-term use of headsets to avoid dizziness or hearing damage.
7. If the device is damaged due to any reasons, contact our after-sales service promptly. Unauthorized disassembly of the product invalidates the warranty.

Structure explanation:



Wearing method:
Rotate the crystal rubber to a suitable angle, lightly insert into the ear hole, hang the rear hanging part behind the ear, and wear it.
Basic functions .Power on, Bluetooth pairing
The pairing steps are as follows (please confirm that your phone has Bluetooth function)
1 Power on: Turn the switch to the ON position, the white and orange light flashing alternately, and the voice prompts "Power on pairing " at the same time
2 Enable the Bluetooth function to search for the unit by following the operations in your phone's instruction manual.
3 When the device name is searched to be "H20", click "H20" to pair with the headset. If you are asked whether you are ready to pair with it, press the "Yes" or "OK" button to pair.
4 If you need a pairing password, please enter "0000", then press "Yes" or "OK" button. At this time, the indicator light will stop flashing, which means the headset has connected successfully, and the voice prompts "connected" . If your phone has a Bluetooth version of V2.1 or higher, you are not required entering the pairing password in the above procedure.

***Notes:**

- A The pairing mode lasts for 300 seconds. If you do not pair during this time, it will automatically return to standby mode. If you need to reconnect, please turn off the phone Bluetooth, then repeat steps "1" to "4".
 - B After the headset is powered on, it will be connected to the mobile phone automatically (Bluetooth is on) which was connected before shutting down. The phone does not need to perform steps such as reconnection for search.
When there is no obstacle between the product and the phone, the performance sound quality will be better.
- How to connect two phones at the same time:**
1. Pair with the first mobile phone successfully, then turn off both the Bluetooth headset and the Bluetooth function of the first mobile phone.
 2. Turn on the headset again, pair with the second mobile phone as normal.
 3. Turn on the Bluetooth function of your first phone. connect to the headset again. Then 2 mobiles connected.

Instructions:

- Power on/off :**
Power on/off. Power on the mobile phone to the ON position, and voice prompts "power on/pairing." Turn the switch to the OFF position, and voice prompts "Power off".
- Answer a call:**
Press the phone key when receiving a call.
* After the pairing of some brands of mobile phones with Bluetooth, the incoming call is preset to be answered by the receiver of the mobile phone. If you need to change the setup, please check your mobile phone information.
End a call: Press the phone Key during a call.
- Reject an incoming call:**
Press the phone Key for 2 seconds to reject the incoming call.
- Redial:**
Double click the phone key, then it will dial the latest phone number you called .
- Volume adjustment:**
During a call or under music mode, press the volume "+" key to increase the volume and "-" to decrease the volume.
- Song switching:**
In the music state, hold the volume "+"key for 2 seconds for the next song, and hold the volume "-" key to play the previous song.
- Launch Siri and Google Assistant:**
While ear-phone in standby mode , hold and press the phone key for 3 seconds (multi-function key), then release immediately. Siri will start up.

How to connect the H20 Bluetooth headphone with computer

1. Please switch the power button to On place, then the light flashing to enter pairing mode. (You can hear the voice of "Power on")
2. Click your computer's Bluetooth devices and select the add device button, enter the search mode. Search the "H20" then click it to connect. You can hear the voice of "Connected successfully", but you need to continue the 3 step.
3. Click your computer's Bluetooth devices and select the display Bluetooth devices to find the H20 Bluetooth headphone, then click twice to enter the paired interface. You need to click the listen to music and the switch to handsfree earpiece button, the light stop flashing when connecting successfully.




Charging:

1. This product is provided with non-removable rechargeable battery using USB charging mode.
2. The charging current voltage is 5V1A. You cannot charge the product with a charger that exceeds 5V1A.
3. Charge for 2 hours before initial use, and then charge for about 2 hours each time.
4. When the current call/music time is less than 10 minutes, the Bluetooth headset will prompt "low battery" at regular intervals to remind the user charging on time.
5. The orange light is always on when the Bluetooth is charging, and the white LED lights up when it is fully charged.

***Notes**


- A. Please choose a charger that is certified by a formal manufacturer for safety.
 - B. Repeatedly charging and discharging the headset degrades the battery performance over time. It is normal for all rechargeable batteries.
- Bluetooth version: V4.1
Bluetooth accessible distance: 10M
Charging method: USB charging
Protocol supported: A2DP, HFP, HSP, AVRCP
Continuing call duration: about 30 hours
Duration of continuous playback: about 28 hours
Hands-free function: Supported
iPhone battery indicator: Supported




FAQ:

- Q: Connection pairing failed**
A: Most of the connections and pairings are unsuccessful because the headset does not enter the pairing state. When using the headset, turn the headset on to the pairing state.
- Q: Weakly worn**
A: Since the shapes of the auricles of users differ, the user needs to rotate the headset to the most suitable position according to the actual use.
- Q: Signal instability**
A: Because the Bluetooth transmission is a barrier-free transmission. In case of obstacles, the signal will be affected and even interrupted. To allow users to have the best experience, please ensure that there is no obstacle between the headset and the mobile phone during use. Such as: walls, metal equipment, electronic equipment, and human body., etc.
- Q: There is no voice in the headset during a call (for iPhone)**
A: If the headset can listen to music, then the quality problem can be eliminated. This situation is usually a problem arising from mobile phone settings. Please select the "Audio" on the top right of the mobile phone interface during the call, and then click to select "H20".
- Q: There is no voice in the headset during a call (for Android phone)**
A: Please find the setting function of Bluetooth on the phone's settings, set the options "Media Audio" and "Mobile Audio" options, and then try again.

CE



Glazata



FCC ID: 2AMLT-H20

FCC WARNING:

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter