使用说明书
Instructions

T02S
INSTRUCTIONS

真无线双耳立体声迷你无线耳机

产品概览



确认您的无线耳机配有下列物品:
- 主机*1
- USB连接线*1
- S,S尺寸耳套各*1对
（购买时安装的是M尺寸的耳套）

入门指南



耳套选择

选择正确的耳套尺寸，为了获得最佳的音频体验和舒适感，请选择正确的耳套尺寸进行佩戴。

功能按键

开机-长按多功能键约3秒，绿灯闪烁。
关机-长按多功能键约3秒，红灯闪烁。
配对模式（单只使用）-在关机状态，长按多功能键约5秒，红绿灯交替闪烁。
配对模式（双耳使用）-首次使用时，主副耳机长按多功能键3秒开机（红绿同时快速闪），耳机自动成对TWS配对，配对成功后，右耳作为主机自动进入手机配对模式（红绿灯交替闪烁），用手机连接耳机。
手机配对-主副耳机同时长按多功能键3秒开机，主机进入回连状态（10秒），10秒后主机自动进入配对状态。
耳机复位-关机状态下，长按多功能键10秒清除手机配对记录，长按多功能键20秒清除TWS配对记录，清除成功红绿灯同时长亮1秒钟。（耳机功能异常的情况下，用此功能复位耳机，主副耳机无法自动连接）

按键操作

唤醒Siri/Google assistant-长按功能键1.5秒
接听来电-来电状态，短按多功能键
拒接来电-来电状态，长按1秒多功能键
挂断来电-通话状态，短按多功能键
语音助手-连接手机状态下，长按1秒多功能键

播放/暂停-音乐状态下，短按多功能键
音量加/减-不支持
上一曲-在播放音乐模式下三击多功能键
下一曲-在播放音乐模式下双击多功能键

耳机充电指示灯-红耳机正确放进充电盒里，确保正常充电。红色呼吸灯表示正在充电，绿色呼吸灯表示充满电，满电后1分钟绿灯灭掉。

充电盒功能参数

开机-短按多功能键，白灯亮
关机-双击多功能键，白灯灭

充电盒对耳机充电指示灯-充电时白灯亮起然后保持显示充电金书量。
自动检测充电功能-当耳机放回充电盒，充电盒自动检测到耳机并对耳机充电。
智能检测耗电功能-充电盒充电带智能检测功能，当充电盒检测到2只耳机处满电后，约30秒后会关断内部升压电路，降低充电盒内部电池损耗。
智能自燃保护功能-耳机充满电后，充电盒只有在检测到2只耳机离开充电盒时，才会重新开启充电检测，耳机重新放回去才会再次充电，此功能是为了避免在携带过程中圆边导致后机掉落弹起再回去导致反复充电。

产品参数

蓝牙芯片	RTL8763B
蓝牙版本	V5.0
传递系统	真立体
工作频率	2.402-2.480GHz
支持协议	HSP/HFP/A2DP/AVRCP
传输距离	10米
传输功率	Class 2
信噪比输比	98dB
响应频率	20~20000Hz

充电输入标准	输出,DC 5V/0.5-1A
电池类型	耳机:3.7V锂电池,40mAh 充电盒500mAh
充电时间	约1.5小时
工作时间	约4小时
待机时间	约40小时
耳机尺寸	23.3×25.38×24.38mm
充电盒尺寸	75×40×30m
特别说明	本产品支持协议HFP/HSP/A2DP/AVRCP 左右耳均具有完整无线耳机功能，可单独使用，也可成对使用。

***产品参数因机型，使用方式，环境等等因会有所差异！**

注意事项

- 产品说明书所记载的内容是在恒定的实验环境下测试出的参考数据，实际产品性能请以实际使用为准。
- 产品目录所记载的内容，在产品改良时，有不予先告知而进行变更的可能。
- 产品目录所记载的产品，是用于一般电子产品(如:信息机器类,通信机器类,音响映像机器类,测量机器类,家电产品类等)。对用于有特殊品质/信赖性要求的,其故障或误动作直接威胁人体生命的装置及系统如:交通工具,安全装置,节能机,核动力制御,生命维持装置等,请务必事先和销售窗口联系咨询。
- 本公司致力追求产品的高品质,音响敏感,但为预防万一,也请在保证装置及系统的安全之上,未进行设计使用。
- 在设计时,请在最大使用/动作电源电压,动作温度等保证范围内使用,超过保证范围数值进行使用,说明,不正确使用等所引起的一切后果,本公司概不负责。
- 产品目录所记载的动作概要及设计回路等,是用于说明产品的标准动作和使用方法。
在实际使用产品时,请考虑外部诸多使用条件之后,再进行回路/安装设计。
- 产品目录所记载的技术情报是为了说明产品代表性的动作或应用,他方在使用此技术情报时,并不代表取得本公司及第三方的知识产权等权利的保证或承诺。

Instructions

T02S
True wireless earbuds

The parameters vary on different features, different models.

Package Contents



- 1x pair of T02S wireless earphones
- 1x T02S charging case
- 1 x USB charging cable
- 1 x pairs of additional earplugs (Small&Large)

Overview



Pairing way

1. Mono ear bud use

- Long press MFB for 5 seconds, red & green light will flash alternately.
- Turn on Bluetooth on your phone/media device and scan for the earphone and pair.

2. Stereo ear buds use

Smart pairing:
- For first use, long press both units for 3 seconds (red & green light quick flash).
- Two units will pair each other automatically.
- After TWS connected, Right unit will be master unit(red & green light will be flash alternately)
- Turn on Bluetooth on your phone/media device and scan to pair.

Force pairing:
Long press master unit(right one) for 5 seconds, red & green light flash alternatively, pair with phone, then power on vice unit(left one), finally vice will pair with Master automatically.

When power off status: long press MFB 10 seconds for clearing phone/media device pairing record.
When power off status: long press MFB 20 seconds for cleaning true wireless pairing record, green light will flash for 1 second if clean successfully.
In case of abnormal earphone function, also can use this function for reset. Master & vice units can* pair automatically.
- To turn off the earphones, press MFB for 3 seconds (red light will flash) or simply put them back into the charging case.

Charging The Earphones

Place the earphones into the charging case in their correct orientation making sure the charging points make contact. A red breathing light on the earphones will indicate they are still being charged.
A green breathing lighton the earphones will indicate they are full charged.
Green light will be off after 60 seconds.

Charging the Case

To charge the case, plug in the USB cable and connect it to any USB port. The 4 lights aligned vertically in the centre of the charging case indicates the charge status. If all 4 lights are illuminated, the case is fully charged.

Basic Function

- Answering phone calls- press the MFB to answer
- Rejecting phone calls: hold MFB for 1s to reject an incoming call
- Play/pause- short press MFB when music status
- Volume up/volume down-don't support
- Previous track-three click MFB when music status
- Next track-double click MFB when music status

Call-Waiting Functions

Activate the call waiting function on your phone:
- To switch to an incoming call whilst already on a call, press the MFB to switch.

- Suppose you are on a call and there is another call on hold, you may switch between calls by double pressing the MFB.

Power-on

Hold MFB for roughly 3S(Green light will be on)
If the units are charging in the case , they will be activated whenever you take them out.

Power-off

Two units are in series connection while the main unit (L) is connected with cellphone, hold MFB of either of them for about 4S, they will be switched off at the same time (red lights are on)

It also can switch off when pull the connected units back to case

Media sharing between two units

Two units are in series connection while the main unit (L) is connected with cellphone, press MFB of either of them to play or pause music and you can enjoy songs by both units together. Note: both two units are available to answer a call.

Specifications：

Model No.	T02S
Bluetooth version	V5.0
Earphone battery capacity	3.7V, 40mAhx2
Earphone Weight	5g each
Charging case weight	45g
Charging case battery capacity	500mAh
Working range	10m
Talk Time	4Hours
Standby time	40Hours
Charging case size	7.5*3.5*2.5CM

- With the new 5.0 Bluetooth version, T02S brings you more HD experience.
- TWS style delivers true wireless stereo sound effect
- Charging case allows you to charge the device when stored

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-Consult the dealer or an experienced radio/TV technician for help
Changes or modifications not expressly approved by the party responsible for compliance
could void the user's authority to operate the equipment.
This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may
cause undesired operation.