

TWS-X9J Use Manual

Wearing sketches

Choose the suitable ear-pad from three sizes (small, medium, large) to make you more comfortable.

Tip: Insert earphones with your ear-pads into your ear canal, then turn the earphones to a firm and comfortable position.

Functional operation

First use instructions:

When using it for the first time (or not using it for a long time), please make sure to charge the earphones and charging box before use.

Power on:

- 1)Auto Power On: Open the top cover of the charging box, the white light of earphones flash for 3 times, and these two earphones will be turned on and connected automatically.
- 2)If these two earphones are power off, and the charging case is not around, please simultaneously long press the power button for the earphones for 3 seconds until both earphones are flash white light, then release the fingers, the earphones will enter into pairing mode.

Get quick started:

- 1) Take the L/R earphones out from the charging box and the L/R earphones will power on and connect to each other automatically.
- 2) After successful connection, the blue & white light of the master earphone (left earphone) will blink alternately and it voices "connected, left channel, pairing" as well. While the right earphone will be blue light blinking slowly and it voices "connected, right channel".
- 3) Turn on the mobile phone search Bluetooth device "TAOTRONICS SoundLiberty 77", then click connect and it voices "second device connected" in the master earphone (left earphone).

Power off:

There are two ways to power off the earphones --

- 1) Put the earphones into the charging box , they will power off automatically and enter into charging mode.
- 2) Disconnect the Bluetooth connection between your mobile phone and the earphones, the earphones will power off automatically after about 10 minutes.

Indicator light status:

- A. White indicator flashes three times-Power on; Blue indicator flashes three times-Power off.
- B. Blue and White indicator flashes alternately- Two earphones connected and waiting connection with mobile phone.
- C. Blue indicator flashes slowly every 5 seconds- Connected with mobile phone.

IOS/Siri Active:

long touch the either of earphone for 2 seconds to activate Siri, Siri will be ready to take commands after a sound "Siri" played through. (This function is only supported for IOS system devices).

Use earphones again:

Take the L/R earphones out of the charging box and the L/R earphones will power on and connect to each other automatically. Then they will connect the Bluetooth device automatically. (The last connected Bluetooth device.)

Use a single earphone:

Only take out any one earphone, the White light of this one will flash soon. Then double click it, the indicator is changed to blue & white light flickering. While turn on the cellphone, search the Bluetooth "TAOTRONICS SoundLiberty 77" and connect. Left and right earphone can be used separately.

Tips: If the earphone has been used as single earphone and want to change TWS mode, you only need to pick up the other earphone from the charging box. These two earphone will connect each other automatically.

Functional operation:

Phone ring tone and sound can be heard from Both earphones.

Answer the phone: when calls come in, single-click either of earphones. (Sounds can be heard from both earphones.)

Hang up the phone: during the call, double-click either of earphones.

Reject a call: when calls come in, long touch the either of earphones for 2 seconds.

Music play: In playing music, triple-click the left earphone for previous track; triple-click the right earphone for next track; double-click the either of earphones for pause or play music.

Decrease the volume(-): single-click the left earphone to turn the volume down.

Increase the volume(+): single-click the right earphone to turn the volume up.

Tips: 1. Please make reasonable volume and time, it will damage your hearing if it is continuous long time and high volume.

2. When using a single earphone, you cannot use the volume(+)/volume (-) function.

Reset:

If two earphones cannot be connected each other or they cannot connect to the mobile phone Bluetooth due to mis-operation, you can reset the earphones as the following methods.

Put the earphones into the charging box and enter into the charging mode, long touch the earphones for 3 times at the same time, until the white lights of the earphones flashes. (You can do this one by one.) Then take the both earphones out of the charging box. They will enter into pairing mode automatically. After successfully connection, turn on the mobile phone Bluetooth and connect.

Earphone charging:

1. Put two earphones into the charging box, cover the lid and the they will enter into charging mode after several seconds.
2. Charging is completed: after the earphones are full power, the blue light on the earphones and the related displays LED on the charging box will go out, and the charging box will automatically cut off after 30 seconds.

Charging box battery charging

Please power the charging case by DC5V/1A adapter, PC USB port of PC or other DC5V is OK.

Note: please charge for the case with DC5V/1A charger or Computer USB; As the charging and discharging of the earphones increases, the battery performance will decrease, which is normal for all rechargeable batteries. (Don't press the contact of the spring pin hard to avoid improper use.)

Specification:

Bluetooth version	V5.0
Support profile	A2DP/AVRCP/HFP/HSP
Transmission distance	10M
Frequency range	2402MHz~2480MHz
Driver	Φ6MM*2 Hi-Fi Speaker
Impedance	16 Ω
Voltage	3.7V
Standby time	70H
Talking time	3-5H
Playing time	2.5H
Earphone battery	50MAH
Earphone charging time	≤1.5H
Charging box battery	410MAH
Charging box charging time	About 1H
Support system	IOS/Android/Windows
Certification	CE/FCC/ROHS

Attention:

1. Do not remove or refit earphones for any reason, otherwise it will lead to headset damaged

and burn. These are not covered by warranty.

2. Do not touch the earphones in corrosive liquid, otherwise it will cause serious damage. The manufacturer will not guarantee the damage caused under this situation.

3. Do not put the equipment under too high or too low temperature(Below 0°C or above 45°C).

4. Please avoid approaching the eyes of children or animals when using equipment lights.

5. Do not use equipment in the thunderstorm weather. Thunderstorms may cause abnormal equipment operation and increase the risk of electric shock.

Warning:

This product contains a built-in lithium battery. Please do not expose this product to strong sunlight, roasting or throwing it into the fire, as they may explod.

FAQ

Q: Charging case can not charge?

A: Ensure that the charging cable is properly connected to the charging port or replace charging cable.

Q: Signal is not stable or left earphone is out of voice?

A: Try to wear the earphones well, and put the mobile on front pocket when used in outdoor.

Q: When search the Bluetooth, display two connection names of “TAOTRONICS SoundLiberty 77”?

A: Forget the two Bluetooth name of “TAOTRONICS SoundLiberty 77”, turn off the Bluetooth and connect as above “get quick start”.

Q: The sound volume is down or not clear when making calls?

A: Try to turn the earphone volume up or turn the mobile phone volume up, and move phone closer to the earphones.

Q: How to connect two cellphones to an earphone?

A: Connect your first mobile phone to Bluetooth and then turn off Bluetooth , then connect second mobile phone. Finally, turn on the first mobile phone Bluetooth and connect it again.

Q: How far is the distance between the left earphone and the right one?

A: 3M in the normal environment without barrier.

For better sound quality experience, suggest use IOS 8.0/ Android 4.3 or above operation system.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance

could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC ID: 2AOQKTWS-X9J