Macaw

Bluetooth®

TX-90

Bluetooth headset

FAVORED



Product features / Functions

The headset is equipped with LOGO type breathing lamp:

Operation chart of function key by wire:



Basic specification

Product Name: TX-90

Bluetooth pairing name: TX-90

Bluetooth chip: CSR8640

Bluetooth version: V4.1

Bluetooth level: CLASS 2

Bluetooth protocol: HFP/HSP/A2DP/AVRCP

Audio decoding: Support hp3 4/SBC

Transmission radius: More than 10 meters

Main unit: 10mm moving coil

Sound track: Stereo2 stereo

Body weight: 42g

Battery capacity: 150mAh

Continuous music time: 12H

Standby time: 350H

Charging time: 2H

Waterproof class: IPX5class

Voice calls: Support

Wire-control song switching: Support

Multiple pairs: Support

Support equipment: Apple/ Android/ PC

Power display: iOS/Android system power display

Basic function operation

Power on:
Under power-off state, long press MFB button for 3 seconds to red light for a second with a prompt tone "Power On".

Power off:
Under power-on state, long press MFB button for 3 seconds to red light for a second with a prompt tone "Power Off".

Pairing:
Under power-off state, long press the MFB button for 5 seconds to red and blue light flash alternately for a second with the prompt tone "Pairing", do not let go and continue the long press to the prompt tone "Lumenis out", and then press the mobile phone to connect it.

Auto power-off:
If the connection of Earphone and mobile phone is beyond 10 minutes and there was one connection in 5 minutes, it' ll power off automatically.
It will power off if there' s no connection with device in 5 minutes.

Wait-points connection:
The first mobile phone will be connected automatical-ly, the second mobile phone can be connected by setting the Bluetooth in phone manually.

Connection out of range:
There will be a voice when the earphone and mobile connection is beyond 10 meters of range for 10 seconds and a connection can last for 10 minutes.

Basic function operation

Volu+ control:
Under connected state, long press MFB for 1 second (need the support of mobile phone).

Answering a call:
Under the incoming call state, short press MFB Button.

Rejecting a call:
Under the incoming call state, long press MFB button for 1 second.

Finishing a call:
Short press MFB to finish a call.

Tripartite call:
In a two-person call, if a third party calls, pressing the multi-function button once will hang up the last call and get through the third party' s call.
In a two-person call, if a third party calls, double-press the multi-function button twice will reserve the first call and get through the third party' s call, and then double-press the multi-function button twice will hang up the third party' s call and go back to the first call. If the third party hang up, and then double-press the multi-function button will go back to the first call.

MIC Mute function:
Short press the volume-up and volume-down at the same time to open the MIC mute function; Short press again the volume-up and volume-down at the same time to open MIC mute function.

Basic function operation

Music / Play:
During music playing, short press MFB button to pause music and again short press MFB button to play music.

Repertoire selection:
During the music playing, long press the volume-up a second to play the next song; long press the volume-down a second to play the last song (part 4 the music player' s first long press is to return to the song head, and the second long press is to play the last song).

Volume control:
When playing music, short press the volume-up to adjust the volume up, short press the volume down to lower the volume , (Apple watching system has volume synchronization function).

Low battery notice:
When the LED charging is red, the prompt tone "Low Battery" will prompt one time every 1 minute; when the power is very low, it will prompt "Power Off" and then automatically power off.

LED Indication state

Power on:
Blue light is on for 1 second.

Power off:
Red light is on for 1 second and then off.

Low battery:
LED turns red flashing.

Charge
When charging, the red light is on and when finishing charging, the blue light is on.

Bluetooth is connected:
Blue light is on and off for 0.1 second each, repeat once every 03 second.

Bluetooth pairing:
The red and blue light flash alternately every 0.1 second

Bluetooth connected:
Blue light is on and off for 0.1 second, repeat once every 5seconds.

Incoming call:
Blue light is on and off 0.15 second and flash 2 times, repeat once every one second.

Calling:
Blue light is on and off for 0.1 second, repeat once every 5seconds.

LED Indication state

Call:
Blue light is on and off for 0.1 second, repeat once every 5 seconds.

Tripartite call waiting:
Blue light is on and off for 0.1 second, repeat once every 5 seconds.

Tripartite call hold:
Blue light is on and off for 0.1 second, repeat once every 5 seconds.

Tripartite call of multi-parties:
Blue light is on and off for 0.1 second, repeat once every 5 seconds.

Music playing:
Blue light is on and off for 0.1 second, repeat once every 5 seconds.

Prompt tone

Power on

Power off

Pairing

Connected

Low battery

FCC Statement

This equipmenthas been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits aredesigned to provide reasonable protection against harmful interference in a residential installation. This equipment generates, usesand can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

• Reorient or relocate the receiving antenna.

• Increase the separation between the equipment and receiver.

• Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

• Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Information

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

Adorning ways

Before adorning, please adjust the volume to the best, Both sides of the earphone are marked with "L" and "R", which stands for left and right, hook the headset on to the monks, and keep the headset tail up, the circle the cables at the ear back based on the ear, **pull gently.** If you feel any uncomfortable, please adjust the adorning angle of the earphone cable, then the adorning is done!

Safety tips:

Please read the safety tips carefully before using.

- Do not use liquid to clean
- Please away from high temperature and open flames
- Please avoid the earphone falling off from high place
- Do not put it into water
- Please do not disassemble it

Warranty Card

User Information	
Name	
Email	
Address	
Phone	
Mail code	
Product information	
Model	
Dat code	
Dealer information	
Name	
Address	
Phone	
Sale date	
Invoice number	
Mail code	
Notes:	

The following conditions are beyond the scope of warranty:

1. Exceed the warranty period;
2. Failure to use the product in accordance with the instructions;
3. Failure to make warranty certificate and valid invoice (unable to confirm whether warranty period is still valid);
4. Warranty certificate information inconsistent with the product;
5. Product breaks down by artificial damage.

1-SERIES