

电吉他音箱 AG-05 **使用说明书**

非常感谢您购买AROMA音箱AG-05。请在使用本产品前，仔细阅读使用说明书。

AROMA aromamusic.cn
© 2020惠州市阿诺玛科技有限公司

注意事项

避免放置的位置
在以下地方使用音箱可能会导致功能失常。

- 太阳直射的地方。
- 高温或过度潮湿的地方。
- 灰尘过多的地方。
- 避免震动的地方。
- 与磁场接近的地方。

电源
本产品内置锂电池，当不使用音箱时，请及时关闭电源开关。

应远离的其他电器设备
本产品靠手机或无线电发射设备太近可能导致使用干扰。在使用音箱时应与这类设备保持适当的距离。

小心操作
为了避免损坏机器，请不要太用力按按钮或其他操作部件。如果产品需要维修，请联系合格的技术人员操作。

清洁
如果产品表面脏了，请用干净的干布擦拭。不要使用液体清洁剂，譬如：茶，稀酒精，或者其他含有腐蚀性成分的清洁剂。

防止异物进入产品内
不要把含有液体的器皿放置在产品旁边。如果液体浸入本产品，可能会引起死机、火灾或电击。非专业人士不要将异物进入产品内。

保留说明书
阅读完成说明书后，请保留以备后用。

主要特征

AG-05 迷你电吉他音箱是一款充电的迷你练习音箱。外观精美，小巧便携，适用于多种场合使用。可以简单的切换失真效果。可以作为普通的蓝牙音箱使用。

- 本音箱由大容量锂电池供电，可以使用附带的Type-C 数据线充电。
- 双声道音频输出，最大输出功率4W。使用全模拟音频处理，可以简洁直观调控音色。
- 2组高品质音效：原音（clean）和失真（distortion）
- 内置蓝牙功能，可与手机等蓝牙设备连接，播放音乐。

连接音箱

简单步骤按照连接本音箱，开始享受音乐之旅。

1. 把主音量键（MASTER）调到最小。
2. 连接您的吉他的音箱背面的输入(INPUT)接口。
3. 顺时针方向转动音箱上面的电源按钮（ON/OFF），打开电源。
4. 顺时针方向转动音量按钮（MASTER）至适当位置，获得自己满意的音量水平。

面板介绍

1. 效果切换按钮
按下按钮，获得失真音色。按钮复位，为原音。
2. 增益按钮
此按钮可以调节所选音色的增益输出。
3. 音色按钮
此按钮可以调节音色的音色。
4. 音量按钮/电源开关
此按钮可以控制音箱的总音量及电源开关。
5. 电源指示灯
音箱开启后，指示灯点亮。若音箱电量过低，蓝色指示灯闪烁。
6. 蓝牙按钮
按下可以开启或关闭蓝牙。开启及关闭时会有提示音。

请依以下步骤通过蓝牙播放音乐

1. 开启智能手机蓝牙。
2. 开启手机蓝牙功能。
3. 在蓝牙设备表中找到“AROMA AG-05”，手动连接。
4. 连接成功后你可以像使用其他任何普通蓝牙音箱一样将手机的音频通过本音箱播放。

背面面板

7. 耳机接口
接口规格：3.35mm，双声道。

▲ 温馨提示

- 当连接接口时，音箱的喇叭会静音。
- 请使用双声道音频插头。
- 当耳机连接后，蓝牙连接的外接音箱播放也会输出到耳机。

8. 吉他输入
此接口为6.35mm，用于接入电吉他。
9. 充电指示灯
充电时，指示灯点亮；充满电后，指示灯熄灭。
10. 充电接口
规格：Type-C接口数据线；充电电压要求：5V~2A。

消费者若使用电源适配器充电，则应购买配套使用获得CCC认证并满足标准要求电源适配器。

产品规格

输出功率：5W
喇叭：2个，2寸 5A
蓝牙版本：5.0
动态范围：96dB
THD+N：0.05%
采样能力：24bit/44.1KHz
电源：7.4V/2200mAh
充电时间：+3.5h(2A充电时)
满电使用时间：8h以上
尺寸：125x80x90mm
净重：450g
附件：Type-C 充电线*1，说明书*1，合格证*1

惠州市阿诺玛科技有限公司
Arroma Technology Co., Limited
地址：广东省惠州市博罗县技术保障
室（博罗县石湾镇）
电话：0752-3189101

CE, FCC, RoHS, REACH, MADE IN CHINA

Electric Guitar Amp AG-05 **OWNER'S MANUAL**

Thank you for purchasing AROMA amp AG-05, please read this manual carefully before your operation.

AROMA aromamusic.cn
©2020 Arroma Music Co., Ltd.

Precautions

Location
Using the unit in the following locations can result in a malfunction.

- In direct sunlight
- Locations of extreme temperature or humidity
- Excessively dusty or dirty locations
- Locations of excessive vibration
- Close to magnetic fields

Power supply
Be sure to turn the power OFF when the unit is not in use. The amp is powered by rechargeable Li battery.

Interference with other electrical devices
Radios and televisions placed nearby may experience reception interference. Operate this unit at a suitable distance from radios and televisions.

Handling
To avoid breakage, do not apply excessive force to the switches or controls. Please ask qualified technician to operate in case that the amp needs to be repaired.

Care
If the exterior becomes dirty, wipe it with a clean, dry cloth. Do not use liquid cleaners such as benzene or thinner, or cleaning compounds of flammable solvents.

Prevent foreign matter out of your amplifier
Never set any container with liquid in it near this amplifier. If liquid gets into the amplifier, it could cause a breakdown, fire, or electrical shock. Be careful not to let metal objects get into the amplifier.

Keep this manual
After reading this manual, please keep it for later reference.

Main features

AG-05 is a power rechargeable mini amp for electric guitars. Simple compact design. Portable to use in many occasions. Easy and fast to switch On distortion effect. Best quality as a bluetooth speaker.

- This portable amplifier is powered by high capacity rechargeable lithium batteries inside, use the attached Type-C cable to recharge anytime.
- 5 watt stereo analog amp. Easy and direct to operate.
- High quality effects: clean and distortion.
- Use Bluetooth to play music from your phone. Line out to connect to other speakers.

Setup

Easy steps to follow before you enjoying playing your guitar.

1. Turn the Master volume on the amp all the way down.
2. Connect your guitar to INPUT jack in the rear Panel.
3. Turn the master knob clockwise to turn on the power supply.
4. Slowly raise the Master volume to a desired level.

Panel guide

1. Effect switch
Press the button to turn On distortion effect. Release the button to get a clean sound.
2. Gain knob
Control the output level of the selected effect.
3. Tone knob
Control the output tone of the instrument.
4. Power / Volume knob
Turn clockwise to turn the amp power On, and then turn up the volume. Turn counter clockwise to turn down the volume and Off the power.
5. Power indicator
The indicator is On and solid when turning the amp power On. A blue indicator flashes when power turns flat.
6. Bluetooth button
Press to turn On/Off Bluetooth, a beep sound generated.

How to link Bluetooth

1. Turn On amp Bluetooth.
2. Turn On smart phone or any other device Bluetooth.
3. Find name "AROMA AG-05" in the Bluetooth devices list, and click the name to link.
4. Play music in your smart phone or other devices and output music via the amp.

Rear Panel

7. Earphone output jack
Specification: gauge 3.35mm, stereo.

▲Notice:

- The amp speaker is mute when an earphone is connected to the amp.
- A stereo earphone is required.
- Bluetooth music is also outputted to the earphone.

8. Guitar input jack
Connect the cable from your guitar into this jack.
9. Charge indicator
The charge indicator is On and solid when charging. The indicator turns Off automatically when charging finished.
10. Charge jack
Specifications: Type-C USB charging cable, power requirements: 5V~2A.

Specifications

Output peak: 5W
Speaker: 2*2 inches
Bluetooth version: 5.0
Dynamic range: 96dB
THD+N: 0.05%
Sampling frequency: 24 bit /44.1 KHz
Power supply: 7.4V/2200mAh
Full charging time: 3.5h
Work hour after full recharged: 8h
Dimension: 125x80x90mm
Weight: 450g
Included items: Type-C cable*1, Operation manual*1

FCC Statement
Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment Off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.
This device complies with part 15 of the FCC rules. Operator is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

follow us

- Facebook.com/ArromaMusicGear
- info@arromamusic.cn

Designed and engineered by AROMA MUSIC

FCC, CE, REACH, MADE IN CHINA

size:430 × 213mm